

Directed PieClam

Daniel Zilberg

10 August 2025

1 Derivation

1.1 Setting

Consider a directed graph G with N nodes. The adjacency matrix is $A \in \mathbb{R}^{N \times N}$. consider the undirected bipartite graph G_b with $2N$ nodes, where the off diagonal $N \times N$ blocks of A are the adjacency matrix of G and it's transpose accordingly, and the diagonal blocks are all zeros.

The duplicate set of nodes can be considered as "Sender" and "Receiver" sets. To extract the the original directed graph we simply only consider the connections from the "Sender" to the "Receiver".

1.2 Probabilistic Model

We write the PieClam probabilistic model of G_b as:

$$p(E|\mathbf{F}) = \prod_{n=1}^N \left(\prod_{m \neq n}^N e^{-\mathbf{f}_n^T \mathbf{L} \mathbf{f}_m} \prod_{\substack{N+1 \leq m \leq 2N \\ m \sim n}} \left(1 - e^{-\mathbf{f}_n^T \mathbf{L} \mathbf{f}_m} \right) \prod_{\substack{N+1 \leq m \leq 2N \\ m \not\sim n}} e^{-\mathbf{f}_n^T \mathbf{L} \mathbf{f}_m} \right) \\ \times \prod_{n=N+1}^{2N} \left(\prod_{\substack{N+1 \leq m \leq 2N \\ m \neq n}} e^{-\mathbf{f}_n^T \mathbf{L} \mathbf{f}_m} \prod_{\substack{1 \leq m \leq N \\ m \sim n}} \left(1 - e^{-\mathbf{f}_n^T \mathbf{L} \mathbf{f}_m} \right) \prod_{\substack{1 \leq m \leq N \\ m \not\sim n}} e^{-\mathbf{f}_n^T \mathbf{L} \mathbf{f}_m} \right) \quad (1)$$

In this case, the nodes $[1, N]$ are the "Sender" nodes and the nodes $[N+1, 2N]$ are the "Receiver" nodes.

The reconstruction of the directed graph is then:

$$p(n \rightarrow m|\mathbf{F}) = 1 - e^{-\mathbf{f}_n^T \mathbf{L} \mathbf{f}_{m+N}} \quad (2)$$

1.3 Feature Representation

By creating a second set of nodes, we in fact create a second set of features for each of the nodes. We may use this intuition and add the second set directly. Each node will now have two feature sets $\mathbf{s} \in \mathbb{R}^{N \times d}$ (sender) and $\mathbf{r} \in \mathbb{R}^{N \times d}$ (receiver).

Rewrite 1 as:

$$p(E|F) = \prod_{n=1}^N \left[\sqrt{\left(\prod_{m \neq n}^N e^{-\mathbf{s}_n^T \mathbf{L} \mathbf{s}_m} \prod_{m \leftarrow n} \left(1 - e^{-\mathbf{s}_n^T \mathbf{L} \mathbf{r}_m} \right) \prod_{m \not\leftarrow n} e^{-\mathbf{s}_n^T \mathbf{L} \mathbf{r}_m} \right)} \right. \\ \left. \times \sqrt{\left(\prod_{m \neq n}^N e^{-\mathbf{r}_n^T \mathbf{L} \mathbf{r}_m} \prod_{m \rightarrow n} \left(1 - e^{-\mathbf{s}_m^T \mathbf{L} \mathbf{r}_n} \right) \prod_{m \not\rightarrow n} e^{-\mathbf{s}_m^T \mathbf{L} \mathbf{r}_n} \right)} \right] \quad (3)$$

Notice that the directed terms have the same elements but in different order. We can therefore rewrite the expression as:

$$p(E|F) = \prod_{n=1}^N \left(\prod_{m \neq n}^N e^{-\frac{1}{2}(\mathbf{s}_n^T \mathbf{L} \mathbf{s}_m + \mathbf{r}_n^T \mathbf{L} \mathbf{r}_m)} \prod_{m \rightarrow n} \left(1 - e^{-\mathbf{s}_m^T \mathbf{L} \mathbf{r}_n} \right) \prod_{m \not\rightarrow n} e^{-\mathbf{s}_m^T \mathbf{L} \mathbf{r}_n} \right) \quad (4)$$

The log likelihood is then:

$$\log p(E|F) = \sum_{n=1}^N \left(\sum_{m \neq n}^N -\frac{1}{2}(\mathbf{s}_n^T \mathbf{L} \mathbf{s}_m + \mathbf{r}_n^T \mathbf{L} \mathbf{r}_m) + \sum_{m \rightarrow n}^N \log(1 - e^{-\mathbf{s}_m^T \mathbf{L} \mathbf{r}_n}) - \sum_{m \not\rightarrow n}^N \mathbf{s}_m^T \mathbf{L} \mathbf{r}_n \right) \quad (5)$$

Which can be rewritten using a parameterization trick:

$$\begin{aligned} \log p(E|F) &= \sum_{n=1}^N \left(\sum_{m \neq n}^N -\frac{1}{2}(\mathbf{s}_n^T \mathbf{L} \mathbf{s}_m + \mathbf{r}_n^T \mathbf{L} \mathbf{r}_m + 2\mathbf{s}_m^T \mathbf{L} \mathbf{r}_n) + \sum_{m \rightarrow n}^N \log(e^{\mathbf{s}_m^T \mathbf{L} \mathbf{r}_n} - 1) \right) \\ &= \sum_{n=1}^N \left(\sum_{m \neq n}^N -\frac{1}{2}(\mathbf{s}_n + \mathbf{r}_n)^T \mathbf{L} (\mathbf{s}_m + \mathbf{r}_m) + \sum_{m \rightarrow n}^N \log(e^{\mathbf{s}_m^T \mathbf{L} \mathbf{r}_n} - 1) \right) \end{aligned} \quad (6)$$

Where we use the fact that

$$\sum_{n=1}^N \sum_{m \neq n}^N \mathbf{s}_m^T \mathbf{L} \mathbf{r}_n = \sum_{n=1}^N \sum_{m \neq n}^N \mathbf{s}_n^T \mathbf{L} \mathbf{r}_m \quad (7)$$

The gradient updates are then (remembering that every node appears twice in first term):

$$\begin{aligned} \nabla_{\mathbf{s}_n} l &= - \sum_{m \neq n}^N \mathbf{L}(\mathbf{s}_m + \mathbf{r}_m) + \sum_{m \leftarrow n}^N \frac{\mathbf{L} \mathbf{r}_m}{e^{\mathbf{s}_n^T \mathbf{L} \mathbf{r}_m} - 1} \\ \nabla_{\mathbf{r}_n} l &= - \sum_{m \neq n}^N \mathbf{L}(\mathbf{s}_m + \mathbf{r}_m) + \sum_{m \rightarrow n}^N \frac{\mathbf{L} \mathbf{s}_m}{e^{\mathbf{s}_m^T \mathbf{L} \mathbf{r}_n} - 1} \end{aligned} \quad (8)$$

Which can be implemented as a message passing algorithm.

The reconstruction of the graph can be written as:

$$\hat{A}_{n,m} = p(n \rightarrow m|F) = 1 - e^{-\mathbf{s}_n^T \mathbf{L} \mathbf{r}_m} \quad (9)$$

Example: A directed bipartite with no self loop ($1 \rightarrow 2$) i.e. an adjacency with diagonal 0 and off diagonals 0 and $1 - e^{-a^2}$ can now be represented by: $\mathbf{s}_1 = \mathbf{r}_1 = \mathbf{s}_2 = (a, a)$

$\mathbf{r}_2 = (a, -a)$