



## **Details for Users**

### **Ordering Information**

Catalogue-Number: TC64-# (please replace # by cap size)

Cap sizes are given in cm head circumference:

- Adult caps: 54, 56, 58, 60, 62 (average male: 58, average female: 54)
- Children caps: 50 (5 years), 52 (7 years), 54 (11 years)
- Infant caps: 42, 44 (7 month), 46, 48 (3 years)

**Note:** *We supply cap-cuts for Asian Headshapes upon request. If you want this, please mention on your order.*

Catalogue-Number comprises cap as described in this document, serial number and this document. Please order other accessories / consumables extra.

### **Cap**

Subtemporal cap with integrated chin belt  
AsiaCut upon request

### **Electrodes**

Tin Electrodes B08, cable colours according to above graphic. No labels.

2 cable trees leave the cap plait-like behind the ears, pointing downwards. 30 cm beyond cap rim there is a crossing-point. Lengths of cable trees is approx. 120 cm.

### **Termination**

The cables are connected to 2 BrainAmp-connector boxes.

### **Theta/Phi-Coordinates**

Please find a table with Theta/Phi-Coordinates of all electrode sites at the end of this file.

**Table of Spherical (Theta/Phi) Coordinates**

<b>Channel-number</b>	<b>Name</b>	<b>Theta</b>	<b>Phi</b>
1	Fp1	-90	-72
2	Fp2	90	72
3	F3	-60	-51
4	F4	60	51
5	C3	-45	0
6	C4	45	0
7	P3	-60	51
8	P4	60	-51
9	O1	-90	72
10	O2	90	-72
11	F7	-90	-36
12	F8	90	36
13	T7	-90	0
14	T8	90	0
15	P7	-90	36
16	P8	90	-36
17	Fz	45	90
18	Cz	0	0
19	Pz	45	-90
20	IO	?? 130	?? 80
21	FC1	-31	-46
22	FC2	31	46
23	CP1	-31	46
24	CP2	31	-46
25	FC5	-69	-21
26	FC6	69	21
27	CP5	-69	21
28	CP6	69	-21
29	FT9	-113	-18
30	FT10	113	18
31	TP9	-113	18
32	TP10	113	-18
33	F1	-49	-68
34	F2	49	68
35	C1	-23	0
36	C2	23	0
37	P1	-49	68
38	P2	49	-68
39	AF3	-74	-68
40	AF4	74	68
41	FC3	-49	-29
42	FC4	49	29
43	CP3	-49	29
44	CP4	49	-29
45	PO3	-74	68
46	PO4	74	-68
47	F5	-74	-41
48	F6	74	41
49	C5	-68	0
50	C6	68	0
51	P5	-74	41

52	P6	74	-41
53	AF7	-90	-54
54	AF8	90	54
55	FT7	-90	-18
56	FT8	90	18
57	TP7	-90	18
58	TP8	90	-18
59	PO7	-90	54
60	PO8	90	-54
61	Fpz	90	90
62	CPz	22	-90
63	POz	67	-90
64	Oz	90	-90
Gnd	Afz	67	90
Ref	FCz	23	90

These values are standardized to a Theta of 90° for the plane through Fpz, T7, T8, Oz.

The signs follow this convention:

