Symptom:

P0563-BATTERY VOLTAGE HIGH

When Monitored and Set Condition:

P0563-BATTERY VOLTAGE HIGH

When Monitored: With the ignition on. Engine RPM greater than 1000 RPM. With no other charging system codes set.

Set Condition: The battery sensed voltage is 1 volt above the charging goal for 13.47 seconds. The PCM senses the battery voltage turns off the field driver and senses the battery voltage again. If the voltages are the same, the code is set.

POSSIBLE CAUSES
GOOD TRIP EQUAL TO ZERO
GENERATOR OPERATION
(K125) GEN FIELD CONTROL CIRCUIT SHORTED TO BATTERY VOLTAGE
PCM

TEST	ACTION	APPLICABILITY
1	**NOTE: Make sure the Battery is in good condition. Using the Midtronics Battery Tester, test the Battery before continuing.** **NOTE: Inspect the vehicle for after market accessories that may exceed the Generator System output.** Turn the ignition off. **NOTE: Make sure the generator drive belt is in good operating condition.** **NOTE: Inspect the fuses in the PDC. If a fuse is found to be open use the wiring diagram/schematic as a guide, inspect the wiring and connectors for damage.** Ignition on, engine not running. With the DRBIII®, read DTCs and record the related Freeze Frame data. Is the Good Trip Counter displayed and equal to zero? Yes → Go To 2 No → Refer to the INTERMITTENT CONDITION Symptom (Diagnostic Procedure). Perform POWERTRAIN VERIFICATION TEST VER - 3.	All
2	Turn the ignition off. Disconnect the Generator Field harness connector. Using a 12-volt test light, jump it across the Generator Field harness connector. Ignition on, engine not running. With the DRBIII®, actuate the Generator Field Control circuit. Does the test light illuminate brightly and flash on and off? Yes → Replace the Generator. Perform POWERTRAIN VERIFICATION TEST VER - 3. No → Go To 3	All