



L920

Extension Bases for A920

PAX L920 extension bases come in two versatile options: a charging base or a multifunctional wireless base. The L920 extension bases are designed to add functionality and optimize the performance of the A920. The charging base is exclusively for charging, whereas the multifunctional wireless base provides multiple extension ports and communication options while simultaneously charging the A920.



Perfect Companion for A920

Ergonomic Design

6-pin POGO pin Connection

2 Versions Available

L920

SPECIFICATIONS



L920-BC

L920-BE

Product Type	Charging Base	Wireless Base
RS232	N/A	Default (RJ45 x 1)
LAN	N/A	RJ45 x 1 (Ethernet, 100M)
USB	Micro USB x 1 (Charging Only)	Micro USB x 1 (Charging Only) Micro USB x 1 (Device) USB Type-A x 1 (HOST)
Power Supply	5V/2A (Micro USB)	5V/2A (Micro USB)
Weight	3.49 oz	4.73 oz
Operating Environment	Operating Temperature: 0°C ~ 50°C Relative Humidity: 5% ~ 95% (non-condensing)	Operating Temperature: 0°C ~ 50°C Relative Humidity: 5% ~ 95% (non-condensing)
Storage Conditions	-20°C ~ 70°C Relative Humidity: 5% ~ 95% (non-condensing)	-20°C ~ 70°C Relative Humidity: 5% ~ 95% (non-condensing)

This document is provided to you for informational purposes only. All features and specifications are subject to change without notice. PAX and the PAX logo are either trademarks or registered trademarks of PAX Technology Limited in China and/or other countries. All other trademarks or brand names are the properties of their respective holders. © 2020 PAX Technology Limited. All rights reserved.