

Actual-size screw key

Print at 100% (actual size). Turn off Fit, Shrink and Scale to page.

Check the 50 mm ruler and the 20 × 20 mm square with a real ruler before use.

Measure from the middle of the printed lines. A screen is not a size reference.



20 × 20 mm
check square

Lay each screw on its drawing with the underside of the head on the start line.

The length doesn't include the head. Outlines show the largest head that fits:

M2 heads up to 3.8 mm across and 2 mm tall; M3 socket heads up to 5.5 mm across and 3 mm tall.

M2 × 6 · 16 used




M2 × 8 · 9 used



M2 × 10 · 8 used



M2 × 12 · 4 used



Three of the 9 M2 × 8 are button heads (drawn: 3.5 × 1.3 mm).
They fix the head to its shelf, without washers.

M3 × 10 countersunk · 3 used



Length 10 mm including the head; 90° head, 6 mm across.

M3 × 6 · 7 used



M3 × 8 · 7 used



M3 × 10 · 2 used



M3 × 12 · 30 used



M3 × 14 · 2 used



M3 × 16 · 7 used



M3 × 18 · 2 used



M3 × 20 · 2 used



Nuts, seen from above (ordinary hex nuts)



M2 nuts · 37 used



M3 nuts · 62 used

Washers: inside and outside diameter



M2 metal: 4, 0.25 mm thick



M3: 8, 0.53 mm thick

M2 nuts are 4 mm across the flats and 1.6 mm thick.

Servo center screws · 3

These come with the servos and aren't drawn here.

Keep each one with its servo horn.

Don't use M2 screws in their place.