

MaxNet Connections from DB 37 Cable		
DB Pin #	MaxNet Pin #	Component
8	58 (GND)	Rotation +/- Limit GND
9	58 (GND)	Rotation Pot. GND
10	58 (GND)	Translation + Limit GND, Foil 3 GND
11	58 (GND)	Foils 2 and 4 GND
12	58 (GND)	Foil 1 GND, Translation - Limit GND
13	58 (GND)	Trans. Pot. GND
20	34 (5V)	Rotation +/- Limit PWR
21	External 2Reference	Rotation Potentiometer PWR
22	34 (5V)	Trans + Limit PWR, Foil 3 PWR
23	34 (5V)	Foils 2 and 4 PWR
24	34 (5V)	Foil 1 PWR, Translation - Limit PWR
25	External Reference	Translation Pot. PWR
28	18 (x + limit)	Rotation + Limit
29	68 (x - limit)	Rotation - Limit
30	93 (ADC 1)	Rotation Potentiometer Wiper
31	19 (y + limit)	Translation + Limit (Extended)
32	39 (IO2)	Foil 3 Switch
33	88 (IO1)	Foil 2 Switch
34	89 (IO3)	Foil 4 Switch
35	38 (IO0)	Foil 1 Switch
36	69 (y - limit)	Translation - Limit (Retracted)
37	43 (ADC 0)	Translation Potentiometer Wiper

Stepping Motor Drive Connections			
	MaxNet Pin	Drive Output	Drive
Wire #1 of 4	34 (5 Volts)	Pul+(+5V)	M6128 (Rot.)
Wire #2 of 4	Pin 81 (X Step)	Pul-(Pul)	M6128 (Rot.)
Wire #3 of 4	34 (5 Volts)	Dir+(+5V)	M6128 (Rot.)
Wire #4 of 4	Pin 74 (X Direction)	Dir-(Dir)	M6128 (Rot.)
Wire #1 of 4	NC	Ena	DM422C (Trans.)
Wire #2 of 4	34 (5 Volts)	Opto	DM422C (Trans.)
Wire #3 of 4	Pin 75 (Y Direction)	Dir	DM422C (Trans.)
Wire #4 of 4	Pin 82 (Y Step)	Pul	DM422C (Trans.)
NOTES: PIN 34 (5V) CAN SUPPLY ½ AMP I/O PINS CAN ACCEPT ±10V			

MOTOR WINDING CONNECTIONS				
	A+	A-	B+	B-
Translation	Black	Blue	Green	Red
Rotation	Black	Green	Red	Blue