

Is Now Part of



ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at www.onsemi.com

Please note: As part of the Fairchild Semiconductor integration, some of the Fairchild orderable part numbers will need to change in order to meet ON Semiconductor's system requirements. Since the ON Semiconductor product management systems do not have the ability to manage part nomenclature that utilizes an underscore (_), the underscore (_) in the Fairchild part numbers will be changed to a dash (-). This document may contain device numbers with an underscore (_). Please check the ON Semiconductor website to verify the updated device numbers. The most current and up-to-date ordering information can be found at www.onsemi.com. Please email any questions regarding the system integration to Fairchild guestions@onsemi.com.

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officer



August 2013

FFB3946 / FMB3946 NPN & PNP General-Purpose Amplifier


Description

This complementary device is designed for use as a general-purpose amplifier and switch, The useful dynamic range extends to 100 mA as a switch and 100 MHz as an amplifier. Sourced from Process 23 and 66. See FFB3904 (NPN) and FFB3906 (PNP) for characteristics.


Ordering Information

| Part Number | Top Mark | Package | Packing Method |
|-------------|----------|---------|----------------|
| FFB3946 | AB | SC70 6L | Tape and Reel |
| FMB3946 | 002 | SSOT 6L | Tape and Reel |

Block Diagram




FFB3946 Device Package




FFB3946 Internal Connection

TRANSISTOR TYPE
C1 B1 E1 NPN
C2 B2 E2 PNP



FMB3946 Device Package



FMB3946 Internal Connection

Figure 1. Block Diagram

Absolute Maximum Ratings(1)

Stresses exceeding the absolute maximum ratings may damage the device. The device may not function or be operable above the recommended operating conditions and stressing the parts to these levels is not recommended. In addition, extended exposure to stresses above the recommended operating conditions may affect device reliability. The absolute maximum ratings are stress ratings only. Values are at $T_A = 25$ °C unless otherwise noted.

| Symbol | Parameter | Value | Units |
|-----------------------------------|----------------------------------|-------------|-------|
| V _{CEO} | Collector-Emitter Voltage | 40 | V |
| V _{CBO} | Collector-Base Voltage | 40 | V |
| V _{EBO} | Emitter-Base Voltage | 5.0 | V |
| I _C | Collector Current - Continuous | 200 | mA |
| T _J , T _{stg} | Junction and Storage Temperature | -55 to +150 | °C |

Notes:

- 1. These ratings are based on a maximum junction temperature of 150 $^{\circ}\text{C}.$
- 2. These are steady-state limits. Fairchild Semiconductor should be consulted on applications involving pulsed or low-duty cycle operations.
- 3. All voltages (V) and currents (A) are negative polarity for PNP transistors.
- 4. These ratings are limiting values above which serviceability of any semiconductor advice may be impaired.

Thermal Characteristics(2)

Values are at $T_A = 25$ °C unless otherwise noted.

| Symbol | Parameter | Maxi | Units | |
|-----------------|---|---------|---------|--------|
| | | FFB3946 | FMB3946 | Ullits |
| P _D | Total Device Dissipation | 300 | 700 | mW |
| | Derate Above 25°C | 2.4 | 5.6 | mW/°C |
| $R_{\theta JA}$ | Thermal Resistance, Junction to Ambient | 415 | 180 | °C/W |

Note:

2. PCB board size: FR-4 76 x 114 x 0.6T mm³ (3.0 inch x 4.5 inch x 0.062 inch) with minimum land pattern size.

Electrical Characteristics(3)

Values are at $T_A = 25$ °C unless otherwise noted.

| Symbol | Parameter | Test Condition | Min. | Тур. | Max. | Units |
|----------------------|--------------------------------------|--|------|------|------|-------|
| Off Charac | cteristics | | • | l | l | |
| V _{(BR)CEO} | Collector-Emitter Breakdown Voltage | $I_C = 10 \text{ mA}, I_B = 0$ | 40 | | | V |
| V _{(BR)CBO} | Collector-Base Breakdown Voltage | $I_C = 10 \mu A, I_E = 0$ | 40 | | | V |
| V _{(BR)EBO} | Emitter-Base Breakdown Voltage | $I_E = 10 \mu A, I_C = 0$ | 5.0 | | | V |
| I _{CBO} | Collector Cut-Off Current | $V_{CB} = 30 \text{ V}, I_{E} = 0$ | | | 50 | nA |
| I _{EBO} | Emitter Cut-Off Current | $V_{EB} = 4.0 \text{ V}, I_{C} = 0$ | | | 50 | nA |
| On Charac | teristics | | | • | | |
| h _{FE} | DC Current Gain | $I_C = 100 \mu A, V_{CE} = 1.0 V$ | 40 | | | |
| | | $I_C = 1.0 \text{ mA}, V_{CE} = 1.0 \text{ V}$ | 70 | | | |
| | | $I_C = 10 \text{ mA}, V_{CE} = 1.0 \text{ V}$ | 100 | | 300 | |
| | | $I_C = 50 \text{ mA}, V_{CE} = 1.0 \text{ V}$ | 60 | | | |
| | | I _C = 100 mA, V _{CE} = 1.0 V | 30 | | | |
| V _{CE(sat)} | Collector-Emitter Saturation Voltage | I _C = 10 mA, I _B = 1.0 mA | | | 0.25 | V |
| V _{BE(sat)} | Base-Emitter Saturation Voltage | $I_C = 10 \text{ mA}, I_B = 1.0 \text{ mA}$ | | | 0.9 | V |
| | nal Characteristics | | | • | | |
| f _T | Current Gain-Bandwidth Product | I _C = 10 mA, V _{CE} = 20 V, f = 100 MHz | | 200 | | MHz |
| C _{obo} | Output Capacitance | V _{CB} = 5.0 V, f = 100 kHz | | 4.5 | | pF |
| C _{ibo} | Input Capacitance | $V_{CB} = 0.5 \text{ V}, f = 100 \text{ kHz}$ | | 10 | | pF |

Note:

3. All voltages (V) and currents (A) are negative polarity for PNP transistors.

Physical Dimensions

SC70 6L




Figure 2. 6-LEAD, SC70, EIAJ SC-88, 1.25 MM WIDE (ACTIVE)

Package drawings are provided as a service to customers considering Fairchild components. Drawings may change in any manner without notice. Please note the revision and/or date on the drawing and contact a Fairchild Semiconductor representative to verify or obtain the most recent revision. Package specifications do not expand the terms of Fairchild's worldwide terms and conditions, specifically the warranty therein, which covers Fairchild products.

Always visit Fairchild Semiconductor's online packaging area for the most recent package drawings: http://www.fairchildsemi.com/dwg/MA/MAA06A.pdf.

For current tape and reel specifications, visit Fairchild Semiconductor's online packaging area:

http://www.fairchildsemi.com/packing_dwg/PKG-MAA06A_JCET.pdf.

Physical Dimensions (Continued)

SSOT 6L




Figure 3. 6-LEAD, SUPERSOT6, JDEC MO-193, 1.6 MM WIDE (ACTIVE)

Package drawings are provided as a service to customers considering Fairchild components. Drawings may change in any manner without notice. Please note the revision and/or date on the drawing and contact a Fairchild Semiconductor representative to verify or obtain the most recent revision. Package specifications do not expand the terms of Fairchild's worldwide terms and conditions, specifically the warranty therein, which covers Fairchild products.

Always visit Fairchild Semiconductor's online packaging area for the most recent package drawings: http://www.fairchildsemi.com/dwg/MA/MA06A.pdf.

For current tape and reel specifications, visit Fairchild Semiconductor's online packaging area:

http://www.fairchildsemi.com/packing_dwg/PKG-MA06A.pdf.





TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

 Build it Now™
 GreenBridge™

 CorePLUS™
 Green FPS™

 CorePOWER™
 Green FPS™ e-Series™

 $\begin{array}{lll} \textit{CROSSVOLT}^{\text{\tiny{TM}}} & \textit{Gmax}^{\text{\tiny{TM}}} \\ \textit{CTL}^{\text{\tiny{TM}}} & \textit{GTO}^{\text{\tiny{TM}}} \\ \textit{Current Transfer Logic}^{\text{\tiny{TM}}} & \textit{IntelliMAX}^{\text{\tiny{TM}}} \end{array}$

DEUXPEED® ISOPLANAR™
Dual Cool™ Making Small Speakers Sound Louder

EcoSPARK[®]
EfficientMax[™]
ESBC[™]

ESBC™ ® Fairchild®

Fairchild Semiconductor[®]
FACT Quiet Series[™]
FACT[®]

FACT[®]
FAST[®]
FastvCore™
FETBench™

PowerTrench® PowerXS™

Programmable Active Droop™

QFET[®] QS™ Quiet Series™ RapidConfigure™

Saving our world, 1mW/W/kW at a time™ SignalWise™

SignalWise™ SmartMax™ SMART START™

Solutions for Your Success™

SPM® STEALTH™ SuperFET® SuperSOT™-3 SuperSOT™-6 SuperSOT™-8 SupreMOS® SyncFET™ TinyBoost®
TinyBoost®
TinyBuck®
TinyCalc™
TinyLogic®
TiNYOPTO™
TinyPower™
TinyPower™

Sync-Lock™

TinyWire™
TranSiC™
TriFault Detect™
TRUECURRENT®*
μSerDes™

SerDes®
UHC®
Ultra FRFET™
UniFET™
VCX™
VisualMax™
VoltagePlus™

XS™

and Better™

MICROCOUPLER™

MegaBuck™

MicroFET™

MicroPak™

MicroPak2™

MillerDrive™

MotionMax™

OPTOLOGIC®

OPTOPLANAR®

mWSaver⁶

OptoHiT™

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein

- Life support devices or systems are devices or systems which, (a) are
 intended for surgical implant into the body or (b) support or sustain
 life, and (c) whose failure to perform when properly used in
 accordance with instructions for use provided in the labeling, can be
 reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

PRODUCT STATUS DEFINITIONS

Definition of Terms

| Definition of Terms | | | | |
|--------------------------|-----------------------|---|--|--|
| Datasheet Identification | Product Status | Definition | | |
| Advance Information | Formative / In Design | Datasheet contains the design specifications for product development. Specifications may change in any manner without notice. | | |
| Preliminary | First Production | Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design. | | |
| No Identification Needed | Full Production | Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design. | | |
| Obsolete | Not In Production | Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only. | | |

Rev. 165

^{*} Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

ON Semiconductor and in are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdt/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and exp

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada
Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81–3–5817–1050

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative