

PP_verde

```
1|          10|          20|          30|          40|          50|          60|          70|          80|          90|          100|          110|
1  (* ===== *)
2  (* SECCIÓN: PP_verde *)
3  (* Gestion del pick and place para piezas verdes *)
4  (* ===== *)
5
6  IF IN_Vision_Sensor_1_Bool_2 and IN_Vision_Sensor_1_Bool_1 THEN
7  OUT_Emitter4_Emit:= TRUE;
8  END_IF;
9
10 IF OUT_Emitter4_Emit then
11 SET (OUT => OUT_BeltConveyor_4_2);
12 END_IF;
13
14 F_TRIG_12 (CLK := IN_Diffuse_Sensor_12);
15
16 IF F_TRIG_12.Q THEN
17 RESET (OUT =>OUT_BeltConveyor_4_2);
18 SET(OUT => OUT_Two_Axis_Pick_Place_1_Z);
19 OUT_Emitter4_Emit:= FALSE;
20 END_IF;
21
22
23 R_TRIG_26 (CLK := IN_TwoAxis_PickPlace_1_Detected );
24
25 IF R_TRIG_26.Q THEN
26 set ( OUT => OUT_Two_Axis_Pick_Place_1_Grab);
27 END_IF;;
28
29 R_TRIG_25 (CLK := OUT_Two_Axis_Pick_Place_1_Grab);
30
31 IF R_TRIG_25.Q THEN
32 RESET( OUT => OUT_Two_Axis_Pick_Place_1_Z);
33
34 END_IF;
35
36 F_TRIG_13 (CLK := IN_TwoAxis_PickPlace_1_Moving_Z);
37
38 IF F_TRIG_13.Q THEN
39 Set ( OUT_Two_Axis_Pick_Place_1_X );
40 END_IF;
41
42 F_TRIG_14 (CLK := IN_Diffuse_Sensor_18);
43
44
45 IF OUT_TWO_AXIS_PICK_PLACE_1_X AND IN_Right_Positioner_2_Clamped THEN
46 Set ( OUT_Two_Axis_Pick_Place_1_Z );
47 END_IF;;
48
49 F_TRIG_15 (CLK := IN_TwoAxis_PickPlace_1_Moving_Z);
50
51 IF OUT_Two_Axis_Pick_Place_1_Z AND OUT_Two_Axis_Pick_Place_1_X AND F_TRIG_15.Q then
52 Reset (OUT_Two_Axis_Pick_Place_1_Grab);
53 RESET( OUT => OUT_Two_Axis_Pick_Place_1_Z);
54 END_IF;
55
56
57 IF F_TRIG_14.Q THEN
58 SET ( OUT_Right_Positioner_2_Clamp);
59 END_IF;
60
61
62
63 F_TRIG_16 (CLK := IN_TwoAxis_PickPlace_1_Moving_Z);
64
65 IF F_TRIG_16.Q AND OUT_Right_Positioner_2_Clamp THEN
66 RESET( OUT => OUT_Two_Axis_Pick_Place_1_X);
67 END_IF;;
68
69 F_TRIG_19 (CLK := IN_TwoAxis_PickPlace_1_Moving_X);
70
71 IF F_TRIG_19.Q AND OUT_Right_Positioner_2_Clamp THEN
72 RESET ( OUT_Right_Positioner_2_Clamp);
73 SET (OUT_Right_Positioner_2_Raise);
74 END_IF;
75
76 F_TRIG_18 (CLK := IN_Diffuse_Sensor_19);
77
78 IF F_TRIG_18.Q THEN
79 RESET(OUT=>OUT_Right_Positioner_2_Raise);
80 RESET(OUT=>OUT_Right_Positioner_2_Clamp);
81 END_IF;
82
83
84
```