DIHWorld Audio

Template Starter Pack

Compact customer edition

Starter workflows only. They contain no case-study results, guaranteed output targets, or back-office client material.

More current information: dihworldaudio.com/#documentation

DIHWorld Audio - Cascading Effects Bus Template

Effects -> Width -> Color -> Collection -> Master | Enhanced for ANKH family placement Enhanced: 2026-10-19

User authority: `DIHWorld_Audio_Complete_Manual_CURRENT.pdf`

Current product behavior: ANUBIS has a named stereo Sidechain bus with separate Key/Duck functions; DEBO uses the balanced canonical bank; TRIPLER uses the repaired clean left/right harmony path; SESHAT named views hide unrelated panels; AU and Drum Morpher are current registered instruments.

Use this when a session needs three deliberate parallel lanes feeding one clean collection point. The buses carry the work; source tracks stay lean.

Core Operating Law

- Start buses and sends around -18 dB as a safe audition point, not a fixed operating target.
- In normal use, many DIH processors will feel optimal around -14 to -10 dB, depending on source, family, and FieldState.
- Some plugins operate cleanly at unity when the use case supports it; approve unity only after bypass/output matching and no clipping, ringing, or level jump.
- Output-match to bypass before approving tone, width, spatial placement, or loudness.
- Use up to three active processors on a track or bus. More than three is an audition rack, not a committed mix chain. For Color and Effects, the normal committed choice is one primary stage or independent parallel returns.
- SESHAT is observation only and may sit last on the print/master endpoint.
- Presets never control Input, Output, Mix, Bypass, or protected ceiling/safety controls.
- Keep each plugin in its primary family when possible; if moved, it replaces a slot instead of extending the chain.
- SLOTMACHINE is always last in any chain that uses it. ANKH is the containment authority.

Architecture

```
SOURCE TRACKS
  Send 1 start -18 dB -> EFFECTS BUS [FX_SPATIAL]
  Send 2 start -18 dB -> WIDTH BUS   [DIMENSIONAL_IMPACT_MOVE]
  Send 3 start -18 dB -> COLOR BUS   [COLOR_AMP_TAPE]
  Optimize commonly toward -14 to -10 dB; unity is valid only when clean.

EFFECTS BUS + WIDTH BUS + COLOR BUS
  -> COLLECTION CHANNEL              [no inserts, summing only]
  -> PRINT / MASTER BUS
  -> Stereo Out
```

Bus Chains

Bus	Three-active starter chain	Substitutions / notes
EFFECTS BUS	Independent 100% wet NTRSTLLR, Cathedral, and SacredVerb returns	Choose the return for the required space; do not serially stack reverbs. Route the chosen returns to COLLECTION.
WIDTH BUS	DEPTH_IMPACT_HYBRID_X **or** PARALLAX **or** NSR	Choose one primary width move. SERQET replaces PARALLAX for a creative move; it does not extend the chain. Mono-check before print.

Bus	Three-active starter chain	Substitutions / notes
COLOR BUS	`Chain: Music Bus Foundation` in KHEPRI -> APIS	PTAHTUBE or SOVEREIGN replaces APIS when a second color voice is required; do not run all three by default.
COLLECTION	No inserts	Collection is a summing point only. If it needs tone, the tone belongs on a lane above or the print bus below.

Print / Master Choices

Use case	Active chain	When
Clean	SPHYNX -> MAAT -> ANKH -> SESHAT	Prepare, balance, contain, then observe.
Authority	PLATINUM -> IMHOTEP -> ANKH -> SESHAT	Master authority plus macro field structure.
Loud / modern	SPHYNX -> HORIZON_X -> ANKH -> SESHAT	Lift and finish before containment.
Dimensional	DEPTH_IMPACT_HYBRID_X -> MAAT -> ANKH -> SESHAT	Front/back placement before balance and containment.
Color master	KHEPRI or SOVEREIGN -> MAAT -> ANKH -> SESHAT	One color stage, one balance stage, then containment.

Factory Recall

Use `06_Optimized_Preset_Recall_Map_CURRENT.md` for the exact current-program names. The Color Bus default is `Chain: Music Bus Foundation` in KHEPRI; `ACOUSTIC CLARITY [Stereo]` in WPR is its transformer/ribbon alternative, not an additional insert.

Send Discipline

From	To	Level	Rule
Every source track	EFFECTS BUS	Start -18; -14 to -10 usual; unity clean	Spatial material only. Do not hide color or dynamics here.
Every source track	WIDTH BUS	Start -18; -14 to -10 usual; unity clean	Width/depth moves only. Collapse-check before printing.
Every source track	COLOR BUS	Start -18; -14 to -10 usual; unity clean	Harmonic color lane. Pick three active processors maximum.
All buses	COLLECTION	unity route	No inserts on collection.

Output Approval

- Match the delivery specification for the project or platform; this template does not impose a fixed RMS, peak, or crest target.
- Preserve musical dynamics and confirm zero unintended clipping.
- Compare at matched loudness before approving the print.

DIHWorld Audio - 7 Main Bus Template

Drums | Bass | Vocal | Instrument | Effects | Color | Dynamics -> Master Enhanced: 2026-10-19

User authority: `DIHWorld_Audio_Complete_Manual_CURRENT.pdf`

Current product behavior: ANUBIS has a named stereo Sidechain bus with separate Key/Duck functions; DEBO uses the balanced canonical bank; TRIPLER uses the repaired clean left/right harmony path; SESHAT named views hide unrelated panels; AU and Drum Morpher are current registered instruments.

Use this as the main multitrack routing template. Each source track feeds one musical family bus; optional parallel buses add effects, color, or dynamics without overloading individual tracks.

Core Operating Law

- Start buses and sends around -18 dB as a safe audition point, not a fixed operating target.
- In normal use, many DIH processors will feel optimal around -14 to -10 dB, depending on source, family, and FieldState.
- Some plugins operate cleanly at unity when the use case supports it; approve unity only after bypass/output matching and no clipping, ringing, or level jump.
- Output-match to bypass before approving tone, width, spatial placement, or loudness.
- Use up to three active processors on a track or bus. More than three is an audition rack, not a committed mix chain.
- SESHAT is observation only and may sit last on the print/master endpoint.
- Presets never control Input, Output, Mix, Bypass, or protected ceiling/safety controls.
- Keep each plugin in its primary family when possible; if moved, it replaces a slot instead of extending the chain.
- SLOTMACHINE is always last in any chain that uses it. ANKH is the containment authority.

Architecture

```
Kick, Snare, OH, Room      -> DRUMS BUS
Bass DI, Sub               -> BASS BUS
Lead Vox, BG Vox           -> VOCAL BUS
Guitars, Keys, Synths      -> INSTRUMENT BUS
FX sends                   -> EFFECTS BUS
Color sends                -> COLOR BUS
Parallel compression       -> DYNAMICS BUS

All seven buses -> PRINT / MASTER BUS -> Stereo Out
```

DIH 08 Logic package collector routing

The current downloadable Logic package uses three structural collectors after the seven musical buses:

- Bus 12 / Aux 12 collects DRUM and BASS, then feeds Bus 9 MASTER BUS.
- Bus 13 / Aux 13 collects COLOR, then feeds Bus 9 MASTER BUS.
- Bus 14 / Aux 14 collects EFFECTS, WIDTH, and the independent spatial returns, then feeds Bus 9 MASTER BUS.

NTRSTLLR Delay, Cathedral Room, and SacredVerb are individual shared spatial returns on Bus 16, Bus 17, and Bus 18. Each return should be treated as a 100% wet aux and should output to Bus 14, not directly to the master. This keeps the main seven-bus architecture readable while avoiding one overloaded serial effects bus.

Seven Bus Working Chains

Bus	Receives	Three-active starter chain	Best substitutions
DRUMS	Kick, snare, rooms, percussion	DIH_DRUM_MORPHER -> `TIGHT BUS GLUE [Stereo]` in DRUMKRUSHGLUE	Add ANUBIS only for a defined transient/duck need. `DRUM OVERHEAD PHI [Stereo]` in WPR belongs on an overhead/room return, not the full drum bus.

Bus	Receives	Three-active starter chain	Best substitutions
BASS	Bass DI, sub, low-end instruments	`KHEPRI BASS FOUNDATION` -> `MONOLITH BODY WEIGHT`	DEPTH_BOOST_PRO replaces MONOLITH for definition. NTRPL is an optional earlier Harmonics & Pitch insert, not a Bass-family bus stage.
VOCAL	Lead, backgrounds, harmonies	`Vocal Reveal [Stereo]` in SILVER; optional `Body Open` in GOLD **or** `VOCAL INTIMACY [Stereo]` in WPR	SILVER is the baseline. GOLD and WPR are mutually exclusive color choices after level-matched comparison. TRIPLER is BG/harmony only. EchoLocate is for localization.
INSTRUMENT	Guitars, keys, piano, synths	`Chain: Music Bus Foundation` in KHEPRI -> APIS	`ACOUSTIC CLARITY [Stereo]` in WPR replaces KHEPRI for ribbon/mic definition. THOTH or TEHUTI replaces a color slot when harmonic pitch is the actual problem.
EFFECTS	FX returns and spatial sends	Optional serial lane, or clean collector feed to Bus 14	Preferred DIH 08 setup uses Bus 16 NTRSTLLR DELAY, Bus 17 CATHEDRAL ROOM, and Bus 18 SACREDVERB as independent returns into Bus 14. Do not stack PARALLAX here if a WIDTH bus exists; use the WIDTH bus.
COLOR	Vocal and instrument color sends	`Chain: Music Bus Foundation` in KHEPRI -> APIS	PTAHTUBE or SOVEREIGN replaces APIS when a distinct second color decision is approved. PLATINUM belongs to Mastering Core with secondary color support.
DYNAMICS	Parallel dynamics send	`DEBO MIX BUS SETTLE [Stereo]` -> `LOOKOUT MIX BUS COMPOSURE`	Use `DEBO DRUM REINFORCE [Stereo]` -> `LOOKOUT DRUM SNAP LOCK` only for drums. SPHYNX belongs on the print/master chain unless this bus is acting as mix-bus preparation.

Print / Master Choices

Use case	Active chain	When
Clean	SPHYNX -> MAAT -> ANKH -> SESHAT	Prepare, balance, contain, then observe.
Authority	PLATINUM -> IMHOTEP -> ANKH -> SESHAT	Master authority plus macro field structure.
Loud / modern	SPHYNX -> HORIZON_X -> ANKH -> SESHAT	Lift and finish before containment.
Dimensional	DEPTH_IMPACT_HYBRID_X -> MAAT -> ANKH -> SESHAT	Front/back placement before balance and containment.
Color master	KHEPRI or SOVEREIGN -> MAAT -> ANKH -> SESHAT	One color stage, one balance stage, then containment.

Preset Recall

Exact current-program selections, approved alternates, and the Chicago/Bay/Top Score Drum Morpher kit roles are maintained in `06_Optimized_Preset_Recall_Map_CURRENT.md`.

Routing Rules

- Seven musical buses are enough for this formation. New auxes require a written reason in the deployment register unless they are part of the verified DIH 08 collector/spatial-return design.
- Bus 12, Bus 13, and Bus 14 are structural collectors, not creative chains. Keep them clean unless a future deployment note explicitly changes their purpose.
- Family buses may receive up to three active inserts; source tracks should usually carry zero to two.
- Use COLOR and EFFECTS buses for parallel tone and space instead of building long chains on every track. For shared space, prefer separate sends to NTRSTLLR Delay, Cathedral Room, and SacredVerb, then collect those returns through Bus 14.

- If a plugin is used outside its home family, document it as a replacement: source problem, chosen substitute, and bypass-matched result.

DIHWorld Audio - FAMILY AFFAIR Use Case Demo Template

One-session Logic demo featuring all 42 plugins Enhanced: 2026-10-19

User authority: `DIHWorld_Audio_Complete_Manual_CURRENT.pdf`

Current product behavior: ANUBIS has a named stereo Sidechain bus with separate Key/Duck functions; DEBO uses the balanced canonical bank; TRIPLER uses the repaired clean left/right harmony path; SESHAT named views hide unrelated panels; AU and Drum Morpher are current registered instruments.

This template turns the full DIHWorld Audio suite into one clear family demo. It is not a permission slip to stack every processor on a record. Every plugin appears in the session, but each lane stays organized by family, and the demo moves through the families one scene at a time.

Core Operating Law

- Start buses and sends around -18 dB as a safe audition point, not a fixed operating target.
- In normal use, many DIH processors will feel optimal around -14 to -10 dB, depending on source, family, and FieldState.
- Output-match to bypass before approving tone, width, spatial placement, or loudness.
- Use up to three active processors on a track or bus. Extra plugins in this template are demo alternates, bypassed slots, or scene-based reveals.
- Keep each plugin in its primary family when possible. If moved, it replaces a slot instead of extending the chain.
- SLOTMACHINE is always last in any chain that uses it. ANKH is the containment authority.
- SESHAT is observation only and may sit last on the print/master endpoint.
- Presets never control protected Input, Output, Mix, Bypass/Power, or final ceiling/safety controls unless a plugin-specific canon explicitly makes that control part of the musical engine.

Use Case

Build one Logic session around a full-song reference or stem set. The listener hears the raw source first, then each DIHWorld family enters in order: drums, bass, vocals, instruments, effects, color, width, dynamics, creative transform, harmonic pitch, field balance, master structure, and observation.

The goal is to show the system as a family, not to compare it to outside brands. The proof is organized placement: each plugin has a job, a family home, and a moment in the demo.

Template Lane Order

Lane	Purpose	Starter chain	Demo note
DRUM	Drum identity and punch	Drum Morpher -> `TIGHT BUS GLUE [Stereo]` in DRUMKRUSHGLUE	Add ANUBIS only if transient guard is needed. `DRUM OVERHEAD PHI [Stereo]` in WPR is a separate room/overhead reveal.
BASS	Foundation and low-end shape	`KHEPRI BASS FOUNDATION` -> `MONOLITH BODY WEIGHT`	DEPTH_BOOST_PRO is the definition/weight reveal. NTRPL may precede this lane only as a Harmonics & Pitch source insert.
VOCAL	Lead and stack source tone	`Vocal Reveal [Stereo]` in SILVER; optional `Body Open` in GOLD **or** `VOCAL INTIMACY [Stereo]` in WPR	SILVER is the neutral baseline. GOLD and WPR are mutually exclusive color alternates. TRIPLER and EchoLocate remain separate BG-movement scenes.
INSTRUMENT	Music bed, keys, guitars, synths	`Chain: Music Bus Foundation` in KHEPRI -> APIS	`ACOUSTIC CLARITY [Stereo]` in WPR replaces KHEPRI when mic/ribbon definition is the point. Swap in THOTH or TEHUTI for corrective harmonic work.

Lane	Purpose	Starter chain	Demo note
EFFECTS	Space and reverb returns	Independent 100% wet NTRSTLLR, Cathedral, or SacredVerb return	Spatial lane only: select the return, do not serially stack it. Keep color and dynamics elsewhere.
COLOR	Parallel color and amp/tape authority	`Chain: Music Bus Foundation` in KHEPRI -> APIS	PTAHTUBE or SOVEREIGN replaces APIS for a deliberate second color decision.
WIDTH	Field width and dimensional movement	Depth Impact Hybrid X **or** PARALLAX **or** NSR	SERQET replaces PARALLAX for a creative width reveal; it does not extend the chain.
DYNAMICS	Parallel protection and movement	`DEBO MIX BUS SETTLE [Stereo]` -> `LOOKOUT MIX BUS COMPOSURE`	ANUBIS and DrumKrushGlue enter only where the source needs guard/glue.
CREATIVE	One special moment, not the whole mix	ARCHAEOLOGIST X -> SERQET -> SlotMachine	SlotMachine stays last.
MASTER BUS	Three-stage print chain	SPHYNX -> Maat -> ANKH -> SESHAT	PLATINUM, IMHOTEP, or Horizon X appear as bypassed alternates and replace a stage for their scene.

Demo Timeline

Section	Action	Families featured
Bars 1-16	Raw source, no DIH processing.	None; establish the before picture.
Bars 17-32	Bring in DRUM and BASS lanes.	DRUM_INSTRUMENT, BASS_LOW_END, selected DYNAMICS_GUARD.
Bars 33-48	Bring in VOCAL and INSTRUMENT lanes.	VOCAL_MIC_SOURCE, COLOR_AMP_TAPE, HARMONICS_PITCH.
Bars 49-64	Open EFFECTS and WIDTH sends.	FX_SPATIAL, DIMENSIONAL_IMPACT_MOVE, SERQET as width reveal.
Bars 65-80	Add COLOR and CREATIVE moments.	COLOR_AMP_TAPE, CREATIVE_TRANSFORM, FIELD_TONE_BALANCE.
Bars 81-96	Engage MASTER BUS clean chain.	MASTERING_CORE, MASTER_FIELD, UTILITY_OBSERVATION.
Bars 97-112	Print loud/modern reveal, then bypass-match.	HORIZON_X lift, ANKH containment, SESHAT confirmation.

All 42 Plugin Coverage

Primary family	Count	Plugins
VOCAL_MIC_SOURCE	6	GOLD, SILVER, WPR, AegisNova, TRIPLER, EchoLocate
DYNAMICS_GUARD	4	ANUBIS, OTIS, DeBo, LookOut
BASS_LOW_END	3	MARIANA, MONOLITH, DEPTH_BOOST_PRO
DRUM_INSTRUMENT	3	Drum Morpher, Ballpark, DrumKrushGlue
COLOR_AMP_TAPE	4	APIS, PtahTube, Khepri Sacred Tape Machine, SOVEREIGN
FIELD_TONE_BALANCE	2	AUSET, AUSAR
DIMENSIONAL_IMPACT_MOVE	3	Depth Impact Hybrid X, PARALLAX, NSR
FX_SPATIAL	3	NTRSTLLR, Cathedral, SacredVerb
HARMONICS_PITCH	4	Thoth, NTRPL, TEHUTI, AU

Primary family	Count	Plugins
CREATIVE_TRANSFORM	3	SlotMachine, ARCHAEOLOGIST X, SERQET
MASTERING_CORE	5	ANKH, SPHYNX, Maat, Horizon X, PLATINUM
MASTER_FIELD	1	IMHOTEP
UTILITY_OBSERVATION	1	SESHAT

Print Checklist

- Every plugin appears at least once in the session.
- No source track or bus has more than three active processors during a musical pass.
- Extra plugins are labeled as BYPASSED ALT, SCENE REVEAL, or QC ONLY.
- SESHAT is last and observation only.
- Match the project delivery specification; this template does not impose fixed RMS, peak, or crest targets. Confirm zero unintended clipping.
- Save two versions: `FAMILY_AFFAIR_TEMPLATE.logicx` and `FAMILY_AFFAIR_DEMO_PRINT.wav`.
- Record all current preset recalls using `06_Optimized_Preset_Recall_Map_CURRENT.md`.

DIHWorld Audio - Better Buses Template

Customer-safe Logic bus starters | Current ANKH families | Website template 4 Enhanced: 2026-10-19

User authority: `DIHWorld_Audio_Complete_Manual_CURRENT.pdf`

Current product behavior: ANUBIS has a named stereo Sidechain bus with separate Key/Duck functions; DEBO uses the balanced canonical bank; TRIPLER uses the repaired clean left/right harmony path; SESHAT named views hide unrelated panels; AU and Drum Morpher are current registered instruments.

Use this when you want a cleaner Logic mixer layout with descriptive bus names, short chains, and clear family placement. It is the practical companion to the 7 Main Bus Template: fewer mystery buses, fewer stacked inserts, and easier handoff to another mixer.

Core Operating Law

- Start buses and sends around -18 dB as a safe audition point, not a fixed operating target.
- In normal use, many DIH processors will feel optimal around -14 to -10 dB, depending on source, family, and FieldState.
- Some plugins operate cleanly at unity when the use case supports it; approve unity only after bypass/output matching and no clipping, ringing, or level jump.
- Output-match to bypass before approving tone, width, spatial placement, or loudness.
- Keep source tracks lean. Use buses for color, space, width, dynamics, and print decisions.
- Use up to three active processors on a source track or bus during a musical pass. Extra inserts are audition alternates, not the committed chain.
- SESHAT is observation only and may sit last on the print/master endpoint.
- ANKH is the final containment authority.

Better Bus Architecture

```
SOURCE TRACKS
  -> DRUM BUS
  -> BASS BUS
  -> LEAD VOCAL BUS
  -> BG VOCAL BUS
  -> INSTRUMENT BUS
  -> optional sends: FX BUS, COLOR BUS, WIDTH BUS, DYNAMICS BUS

FAMILY BUSES
  -> PRINT / MASTER BUS
  -> Stereo Out
```

Customer Bus Starters

Bus	Three-active starter	Best use	Notes
LEAD VOCAL BUS	`Vocal Reveal [Stereo]` in SILVER; optional `Body Open` in GOLD **or** `VOCAL INTIMACY [Stereo]` in WPR	Lead vocal source tone and protection	Gain-match SILVER and the selected color alternate. GOLD and WPR are alternatives, not a serial default.
BG VOCAL BUS	`Body Open` in GOLD -> TRIPLER	Stacks, doubles, localization	Use EchoLocate only when location is the musical decision. Keep lead diction clear.

Bus	Three-active starter	Best use	Notes
DRUM BUS	DIH_DRUM_MORPHER -> `TIGHT BUS GLUE [Stereo]` in DRUMKRUSHGLUE	Drum identity, punch, and glue	Use ANUBIS only where individual transient guard is needed.
BASS BUS	`KHEPRI BASS FOUNDATION` -> `MONOLITH BODY WEIGHT`	Low-end focus and foundation	DEPTH_BOOST_PRO can replace MONOLITH for definition. NTRPL is an optional earlier Harmonics & Pitch source insert.
INSTRUMENT BUS	`Chain: Music Bus Foundation` in KHEPRI -> APIS	Music-bed tone, body, and harmonic color	`ACOUSTIC CLARITY [Stereo]` in WPR replaces KHEPRI for ribbon/mic definition. THOTH or TEHUTI replaces a color slot when harmonic pitch is the actual problem.
FX BUS	Independent 100% wet NTRSTLLR, Cathedral, or SacredVerb returns	Shared spatial identity and room field	Select the return; do not serially stack reverbs.
COLOR BUS	`Chain: Music Bus Foundation` in KHEPRI -> APIS	Parallel tone and bus color	PTAHTUBE or SOVEREIGN replaces APIS for stronger color authority.
WIDTH BUS	DEPTH_IMPACT_HYBRID_X **or** PARALLAX **or** NSR	Width, placement, and front/back movement	SERQET can replace PARALLAX for a creative width move. Mono-check before print.
DYNAMICS BUS	`DEBO MIX BUS SETTLE [Stereo]` -> `LOOKOUT MIX BUS COMPOSURE`	Parallel guard and movement	Use the drum-specific DEBO/LOOKOUT pair only for drums. DRUMKRUSHGLUE belongs on drum glue when needed.

Print / Master Bus Choices

Goal	Chain	When
Clean print	SPHYNX -> MAAT -> ANKH -> SESHAT	Prepare, balance, contain, then observe.
Authority print	PLATINUM -> IMHOTEP -> ANKH -> SESHAT	Master authority plus macro field structure.
Loud / modern print	SPHYNX -> HORIZON_X -> ANKH -> SESHAT	Lift and finish without replacing ANKH.
Dimensional print	DEPTH_IMPACT_HYBRID_X -> MAAT -> ANKH -> SESHAT	Front/back placement before balance and containment.
Color master	KHEPRI or SOVEREIGN -> MAAT -> ANKH -> SESHAT	One color stage, one balance stage, then containment.

Handoff Labels

Label	Meaning
ACTIVE	Processor is part of the current musical pass.
BYPASSED ALT	Processor is present as a documented alternate, not active.
QC ONLY	Observation, metering, or validation only.
PRINT CHAIN	Final chain chosen for the bounce.

Approval Checklist

- Every bus has a clear musical reason.

- No source track is carrying a long chain that belongs on a family bus.
- COLOR, FX, WIDTH, and DYNAMICS are sends or parallel buses, not hidden source-track clutter.
- SESHAT is observation only.
- ANKH remains final containment authority.
- The final print is bypass/output matched before approval.
- Use `06_Optimized_Preset_Recall_Map_CURRENT.md` to document every approved factory recall in the Logic template.

DIHWorld Dynamics / Kick-Key / Duck Template

Current: 2026-10-19

Session lanes

Lane	Insert / Route	Starting action
Kick key	Send to named sidechain	Unity or pre-fader as needed
Bass target	ANUBIS	DUCK on; KEY optional
Music target	ANUBIS	Vocal sidechain; gentle Range
Reverb return	ANUBIS	KEY on from lead vocal
Drum parallel	`DRUMKRUSHGLUE PARALLEL KRUSH RETURN [Stereo]` or `DEBO DRUM REINFORCE [Stereo]` → `LOOKOUT DRUM SNAP LOCK`	Choose one parallel color/dynamics direction; blend below clean drums.
Dynamics bus	`DEBO MIX BUS SETTLE [Stereo]` → `LOOKOUT MIX BUS COMPOSURE`	Match the return to bypass before blending.
Print endpoint	SESHAT	Observation only

Kick-to-bass starting card

- Route kick to ANUBIS Sidechain.
- Enable DUCK for rhythmic clearance.
- Enable KEY only if kick should drive gate detection.
- Start with shallow Range.
- Set fast Attack and tempo-aware Release.
- Check mono and bypass-match.

Vocal-clearance starting card

- Insert ANUBIS on music or ambience target.
- Route lead vocal to Sidechain.
- Use DUCK for space around words.
- Use KEY on ambience returns that should open with the vocal.
- Keep Range gentle and Release natural.

Dynamics stack options

Goal	Suggested order	Note
Clean transient control	LOOKOUT → OTIS	Shape edge, then density
Pressure and body	OTIS → DEBO	Build gradually; Gain Match
Drum parallel impact	DRUMKRUSHGLUE → LOOKOUT	Blend beneath clean bus
Keyed ambience	ANUBIS → effect return	KEY only; no audible key
Rhythmic clearance	ANUBIS on target	DUCK from kick or vocal

Approval checklist

- Sidechain source is correct and audible to the detector.
- KEY and DUCK states match the intended behavior.

- Range is no deeper than required.
- Attack, Hold, and Release follow the groove.
- Bypass and output levels are matched.
- Mono remains stable.
- No clipping, static, harshness, or unintended level loss.
- No more than three active processors per lane unless deliberate.
- Factory recall names are maintained in `06_Optimized_Preset_Recall_Map_CURRENT.md`.

DIHWorld Audio - Optimized Preset Recall Map

Current: 2026-10-19 Scope: website Logic-template starters and the DIH 08 routing package

This map makes the published chains recallable with current factory-program names. It deliberately reduces default serial processing: one primary color decision, one spatial return per send, and one dynamics decision before containment. Input, Output, Mix, Power, and final ceiling remain user decisions and must be bypass/output matched before approval.

Recall Rules

- A named **alternate** replaces the preceding processor; it does not extend the chain.
- Use each reverb as its own 100% wet return. Do not serially stack NTRSTLLR, Cathedral, and SacredVerb.
- Use one main color stage per lane. A second color stage is an intentional audition, not a default.
- For track processing, start in Stereo unless the source itself is mono. Use Dual Mono only where independent left/right behavior is intentional.
- These choices are starting positions, not loudness targets. Gain-match to bypass before keeping a tone decision.

Source and Bus Starters

Lane	Primary recall	Approved alternate	Use / protection
Lead vocal	`Vocal Reveal [Stereo]` in SILVER	`Body Open` in GOLD **or** `VOCAL INTIMACY [Stereo]` in WPR	SILVER is the clarity baseline. Select one color alternate after a level-matched comparison; do not stack GOLD and WPR on the same lead by default.
BG vocal	`Body Open` in GOLD	`Breath Silver [Stereo]` in SILVER	Use GOLD for density; use SILVER when the stack needs air instead. Keep TRIPLER as a separate harmony decision.
Drum bus	`DRUMKRUSHGLUE TIGHT BUS GLUE [Stereo]`	`DRUMKRUSHGLUE GENTLE BUS POCKET [Stereo]`	The first is the normal bus glue choice; use the pocket option only when kick-led clearance is needed.
Drum overhead / room color	`DRUM OVERHEAD PHI [Stereo]` in WPR	`ROOM AMBIENCE [Stereo]` in WPR	Keep WPR on the overhead/room return rather than the entire drum bus when transient punch is the priority.
Bass	`KHEPRI BASS FOUNDATION` -> `MONOLITH BODY WEIGHT`	`MONOLITH PHI IMPACT`	KHEPRI supplies harmonic foundation; Monolith supplies the transient/body decision. Do not add a second saturator by default.
Music / instrument bus	`Chain: Music Bus Foundation` in KHEPRI	`ACOUSTIC CLARITY [Stereo]` in WPR	WPR replaces KHEPRI when microphone/ribbon definition is the target. `PTAHTUBE` is a deliberate audition after KHEPRI, not a permanent third color stage.
Harmonic corrective lane	`THOTH MIX POLISH`	`TEHUTI OPEN REFERENCE`	Choose THOTH for static harmonic contour or TEHUTI for movement; do not run both by default.
Parallel dynamics	`DEBO MIX BUS SETTLE [Stereo]` -> `LOOKOUT MIX BUS COMPOSURE`	`DEBO DRUM REINFORCE [Stereo]` -> `LOOKOUT DRUM SNAP LOCK`	Blend the return under the clean bus. Do not use final containment here.

Instrument and Pattern Selection

Role	Recall
Chicago house / four-on-the-floor starter	Drum Morpher `DIH CHICAGO` kit; keep the sequencer pattern as the rhythm decision and use `TIGHT BUS GLUE [Stereo]` only on the drum bus.

Role	Recall
Bay / West Coast starter	Drum Morpher `DIH BAY HYPHY` kit; use `GENTLE BUS POCKET [Stereo]` when kick/bass clearance is needed.
Game-informed hard percussion starter	Drum Morpher `DIH TOP SCORE` kit; use `TRAP SNAP KRUSH [Stereo]` on a parallel return, not the full drum bus.
Clean vocal source check	`Source True [Stereo]` in SILVER, then compare against `Vocal Reveal [Stereo]` in SILVER.
Master-clean color audition	`Chain: Clean Print Finish` in KHEPRI; replace it with `MU-METAL SILK [Stereo]` in WPR when transformer softness, not tape motion, is needed.

Print / Master Choices

Goal	Recall chain	Notes
Neutral print	`SPHYNX` -> `MASTER READY [Stereo]` in MAAT -> `ANKH` -> `SESHAT LUFS BODY`	MAAT is the sole tonal balance stage; SESHAT is observation only.
Warm print	`Chain: Clean Print Finish` in KHEPRI -> `WARM BALANCE [Stereo]` in MAAT -> `ANKH` -> `SESHAT LUFS BODY`	Use only after the neutral print has been checked at matched level.
Modern lift	`SPHYNX` -> `[FINALIZER] Canon Open` in HORIZON X -> `ANKH` -> `SESHAT PEAK / TRUE PEAK`	Keep the lift restrained; ANKH remains the final containment stage.
Authority	`PLATINUM` -> `IMHOTEP MASTER BUILDER CANON` -> `ANKH` -> `SESHAT FULL OBSERVATION`	This replaces the clean print chain, not an added parallel master path.

Approval Before Saving a Logic Template

- Confirm every source/bus has no more than two audible tone processors; the third slot is reserved for a specific dynamics, width, or corrective purpose.
- Confirm that parallel reverbs are separate 100% wet auxes and not serial inserts.
- Confirm bypass/output matching on each active color or dynamics processor.
- Save the selected factory program name in the Logic channel-strip setting or track note, together with the source role and any alternate that was rejected.

DIH 08 - Seven Main Buses Core Mix Routing

Status: website-ready Logic starter, preset-recall revision 2026-10-19.

This is the public configuration note for the downloadable Logic Pro package `DIH 08 - Seven Main Buses - Core Mix Routing.logicx`. WIDTH, FIELD TONE ALT, CREATIVE TRANSFORM, and individual spatial returns are optional support lanes, not additional mandatory main buses. The current family authority and routing placement canon control family membership and lane purpose; the plugin source code controls wet/dry and gain behavior.

Main signal path

```
Source tracks -> one of DRUM / BASS / INSTRUMENT / VOCAL
             -> optional sends to EFFECTS / COLOR / DYNAMICS / WIDTH
All active buses and returns -> Bus 9 MASTER BUS -> Stereo Out
```

- DRUM: Drum Morpher belongs on an instrument track; start the Drum bus with `TIGHT BUS GLUE [Stereo]` in DRUMKRUSHGLUE. `DRUM OVERHEAD PHI [Stereo]` in WPR belongs on an overhead/room return. SlotMachine on this bus is a bypassed creative alternate, not default drum glue.
- BASS: `KHEPRI BASS FOUNDATION` -> `MONOLITH BODY WEIGHT`. NTRPL and DEPTH BOOST PRO are bypassed alternatives, not additional default active stages.
- INSTRUMENT and COLOR: `Chain: Music Bus Foundation` in KHEPRI -> APIS. PTAHTUBE or SOVEREIGN replaces APIS when approved; do not make all three active by default.
- VOCAL: choose the lead-vocal reference or the purpose-matched alternate after level matching. Do not activate every vocal insert by default.
- DYNAMICS: use only the processors needed for the pass, at most three active.
- WIDTH: dimensional movement is distinct from shared reverb/delay. Mono-check before print.
- MASTER BUS: PLATINUM -> IMHOTEP -> ANKH, with SESHAT on the final observation endpoint. IMHOTEP is the sole MASTER_FIELD family member. Do not send the MASTER BUS to a parallel path that reaches Stereo Out around ANKH.

Collector buses

Bus 12, Bus 13, and Bus 14 are structural collector returns, not extra creative effects sends.

- Bus 12 / Aux 12: collects DRUM and BASS, then feeds Bus 9.
- Bus 13 / Aux 13: collects COLOR, then feeds Bus 9.
- Bus 14 / Aux 14: collects EFFECTS, WIDTH, and the independent spatial returns, then feeds Bus 9.

Keep these collectors clean and boring. They exist to preserve the seven-bus architecture and make the final route easy to audit.

Shared spatial effects

For the most controllable starter, use three individual 100%-wet send returns: NTRSTLLR Delay, Cathedral Room, and SacredVerb Chamber. Route their outputs to Bus 14 / Aux 14, then Bus 9. Start source sends at minus infinity; raise only the send needed. This is a control and gain-staging improvement, not an inherent fidelity upgrade. The existing Bus 5 EFFECTS lane can remain available as the serial Parallel Spatial Bus option, but it should not be the default path for three independent shared spaces.

Code basis: NTRSTLLR and Cathedral default to Mix 1.0; SacredVerb implements a wet/dry blend and therefore needs Wet Mix 1.0 for a conventional aux return. Compare level and tail behavior after changing any preset.

Current saved Logic state, 2026-09-26: Bus 16 is named NTRSTLLR DELAY, contains NTRSTLLR, and outputs Bus 14. Bus 17 is named CATHEDRAL ROOM, contains Cathedral with Mix 1.00, and outputs Bus 14. Bus 18 is labeled SACREDVERB, contains SacredVerb, is active, and outputs Bus 14.

Creative Transform

Primary placement is a deliberate source insert. The optional Bus 15 CREATIVE TRANSFORM return is for a parallel creative blend only; it routes to Bus 9 and starts with source sends at minus infinity. Keep Archaeologist X -> SERQET -> SlotMachine available, but normally activate just the chosen creative processor. SlotMachine stays last whenever it is in a chain.

Archaeologist X defaults to an internal Mix of about 0.618 and SlotMachine always retains a dry component even at maximum Blend. On a send return, that dry contribution sums with the main path and may change level or tone. For Archaeologist X parallel use, audition Mix 1.0, level-match, and check the result in mono. SlotMachine is better treated as an insert or a consciously blended effect than as a conventional wet-only return. SERQET is a creative width/movement choice, not transparent correction; mono-check it.

Field Tone Balance

AUSAR restoration and AUSET field tilt belong to FIELD_TONE_BALANCE, not MASTER_FIELD. FIELD TONE ALT is an optional source/stem-fed Bus 11 return into Bus 9. Do not feed it from Bus 9: that would create a loop. HORIZON X is a bypassed mastering alternate, not part of the field-tone pair. If field-tone processing is not called for, leave Bus 11 without active sends.

Website release gate

1. Keep customer media out of the downloadable Logic starter.
2. Verify COLOR uses `Chain: Music Bus Foundation` in KHEPRI -> APIS; PTAHTUBE or SOVEREIGN is an approved replacement, not an added third color stage.
3. Verify every aux destination reaches Bus 9 exactly once through the intended collector: Bus 12 for DRUM/BASS, Bus 13 for COLOR, and Bus 14 for EFFECTS/WIDTH/spatial returns.
4. Verify every default send is off, the master chain is serial, and no lane has more than three active musical processors.
5. Reopen the saved project in Logic, confirm no missing-media or missing-plugin alert, and perform a level-matched audible/mono check on each optional return.

Sources: `CURRENT_FAMILY_AUTHORITY.md`, `ROUTING_PLACEMENT_CANON.md`, `MANUALS_CURRENT/CREATIVE_TRANSFORM/USER_MANUAL.md`, and current processor code in `DIH_FINISHED` for NTRSTLLR, Cathedral, SacredVerb, Archaeologist X, SERQET, and SlotMachine.