DIHWorld Audio - 7 Main Bus Template

Drums | Bass | Vocal | Instrument | Effects | Color | Dynamics -> Master Enhanced: 2026-10-19

User authority: `DIHWorld_Audio_Complete_Manual_CURRENT.pdf`

Current product behavior: ANUBIS has a named stereo Sidechain bus with separate Key/Duck functions; DEBO uses the balanced canonical bank; TRIPLER uses the repaired clean left/right harmony path; SESHAT named views hide unrelated panels; AU and Drum Morpher are current registered instruments.

Use this as the main multitrack routing template. Each source track feeds one musical family bus; optional parallel buses add effects, color, or dynamics without overloading individual tracks.

Core Operating Law

- Start buses and sends around -18 dB as a safe audition point, not a fixed operating target.
- In normal use, many DIH processors will feel optimal around -14 to -10 dB, depending on source, family, and FieldState.
- Some plugins operate cleanly at unity when the use case supports it; approve unity only after bypass/output matching and no clipping, ringing, or level jump.
- Output-match to bypass before approving tone, width, spatial placement, or loudness.
- Use up to three active processors on a track or bus. More than three is an audition rack, not a committed mix chain.
- SESHAT is observation only and may sit last on the print/master endpoint.
- Presets never control Input, Output, Mix, Bypass, or protected ceiling/safety controls.
- Keep each plugin in its primary family when possible; if moved, it replaces a slot instead of extending the chain.
- SLOTMACHINE is always last in any chain that uses it. ANKH is the containment authority.

Architecture

```
Kick, Snare, OH, Room      -> DRUMS BUS
Bass DI, Sub               -> BASS BUS
Lead Vox, BG Vox           -> VOCAL BUS
Guitars, Keys, Synths      -> INSTRUMENT BUS
FX sends                   -> EFFECTS BUS
Color sends                -> COLOR BUS
Parallel compression       -> DYNAMICS BUS

All seven buses -> PRINT / MASTER BUS -> Stereo Out
```

DIH 08 Logic package collector routing

The current downloadable Logic package uses three structural collectors after the seven musical buses:

- Bus 12 / Aux 12 collects DRUM and BASS, then feeds Bus 9 MASTER BUS.
- Bus 13 / Aux 13 collects COLOR, then feeds Bus 9 MASTER BUS.
- Bus 14 / Aux 14 collects EFFECTS, WIDTH, and the independent spatial returns, then feeds Bus 9 MASTER BUS.

NTRSTLLR Delay, Cathedral Room, and SacredVerb are individual shared spatial returns on Bus 16, Bus 17, and Bus 18. Each return should be treated as a 100% wet aux and should output to Bus 14, not directly to the master. This keeps the main seven-bus architecture readable while avoiding one overloaded serial effects bus.

Seven Bus Working Chains

Bus	Receives	Three-active starter chain	Best substitutions
DRUMS	Kick, snare, rooms, percussion	DIH_DRUM_MORPHER -> `TIGHT BUS GLUE [Stereo]` in DRUMKRUSHGLUE	Add ANUBIS only for a defined transient/duck need. `DRUM OVERHEAD PHI [Stereo]` in WPR belongs on an overhead/room return, not the full drum bus.

Bus	Receives	Three-active starter chain	Best substitutions
BASS	Bass DI, sub, low-end instruments	`KHEPRI BASS FOUNDATION` -> `MONOLITH BODY WEIGHT`	DEPTH_BOOST_PRO replaces MONOLITH for definition. NTRPL is an optional earlier Harmonics & Pitch insert, not a Bass-family bus stage.
VOCAL	Lead, backgrounds, harmonies	`Vocal Reveal [Stereo]` in SILVER; optional `Body Open` in GOLD **or** `VOCAL INTIMACY [Stereo]` in WPR	SILVER is the baseline. GOLD and WPR are mutually exclusive color choices after level-matched comparison. TRIPLER is BG/harmony only. EchoLocate is for localization.
INSTRUMENT	Guitars, keys, piano, synths	`Chain: Music Bus Foundation` in KHEPRI -> APIS	`ACOUSTIC CLARITY [Stereo]` in WPR replaces KHEPRI for ribbon/mic definition. THOTH or TEHUTI replaces a color slot when harmonic pitch is the actual problem.
EFFECTS	FX returns and spatial sends	Optional serial lane, or clean collector feed to Bus 14	Preferred DIH 08 setup uses Bus 16 NTRSTLLR DELAY, Bus 17 CATHEDRAL ROOM, and Bus 18 SACREDVERB as independent returns into Bus 14. Do not stack PARALLAX here if a WIDTH bus exists; use the WIDTH bus.
COLOR	Vocal and instrument color sends	`Chain: Music Bus Foundation` in KHEPRI -> APIS	PTAHTUBE or SOVEREIGN replaces APIS when a distinct second color decision is approved. PLATINUM belongs to Mastering Core with secondary color support.
DYNAMICS	Parallel dynamics send	`DEBO MIX BUS SETTLE [Stereo]` -> `LOOKOUT MIX BUS COMPOSURE`	Use `DEBO DRUM REINFORCE [Stereo]` -> `LOOKOUT DRUM SNAP LOCK` only for drums. SPHYNX belongs on the print/master chain unless this bus is acting as mix-bus preparation.

Print / Master Choices

Use case	Active chain	When
Clean	SPHYNX -> MAAT -> ANKH -> SESHAT	Prepare, balance, contain, then observe.
Authority	PLATINUM -> IMHOTEP -> ANKH -> SESHAT	Master authority plus macro field structure.
Loud / modern	SPHYNX -> HORIZON_X -> ANKH -> SESHAT	Lift and finish before containment.
Dimensional	DEPTH_IMPACT_HYBRID_X -> MAAT -> ANKH -> SESHAT	Front/back placement before balance and containment.
Color master	KHEPRI or SOVEREIGN -> MAAT -> ANKH -> SESHAT	One color stage, one balance stage, then containment.

Preset Recall

Exact current-program selections, approved alternates, and the Chicago/Bay/Top Score Drum Morpher kit roles are maintained in `06_Optimized_Preset_Recall_Map_CURRENT.md`.

Routing Rules

- Seven musical buses are enough for this formation. New auxes require a written reason in the deployment register unless they are part of the verified DIH 08 collector/spatial-return design.
- Bus 12, Bus 13, and Bus 14 are structural collectors, not creative chains. Keep them clean unless a future deployment note explicitly changes their purpose.
- Family buses may receive up to three active inserts; source tracks should usually carry zero to two.
- Use COLOR and EFFECTS buses for parallel tone and space instead of building long chains on every track. For shared space, prefer separate sends to NTRSTLLR Delay, Cathedral Room, and SacredVerb, then collect those returns through Bus 14.

- If a plugin is used outside its home family, document it as a replacement: source problem, chosen substitute, and bypass-matched result.