DIHWorld Audio - Better Buses Template

Customer-safe Logic bus starters | Current ANKH families | Website template 4 Enhanced: 2026-10-19

User authority: `DIHWorld_Audio_Complete_Manual_CURRENT.pdf`

Current product behavior: ANUBIS has a named stereo Sidechain bus with separate Key/Duck functions; DEBO uses the balanced canonical bank; TRIPLER uses the repaired clean left/right harmony path; SESHAT named views hide unrelated panels; AU and Drum Morpher are current registered instruments.

Use this when you want a cleaner Logic mixer layout with descriptive bus names, short chains, and clear family placement. It is the practical companion to the 7 Main Bus Template: fewer mystery buses, fewer stacked inserts, and easier handoff to another mixer.

Core Operating Law

- Start buses and sends around -18 dB as a safe audition point, not a fixed operating target.
- In normal use, many DIH processors will feel optimal around -14 to -10 dB, depending on source, family, and FieldState.
- Some plugins operate cleanly at unity when the use case supports it; approve unity only after bypass/output matching and no clipping, ringing, or level jump.
- Output-match to bypass before approving tone, width, spatial placement, or loudness.
- Keep source tracks lean. Use buses for color, space, width, dynamics, and print decisions.
- Use up to three active processors on a source track or bus during a musical pass. Extra inserts are audition alternates, not the committed chain.
- SESHAT is observation only and may sit last on the print/master endpoint.
- ANKH is the final containment authority.

Better Bus Architecture

```
SOURCE TRACKS
  -> DRUM BUS
  -> BASS BUS
  -> LEAD VOCAL BUS
  -> BG VOCAL BUS
  -> INSTRUMENT BUS
  -> optional sends: FX BUS, COLOR BUS, WIDTH BUS, DYNAMICS BUS

FAMILY BUSES
  -> PRINT / MASTER BUS
  -> Stereo Out
```

Customer Bus Starters

Bus	Three-active starter	Best use	Notes
LEAD VOCAL BUS	`Vocal Reveal [Stereo]` in SILVER; optional `Body Open` in GOLD **or** `VOCAL INTIMACY [Stereo]` in WPR	Lead vocal source tone and protection	Gain-match SILVER and the selected color alternate. GOLD and WPR are alternatives, not a serial default.
BG VOCAL BUS	`Body Open` in GOLD -> TRIPLER	Stacks, doubles, localization	Use EchoLocate only when location is the musical decision. Keep lead diction clear.

Bus	Three-active starter	Best use	Notes
DRUM BUS	DIH_DRUM_MORPHER -> `TIGHT BUS GLUE [Stereo]` in DRUMKRUSHGLUE	Drum identity, punch, and glue	Use ANUBIS only where individual transient guard is needed.
BASS BUS	`KHEPRI BASS FOUNDATION` -> `MONOLITH BODY WEIGHT`	Low-end focus and foundation	DEPTH_BOOST_PRO can replace MONOLITH for definition. NTRPL is an optional earlier Harmonics & Pitch source insert.
INSTRUMENT BUS	`Chain: Music Bus Foundation` in KHEPRI -> APIS	Music-bed tone, body, and harmonic color	`ACOUSTIC CLARITY [Stereo]` in WPR replaces KHEPRI for ribbon/mic definition. THOTH or TEHUTI replaces a color slot when harmonic pitch is the actual problem.
FX BUS	Independent 100% wet NTRSTLLR, Cathedral, or SacredVerb returns	Shared spatial identity and room field	Select the return; do not serially stack reverbs.
COLOR BUS	`Chain: Music Bus Foundation` in KHEPRI -> APIS	Parallel tone and bus color	PTAHTUBE or SOVEREIGN replaces APIS for stronger color authority.
WIDTH BUS	DEPTH_IMPACT_HYBRID_X **or** PARALLAX **or** NSR	Width, placement, and front/back movement	SERQET can replace PARALLAX for a creative width move. Mono-check before print.
DYNAMICS BUS	`DEBO MIX BUS SETTLE [Stereo]` -> `LOOKOUT MIX BUS COMPOSURE`	Parallel guard and movement	Use the drum-specific DEBO/LOOKOUT pair only for drums. DRUMKRUSHGLUE belongs on drum glue when needed.

Print / Master Bus Choices

Goal	Chain	When
Clean print	SPHYNX -> MAAT -> ANKH -> SESHAT	Prepare, balance, contain, then observe.
Authority print	PLATINUM -> IMHOTEP -> ANKH -> SESHAT	Master authority plus macro field structure.
Loud / modern print	SPHYNX -> HORIZON_X -> ANKH -> SESHAT	Lift and finish without replacing ANKH.
Dimensional print	DEPTH_IMPACT_HYBRID_X -> MAAT -> ANKH -> SESHAT	Front/back placement before balance and containment.
Color master	KHEPRI or SOVEREIGN -> MAAT -> ANKH -> SESHAT	One color stage, one balance stage, then containment.

Handoff Labels

Label	Meaning
ACTIVE	Processor is part of the current musical pass.
BYPASSED ALT	Processor is present as a documented alternate, not active.
QC ONLY	Observation, metering, or validation only.
PRINT CHAIN	Final chain chosen for the bounce.

Approval Checklist

- Every bus has a clear musical reason.

- No source track is carrying a long chain that belongs on a family bus.
- COLOR, FX, WIDTH, and DYNAMICS are sends or parallel buses, not hidden source-track clutter.
- SESHAT is observation only.
- ANKH remains final containment authority.
- The final print is bypass/output matched before approval.
- Use `06_Optimized_Preset_Recall_Map_CURRENT.md` to document every approved factory recall in the Logic template.