DIHWorld Audio - Optimized Preset Recall Map

Current: 2026-10-19 Scope: website Logic-template starters and the DIH 08 routing package

This map makes the published chains recallable with current factory-program names. It deliberately reduces default serial processing: one primary color decision, one spatial return per send, and one dynamics decision before containment. Input, Output, Mix, Power, and final ceiling remain user decisions and must be bypass/output matched before approval.

Recall Rules

- A named **alternate** replaces the preceding processor; it does not extend the chain.
- Use each reverb as its own 100% wet return. Do not serially stack NTRSTLLR, Cathedral, and SacredVerb.
- Use one main color stage per lane. A second color stage is an intentional audition, not a default.
- For track processing, start in Stereo unless the source itself is mono. Use Dual Mono only where independent left/right behavior is intentional.
- These choices are starting positions, not loudness targets. Gain-match to bypass before keeping a tone decision.

Source and Bus Starters

Lane	Primary recall	Approved alternate	Use / protection
Lead vocal	`Vocal Reveal [Stereo]` in SILVER	`Body Open` in GOLD **or** `VOCAL INTIMACY [Stereo]` in WPR	SILVER is the clarity baseline. Select one color alternate after a level-matched comparison; do not stack GOLD and WPR on the same lead by default.
BG vocal	`Body Open` in GOLD	`Breath Silver [Stereo]` in SILVER	Use GOLD for density; use SILVER when the stack needs air instead. Keep TRIPLER as a separate harmony decision.
Drum bus	`DRUMKRUSHGLUE TIGHT BUS GLUE [Stereo]`	`DRUMKRUSHGLUE GENTLE BUS POCKET [Stereo]`	The first is the normal bus glue choice; use the pocket option only when kick-led clearance is needed.
Drum overhead / room color	`DRUM OVERHEAD PHI [Stereo]` in WPR	`ROOM AMBIENCE [Stereo]` in WPR	Keep WPR on the overhead/room return rather than the entire drum bus when transient punch is the priority.
Bass	`KHEPRI BASS FOUNDATION` -> `MONOLITH BODY WEIGHT`	`MONOLITH PHI IMPACT`	KHEPRI supplies harmonic foundation; Monolith supplies the transient/body decision. Do not add a second saturator by default.
Music / instrument bus	`Chain: Music Bus Foundation` in KHEPRI	`ACOUSTIC CLARITY [Stereo]` in WPR	WPR replaces KHEPRI when microphone/ribbon definition is the target. `PTAHTUBE` is a deliberate audition after KHEPRI, not a permanent third color stage.
Harmonic corrective lane	`THOTH MIX POLISH`	`TEHUTI OPEN REFERENCE`	Choose THOTH for static harmonic contour or TEHUTI for movement; do not run both by default.
Parallel dynamics	`DEBO MIX BUS SETTLE [Stereo]` -> `LOOKOUT MIX BUS COMPOSURE`	`DEBO DRUM REINFORCE [Stereo]` -> `LOOKOUT DRUM SNAP LOCK`	Blend the return under the clean bus. Do not use final containment here.

Instrument and Pattern Selection

Role	Recall
Chicago house / four-on-the-floor starter	Drum Morpher `DIH CHICAGO` kit; keep the sequencer pattern as the rhythm decision and use `TIGHT BUS GLUE [Stereo]` only on the drum bus.

Role	Recall
Bay / West Coast starter	Drum Morpher `DIH BAY HYPHY` kit; use `GENTLE BUS POCKET [Stereo]` when kick/bass clearance is needed.
Game-informed hard percussion starter	Drum Morpher `DIH TOP SCORE` kit; use `TRAP SNAP KRUSH [Stereo]` on a parallel return, not the full drum bus.
Clean vocal source check	`Source True [Stereo]` in SILVER, then compare against `Vocal Reveal [Stereo]` in SILVER.
Master-clean color audition	`Chain: Clean Print Finish` in KHEPRI; replace it with `MU-METAL SILK [Stereo]` in WPR when transformer softness, not tape motion, is needed.

Print / Master Choices

Goal	Recall chain	Notes
Neutral print	`SPHYNX` -> `MASTER READY [Stereo]` in MAAT -> `ANKH` -> `SESHAT LUFS BODY`	MAAT is the sole tonal balance stage; SESHAT is observation only.
Warm print	`Chain: Clean Print Finish` in KHEPRI -> `WARM BALANCE [Stereo]` in MAAT -> `ANKH` -> `SESHAT LUFS BODY`	Use only after the neutral print has been checked at matched level.
Modern lift	`SPHYNX` -> `[FINALIZER] Canon Open` in HORIZON X -> `ANKH` -> `SESHAT PEAK / TRUE PEAK`	Keep the lift restrained; ANKH remains the final containment stage.
Authority	`PLATINUM` -> `IMHOTEP MASTER BUILDER CANON` -> `ANKH` -> `SESHAT FULL OBSERVATION`	This replaces the clean print chain, not an added parallel master path.

Approval Before Saving a Logic Template

- Confirm every source/bus has no more than two audible tone processors; the third slot is reserved for a specific dynamics, width, or corrective purpose.
- Confirm that parallel reverbs are separate 100% wet auxes and not serial inserts.
- Confirm bypass/output matching on each active color or dynamics processor.
- Save the selected factory program name in the Logic channel-strip setting or track note, together with the source role and any alternate that was rejected.