

DIHWorld Audio Sidechain Routing Guide

Current sidechain guide - DIHWorld Audio only - August 13, 2026

Sidechain concept

A sidechain is an external control signal. The key signal tells the inserted DIHWorld Audio plugin when to react, but the key is not mixed into the program output by the plugin. In Logic Pro, the key is selected from the native Side Chain menu above the plugin editor.

Plugin roster and placement

Plugin	Primary placement	Secondary/key source	Expected behavior
ANUBIS	Dialogue, drums, vocal cleanup, room tracks	Trigger, vocal, drum transient, or rhythmic key	Gate/expander opens or ducks based on the key.
TEHUTI	Bass, music bed, pad, FX return, or mix element	Kick, vocal, hats, or drum bus	Low/mid/high spectral ducking creates frequency-selective space.
MARIANA	Bass or low-end support track	Kick or low-frequency key	Generated low-end layer follows the key while dry bass remains controlled.
MONOLITH	Bass bus, low-end bus, or heavy tone return	Kick or low-frequency key	Wet low-frequency field makes room for the keyed source.
NTRPL	Music, bass, texture, or rewrite layer	Kick, rhythm key, or vocal	Alternate rewrite layer ducks while main program stays present.
DrumKrushGlue	Drum track or drum bus	Kick, snare, or transient bus	Key controls impact/glue intensity without audible key bleed.
Balance Restore	Program, subgroup, or mix bus	Stereo reference track	External reference guides left/right correction.

Basic routing schematic

PROGRAM TRACK -> insert DIHWorld plugin -> stereo output. KEY TRACK -> DAW native Side Chain selector -> detector input. The key should not be audible through the plugin output.

Working examples on the website

Use the website documentation section for the PDF guide. The local routing folder also contains interactive HTML demos and PNG schematics for each listed DIHWorld sidechain plugin.