

DIHWorld Audio

Template Starter Pack

Corrected routing templates for current DIHWorld Audio workflows.

Vocal mic decision law: SILVER is the neutral M50 reference. Compare GOLD only as a level-matched color choice; do not use a serial GOLD -> AEGIS_NOVA -> SILVER chain as a default.

DIHWorld Audio - Cascading Effects Bus Template

Effects -> Width -> Color -> Collection -> Master | Enhanced for ANKH family placement Enhanced: 2026-07-25

User authority: DIHWorld_Audio_Complete_Manual_CURRENT.pdf

Current product behavior: ANUBIS has a named stereo Sidechain bus with separate Key/Duck functions; DEBO uses the balanced canonical bank; TRIPLER uses the repaired clean left/right harmony path; SESHAT named views hide unrelated panels; AU and Drum Morpher are current registered instruments.

Use this when a session needs three deliberate parallel lanes feeding one clean collection point. The buses carry the work; source tracks stay lean.

Core Operating Law

- Start buses and sends around -18 dB as a safe audition point, not a fixed operating target.
- In normal use, many DIH processors will feel optimal around -14 to -10 dB, depending on source, family, and FieldState.
- Some plugins operate cleanly at unity when the use case supports it; approve unity only after bypass/output matching and no clipping, ringing, or level jump.
- Output-match to bypass before approving tone, width, spatial placement, or loudness.
- Use up to three active processors on a track or bus. More than three is an audition rack, not a committed mix chain.
- SESHAT is observation only and may sit last on the print/master endpoint.
- Presets never control Input, Output, Mix, Bypass, or protected ceiling/safety controls.
- Keep each plugin in its primary family when possible; if moved, it replaces a slot instead of extending the chain.
- SLOTMACHINE is always last in any chain that uses it. ANKH is the containment authority.

Architecture

```
SOURCE TRACKS
  Send 1 start -18 dB -> EFFECTS BUS [FX_SPATIAL]
  Send 2 start -18 dB -> WIDTH BUS   [DIMENSIONAL_IMPACT_MOVE]
  Send 3 start -18 dB -> COLOR BUS   [COLOR_AMP_TAPE]
  Optimize commonly toward -14 to -10 dB; unity is valid only when clean.
```

```
EFFECTS BUS + WIDTH BUS + COLOR BUS
-> COLLECTION CHANNEL           [no inserts, summing only]
-> PRINT / MASTER BUS
-> Stereo Out
```

Bus Chains

EFFECTS BUS	NTRSTLLR -> Cathedral -> SacredVerb	All three are FX_SPATIAL and bus preferred. Keep reverbs here, not as random track inserts.
WIDTH BUS	DEPTH_IMPACT_HYBRID_X -> PARALLAX -> NSR	SERQET replaces PARALLAX for a creative width move; it does not extend the chain. Mono-check before print.
COLOR BUS	KHEPRI -> PTAHTUBE -> APIS	SOVEREIGN replaces one color slot when the whole bus needs stronger color authority. PLATINUM is Mastering Core with secondary color support, not a primary Color insert.

COLLECTION	No inserts	Collection is a summing point only. If it needs tone, the tone belongs on a lane above or the print bus below.

Print / Master Choices

Clean	SPHYNX -> MAAT -> ANKH -> SESHAT	Prepare, balance, contain, then observe.
Authority	PLATINUM -> IMHOTEP -> ANKH -> SESHAT	Master authority plus macro field structure.
Loud / modern	SPHYNX -> HORIZON_X -> ANKH -> SESHAT	Lift and finish before containment.
Dimensional	DEPTH_IMPACT_HYBRID_X -> MAAT -> ANKH -> SESHAT	Front/back placement before balance and containment.
Color master	KHEPRI or SOVEREIGN -> MAAT -> ANKH -> SESHAT	One color stage, one balance stage, then containment.

Send Discipline

Every source track	EFFECTS BUS	Start -18; -14 to -10 usual; unity clean	Spatial material only. Do not hide color or dynamics here.
Every source track	WIDTH BUS	Start -18; -14 to -10 usual; unity clean	Width/depth moves only. Collapse-check before printing.
Every source track	COLOR BUS	Start -18; -14 to -10 usual; unity clean	Harmonic color lane. Pick three active processors maximum.
All buses	COLLECTION	unity route	No inserts on collection.

Output Approval

- Match the delivery specification for the project or platform; this template does not impose a fixed RMS, peak, or crest target.
- Preserve musical dynamics and confirm zero unintended clipping.
- Compare at matched loudness before approving the print.

DIHWorld Audio - 7 Main Bus Template

Drums | Bass | Vocal | Instrument | Effects | Color | Dynamics -> Master Enhanced: 2026-07-25

User authority: DIHWorld_Audio_Complete_Manual_CURRENT.pdf

Current product behavior: ANUBIS has a named stereo Sidechain bus with separate Key/Duck functions; DEBO uses the balanced canonical bank; TRIPLER uses the repaired clean left/right harmony path; SESHAT named views hide unrelated panels; AU and Drum Morpher are current registered instruments.

Use this as the main multitrack routing template. Each source track feeds one musical family bus; optional parallel buses add effects, color, or dynamics without overloading individual tracks.

Core Operating Law

- Start buses and sends around -18 dB as a safe audition point, not a fixed operating target.
- In normal use, many DIH processors will feel optimal around -14 to -10 dB, depending on source, family, and FieldState.
- Some plugins operate cleanly at unity when the use case supports it; approve unity only after bypass/output matching and no clipping, ringing, or level jump.
- Output-match to bypass before approving tone, width, spatial placement, or loudness.
- Use up to three active processors on a track or bus. More than three is an audition rack, not a committed mix chain.
- SESHAT is observation only and may sit last on the print/master endpoint.
- Presets never control Input, Output, Mix, Bypass, or protected ceiling/safety controls.
- Keep each plugin in its primary family when possible; if moved, it replaces a slot instead of extending the chain.
- SLOTMACHINE is always last in any chain that uses it. ANKH is the containment authority.

Architecture

Kick, Snare, OH, Room -> DRUMS BUS
Bass DI, Sub -> BASS BUS
Lead Vox, BG Vox -> VOCAL BUS
Guitars, Keys, Synths -> INSTRUMENT BUS
FX sends -> EFFECTS BUS
Color sends -> COLOR BUS
Parallel compression -> DYNAMICS BUS

All seven buses -> PRINT / MASTER BUS -> Stereo Out

Seven Bus Working Chains

DRUMS	Kick, snare, rooms, percussion	ANUBIS -> DIH_DRUM_MORPHER -> BALLPARK	DRUMKRUSHGLUE replaces ANUBIS or BALLPARK when the bus needs glue more than guard.
BASS	Bass DI, sub, low-end instruments	MARIANA -> MONOLITH	DEPTH_BOOST_PRO replaces MONOLITH for definition. NTRPL is an optional earlier Harmonics & Pitch insert, not a Bass-family bus stage.
VOCAL	Lead, backgrounds, harmonies	SILVER M50 reference check; optional GOLD -> AEGIS_NOVA	SILVER is the neutral baseline; GOLD and WPR are separate color choices after level-matched comparison. TRIPLER is BG/harmony only. EchoLocate is for localization.

INSTRUMENT	Guitars, keys, piano, synths	KHEPRI -> PTAHTUBE -> APIS	THOTH or TEHUTI replaces a color slot when harmonic pitch is the real problem.
EFFECTS	FX returns and spatial sends	NTRSTLLR -> Cathedral -> SacredVerb	Do not stack PARALLAX here if a WIDTH bus exists; use the WIDTH bus.
COLOR	Vocal and instrument color sends	KHEPRI -> PTAHTUBE -> APIS	SOVEREIGN replaces one color slot for stronger bus color. PLATINUM belongs to Mastering Core with secondary color support.
DYNAMICS	Parallel dynamics send	OTIS -> DEBO -> LOOKOUT	SPHYNX belongs on the print/master chain unless this bus is acting as mix-bus preparation.

Print / Master Choices

Clean	SPHYNX -> MAAT -> ANKH -> SESHAT	Prepare, balance, contain, then observe.
Authority	PLATINUM -> IMHOTEP -> ANKH -> SESHAT	Master authority plus macro field structure.
Loud / modern	SPHYNX -> HORIZON_X -> ANKH -> SESHAT	Lift and finish before containment.
Dimensional	DEPTH_IMPACT_HYBRID_X -> MAAT -> ANKH -> SESHAT	Front/back placement before balance and containment.
Color master	KHEPRI or SOVEREIGN -> MAAT -> ANKH -> SESHAT	One color stage, one balance stage, then containment.

Routing Rules

- Seven buses are enough for this formation. New auxes require a written reason in the deployment register.
- Family buses may receive up to three active inserts; source tracks should usually carry zero to two.
- Use COLOR and EFFECTS buses for parallel tone and space instead of building long chains on every track.
- If a plugin is used outside its home family, document it as a replacement: source problem, chosen substitute, and bypass-matched result.

DIHWorld Audio - FAMILY AFFAIR Use Case Demo Template

One-session Logic demo featuring all 42 plugins Enhanced: 2026-07-25

User authority: DIHWorld_Audio_Complete_Manual_CURRENT.pdf

Current product behavior: ANUBIS has a named stereo Sidechain bus with separate Key/Duck functions; DEBO uses the balanced canonical bank; TRIPLER uses the repaired clean left/right harmony path; SESHAT named views hide unrelated panels; AU and Drum Morpher are current registered instruments.

This template turns the full DIHWorld Audio suite into one clear family demo. It is not a permission slip to stack every processor on a record. Every plugin appears in the session, but each lane stays organized by family, and the demo moves through the families one scene at a time.

Core Operating Law

- Start buses and sends around -18 dB as a safe audition point, not a fixed operating target.
- In normal use, many DIH processors will feel optimal around -14 to -10 dB, depending on source, family, and FieldState.
- Output-match to bypass before approving tone, width, spatial placement, or loudness.
- Use up to three active processors on a track or bus. Extra plugins in this template are demo alternates, bypassed slots, or scene-based reveals.
- Keep each plugin in its primary family when possible. If moved, it replaces a slot instead of extending the chain.
- SLOTMACHINE is always last in any chain that uses it. ANKH is the containment authority.
- SESHAT is observation only and may sit last on the print/master endpoint.
- Presets never control protected Input, Output, Mix, Bypass/Power, or final ceiling/safety controls unless a plugin-specific canon explicitly makes that control part of the musical engine.

Use Case

Build one Logic session around a full-song reference or stem set. The listener hears the raw source first, then each DIHWorld family enters in order: drums, bass, vocals, instruments, effects, color, width, dynamics, creative transform, harmonic pitch, field balance, master structure, and observation.

The goal is to show the system as a family, not to compare it to outside brands. The proof is organized placement: each plugin has a job, a family home, and a moment in the demo.

Template Lane Order

DRUM	Drum identity and punch	Drum Morpher -> Ballpark -> DrumKrushGlue	Add ANUBIS only if transient guard is needed.
BASS	Foundation and low-end shape	MARIANA -> MONOLITH	DEPTH_BOOST_PRO is the definition/weight reveal. NTRPL may precede this lane only as a Harmonics & Pitch source insert.
VOCAL	Lead and stack source tone	SILVER M50 reference check; optional GOLD -> AegisNova	SILVER is the neutral baseline; GOLD is deliberate color after level-matched comparison. WPR, TRIPLER, and EchoLocate show separate alternates and BG movement.
INSTRUMENT	Music bed, keys, guitars, synths	Khepri Sacred Tape Machine -> PtahTube -> APIS	Swap in Thoth, TEHUTI, or AU when harmonic pitch is the point.
EFFECTS	Space and reverb returns	NTRSTLLR -> Cathedral -> SacredVerb	Spatial lane only. Keep color and dynamics elsewhere.
COLOR	Parallel color and amp/tape authority	Khepri Sacred Tape Machine -> PtahTube -> APIS	SOVEREIGN replaces one slot for stronger bus color.

WIDTH	Field width and dimensional movement	Depth Impact Hybrid X -> PARALLAX -> NSR	SERQET replaces PARALLAX for a creative width reveal; it does not extend the chain.
DYNAMICS	Parallel protection and movement	OTIS -> DeBo -> LookOut	ANUBIS and DrumKrushGlue enter where the source needs guard/glue.
CREATIVE	One special moment, not the whole mix	ARCHAEOLOGIST X -> SERQET -> SlotMachine	SlotMachine stays last.
MASTER BUS	Three-stage print chain	SPHYNX -> Maat -> ANKH -> SESHAT	PLATINUM, IMHOTEP, or Horizon X appear as bypassed alternates and replace a stage for their scene.

Demo Timeline

Bars 1-16	Raw source, no DIH processing.	None; establish the before picture.
Bars 17-32	Bring in DRUM and BASS lanes.	DRUM_INSTRUMENT, BASS_LOW_END, selected DYNAMICS_GUARD.
Bars 33-48	Bring in VOCAL and INSTRUMENT lanes.	VOCAL_MIC_SOURCE, COLOR_AMP_TAPE, HARMONICS_PITCH.
Bars 49-64	Open EFFECTS and WIDTH sends.	FX_SPATIAL, DIMENSIONAL_IMPACT_MOVE, SERQET as width reveal.
Bars 65-80	Add COLOR and CREATIVE moments.	COLOR_AMP_TAPE, CREATIVE_TRANSFORM, FIELD_TONE_BALANCE.
Bars 81-96	Engage MASTER BUS clean chain.	MASTERING_CORE, MASTER_FIELD, UTILITY_OBSERVATION.
Bars 97-112	Print loud/modern reveal, then bypass-match.	HORIZON_X lift, ANKH containment, SESHAT confirmation.

All 42 Plugin Coverage

VOCAL_MIC_SOURCE	6	GOLD, SILVER, WPR, AegisNova, TRIPLER, EchoLocate
DYNAMICS_GUARD	4	ANUBIS, OTIS, DeBo, LookOut
BASS_LOW_END	3	MARIANA, MONOLITH, DEPTH_BOOST_PRO
DRUM_INSTRUMENT	3	Drum Morpher, Ballpark, DrumKrushGlue
COLOR_AMP_TAPE	4	APIS, PtahTube, Khepri Sacred Tape Machine, SOVEREIGN
FIELD_TONE_BALANCE	2	AUSET, AUSAR
DIMENSIONAL_IMPACT_MOVE	3	Depth Impact Hybrid X, PARALLAX, NSR
FX_SPATIAL	3	NTRSTLLR, Cathedral, SacredVerb
HARMONICS_PITCH	4	Thoth, NTRPL, TEHUTI, AU
CREATIVE_TRANSFORM	3	SlotMachine, ARCHAEOLOGIST X, SERQET
MASTERING_CORE	5	ANKH, SPHYNX, Maat, Horizon X, PLATINUM
MASTER_FIELD	1	IMHOTEP

UTILITY_OBSERVATION	1	SESHAT

Print Checklist

- Every plugin appears at least once in the session.
- No source track or bus has more than three active processors during a musical pass.
- Extra plugins are labeled as BYPASSED ALT, SCENE REVEAL, or QC ONLY.
- SESHAT is last and observation only.
- Match the project delivery specification; this template does not impose fixed RMS, peak, or crest targets. Confirm zero unintended clipping.
- Save two versions: FAMILY_AFFAIR_TEMPLATE . logicx and FAMILY_AFFAIR_DEMO_PRINT . wav.

DIHWorld Audio - Better Buses Template

Customer-safe Logic bus starters | Current ANKH families | Website template 4 Enhanced: 2026-07-25

User authority: DIHWorld_Audio_Complete_Manual_CURRENT.pdf

Current product behavior: ANUBIS has a named stereo Sidechain bus with separate Key/Duck functions; DEBO uses the balanced canonical bank; TRIPLER uses the repaired clean left/right harmony path; SESHAT named views hide unrelated panels; AU and Drum Morpher are current registered instruments.

Use this when you want a cleaner Logic mixer layout with descriptive bus names, short chains, and clear family placement. It is the practical companion to the 7 Main Bus Template: fewer mystery buses, fewer stacked inserts, and easier handoff to another mixer.

Core Operating Law

- Start buses and sends around -18 dB as a safe audition point, not a fixed operating target.
- In normal use, many DIH processors will feel optimal around -14 to -10 dB, depending on source, family, and FieldState.
- Some plugins operate cleanly at unity when the use case supports it; approve unity only after bypass/output matching and no clipping, ringing, or level jump.
- Output-match to bypass before approving tone, width, spatial placement, or loudness.
- Keep source tracks lean. Use buses for color, space, width, dynamics, and print decisions.
- Use up to three active processors on a source track or bus during a musical pass. Extra inserts are audition alternates, not the committed chain.
- SESHAT is observation only and may sit last on the print/master endpoint.
- ANKH is the final containment authority.

Better Bus Architecture

SOURCE TRACKS
-> DRUM BUS
-> BASS BUS
-> LEAD VOCAL BUS
-> BG VOCAL BUS
-> INSTRUMENT BUS
-> optional sends: FX BUS, COLOR BUS, WIDTH BUS, DYNAMICS BUS

FAMILY BUSES
-> PRINT / MASTER BUS
-> Stereo Out

Customer Bus Starters

LEAD VOCAL BUS	SILVER M50 reference baseline; optional GOLD -> AEGIS_NOVA	Lead vocal source tone and protection	Gain-match SILVER and GOLD before choosing color. WPR is a separate ribbon-color option, not a replacement for the reference baseline.
BG VOCAL BUS	GOLD -> TRIPLER -> EchoLocate	Stacks, doubles, localization	Keep lead diction clear; do not force TRIPLER on every lead.
DRUM BUS	DIH_DRUM_MORPHER -> BALLPARK -> DRUMKRUSHGLUE	Drum identity, punch, and glue	Use ANUBIS before the bus when individual transient guard is needed.

BASS BUS	MARIANA -> MONOLITH	Low-end focus and foundation	DEPTH_BOOST_PRO can replace MONOLITH for definition. NTRPL is an optional earlier Harmonics & Pitch source insert.
INSTRUMENT BUS	KHEPRI -> PTAHTUBE -> APIS	Music-bed tone, body, and harmonic color	THOTH or TEHUTI replaces a color slot when harmonic pitch is the actual problem.
FX BUS	NTRSTLLR -> Cathedral -> SacredVerb	Shared spatial identity and room field	Keep reverbs here instead of scattering long tails across source tracks.
COLOR BUS	KHEPRI -> PTAHTUBE -> APIS	Parallel tone and bus color	SOVEREIGN replaces one slot for stronger color authority.
WIDTH BUS	DEPTH_IMPACT_HYBRID_X -> PARALLAX -> NSR	Width, placement, and front/back movement	SERQET can replace PARALLAX for a creative width move. Mono-check before print.
DYNAMICS BUS	ANUBIS -> OTIS -> DEBO	Parallel guard and movement	LOOKOUT may observe. DRUMKRUSHGLUE belongs on drum glue when needed.

Print / Master Bus Choices

Clean print	SPHYNX -> MAAT -> ANKH -> SESHAT	Prepare, balance, contain, then observe.
Authority print	PLATINUM -> IMHOTEP -> ANKH -> SESHAT	Master authority plus macro field structure.
Loud / modern print	SPHYNX -> HORIZON_X -> ANKH -> SESHAT	Lift and finish without replacing ANKH.
Dimensional print	DEPTH_IMPACT_HYBRID_X -> MAAT -> ANKH -> SESHAT	Front/back placement before balance and containment.
Color master	KHEPRI or SOVEREIGN -> MAAT -> ANKH -> SESHAT	One color stage, one balance stage, then containment.

Handoff Labels

ACTIVE	Processor is part of the current musical pass.
BYPASSED ALT	Processor is present as a documented alternate, not active.
QC ONLY	Observation, metering, or validation only.
PRINT CHAIN	Final chain chosen for the bounce.

Approval Checklist

- Every bus has a clear musical reason.
- No source track is carrying a long chain that belongs on a family bus.
- COLOR, FX, WIDTH, and DYNAMICS are sends or parallel buses, not hidden source-track clutter.
- SESHAT is observation only.

- ANKH remains final containment authority.
- The final print is bypass/output matched before approval.

DIHWorld Audio

Dynamics / Kick-Key / Duck Template

Current: 2026-07-31

Session lanes

Lane	Insert / Route	Starting action
Kick key	Send to named sidechain	Unity or pre-fader as needed
Bass target	ANUBIS	DUCK on; KEY optional
Music target	ANUBIS	Vocal sidechain; gentle Range
Reverb return	ANUBIS	KEY on from lead vocal
Drum parallel	DRUMKRUSHGLUE or DEBO	Blend below clean drums
Dynamics bus	OTIS → LOOKOUT	Shape then observe
Print endpoint	SESHAT	Observation only

Kick-to-bass starting card

- Route kick to ANUBIS Sidechain.
- Enable DUCK for rhythmic clearance.
- Enable KEY only if kick should drive gate detection.
- Start with shallow Range.
- Set fast Attack and tempo-aware Release.
- Check mono and bypass-match.

Vocal-clearance starting card

- Insert ANUBIS on music or ambience target.
- Route lead vocal to Sidechain.
- Use DUCK for space around words.
- Use KEY on ambience returns that should open with the vocal.
- Keep Range gentle and Release natural.

Dynamics stack options

Goal	Suggested order	Note
Clean transient control	LOOKOUT → OTIS	Shape edge, then density
Pressure and body	OTIS → DEBO	Build gradually; Gain Match
Drum parallel impact	DRUMKRUSHGLUE → LOOKOUT	Blend beneath clean bus
Keyed ambience	ANUBIS → effect return	KEY only; no audible key
Rhythmic clearance	ANUBIS on target	DUCK from kick or vocal

Approval checklist

- Sidechain source is correct and audible to the detector.
- KEY and DUCK states match the intended behavior.
- Range is no deeper than required.
- Attack, Hold, and Release follow the groove.
- Bypass and output levels are matched.
- Mono remains stable.
- No clipping, static, harshness, or unintended level loss.
- No more than three active processors per lane unless deliberate.