

Buttons

A, B, the shoulders **LT** and **RT**, **Start** and **Select**. On a desktop build the same controls are Q and W for LT and RT, the arrow keys for the D-pad and space for Start — and the tricky part: the **A** key is **B**, while **S** is **A**.

D-pad Move the cursor.

A Insert note / chain / phrase.

A **A** Insert the next unused one.

A + **D-pad** Change the value under the cursor: up/down by 10, left/right by 1.

B Copy.

B + **A** Cut.

LT + **A** Paste.

B + **D-pad** Fast navigation: page, channel, or 10/1 in value screens. On the song screen, left/right switches Song and Live mode.

RT + **D-pad** Walk between screens.

RT + **B** Mute or unmute the channel.

RT + **A** Solo the channel.

LT + **RT** Undo every mute and solo.

LT + up/down Jump to the next block after a blank row.

LT + (**B,A**) Clone the item into the next unused slot.

Start Play / stop, at the level of the screen you are on.

RT + **Start** Play the song from the edited row, on any screen.

Selections

LT + **B** Select what is under the cursor.

LT + **B** **B** Select the whole row.

LT + **B** **B** **B** Select the whole screen.

D-pad Grow or shrink it, then **B** to copy or **LT+A** to cut.

RT + **B** On a one-column selection in a chain or table: fill values upward.

Live mode

B + left/right on the song screen toggles it. **Start** then queues only the chain under the cursor, not the whole row, so each channel can be on a different row.

Start Queue; the play arrow blinks.

Start **Start** Queue immediately: starts at the end of the current phrase.

LT + **Start** Queue every channel on the row.

RT + **Start** Queue the channel to stop; the arrow becomes an underscore.

Screens

RT + **D-pad** walks the map below; the screen you are on is named top left.

```
project
song ↔ chain ↔ phrase ↔ instrument
      phrase ↑ groove
      phrase ↓ table   instrument ↓ table
```

project Tempo, master, transpose, soft clip, housekeeping, **midi** out, render, save, and **Exit** to quit the tracker.

song The order list: channels across, time down, a chain per cell.

chain Phrases, each row with its own transpose.

phrase Note, instrument, and two commands with their parameters.

instrument Sample, root note, loop, crush, filter, feedback, table.

table Three commands per row, run once per

tick.

groove Ticks per step. Two sixes is straight; 1F swings.

Saving

Stop playback first. Project screen, then **Save Song**; the cursor vanishes while it writes, so do not switch off until it returns. No undo, no autosave — save early and often.

Render writes 16 bit 44.1 kHz WAVs as well as playing: **Stereo** for the mix, **Stems** for a file per channel.

Files

Everything sits beside the binary.

config.xml Screen, theme, MIDI input.

mapping.xml Buttons, joysticks and MIDI events, to tracker events.

lgpt.* / **A** directory per project, holding **lgptsav.dat**.

samplelib / The sample library.

log.txt Everything the tracker says, including the MIDI ports it found.

Commands

Two per phrase row, three per table row. In **aabb**, **aa** is usually a speed or tick count and **bb** the target; speed 00 is instant.

ARPG _{aabc} Arpeggio: cycles root, +a, +b, +c, +d semitones; a zero ends the cycle, so **ARPG** 3000 is root and +3.

CRSH _{aabb} **aa** pre-crush drive, 00 leaves it alone; **bb** crush depth, 0 is 1 bit, **F** is 16 bit.

DLAY _{--bb} Delay the note by **bb** ticks.

FCUT _{aabb} Cutoff to **bb** at speed **aa**: 0080 jumps to half, 1000 closes it.

FLTR _{aabb} Set cutoff **aa** and resonance **bb** out-right. **FLTR** 00FF is unfiltered.

FRES _{aabb} Resonance to **bb** at speed **aa**.

FBMX _{aabb} Feedback mix to **bb** at speed **aa**.

FBTN _{aabb} Feedback tune to **bb** at speed **aa**.

HOP _{aabb} Jump to the next phrase in the chain at row **bb**; **bb=FF** stops the channel. Instant: the rest of the row still runs.

IRTG _{aabb} Retrigger the instrument **bb** semitones up. It accumulates: **IRTG** 0001 climbs a semitone each time.

KILL _{--bb} Stop the instrument after **bb** ticks.

LEGA _{aabb} Exponential slide to **bb** at speed **aa**; **bb** is relative, 00–7F up and 80–FF down.

LPOF _{aaaa} Shift loop start and end by **aaaa**, signed. Reset by the next note.

MCHD _{aabb} Two extra notes **aa** and **bb** semitones above the root, held until the next note; 00 is ignored.

MDCC _{aabb} MIDI continuous controller **aa** to value **bb**, on the running instrument's channel.

MDPG _{--bb} MIDI program change; 0000 is program 1.

MVEL _{--bb} MIDI note velocity.

PAN _{aabb} Pan to **bb** at speed **aa**.

PFIN _{aabb} Pitch fine-tune to **bb** at speed **aa**; 00 back to the root.

PLOF _{aabb} Sample offset. The sample is cut into 256 chunks: jump to chunk **aa**, or move **bb** chunks relative.

PTCH _{aabb} Linear pitch slide to **bb** at speed **aa**.

RTRG _{aabb} Retrigger: loop **bb** ticks from here,

moving **aa** ticks forward on each pass.

TABL _{--bb} Run table **bb**.

TMPO _{--bb} Set tempo. 00 changes nothing, 3C is 60 bpm, 190 is 400 bpm.

VOLM _{aabb} Volume to **bb** at speed **aa**. Start from an instrument at volume 0 to fade sounds in.

Instrument

sample The wav. **A** **A** opens the sample browser.

volume, **pan** Pan 7F is centre.

root note, **detune** Tuning. Your friend when an oscillator sounds wrong.

drive Gain before the crush.

crush Bit depth: **F** clean, lower coarser.

downsample Halves the rate per step up; the aliasing whine.

flt cut/res Cutoff and resonance. Only a low-pass exists in this code.

type Mislabeled: it is wired to the filter *mix*, not a filter type.

Mode Filter distortion: original, bassy, scream.

attenuate Volume after the filter.

fb tune, **fb mix** Feedback delay line. Below 80 the length is the value, above it ten times that.

interpolation linear smooths; **none** takes the nearest sample and grits up low notes.

loop mode none, **loop**, **ping pong**, **oscillator** (the loop becomes a tuned waveform), **looper sync** (retunes the loop to exactly 16 rows).

slices Equal slices from C-2 up; 1 disables.

start, **loop start**, **loop end** Hex sample offsets. End below start plays backwards.

automation, **table** Automation steps the table one row per trigger instead of letting it free-run.

wet/pad print an impulse-response reverb onto the sample. It needs ffmpeg; without it the row does nothing.

MIDI

Whether MIDI is available depends on the platform; the README carries a table. Ports are listed once, at startup, in **log.txt**:

```
[RTMidiService] 1 input port(s)
[RTMidiService] Launchpad:0
```

Input. **config.xml** holds MIDICTRLDEVICE, matched as a *prefix* of the port name, so with no match no input is opened at all. What an event then does is decided by **mapping.xml**:

```
<MAP src="midi:all:0:note:60"
      dst="/event/start" />
```

That reads *midi:device:channel:type:id*, where the channel is 0–F for MIDI 1–16, the device is a name from **log.txt** or **all**, and the type is **note**, **cc**, **pc**, **pb** or **at**. Destinations are the ones the buttons use: **/event/start**, **/event/up**, **/event/a** and so on.

Output. Which interface the tracker sends to is a *project* setting — the **midi** line on the project screen — and notes come from MIDI instruments, whose screen sets channel, volume and gate length. While it plays the tracker also sends clock, start and stop, so it can drive external gear. The list is read when the project opens, so an interface plugged in later is not offered until you reload.

Ports are only enumerated at startup: connect the interface first, then start the tracker. One plugged in later is not offered until you reload.