

# TRI-CITY INATOR

## TRADING CHEATSHEET

Updated 2026-05-19 · Paper mode ON · 15-min ORB · [github.com/djmusstrd/tri-city-inator](https://github.com/djmusstrd/tri-city-inator)

### DAILY SESSION FLOW (all times CT)

| TIME           | ACTION                                                              | WHO  |
|----------------|---------------------------------------------------------------------|------|
| Before 7:30 AM | Open TradingView → TRI CITY INATOR III layout                       | You  |
| Before 7:30 AM | Run tricity in terminal to register crons                           | You  |
| 7:30 AM        | Premarket scanner — ranks gap-up candidates, pushes to TV watchlist | Auto |
| 8:30 AM        | Symbol swap — top 15 candidates loaded into scanner                 | Auto |
| 8:45 AM        | ORH/ORL lock — signal monitor starts (8:30 + 15 min ORB)            | Auto |
| Every 3 min    | Signal check on all 15 symbols — auto-executes qualifying setups    | Auto |
| 3:45 PM        | EOD close — all open positions exited                               | Auto |

### SIGNAL TYPES & ENTRY CONDITIONS

| SIGNAL       | REQUIRED CONDITIONS                                     | STOP                       |
|--------------|---------------------------------------------------------|----------------------------|
| BREAKOUT     | Price > ORH · RSI > 50 · EMA Dev% > 0 · RVOL ≥ 2.0x     | 13¢ below ORH              |
| CONTINUATION | Price > ORH · EMA Dev% 0% to +1.0% · RVOL ≥ 1.75x       | 13¢ below ORH              |
| PULLBACK     | EMA Dev% 0% to +0.8% · RSI 38–55 (rising) · RVOL ≥ 1.5x | EMA20 – 30¢ (widened stop) |

CUP = YES → High-conviction setup. Logged with --cup flag.

### POSITION STRUCTURE (50 – 25 – 25)

| TARGET | TRIGGER | ACTION               | STOP MOVES TO                      |
|--------|---------|----------------------|------------------------------------|
| T1     | +10%    | Sell 50% of position | Breakeven                          |
| T2     | +20%    | Sell 25% of position | T2 price (locked)                  |
| T3     | +30%    | Trail remaining 25%  | Exit on EMA20 + VWAP breach or EOD |
| STOP   | -5%     | Sell ALL             | —                                  |

### ENTRY GUARDS (checked in order before every trade)

| # | CONDITION                                 | DEFAULT    | ACTION                    |
|---|-------------------------------------------|------------|---------------------------|
| 1 | Already traded this symbol today          | —          | BLOCK                     |
| 2 | Already in a position for this symbol     | —          | BLOCK                     |
| 3 | Too many open positions                   | 3 max      | BLOCK                     |
| 4 | Daily loss limit hit                      | -\$300     | BLOCK (circuit breaker)   |
| 5 | After entry cutoff                        | 1:00 PM CT | BLOCK (POST_CUTOFF alert) |
| 6 | SPY down from prior close                 | -1.5%      | BLOCK (bear regime)       |
| 7 | RVOL below setup floor (see RVOL section) | varies     | BLOCK                     |

### RVOL RULES

| FEATURE | DETAIL |
|---------|--------|
|---------|--------|

|                   |                                                                                                |
|-------------------|------------------------------------------------------------------------------------------------|
| Scanner colors    | Red < 1.5x (weak) · Yellow 1.5–2.5x (moderate) · Green ≥ 2.5x (strong)                         |
| Setup floors      | BREAKOUT 2.0x · CONTINUATION 1.75x · PULLBACK 1.5x                                             |
| Afternoon tighten | After noon CT → floor = max(setup floor, 2.0x)                                                 |
| Size boost        | Linear ramp: 1.5x RVOL = no boost → 3.0x RVOL = +25% position size                             |
| Collapse exit     | After T1 hit (breakeven set): if RVOL drops below 1.0x → EXIT                                  |
| Candle type       | PULLBACK: HAMMER = full size · NEUTRAL/BEARISH = -25% size · auto-detected from last 1-min bar |

SCANNER TABLE COLUMNS

| COLUMN   | MEANING                                                        |
|----------|----------------------------------------------------------------|
| SYMBOL   | Ticker (exchange prefix stripped for display)                  |
| PRICE    | Current price on scanner timeframe (15-min)                    |
| RSI      | RSI-14 on 15-min bars                                          |
| EMA DEV% | % distance from 21 EMA. Negative = below EMA, positive = above |
| RVOL     | Current bar volume ÷ 10-bar avg volume                         |
| ORH/ORL  | Opening Range High / Low — locks at 8:45 AM (15-min ORB)       |
| CUP      | 20-bar range < 6% AND price within 1% of 20-bar high           |
| SIGNAL   | BREAKOUT · CONTINUATION · PULLBACK · --- (no signal)           |

TERMINAL COMMANDS

| COMMAND        | ACTION                                                       |
|----------------|--------------------------------------------------------------|
| tricity        | Start session: open TradingView + Claude, register all crons |
| tricity-scan   | Run premarket scanner manually                               |
| tricity-status | Show all open positions                                      |
| tricity        | Today's trade report (P&L, R-multiples)                      |
| tricity-all    | All-time performance report                                  |

Dry-run (no order placed):

```
python -W ignore ~/tri-city-inator/scripts/tri_city_execute.py \  
  --symbol NVDA --price 225.00 --orh 223.16 --orl 218.37 \  
  --rsi 55.0 --ema_dev 0.85 --signal "BREAKOUT" --setup BREAKOUT --dry-run
```

Force EOD close now:

```
python -W ignore ~/tri-city-inator/scripts/tri_city_position_manager.py --eod
```

.ENV REFERENCE

| KEY           | DEFAULT | NOTES                                 |
|---------------|---------|---------------------------------------|
| ALPACA_PAPER  | true    | Set to false for live trading         |
| MIN_GAP_PCT   | 1.5     | Minimum gap % to qualify as candidate |
| FREE_RIDE_PCT | 3       | Profit % to activate free-ride stop   |
| T3_TRAIL_PCT  | 5       | Trailing stop % for T3                |
| MAX_POSITIONS | 3       | Max concurrent open positions         |

|                        |       |                                                         |
|------------------------|-------|---------------------------------------------------------|
| DAILY_LOSS_LIMIT       | -300  | Circuit breaker in dollars                              |
| ORB_MINUTES            | 15    | 5, 15, or 30. Must match TV scanner timeframe           |
| BREAKOUT_MIN_RVOL      | 2.0   | RVOL floor for BREAKOUT entries                         |
| CONTINUATION_MIN_RVOL  | 1.75  | RVOL floor for CONTINUATION entries                     |
| PULLBACK_MIN_RVOL      | 1.5   | RVOL floor for PULLBACK entries                         |
| RVOL_SIZE_BOOST_MAX    | 1.25  | Max position size multiplier at high RVOL               |
| RVOL_SIZE_BOOST_THRESH | 3.0   | RVOL level that triggers max boost                      |
| RVOL_EXIT_FLOOR        | 1.0   | RVOL collapse exit threshold (post-T1 only)             |
| PM_MIN_RVOL            | 2.0   | Afternoon RVOL floor (after noon CT)                    |
| PULLBACK_FAIL_BUFFER   | 0.005 | Fix B: 0.5% buffer below entry before exit fires        |
| EMA_STOP_BUFFER        | 0.30  | Cents below EMA20 for PULLBACK stop (widened)           |
| RE_ENTRY_MAX_LOSS      | 0.50  | Max \$/share loss to allow re-entry after Fix B scratch |

TRADINGVIEW

| ITEM         | VALUE                                                    |
|--------------|----------------------------------------------------------|
| Layout       | TRI CITY INATOR III (ID 168250176)                       |
| Indicator    | Tri-City Inator (Pine v5, shorttitle: Tri-City)          |
| Entity ID    | ur9VaL (used by symbol swap cron)                        |
| Timeframe    | 15-min (must match ORB_MINUTES=15)                       |
| Symbol slots | in_7 through in_21 (15 symbols, auto-swapped at 8:30 AM) |