

```

# garage_counter_lidar_only.py
from rplidar import RPLidar
from flask import Flask, render_template
from threading import Thread
import os
import time

# -----
# CONFIG
# -----
PORT_NAME = '/dev/ttyUSB0'
LINE_A_ANGLE = 80
LINE_B_ANGLE = 100
ANGLE_WIDTH = 2
DISTANCE_THRESHOLD = 2200 # mm
counter = 0
last_cross = None

# -----
# INIT
# -----
lidar = RPLidar(PORT_NAME)
app = Flask(__name__)

# -----
# LIDAR PROCESSING
# -----
def process_scan(scan):
    global counter, last_cross

    line_a_hit = any(
        LINE_A_ANGLE <= angle <= LINE_A_ANGLE + ANGLE_WIDTH and dist <
        DISTANCE_THRESHOLD
        for (_, angle, dist) in scan
    )

    line_b_hit = any(
        LINE_B_ANGLE <= angle <= LINE_B_ANGLE + ANGLE_WIDTH and dist <
        DISTANCE_THRESHOLD
        for (_, angle, dist) in scan
    )

    if line_a_hit:
        if last_cross == 'B':

```

```

        counter -= 1 # EXIT
        print("EXIT detected | Count:", counter)
        last_cross = 'A'

    elif line_b_hit:
        if last_cross == 'A':
            counter += 1 # ENTER
            print("ENTER detected | Count:", counter)
            last_cross = 'B'

# -----
# LIDAR LOOP
# -----
def lidar_loop():
    print("LIDAR started")
    for scan in lidar.iter_scans():
        process_scan(scan)

# -----
# WEB DASHBOARD
# -----
@app.route('/')
def dashboard():
    return render_template('dashboard.html', count=counter)

# -----
# MAIN
# -----
if __name__ == "__main__":
    Thread(target=lidar_loop, daemon=True).start()
    app.run(host='0.0.0.0', port=5000)

```