

A DECLARED STANDPOINT

THE THREE TOOLS, THREE JOBS

ATEM

Switches live. Cuts between the C50 and C400, mixes the mic, records ISO files. The physical buttons you press during the show.

OBS

Graphics + stream. Takes the ATEM feed, lays your animated Dot 1 News overlays on top, sends the show to YouTube / Facebook. Free at obsproject.com.

RESOLVE

Finishes. Opens the ISO recording afterward to re-cut, color-match the two cameras, sweeten audio, and publish the clean version. Free version is plenty.

SIGNAL CHAIN (LIVE)

C50 HDMI → ATEM In 1

C400 HDMI → ATEM In 2

ATEM USB-C → computer (shows as webcam)

OBS → stream out (YouTube / FB / RTMP)

Both Canon Cinema bodies output clean HDMI by default. Do a quick check that no menu overlays ride on the feed before you go live.

MICROPHONE (MD 46)

- The MD 46 is an **XLR** mic; the ATEM has no XLR in.
- **Best route:** plug it into the XLR input on whichever camera you'll mostly be on. Its audio rides embedded in that camera's HDMI into the ATEM, and stays lip-synced.
- Alternative: XLR-to-USB interface into the computer, then nudge audio sync in OBS to match.

RECORD WHILE YOU STREAM

- Turn on **ISO recording** on the ATEM (SD card / drive).
- It saves each camera *and* the program as separate files, plus a **DaVinci Resolve project** with your live cuts already on a timeline.
- So every segment is streamed live *and* re-editable later. No extra work during the show.

OBS SETUP (ONCE)

- 1 Add source **Video Capture Device** → select **ATEM Mini Pro**. This is your switched camera picture.
- 2 Add source **Browser** → Local file → **dot1-news-broadcast.html**. Width 1920, height 1080.
- 3 Drag the Browser source **above** the ATEM capture in the list, so graphics sit on top of camera.
- 4 Paste the Custom CSS below into the Browser source so only the graphics show on air (control panel hidden).
- 5 Open the same HTML in a normal browser window on the side; that window is your **operator panel** for triggering graphics.

```
#panel,.keybtn{display:none!important}
#stageWrap{padding:0!important}
#stage{max-width:none!important;width:100%!important;
height:100%!important;border-radius:0!important}
#stage.key{background:transparent!important}
```

RUN OF SHOW

- 1 **Open:** Play intro (~4s), or Wipe between segments.
- 2 **Bug + clock** stay on all show. LIVE tag off for taped pieces. Pick globe color to suit the shot.
- 3 **Name someone:** type kicker + name + subtitle, Show. Hide after a few seconds.
- 4 **Breaking:** type headline, Show (auto-hides a lower third).
- 5 **Ticker:** headlines split by **I**, Update, Show.
- 6 **Clear all** between segments.

Shortcuts (when not typing): **I** intro **W** wipe **L** lower third **B** breaking **T** ticker **C** clear

FINISH IN RESOLVE (AFTER)

- 1 Open the **.drp project** from the ATEM's card: angles synced, live cuts kept as edit points.
- 2 **Re-cut** anything you missed live.
- 3 **Color page:** match the C50 and C400 so they cut together. Save as a reusable look.
- 4 **Sweeten audio** (levels, noise).
- 5 Export the clean version for the site, app, and socials.

On set, do this: record a few seconds of everyone still and quiet at the top; it gives Resolve clean color reference and a noise sample. Shoot both cameras the same frame rate + picture profile so they conform cleanly.