
Encoder MR Type L, 256-1024 CPT, 3 channels, with line driver





Direction of rotation cw (definition cw p. 78)


Stock program

Standard program					
Special program (on request)	225783	228452	225785	228456	225787
Туре					
Counts per turn	256	500	512	1000	1024
Number of channels	3	3	3	3	3
Max. operating frequency (kHz)	80	200	160	200	320
Max. speed (rpm)	18750	24000	18750	12000	18750
Max. operating frequency (kHz)					320

overall length



maxon Modular System										
+ Motor	Page	+ Gearhead	Page		Overall length [mm] / • see Gearhead					
RE 30, 15 W	147			32	79.4	79.4	79.4	79.4	79.4	
RE 30, 15 W	147	GP 32, 0.75 - 4.5 Nm	394	32	•	•	•	•	•	
RE 30, 60 W	148			32	79.4	79.4	79.4	79.4	79.4	
RE 30, 60 W	148	GP 32, 0.75 - 4.5 Nm	392	32	•	•	•	•	•	
RE 30, 60 W	148	GP 32, 0.75 - 6.0 Nm		32	•	•	•	•	•	
RE 30, 60 W	148	GP 32 S	426-433	32	•	•	•	•	•	
RE 35, 90 W	149			32	82.4	82.4	82.4	82.4	82.4	
RE 35, 90 W	149	GP 32, 0.75 - 4.5 Nm	392	32	•	•	•	•	•	
RE 35, 90 W	149	GP 32, 0.75 - 6.0 Nm	394-399	32	•	•	•	•	•	
RE 35, 90 W	149	GP 32, 4.0 - 8.0 Nm	400	32	•	•	•	•	•	
RE 35, 90 W	149	GP 42, 3 - 15 Nm	405	32	•	•	•	•	•	
RE 35, 90 W	149	GP 32 S	426-433	32	•	•	•	•	•	
RE 40, 25 W	150			32	82.4	82.4	82.4	82.4	82.4	
RE 40, 150 W	151			32	82.4	82.4	82.4	82.4	82.4	
RE 40, 150 W	151	GP 42, 3 - 15 Nm	405	32	•	•	•	•	•	
RE 40, 150 W	151	GP 52, 4 - 30 Nm	410	32	•	•	•	•	•	
A-max 32	176			32	72.7	72.7	72.7	72.7	72.7	
A-max 32	176	GP 32, 0.75 - 6.0 Nm	394-398	32	•	•	•	•	•	
A-max 32	176	GS 38, 0.1 - 0.6 Nm	404	32	•	•	•	•	•	
A-max 32	176	GP 32 S	426-433	32	•	•	•	•	•	
EC-max 40, 70 W	252			31.8	73.7	73.7	73.7	73.7	73.7	
EC-max 40, 70 W	252	GP 42, 3 - 15 Nm	406	31.8	•	•	•	•	•	
EC-max 40, 120 W	253			31.8	103.7	103.7	103.7	103.7	103.7	
EC-max 40, 120 W	253	GP 42, 3.0 - 15.0 Nm	406	31.8	•	•	•	•	•	
EC-max 40, 120 W	253	GP 52, 4 - 30 Nm	411	31.8	•	•	•	•	•	



maxon sensor 479 March 2021 edition / subject to change