ReaOrganize User Manual

Version 1.46 | by vazupReaperScripts | 03/2026

1. Introduction

ReaOrganize is a session organizer for REAPER. It lets you design your session's structure, defining groups, track send routing, FX chains, panning and colors — and then executes everything in one click via the RUN button. The core idea is that ReaOrganize works as a blueprint layer on top of your REAPER session. You define how your session should be structured in the script, and RUN builds it.

Requires: The ReaImGui extension (install via ReaPack: Extensions > ReaPack > Browse packages > search "ReaImGui").

100 groups / 8 sends per group / 8 global sends

Basic Workflow

1. Open ReaOrganize from the REAPER Scripts menu.
2. The **Track Panel** (right) lists all tracks in your session.
3. The **Group Panel** (left) lets you define groups — named, colored buckets with send routing, FX chains and send slots.
4. Assign tracks to groups using the Group dropdown in the Track Panel.
5. Configure your groups: set names, colors, routing, FX chains and sends.
6. Hit **RUN** — ReaOrganize creates folder tracks, colors child tracks, wires up sends and applies FX chains.

2. Group Panel

The Group Panel is the left side of the window. It is the heart of ReaOrganize.

Groups Table

Each row represents one group. Groups are created with **Add Group** and removed with the **X** delete button on each row.

Column	Description
#	Group number and selection checkbox. Click to select/deselect.
Name	Editable name field. This becomes the folder track name in REAPER.
X	Delete this group. CTRL+click deletes all selected groups.
Color	Sets the color of the tracks on that group. Opens a color picker.
R	Randomize the color.
A	Cycle alternates through brightness steps for the color.
Routing	Group parent routing to master or another group for nested groups.

Group Send Slots

Each group can have up to 8 send slots. These represent aux send tracks that will be created for the tracks assigend to that group.

Each send slot has:

- **Name** - the send track name
- **Color** - the send track color
- **FX** - an FX chain assigned to the send track
- **S / 0 / inf / clr** - set a custom dB value / set to 0dB / set to -inf / clear the send value for all tracks in this group
- **Pre** - checkbox for pre-fader mode

Buttons

Located below the options panel.

- **Add Group** - adds a group
- **Add Groups** - adds multiple groups via a prompt
- **Reset Groups** - resets all groups to default
- **Reset Sends** – resets all sends, keeping all groups intact

Global Sends

Below the groups table is the **Global Sends** section. Global sends are shared send tracks that can receive from all tracks in the session. They are placed at the bottom of the session.

Each global send has the same controls as group sends (name, color, FX, S/0/inf/clr, Pre).

Master Panel

Click the **FX** button to assign an FX chain to the Master Track. Click the **X** button to clear it. The Master FX chain is applied on every RUN.

3. Options Panel

Below Global Sends is the **Options** section:

Option	Description
FX Folder	Custom folder path for FX Chains. Defaults to REAPER's FXChains folder.
Global Filter	Hides specific types of plugins/chains.
Sends Position	Place send tracks at the top/bottom of the group, or at the bottom of the session.
Parent Color	Custom shared color for all group tracks. Option to use the individual group track colors.
Send Color	Default color for newly created send tracks.
FX Bypass	Bypass created insert FX and/or FX chains on RUN.

4. Track Panel

The Track Panel is the right side of the window. It lists every track in your REAPER session. If there is no value in a tracks send tab, no send routing will be created. If there is "-inf" in the tracks send tab, a send routing will be created with a value of -inf. So with that you can decide which tracks of a group will be actually routed to that groups send.

Columns

Column	Description
#	Track number, colored with the assigned group color.
☑	Selection checkbox. Header checkbox selects/deselects all.
Name	Track name, changes are applied immediately to REAPER.
Group	Dropdown to assign the track to a group.
◎◎	Links this track with the next one, executes "Xenakios/SWS: Implode items to takes and pan symmetrically".
Pan	Pan value (e.g. C, 30L, 45R). CTRL+Enter applies to all selected tracks.
S1-	Send value fields per active send slot. CTRL+Enter applies to all selected tracks.
GS1-	Global send value fields. CTRL+Enter applies to all selected tracks.
FX	Assigned FX chain for this track. Click to open the FX picker. CTRL+Select FX applies to all selected tracks.

Buttons below the Track Panel

Button	Description
Refresh	Re-scans all REAPER tracks and updates the list.
Clear Groups	Removes all group assignments from all tracks.
Set All	Opens a scope prompt with a value field — sets all send values in the track panel to the typed value.
0 All	Sets all send values to 0 dB (All or Selected tracks).
inf All	Sets all send values to -inf (All or Selected tracks).
Clr All	Clears all send values (All or Selected tracks).
Ctr Pan	Centers pan for all eligible tracks (All or Selected).
Spr Pan	Spreads pan across eligible tracks. Enter a spread value (0–100) in the field next to the button.
Set Track FX	Step-through prompt to assign FX chains to tracks one by one.
Guess Track FX	Auto-applies the first matching FX chain (by track name) to All or Selected tracks.
Save / Load	Saves/loads the current full track panel state.
← / →	Undo / Redo (20 steps).
RUN	Executes the full session build.

Scope Prompt

Many buttons open a scope prompt with three choices:

All - apply to all tracks / **Selected Only** - apply only to selected tracks / **Cancel** - Cancels the prompt

5. Set FX / Guess FX

These two features help you quickly assign FX chains to groups, global sends and the master (group panel) as well as the tracks (track panel). Based on name matching against your FX chain folder, fx are listed or auto applied.

Set FX

Opens a step-through prompt that walks through every group, every global send, and the master one by one. For each item:

- The **name** is shown in large text.
- The **current FX chain** (if any) is shown in green, with an **X** to clear it.
- A list of **matching FX chains** from the FX folder is shown (matched by name containment, case-insensitive).
- Double-click a chain to apply it and advance automatically.

Buttons / Keys:

Action	Description
Apply	Assign the selected chain and move to next
Skip / SPACE	Skip this item, move to next
Cancel / ESC	Stop the process
← / →	Inc/Dec through groups/sends/master
Double-click	Apply FX Chain and advance

Guess FX

Opens the All / Selected / Cancel scope prompt and auto-applies the **first matching FX chain** to all groups (and global sends + master when "All" is chosen). No manual selection needed.

6. Preset Slots, Export and Import

Preset Slots

ReaOrganize has 8 preset slots displayed in the Group Panel. Each slot can store the complete state of the Group Panel (all groups, sends, global sends, options and master).

Button	Description
Store	Save current group panel state into this slot.
Load	Load this slot's state into the group panel.
X	Delete this preset slot.

Presets are saved to REAPER's local ExtState and persist between sessions and REAPER restarts.

Export / Import / Capture buttons

Five buttons at the bottom of the Group Panel:

Button	Description
Export	Export all preset slots to a file.
Import	Import preset slots from a file.
Capture	Capture the current REAPER session into the group panel (see Section 7).
Set FX	Step-through FX assignment prompt for groups, sends and master (see Section 5).
Guess FX	Auto-apply FX chains by name matching (see Section 5).

7. Capture Function

The **Capture** button scans your current REAPER session and automatically populates the Group Panel from what it finds.

What gets captured

Element	How it's captured
Groups	All folder tracks become groups — name, color, pan and routing (nested folders → parent group, top-level folders → Master).
Group Sends	Non-folder tracks inside a folder (with at least one incoming send) become send slots for that group.
Global Sends	Non-folder top-level tracks with at least one incoming send become global sends.
FX chains	The FX chain of each captured folder, send and global send track is extracted and saved as a .RfxChain file.
Master FX	The Master Track's FX chain is captured and saved as Master.RfxChain.

Capture workflow

1. Click **Capture**.
2. Confirm the overwrite prompt.
3. Enter an optional **Prefix** and **Suffix** for the generated .RfxChain filenames. The suffix defaults to today's date (ddmmyyyy). Leave either field empty to omit it.
4. If any .RfxChain files would be overwritten, a conflict dialog appears with three choices: **Overwrite**, **Unique Name** (appends _01, _02 etc.) or **Cancel**.
5. Capture runs and the Group Panel is populated.

Notes

- If your session has more folder tracks than the current number of groups, new group slots are added automatically (up to the maximum of 100).
- All captured FX chains are saved to the configured FX folder (or REAPER's default FXChains folder).
- A send track is recognized by having at least one incoming send from another track.

8. Key Commands / Shortcuts

Group Panel

Shortcut	Target	Action
CTRL + click	Group checkbox	Exclusive, selects all groups routed to same destination
SHIFT + click	Group checkbox	Range select from last clicked
ALT + click	Group checkbox	Exclusive single select (just this group)
CTRL + drag	Group drag handle	Move all selected groups together
CTRL + click	Delete (X) button	Delete all selected groups
CTRL + click	Folder FX X button	Clear folder FX on all selected groups
CTRL + click	Color swatch	Apply chosen color to all selected groups
SHIFT + click	Color swatch	Apply chosen color to entire subtree
CTRL + click	R button	Randomize color for all selected groups
SHIFT + click	R button	Randomize color for entire subtree
CTRL + click	A button	Cycle alternate brightness for all selected groups
SHIFT + click	A button	Cycle alternate brightness for entire subtree
CTRL + Routing	Routing dropdown	Apply same routing to all selected groups
CTRL + click	Folder FX picker	Apply FX to all selected groups
SHIFT + click	Folder FX picker	Apply FX to entire subtree

Track Panel

Shortcut	Target	Action
CTRL + click	Track checkbox	Exclusive select - selects all tracks in same group
ALT + click	Track checkbox	Exclusive single select (just this track)
SHIFT + click	Track checkbox	Range select
CTRL + click	Track FX picker	Apply FX to all selected tracks
SHIFT + click	Track FX picker	Apply FX to all tracks in same group hierarchy
CTRL + click	Track FX X button	Clear FX on all selected tracks
CTRL + Enter	Send field	Apply send value to all selected tracks
CTRL + Enter	Pan field	Apply pan value to all selected tracks

Set FX / Set Track FX Prompt

Shortcut	Action
SPACE	Skip current item
ESC	Cancel and close
←	Go to previous item
→	Go to next item
Double-click	Apply chain and advance