



### Easy temperature monitoring

The IMS Room Temperature Sensor is used exclusively with the Sensaphone IMS system to measure and provide real time indoor air temperatures from 5° to 122°F. The connection between the sensor and IMS unit is made via RJ-45 patch cable. The sensor may be mounted either on a wall or to a single-gang electrical box.

### TECH SPECS

|                          |                                                     |
|--------------------------|-----------------------------------------------------|
| Name                     | Room Temperature Sensor                             |
| Sensor Temperature Range | 5° to 122°F   -15° to 50°C                          |
| Accuracy                 | ± 3°F   ±1.7°C                                      |
| Connection               | RJ45                                                |
| Housing                  | Plastic                                             |
| Dimensions               | 4.5 x 2.8 x 1.3”   110 x 70 x 30mm                  |
| Item Includes            | Temperature sensor, wall mounting hardware, hex key |

| Product Name                                   | Part Number |
|------------------------------------------------|-------------|
| IMS Solution Room Temperature Sensor . . . . . | .IMS-4810E  |



Family owned and made in the USA since 1985

901 Tryens Road

Aston, PA 19301

Phone: 877-373-2700

Web: [sensaphone.com](http://sensaphone.com)



