

 PT. MNA SERANG	WORKING INSTRUCTION	WI/MNASRG-E&I-19-201	
		Dept.	ENGINEERING
	PM LA & GROUNDING	Section	E&I
		Revision	0
		Effective Date	01-Sep-19
		Page	1 of 2

Identifikasi / Identification



Identifikasi grounding pit yang akan dilakukan pengecekan (*Identify the grounding pit which will be checked*)

Pengecekan / Checking



Persiapkan peralatan (*Prepeare the tester equipment (earth tester)))*

Identifikasi lokasi pengecekan apakah banyak tanah atau sudah dicor (*identify the checking location, is it still many of soil or already been casted*)



Jika lokasi grounding pit masih banyak tanah, gunakan cara pengukuran metode 3 titik (*If the grounding pit location still much of soil, use the 3 spot ground checks*)

Untuk mengukur tahanan tanah menggunakan metode 3 titik, lepaskan dahulu grounding rod dari sambungan lain. (*To measure earth resistivity using 3 spot method, firstly release the grounding rod from another junction*)



Ada 3 kabel; Hijau, Merah, Biru, pasang kabel hijau (plug earth) ke grounding pit, pasang kabel biru (plug potensial) ke batang ukur dengan jarak 20 cm dari grounding pit, pasang kabel merah (plug current) ke batang ukur dengan jarak 2 kali dari batang potensial, kemudian tekan test. (*There are 3 wires: Green, Red, and Blue, plug the green wire(Earth plug) to grounding pit, plug the blue wire (potential plug) to measurement rod with distance of 20 cm from grounding pit, then lastly plug the red wire (current plug) tto measurement rod with distance of twice from potential measurement rod, then test it.*)

 PT. MNA SERANG	WORKING INSTRUCTION	WI/MNASRG-E&I-19-010	
		Dept.	ENGINEERING
	PM LA & GROUNDING	Section	E&I
		Revision	0
		Effective Date	
		Page	2 of 2

Pengecekan / Checking



Jika lokasi grounding pit masih sudah dicor, gunakan cara pengukuran metode clamp (If the grounding pit location already being casted, use the clamp measurement method)

Karena pengukuran ini dilakukan dalam kondisi online, cari sambungan kabel ground yang terhubung ke grounding pit (Because this measurement must be done in online condition, find the grounding cable junction which connected to grounding pit)



Pasang clamp dengan tanda kabel biru-merah ke socket besar ke earth tester, kemudian pasang clamp dengan tanda kabel hitam-merah ke socket paling atas dan bawah di earth tester (Plug the clamp with blue-red sign to biggest middle socket on earth tester, plug the clamp with black-red sign to top and bottom socket on earth tester)

Buat jarak antar clamp sekitar 5 sampai 10 cm, pastikan arah induksi tidak terbalik (make the distance between clamp about 5 to 10 cm, make sure the induction sign not on opposite condition)



Tekan tombol tes, lakukan pengtesan 3 kali agar hasilnya meyakinkan untuk semua metode, (Press the test button, do it 3 times to make sure for all methods.)