

GFCI Testing for IPOS

First step:
Inform the workshop operation content, inform the operation purpose, and sign the work ticket.



Second step: Prepare the document & Fluke 1663 Multifunction Tester



Third step: Prepare the lead cable according to the equipment socket to be tested.



Fourth step: Connect cable lead to the Fluke 1663 and plug into the socket outlet which is connected to the GFCI



Fifth step: Turn on the Fluke 1663 by pressing the green button, set the selector switch to ΔN to measure current and press the test button



The sixth step: Record the current measurement result that are displayed into the form FMNASRG-E&I-19-113 for !P IPOS and FMNASRG-E&I-19-114 for 3P IPOS



Seventh step: Set the selector switch to ΔT for measuring the trip time and then press the test button



Eighth step: Record the trip time measurement result that are displayed into the form FMNASRG-E&I-19-113 for !P IPOS and FMNASRG-E&I-19-114 for 3P IPOS



Nineth step: Install the green electrical integrity for "Passed" and ref for "Not Passed"

