IO List - CPKO Fractionation 1

Wilmar Industrial Complex PT MNA Serang, Indonesia

End Customer: **Wilmar Industrial Complex PT MNA Serang, Indonesia**

End Customer Reference Number:

Document File Name: **3258585-PSS-PASH-DWG-00038**

Document Status: **For Final**

Authorisations

	Name	Function	Signature
Developed By:	Zul Hasyidi Hassan	Project Engineer	ZHH
Reviewed By:	Liow Kok Loong	Lead Engineer	LKL
Released By:	Mohd. Nazim Ismail	Project Manager	MNI

Distribution

Name	Company	Name	Company

Revision History

Rev	Status	Description	Date	Developed By	Reviewed By
A	For Review	Issued for Review	18-Sep-18	ZHH	LKL
B	For Review	Issued for Review	11-Oct-18	ZHH	LKL
0	For Final	Issued for Final	31-Oct-19	ZHH	LKL

© Emerson Automation Solution. All rights reserved. Unauthorized duplication, in whole or in part, is prohibited. Trademarks identified in this document are owned by one of the Emerson Process Management group of companies. Unless otherwise agreed to in writing by the parties, any information provided in this document is confidential or proprietary and may not be used or disclosed without the expressed written permission of Emerson Process Management.

Emerson Automation Solution
Process System and Solutions
No. 1, Block A, Jalan SS13/5, SS13
Subang Jaya, 47500, Selangor
Malaysia
T +60 (3) 5624-2888
F +60 (3) 5638-1010
www.EmersonProcess.com

										RIO CABINET															SYSTEM CABINET	
										Marshalling						Relay					DELTA V				DELTA V	
Vendor's tags	Wilmar's Tags	Emerson Database Tags	Module Name	Description	Type	IO Type	Range Proposed (kg/H)	Signal Type	Electrical Connection	Cabinet Name	TB Name	Term. (+)	Term. (-)	24V(+) Term.	24V(-) Term.	Term. (+)	Term. (-)	Name	Term. (+)	Term. (-)	Slot	Channel	Term. (+)	Term. (-)	Cabinet Name	Controller
PF1001A/B	PF1001A/B-SC	CF1-PF1001A/B-SC	CF1_PF1001A_B	Batch Fill Pump	Motor current feedback	AI		4-20 mA	3 wire	CF1-RMCC_1	TB-AI	1	2								S1	1	1	2	SFO-DCS-001	SFO-CTRL1
PF1078C2	PF1078C2-SC	CF1-PF1078C2-SC	CF1_PF1078C2	Batch Fill Pump	Motor current feedback	AI		4-20 mA	3 wire	CF1-RMCC_1	TB-AI	3	4								S1	2	3	4	SFO-DCS-001	SFO-CTRL1
~~PU-1405A~~	~~PU1405A-CU~~	~~CF1-PU1405A-CU~~	~~CF1_PU1405A~~	~~Chilled Water Distribution Pump~~	~~Motor current feedback~~	~~AI~~		~~4-20 mA~~	~~2 wire~~	CF1-RMCC_1	TB-AI	5	6								S1	3	5	6	SFO-DCS-001	SFO-CTRL1
~~PU-1405B~~	~~PU1405B-CU~~	~~CF1-PU1405B-CU~~	~~CF1_PU1405B~~	~~Chilled Water Distribution Pump~~	~~Motor current feedback~~	~~AI~~		~~4-20 mA~~	~~2 wire~~	CF1-RMCC_1	TB-AI	7	8								S1	4	7	8	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-AI	9	10								S1	5	9	10	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-AI	11	12								S1	6	11	12	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-AI	13	14								S1	9	17	18	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-AI	15	16								S1	10	19	20	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-AI	17	18								S1	11	21	22	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-AI	19	20								S1	12	23	24	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-AI	21	22								S1	13	25	26	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-AI	23	24								S1	14	27	28	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-AI	25	26								S1	15	29	30	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-AI	27	28								S1	16	31	32	SFO-DCS-001	SFO-CTRL1
PF1046OV	PU1316OV-XL	CF1-PU1316OV-XL	CF1_PU1316OV	Filter Overflow Recirculating Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	1	2								S3	1	1	NA	SFO-DCS-001	SFO-CTRL1
PF1046OV	PU1316OV-XA	CF1-PU1316OV-XA	CF1_PU1316OV	Filter Overflow Recirculating Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	3	4								S3	2	2	NA	SFO-DCS-001	SFO-CTRL1
PF1050/02A	PU105002A-XL	CF1-PU105002A-XL	CF1_PU105002A	Crystalliser Tempered Water Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	5	6								S3	3	3	NA	SFO-DCS-001	SFO-CTRL1
PF1050/02A	PU105002A-XA	CF1-PU105002A-XA	CF1_PU105002A	Crystalliser Tempered Water Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	7	8								S3	4	4	NA	SFO-DCS-001	SFO-CTRL1
PF1050/02S1	PU11502S1-XL	CF1-PU11502S1-XL	CF1_PU11502S1	Statoliser Tempered Water Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	9	10								S3	5	5	NA	SFO-DCS-001	SFO-CTRL1
PF1050/02S1	PU11502S1-XA	CF1-PU11502S1-XA	CF1_PU11502S1	Statoliser Tempered Water Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	11	12								S3	6	6	NA	SFO-DCS-001	SFO-CTRL1
PF1050/02S2	PU1150S2-XL	CF1-PU1150S2-XL	CF1_PU1150S2	Statoliser Tempered Water Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	13	14								S3	7	7	NA	SFO-DCS-001	SFO-CTRL1
PF1050/02S2	PU1150S2-XA	CF1-PU1150S2-XA	CF1_PU1150S2	Statoliser Tempered Water Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	15	16								S3	8	8	NA	SFO-DCS-001	SFO-CTRL1
PF1050/16	PU125016-XL	CF1-PU125016-XL	CF1_PU125016	Tempered Water Circulating Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	17	18								S3	9	9	NA	SFO-DCS-001	SFO-CTRL1
PF1050/16	PU125016-XA	CF1-PU125016-XA	CF1_PU125016	Tempered Water Circulating Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	19	20								S3	10	10	NA	SFO-DCS-001	SFO-CTRL1
PF1078C1	PU1478C1-XL	CF1-PU1478C1-XL	CF1_PU1478C1	Chilled Water Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	21	22								S3	11	11	NA	SFO-DCS-001	SFO-CTRL1
PF1078C1	PU1478C1-XA	CF1-PU1478C1-XA	CF1_PU1478C1	Chilled Water Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	23	24								S3	12	12	NA	SFO-DCS-001	SFO-CTRL1
PF1078D	PU1478D-XL	CF1-PU1478D-XL	CF1_PU1478D	Warm Water Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	25	26								S3	13	13	NA	SFO-DCS-001	SFO-CTRL1
PF1078D	PU1478D-XA	CF1-PU1478D-XA	CF1_PU1478D	Warm Water Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	27	28								S3	14	14	NA	SFO-DCS-001	SFO-CTRL1
PF1078TR	PU1178TR-XL	CF1-PU1178TR-XL	CF1_PU1178TR	Tracing Water Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	29	30								S3	15	15	NA	SFO-DCS-001	SFO-CTRL1
PF1078TR	PU1178TR-XA	CF1-PU1178TR-XA	CF1_PU1178TR	Tracing Water Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	31	32								S3	16	16	NA	SFO-DCS-001	SFO-CTRL1
PF1082B	PU13082B-XL	CF1-PU13082B-XL	CF1_PU13082B	Olein Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	33	34								S3	17	17	NA	SFO-DCS-001	SFO-CTRL1
PF1082B	PU13082B-XA	CF1-PU13082B-XA	CF1_PU13082B	Olein Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	35	36								S3	18	18	NA	SFO-DCS-001	SFO-CTRL1
PF1082C	PU13082C-XL	CF1-PU13082C-XL	CF1_PU13082C	Filter Cleaning Hot Olein Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	37	38								S3	19	19	NA	SFO-DCS-001	SFO-CTRL1
PF1082C	PU13082C-XA	CF1-PU13082C-XA	CF1_PU13082C	Filter Cleaning Hot Olein Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	39	40								S3	20	20	NA	SFO-DCS-001	SFO-CTRL1
PF1082ST	PU1310ST-XL	CF1-PU1310ST-XL	CF1_PU1310ST	Stearin Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	41	42								S3	21	21	NA	SFO-DCS-001	SFO-CTRL1
PF1082ST	PU1310ST-XA	CF1-PU1310ST-XA	CF1_PU1310ST	Stearin Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	43	44								S3	22	22	NA	SFO-DCS-001	SFO-CTRL1
MF1002A-FAN	FN1002A-XL	CF1-FN1002A-XL	CF1_FN1002A	MF1002A Force Cooling Fan	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	45	46								S3	23	23	NA	SFO-DCS-001	SFO-CTRL1
MF1002A-FAN	FN1002A-XA	CF1-FN1002A-XA	CF1_FN1002A	MF1002A Force Cooling Fan	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	47	48								S3	24	24	NA	SFO-DCS-001	SFO-CTRL1
MF1009S-1-FAN	FN1119S1-XL	CF1-FN1119S1-XL	CF1_FN1119S1	MF1009S-1 Force Cooling Fan	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	49	50								S3	25	25	NA	SFO-DCS-001	SFO-CTRL1
MF1009S-1-FAN	FN1119S1-XA	CF1-FN1119S1-XA	CF1_FN1119S1	MF1009S-1 Force Cooling Fan	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	51	52								S3	26	26	NA	SFO-DCS-001	SFO-CTRL1
MF1009S-2-FAN	FN1109S2-XL	CF1-FN1109S2-XL	CF1_FN1109S2	MF1009S-2 Force Cooling Fan	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	53	54								S3	27	27	NA	SFO-DCS-001	SFO-CTRL1
MF1009S-2-FAN	FN1109S2-XA	CF1-FN1109S2-XA	CF1_FN1109S2	MF1009S-2 Force Cooling Fan	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	55	56								S3	28	28	NA	SFO-DCS-001	SFO-CTRL1
PF1002A-FAN	FN1102A-XL	CF1-FN1102A-XL	CF1_FN1102A	PF1002A Force Cooling Fan	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	57	58								S3	29	29	NA	SFO-DCS-001	SFO-CTRL1
PF1002A-FAN	FN1102A-XA	CF1-FN1102A-XA	CF1_FN1102A	PF1002A Force Cooling Fan	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	59	60								S3	30	30	NA	SFO-DCS-001	SFO-CTRL1
PF1016A/S-FAN	FN1116AS-XL	CF1-FN1116AS-XL	CF1_FN1116AS	PF1016A/S Force Cooling Fan	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	61	62								S3	31	31	NA	SFO-DCS-001	SFO-CTRL1
PF1016A/S-FAN	FN1116AS-XA	CF1-FN1116AS-XA	CF1_FN1116AS	PF1016A/S Force Cooling Fan	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	63	64								S3	32	32	NA	SFO-DCS-001	SFO-CTRL1
PF1078/16/1-FAN	FN1278161-XL	CF1-FN1278161-XL	CF1_FN1278161	PF1078/16/1 Force Cooling Fan	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	65	66								S4	1	1	NA	SFO-DCS-001	SFO-CTRL1
PF1078/16/1-FAN	FN1278161-XA	CF1-FN1278161-XA	CF1_FN1278161	PF1078/16/1 Force Cooling Fan	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	67	68								S4	2	2	NA	SFO-DCS-001	SFO-CTRL1
PF1078/16/2-FAN	FN1278162-XL	CF1-FN1278162-XL	CF1_FN1278162	PF1078/16/2 Force Cooling Fan	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	69	70								S4	3	3	NA	SFO-DCS-001	SFO-CTRL1
PF1078/16/2-FAN	FN1278162-XA	CF1-FN1278162-XA	CF1_FN1278162	PF1078/16/2 Force Cooling Fan	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	71	72								S4	4	4	NA	SFO-DCS-001	SFO-CTRL1
F1002S-1	STT1102S1-XL	CF1-STT1102S1-XL	CF1_STT1102S1	Statolizer	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	73	74								S4	5	5	NA	SFO-DCS-001	SFO-CTRL1
F1002S-1	STT1102S1-XA	CF1-STT1102S1-XA	CF1_STT1102S1	Statolizer	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	75	76								S4	6	6	NA	SFO-DCS-001	SFO-CTRL1
F1002S-2	STT1102S2-XL	CF1-STT1102S2-XL	CF1_STT1102S2	Statolizer	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	77	78								S4	7	7	NA	SFO-DCS-001	SFO-CTRL1
F1002S-2	STT1102S2-XA	CF1-STT1102S2-XA	CF1_STT1102S2	Statolizer	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	79	80								S4	8	8	NA	SFO-DCS-001	SFO-CTRL1
F1016A1	FP1216A1-XL	CF1-FP1216A1-XL	CF1_FP1216A1	Filter Press 1	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	81	82								S4	9	9	NA	SFO-DCS-001	SFO-CTRL1
F1016A1	FP1216A1-XA	CF1-FP1216A1-XA	CF1_FP1216A1	Filter Press 1	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	83	84								S4	10	10	NA	SFO-DCS-001	SFO-CTRL1
F1016A2	FP1216A2-XL	CF1-FP1216A2-XL	CF1_FP1216A2	Filter Press 2	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	85	86								S4	11	11	NA	SFO-DCS-001	SFO-CTRL1
F1016A2	FP1216A2-XA	CF1-FP1216A2-XA	CF1_FP1216A2	Filter Press 2	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	87	88								S4	12	12	NA	SFO-DCS-001	SFO-CTRL1
CH-1402	CH1402-XL	CF1-CH1402-XL	CF1_CH1402	Wica Chiller	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	89	90								S4	13	13	NA	SFO-DCS-001	SFO-CTRL1
CH-1402	CH1402-XA	CF1-CH1402-XA	CF1_CH1402	Wica Chiller	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	91	92								S4	14	14	NA	SFO-DCS-001	SFO-CTRL1
PU-605A	PU605A-XL	CF1-PU605A-XL	CF1_PU605A	Condensate Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	93	94								S4	15	15	NA	SFO-DCS-001	SFO-CTRL1
PU-605A	PU605A-XA	CF1-PU605A-XA	CF1_PU605A	Condensate Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	95	96								S4	16	16	NA	SFO-DCS-001	SFO-CTRL1
PF1001A/B	PF1001A/B-XL	CF1-PF1001A/B-XL	CF1_PF1001A_B	Batch Fill Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	97	98								S4	17	17	NA	SFO-DCS-001	SFO-CTRL1
PF1001A/B	PF1001A/B-XA	CF1-PF1001A/B-XA	CF1_PF1001A_B	Batch Fill Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	99	100								S4	18	18	NA	SFO-DCS-001	SFO-CTRL1
PF1078C2	PF1078C2-XL	CF1-PF1078C2-XL	CF1_PF1078C2	Batch Fill Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	101	102								S4	19	19	NA	SFO-DCS-001	SFO-CTRL1
PF1078C2	PF1078C2-XA	CF1-PF1078C2-XA	CF1_PF1078C2	Batch Fill Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	103	104								S4	20	20	NA	SFO-DCS-001	SFO-CTRL1
PU-904A	PU904A-XL	CF1-PU904A-XL	CF1_PU904A	Effluent Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	105	106								S4	21	21	NA	SFO-DCS-001	SFO-CTRL1
PU-904A	PU904A-XA	CF1-PU904A-XA	CF1_PU904A	Effluent Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	107	108								S4	22	22	NA	SFO-DCS-001	SFO-CTRL1
~~CT-307~~	~~CT307-XL~~	~~CF1-CT307-XL~~	~~CF1_CT307~~	~~Cooling Tower CPKO & EIE~~	~~Motor run feedback~~	~~DI~~		~~DI Dry Contact~~	~~2 wire~~	CF1-RMCC_1	TB-DI	109	110								S4	23	23	NA	SFO-DCS-001	SFO-CTRL1
~~CT-307~~	~~CT307-XA~~	~~CF1-CT307-XA~~	~~CF1_CT307~~	~~Cooling Tower CPKO & EIE~~	~~Motor trip feedback~~	~~DI~~		~~DI Dry Contact~~	~~2 wire~~	CF1-RMCC_1	TB-DI	111	112								S4	24	24	NA	SFO-DCS-001	SFO-CTRL1
PU-605B	PU605B-XL	CF1-PU605B-XL	CF1_PU605B	Cooling Tower CPKO & EIE	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	113	114								S4	25	25	NA	SFO-DCS-001	SFO-CTRL1
PU-605B	PU605B-XA	CF1-PU605B-XA	CF1_PU605B	Cooling Tower CPKO & EIE	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RMCC_1	TB-DI	115	116								S4	26	26	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-DI	117	118								S4	27	27	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-DI	119	120								S4	28	28	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-DI	121	122								S4	29	29	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-DI	123	124								S4	30	30	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-DI	125	126								S4	31	31	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-DI	127	128								S4	32	32	NA	SFO-DCS-001	SFO-CTRL1
PF1046OV	PU1316OV-HS	CF1-PU1316OV-HS	CF1_PU1316OV	Filter Overflow Recirculating Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	1	2								S6	1	1	NA	SFO-DCS-001	SFO-CTRL1
PF1050/02A	PU105002A-HS	CF1-PU105002A-HS	CF1_PU105002A	Crystalliser Tempered Water Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	3	4								S6	2	2	NA	SFO-DCS-001	SFO-CTRL1
PF1050/02S1	PU11502S1-HS	CF1-PU11502S1-HS	CF1_PU11502S1	Statoliser Tempered Water Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	5	6								S6	3	3	NA	SFO-DCS-001	SFO-CTRL1
PF1050/02S2	PU1150S2-HS	CF1-PU1150S2-HS	CF1_PU1150S2	Statoliser Tempered Water Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	7	8								S6	4	4	NA	SFO-DCS-001	SFO-CTRL1
PF1050/16	PU125016-HS	CF1-PU125016-HS	CF1_PU125016	Tempered Water Circulating Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	9	10								S6	5	5	NA	SFO-DCS-001	SFO-CTRL1
PF1078C1	PU1478C1-HS	CF1-PU1478C1-HS	CF1_PU1478C1	Chilled Water Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	11	12								S6	6	6	NA	SFO-DCS-001	SFO-CTRL1
PF1078D	PU1478D-HS	CF1-PU1478D-HS	CF1_PU1478D	Warm Water Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	13	14								S6	7	7	NA	SFO-DCS-001	SFO-CTRL1
PF1078TR	PU1178TR-HS	CF1-PU1178TR-HS	CF1_PU1178TR	Tracing Water Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	15	16								S6	8	8	NA	SFO-DCS-001	SFO-CTRL1
PF1082B	PU13082B-HS	CF1-PU13082B-HS	CF1_PU13082B	Olein Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	17	18								S6	9	9	NA	SFO-DCS-001	SFO-CTRL1
PF1082C	PU13082C-HS	CF1-PU13082C-HS	CF1_PU13082C	Filter Cleaning Hot Olein Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	19	20								S6	10	10	NA	SFO-DCS-001	SFO-CTRL1
PF1082ST	PU1310ST-HS	CF1-PU1310ST-HS	CF1_PU1310ST	Stearin Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	21	22								S6	11	11	NA	SFO-DCS-001	SFO-CTRL1
MF1002A-FAN	FN1002A-HS	CF1-FN1002A-HS	CF1_FN1002A	MF1002A Force Cooling Fan	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	23	24								S6	12	12	NA	SFO-DCS-001	SFO-CTRL1
MF1009S-1-FAN	FN1119S1-HS	CF1-FN1119S1-HS	CF1_FN1119S1	MF1009S-1 Force Cooling Fan	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	25	26								S6	13	13	NA	SFO-DCS-001	SFO-CTRL1
MF1009S-2-FAN	FN1109S2-HS	CF1-FN1109S2-HS	CF1_FN1109S2	MF1009S-2 Force Cooling Fan	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	27	28								S6	14	14	NA	SFO-DCS-001	SFO-CTRL1
PF1002A-FAN	FN1102A-HS	CF1-FN1102A-HS	CF1_FN1102A	PF1002A Force Cooling Fan	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	29	30								S6	15	15	NA	SFO-DCS-001	SFO-CTRL1
PF1016A/S-FAN	FN1116AS-HS	CF1-FN1116AS-HS	CF1_FN1116AS	PF1016A/S Force Cooling Fan	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	31	32								S6	16	16	NA	SFO-DCS-001	SFO-CTRL1
PF1078/16/1-FAN	FN1278161-HS	CF1-FN1278161-HS	CF1_FN1278161	PF1078/16/1 Force Cooling Fan	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	33	34								S6	17	17	NA	SFO-DCS-001	SFO-CTRL1
PF1078/16/2-FAN	FN1278162-HS	CF1-FN1278162-HS	CF1_FN1278162	PF1078/16/2 Force Cooling Fan	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	35	36								S6	18	18	NA	SFO-DCS-001	SFO-CTRL1
F1002S-1	STT1102S1-HS	CF1-STT1102S1-HS	CF1_STT1102S1	Statolizer	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	37	38								S6	19	19	NA	SFO-DCS-001	SFO-CTRL1
F1002S-2	STT1102S2-HS	CF1-STT1102S2-HS	CF1_STT1102S2	Statolizer	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	39	40								S6	20	20	NA	SFO-DCS-001	SFO-CTRL1
F1016A1	FP1216A1-HS	CF1-FP1216A1-HS	CF1_FP1216A1	Filter Press 1	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	41	42								S6	21	21	NA	SFO-DCS-001	SFO-CTRL1
F1016A2	FP1216A2-HS	CF1-FP1216A2-HS	CF1_FP1216A2	Filter Press 2	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	43	44								S6	22	22	NA	SFO-DCS-001	SFO-CTRL1
CH-1402	CH1402-HS	CF1-CH1402-HS	CF1_CH1402	Wica Chiller	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	45	46								S6	23	23	NA	SFO-DCS-001	SFO-CTRL1
PU-605A	PU605A-HS	CF1-PU605A-HS	CF1_PU605A	Condensate Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	47	48								S6	24	24	NA	SFO-DCS-001	SFO-CTRL1
PF1001A/B	PF1001A/B-HS	CF1-PF1001A/B-HS	CF1_PF1001A_B	Batch Fill Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	49	50								S6	25	25	NA	SFO-DCS-001	SFO-CTRL1
PF1078C2	PF1078C2-HS	CF1-PF1078C2-HS	CF1_PF1078C2	Batch Fill Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	51	52								S6	26	26	NA	SFO-DCS-001	SFO-CTRL1
PU-904A	PU904A-HS	CF1-PU904A-HS	CF1_PU904A	Effluent Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	53	54								S6	27	27	NA	SFO-DCS-001	SFO-CTRL1
~~CT-307~~	~~CT307-HS~~	~~CF1-CT307-HS~~	~~CF1_CT307~~	~~Cooling Tower CPKO & EIE~~	~~Motor start command~~	~~DO~~		~~24VDC Wet supply~~	~~2 wire~~	CF1-RMCC_1	TB-DO	55	56								S6	28	28	NA	SFO-DCS-001	SFO-CTRL1
PU-605B	PU605B-HS	CF1-PU605B-HS	CF1_PU605B	Cooling Tower CPKO & EIE	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RMCC_1	TB-DO	57	58								S6	29	29	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-DO	59	60								S6	30	30	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-DO	61	62								S6	31	31	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RMCC_1	TB-DO	63	64								S6	32	32	NA	SFO-DCS-001	SFO-CTRL1
F1002S-1	STT1102S1	CF1-STT1102S1	CF1_STT1102S1	Statolizer	Statolizer Modbus/Profinet Data	Modbus TCP/Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
F1002S-2	STT1102S2	CF1-STT1102S2	CF1_STT1102S2	Statolizer	Statolizer Modbus/Profinet Data	Modbus TCP/Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
F1016A1	FP1216A1	CF1-FP1216A1	CF1_FP1216A1	Filter Press 1	Filter Press Modbus/Profinet Data	Modbus TCP/Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
F1016A2	FP1216A2	CF1-FP1216A2	CF1_FP1216A2	Filter Press 2	Filter Press Modbus/Profinet Data	Modbus TCP/Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1002A	AG1002A-HS	CF1-AG1002A-HS	CF1_AG1002A	Agitator for TX Crystallizer	Motor start command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1002A	AG1002A-XL	CF1-AG1002A-XL	CF1_AG1002A	Agitator for TX Crystallizer	Motor run feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1002A	AG1002A-XA	CF1-AG1002A-XA	CF1_AG1002A	Agitator for TX Crystallizer	Motor trip feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1002A	AG1002A-SC	CF1-AG1002A-SC	CF1_AG1002A	Agitator for TX Crystallizer	Motor speed command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1002A	AG1002A-CU	CF1-AG1002A-CU	CF1_AG1002A	Agitator for TX Crystallizer	Motor current feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1002A	AG1002A-SP	CF1-AG1002A-SP	CF1_AG1002A	Agitator for TX Crystallizer	Motor speed feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~MF1009S-1~~	~~PU1119S1-HS~~	~~CF1-PU1119S1-HS~~	~~CF1_PU1119S1~~	~~Statoliser Cake Conveyor~~	~~Motor start command~~	~~Profinet~~				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~MF1009S-1~~	~~PU1119S1-XL~~	~~CF1-PU1119S1-XL~~	~~CF1_PU1119S1~~	~~Statoliser Cake Conveyor~~	~~Motor run feedback~~	~~Profinet~~				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-1	RE1119S1-XA	CF1-RE1119S1-XA	CF1_RE1119S1	Statoliser Cake Conveyor	Motor trip feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-1	RE1119S1-SC	CF1-RE1119S1-SC	CF1_RE1119S1	Statoliser Cake Conveyor	Motor speed command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-1	RE1119S1-CU	CF1-RE1119S1-CU	CF1_RE1119S1	Statoliser Cake Conveyor	Motor current feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-1	RE1119S1-SP	CF1-RE1119S1-SP	CF1_RE1119S1	Statoliser Cake Conveyor	Motor speed feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~MF1009S-2~~	~~PU1109S2-HS~~	~~CF1-PU1109S2-HS~~	~~CF1_PU1109S2~~	~~Statoliser Cake Conveyor~~	~~Motor start command~~	~~Profinet~~				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~MF1009S-2~~	~~PU1109S2-XL~~	~~CF1-PU1109S2-XL~~	~~CF1_PU1109S2~~	~~Statoliser Cake Conveyor~~	~~Motor run feedback~~	~~Profinet~~				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-2	RE1109S2-XA	CF1-RE1109S2-XA	CF1_RE1109S2	Statoliser Cake Conveyor	Motor trip feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-2	RE1109S2-SC	CF1-RE1109S2-SC	CF1_RE1109S2	Statoliser Cake Conveyor	Motor speed command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-2	RE1109S2-CU	CF1-RE1109S2-CU	CF1_RE1109S2	Statoliser Cake Conveyor	Motor current feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-2	RE1109S2-SP	CF1-RE1109S2-SP	CF1_RE1109S2	Statoliser Cake Conveyor	Motor speed feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1002A	PU1102A-HS	CF1-PU1102A-HS	CF1_PU1102A	Crystallizer Discharge Pump	Motor start command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1002A	PU1102A-XL	CF1-PU1102A-XL	CF1_PU1102A	Crystallizer Discharge Pump	Motor run feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1002A	PU1102A-XA	CF1-PU1102A-XA	CF1_PU1102A	Crystallizer Discharge Pump	Motor trip feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1002A	PU1102A-SC	CF1-PU1102A-SC	CF1_PU1102A	Crystallizer Discharge Pump	Motor speed command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1002A	PU1102A-CU	CF1-PU1102A-CU	CF1_PU1102A	Crystallizer Discharge Pump	Motor current feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1002A	PU1102A-SP	CF1-PU1102A-SP	CF1_PU1102A	Crystallizer Discharge Pump	Motor speed feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1

										RIO CABINET															SYSTEM CABINET	
										Marshalling						Relay					DELTA V				DELTA V	
Vendor's tags	Wilmar's Tags	Emerson Database Tags	Module Name	Description	Type	IO Type	Range Proposed (kg/H)	Signal Type	Electrical Connection	Cabinet Name	TB Name	Term. (+)	Term. (-)	24V(+) Term.	24V(-) Term.	Term. (+)	Term. (-)	Name	Term. (+)	Term. (-)	Slot	Channel	Term. (+)	Term. (-)	Cabinet Name	Controller
PF1016A/S	RE1116AS-HS	CF1-RE1116AS-HS	CF1_RE1116AS	Filter Feed Pump	Motor start command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1016A/S	RE1116AS-XL	CF1-RE1116AS-XL	CF1_RE1116AS	Filter Feed Pump	Motor run feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1016A/S	RE1116AS-XA	CF1-RE1116AS-XA	CF1_RE1116AS	Filter Feed Pump	Motor trip feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1016A/S	RE1116AS-SC	CF1-RE1116AS-SC	CF1_RE1116AS	Filter Feed Pump	Motor speed command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1016A/S	RE1116AS-CU	CF1-RE1116AS-CU	CF1_RE1116AS	Filter Feed Pump	Motor current feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1016A/S	RE1116AS-SP	CF1-RE1116AS-SP	CF1_RE1116AS	Filter Feed Pump	Motor speed feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1078/16/1	PU1278161-HS	CF1-PU1278161-HS	CF1_PU1278161	Squeezing Water Pump	Motor start command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1078/16/1	PU1278161-XL	CF1-PU1278161-XL	CF1_PU1278161	Squeezing Water Pump	Motor run feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1078/16/1	PU1278161-XA	CF1-PU1278161-XA	CF1_PU1278161	Squeezing Water Pump	Motor current feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1078/16/1	PU1278161-SC	CF1-PU1278161-SC	CF1_PU1278161	Squeezing Water Pump	Motor speed command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1078/16/1	PU1278161-CU	CF1-PU1278161-CU	CF1_PU1278161	Squeezing Water Pump	Motor speed feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1078/16/1	PU1278161-SP	CF1-PU1278161-SP	CF1_PU1278161	Squeezing Water Pump	Motor trip feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1078/16/2	PU1278162-HS	CF1-PU1278162-HS	CF1_PU1278162	Squeezing Water Pump	Motor start command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1078/16/2	PU1278162-XL	CF1-PU1278162-XL	CF1_PU1278162	Squeezing Water Pump	Motor run feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1078/16/2	PU1278162-XA	CF1-PU1278162-XA	CF1_PU1278162	Squeezing Water Pump	Motor trip feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1078/16/2	PU1278162-SC	CF1-PU1278162-SC	CF1_PU1278162	Squeezing Water Pump	Motor speed command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1078/16/2	PU1278162-CU	CF1-PU1278162-CU	CF1_PU1278162	Squeezing Water Pump	Motor current feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
PF1078/16/2	PU1278162-SP	CF1-PU1278162-SP	CF1_PU1278162	Squeezing Water Pump	Motor speed feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-1404A~~	~~PU1404A-HS~~	~~CF1-PU1404A-HS~~	~~CF1_PU1404A~~	~~Chilled Water Circulating Pump~~	~~Motor start command~~	~~Profinet~~		~~24VDC Wet supply~~	~~2 wire~~	SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-1404A~~	~~PU1404A-XL~~	~~CF1-PU1404A-XL~~	~~CF1_PU1404A~~	~~Chilled Water Circulating Pump~~	~~Motor run feedback~~	~~Profinet~~		~~DI Dry Contact~~	~~2 wire~~	SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-1404A~~	~~PU1404A-XA~~	~~CF1-PU1404A-XA~~	~~CF1_PU1404A~~	~~Chilled Water Circulating Pump~~	~~Motor trip feedback~~	~~Profinet~~		~~DI Dry Contact~~	~~2 wire~~	SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-1404A~~	~~PU1404A-CU~~	~~CF1-PU1404A-CU~~	~~CF1_PU1404A~~	~~Chilled Water Circulating Pump~~	~~Motor current feedback~~	~~Profinet~~		~~DI Dry Contact~~	~~2 wire~~	SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-1404B~~	~~PU1404B-HS~~	~~CF1-PU1404B-HS~~	~~CF1_PU1404B~~	~~Chilled Water Circulating Pump~~	~~Motor start command~~	~~Profinet~~		~~24VDC Wet supply~~	~~2 wire~~	SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-1404B~~	~~PU1404B-XL~~	~~CF1-PU1404B-XL~~	~~CF1_PU1404B~~	~~Chilled Water Circulating Pump~~	~~Motor run feedback~~	~~Profinet~~		~~DI Dry Contact~~	~~2 wire~~	SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-1404B~~	~~PU1404B-XA~~	~~CF1-PU1404B-XA~~	~~CF1_PU1404B~~	~~Chilled Water Circulating Pump~~	~~Motor trip feedback~~	~~Profinet~~		~~DI Dry Contact~~	~~2 wire~~	SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-1404B~~	~~PU1404B-CU~~	~~CF1-PU1404B-CU~~	~~CF1_PU1404B~~	~~Chilled Water Circulating Pump~~	~~Motor current feedback~~	~~Profinet~~		~~DI Dry Contact~~	~~2 wire~~	SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-1	RE1119S1-HR	CF1-RE1119S1-HR	CF1_RE1119S1	Statoliser Cake Conveyor	Motor start right direction command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-1	RE1119S1-HL	CF1-RE1119S1-HL	CF1_RE1119S1	Statoliser Cake Conveyor	Motor start Left direction command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-1	RE1119S1-XY	CF1-RE1119S1-XY	CF1_RE1119S1	Statoliser Cake Conveyor	Motor right run feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-1	RE1119S1-XZ	CF1-RE1119S1-XZ	CF1_RE1119S1	Statoliser Cake Conveyor	Motor Left run feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-2	RE1109S2-HR	CF1-RE1109S2-HR	CF1_RE1109S2	Statoliser Cake Conveyor	Motor start right direction command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-2	RE1109S2-HL	CF1-RE1109S2-HL	CF1_RE1109S2	Statoliser Cake Conveyor	Motor start Left direction command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-2	RE1109S2-XY	CF1-RE1109S2-XY	CF1_RE1109S2	Statoliser Cake Conveyor	Motor right run feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
MF1009S-2	RE1109S2-XZ	CF1-RE1109S2-XZ	CF1_RE1109S2	Statoliser Cake Conveyor	Motor Left run feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-307	CT307-HS	CF1-CT307-HS	CF1_CT307	Cooling Tower CPKO & EIE	Motor start command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-307	CT307-XL	CF1-CT307-XL	CF1_CT307	Cooling Tower CPKO & EIE	Motor run feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-307	CT307-XA	CF1-CT307-XA	CF1_CT307	Cooling Tower CPKO & EIE	Motor trip feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-307	CT307-SC	CF1-CT307-SC	CF1_CT307	Cooling Tower CPKO & EIE	Motor speed command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-307	CT307-CU	CF1-CT307-CU	CF1_CT307	Cooling Tower CPKO & EIE	Motor current feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-307	CT307-SP	CF1-CT307-SP	CF1_CT307	Cooling Tower CPKO & EIE	Motor speed feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-308A~~	~~PU308A-CU~~	~~CF1-PU308A-CU~~	~~CF1_PU308A~~	~~Cooling Water Pump~~	~~Motor current feedback~~	~~Profinet~~				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-308B~~	~~PU308B-CU~~	~~CF1-PU308B-CU~~	~~CF1_PU308B~~	~~Cooling Water Pump~~	~~Motor current feedback~~	~~Profinet~~				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-308A~~	~~PU308A-XL~~	~~CF1-PU308A-XL~~	~~CF1_PU308A~~	~~Cooling Water Pump~~	~~Motor run feedback~~	~~Profinet~~				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-308A~~	~~PU308A-XA~~	~~CF1-PU308A-XA~~	~~CF1_PU308A~~	~~Cooling Water Pump~~	~~Motor trip feedback~~	~~Profinet~~				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-308B~~	~~PU308B-XL~~	~~CF1-PU308B-XL~~	~~CF1_PU308B~~	~~Cooling Water Pump~~	~~Motor run feedback~~	~~Profinet~~				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-308B~~	~~PU308B-XA~~	~~CF1-PU308B-XA~~	~~CF1_PU308B~~	~~Cooling Water Pump~~	~~Motor trip feedback~~	~~Profinet~~				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-308A~~	~~PU308A-HS~~	~~CF1-PU308A-HS~~	~~CF1_PU308A~~	~~Cooling Water Pump~~	~~Motor start command~~	~~Profinet~~				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
~~PU-308B~~	~~PU308B-HS~~	~~CF1-PU308B-HS~~	~~CF1_PU308B~~	~~Cooling Water Pump~~	~~Motor start command~~	~~Profinet~~				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-308A	CT308A-HS	CF1-CT308A-HS	CF1_CT308A	Cooling Tower CPKO & EIE	Motor start command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-308A	CT308A-XL	CF1-CT308A-XL	CF1_CT308A	Cooling Tower CPKO & EIE	Motor run feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-308A	CT308A-XA	CF1-CT308A-XA	CF1_CT308A	Cooling Tower CPKO & EIE	Motor trip feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-308A	CT308A-SC	CF1-CT308A-SC	CF1_CT308A	Cooling Tower CPKO & EIE	Motor speed command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-308A	CT308A-CU	CF1-CT308A-CU	CF1_CT308A	Cooling Tower CPKO & EIE	Motor current feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-308A	CT308A-SP	CF1-CT308A-SP	CF1_CT308A	Cooling Tower CPKO & EIE	Motor speed feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-308B	CT308B-HS	CF1-CT308B-HS	CF1_CT308B	Cooling Tower CPKO & EIE	Motor start command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-308B	CT308B-XL	CF1-CT308B-XL	CF1_CT308B	Cooling Tower CPKO & EIE	Motor run feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-308B	CT308B-XA	CF1-CT308B-XA	CF1_CT308B	Cooling Tower CPKO & EIE	Motor trip feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-308B	CT308B-SC	CF1-CT308B-SC	CF1_CT308B	Cooling Tower CPKO & EIE	Motor speed command	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-308B	CT308B-CU	CF1-CT308B-CU	CF1_CT308B	Cooling Tower CPKO & EIE	Motor current feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
CT-308B	CT308B-SP	CF1-CT308B-SP	CF1_CT308B	Cooling Tower CPKO & EIE	Motor speed feedback	Profinet				SFO-DCS-001															SFO-DCS-001	SFO-CTRL1
FT-F82B/C	FT1382BC	CF1-FT1382BC	CF1_FT1382BC	Flow Meter	Mass Flowmeter	AI	0-24554 kg/hr	4-20 mA HART	4 wire	CF1-RIO-001	TB-AI	1	2	+ 1	- 1						S1	1	1	2	SFO-DCS-001	SFO-CTRL1
FT-F82ST	FT1382ST	CF1-FT1382ST	CF1_FT1382ST	Flow Meter	Mass Flowmeter	AI	0-15614 kg/hr	4-20 mA HART	4 wire	CF1-RIO-001	TB-AI	3	4	+ 2	- 2						S1	2	3	4	SFO-DCS-001	SFO-CTRL1
FT-F01A	FT1001A	CF1-FT1001A	CF1_FT1001A	Flow Meter	Mass Flowmeter	AI	0-168940 kg/hr	4-20 mA HART	4 wire	CF1-RIO-001	TB-AI	5	6	+ 3	- 3						S1	3	5	6	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI4W-S	1	2	+ 4	- 4						S1	4	7	8	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI4W-S	3	4	+ 5	- 5						S1	5	9	10	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI4W-S	5	6	+ 6	- 6						S1	6	11	12	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI4W-S	7	8	+ 7	- 7						S1	7	13	14	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI4W-S	9	10	+ 8	- 8						S1	8	15	16	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI4W-S	11	12	+ 9	- 9						S1	9	17	18	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI4W-S	13	14	+ 10	- 10						S1	10	19	20	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI4W-S	15	16	+ 11	- 11						S1	11	21	22	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI4W-S	17	18	+ 12	- 12						S1	12	23	24	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI4W-S	19	20	+ 13	- 13						S1	13	25	26	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI4W-S	21	22	+ 14	- 14						S1	14	27	28	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI4W-S	23	24	+ 15	- 15						S1	15	29	30	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI4W-S	25	26	+ 16	- 16						S1	16	31	32	SFO-DCS-001	SFO-CTRL1
FT-F52S	FT1452S	CF1-FT1452S	CF1_FT1452S	Flow Meter	Vortex Flowmeter	AI	0-1763 kg/hr	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	9	10								S2	1	1	2	SFO-DCS-001	SFO-CTRL1
TT-F21C-1	TT1321C1	CF1-TT1321C1	CF1_TT1321C1	Actuator Valve	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	11	12								S2	2	3	4	SFO-DCS-001	SFO-CTRL1
LT-F02A-1	LT1002A1	CF1-LT1002A1	CF1_LT1002A1	Level Transmitter	Differential Pressure	AI	0-5000mmH2O (0-100%)	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	13	14								S2	3	5	6	SFO-DCS-001	SFO-CTRL1
LT-F78/16-1	LT1278161	CF1-LT1278161	CF1_LT1278161	Level Transmitter	Differential Pressure	AI	0-3420mmH2O (0-100%)	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	15	16								S2	4	7	8	SFO-DCS-001	SFO-CTRL1
LT-F78D-1	LT1478D1	CF1-LT1478D1	CF1_LT1478D1	Level Transmitter	Differential Pressure	AI	0-4950mmH2O (0-100%)	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	17	18								S2	5	9	10	SFO-DCS-001	SFO-CTRL1
LT-F82B-1	LT1382B1	CF1-LT1382B1	CF1_LT1382B1	Level Transmitter	Differential Pressure	AI	0-2810mmH2O (0-100%)	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	19	20								S2	6	11	12	SFO-DCS-001	SFO-CTRL1
LT-F82C-1	LT1382C1	CF1-LT1382C1	CF1_LT1382C1	Level Transmitter	Differential Pressure	AI	0-2810mmH2O (0-100%)	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	21	22								S2	7	13	14	SFO-DCS-001	SFO-CTRL1
LT-F82ST-1	LT1382ST1	CF1-LT1382ST1	CF1_LT1382ST1	Level Transmitter	Differential Pressure	AI	0-1250mmH2O (0-100%)	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	23	24								S2	8	15	16	SFO-DCS-001	SFO-CTRL1
PT-PF02A	PT1102A	CF1-PT1102A	CF1_PT1102A	Pressure Transmitter & Indicator	Gauge	AI	0-6 barg	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	25	26								S2	9	17	18	SFO-DCS-001	SFO-CTRL1
PT-PF16A/S-1	PT1116AS1	CF1-PT1116AS1	CF1_PT1116AS1	Pressure Transmitter & Indicator	Gauge	AI	0-10 barg	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	27	28								S2	10	19	20	SFO-DCS-001	SFO-CTRL1
PT-PF78/16/1-1	PT1278161	CF1-PT1278161	CF1_PT1278161	Pressure Transmitter & Indicator	Gauge	AI	0-30 barg	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	29	30								S2	11	21	22	SFO-DCS-001	SFO-CTRL1
PT-PF78/16/2-1	PT1278162	CF1-PT1278162	CF1_PT1278162	Pressure Transmitter & Indicator	Gauge	AI	0-30 barg	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	31	32								S2	12	23	24	SFO-DCS-001	SFO-CTRL1
TT-F460V-1	TT1360V1	CF1-TT1360V1	CF1_TT1360V1	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	33	34								S2	13	25	26	SFO-DCS-001	SFO-CTRL1
TT-F78/16-1	TT1278161	CF1-TT1278161	CF1_TT1278161	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	35	36								S2	14	27	28	SFO-DCS-001	SFO-CTRL1
TT-F78B-1	TT1478B1	CF1-TT1478B1	CF1_TT1478B1	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	37	38								S2	15	29	30	SFO-DCS-001	SFO-CTRL1
TT-F78C-1	TT1478C1	CF1-TT1478C1	CF1_TT1478C1	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	39	40								S2	16	31	32	SFO-DCS-001	SFO-CTRL1
TT-F78D-1	TT1478D1	CF1-TT1478D1	CF1_TT1478D1	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	41	42								S3	1	1	2	SFO-DCS-001	SFO-CTRL1
TT-F82B-1	TT1382B1	CF1-TT1382B1	CF1_TT1382B1	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	43	44								S3	2	3	4	SFO-DCS-001	SFO-CTRL1
TT-F82C-1	TT1382C1	CF1-TT1382C1	CF1_TT1382C1	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	45	46								S3	3	5	6	SFO-DCS-001	SFO-CTRL1
TT-F82ST-1	TT1382ST1	CF1-TT1382ST1	CF1_TT1382ST1	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	47	48								S3	4	7	8	SFO-DCS-001	SFO-CTRL1
TT-F02A-1	TT1002A1	CF1-TT1002A1	CF1_TT1002A1	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	49	50								S3	5	9	10	SFO-DCS-001	SFO-CTRL1
TT-F21A-1	TT1021A1	CF1-TT1021A1	CF1_TT1021A1	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	51	52								S3	6	11	12	SFO-DCS-001	SFO-CTRL1
TT-F21D-1	TT1421D1	CF1-TT1421D1	CF1_TT1421D1	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	53	54								S3	7	13	14	SFO-DCS-001	SFO-CTRL1
TT-F21ST-1	TT1321ST1	CF1-TT1321ST1	CF1_TT1321ST1	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	55	56								S3	8	15	16	SFO-DCS-001	SFO-CTRL1
TT-PF50/02A-1	TT1050A1	CF1-TT1050A1	CF1_TT1050A1	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	57	58								S3	9	17	18	SFO-DCS-001	SFO-CTRL1
TT-PF50/02S1-1	TT1150S11	CF1-TT1150S11	CF1_TT1150S11	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	59	60								S3	10	19	20	SFO-DCS-001	SFO-CTRL1
TT-PF50/02S2-1	TT1150S21	CF1-TT1150S21	CF1_TT1150S21	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	61	62								S3	11	21	22	SFO-DCS-001	SFO-CTRL1
TT-PF78TR-1	TT1178TR1	CF1-TT1178TR1	CF1_TT1178TR1	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	63	64								S3	12	23	24	SFO-DCS-001	SFO-CTRL1
PT-F02S1-1	PT1102S11	CF1-PT1102S11	CF1_PT1102S11	Pressure Transmitter & Indicator	Gauge	AI	0-6 barg	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	65	66								S3	13	25	26	SFO-DCS-001	SFO-CTRL1
PT-F02S2-1	PT1102S21	CF1-PT1102S21	CF1_PT1102S21	Pressure Transmitter & Indicator	Gauge	AI	0-6 barg	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	67	68								S3	14	27	28	SFO-DCS-001	SFO-CTRL1
PT-F16A1-1	PT1216A11	CF1-PT1216A11	CF1_PT1216A11	Pressure Transmitter & Indicator	Gauge	AI	0-6 barg	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	69	70								S3	15	29	30	SFO-DCS-001	SFO-CTRL1
PT-F16A2-1	PT1216A21	CF1-PT1216A21	CF1_PT1216A21	Pressure Transmitter & Indicator	Gauge	AI	0-6 barg	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	71	72								S3	16	31	32	SFO-DCS-001	SFO-CTRL1
TT-F02S1-C	TT1102S1C	CF1-TT1102S1C	CF1_TT1102S1C	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	73	74								S4	1	1	2	SFO-DCS-001	SFO-CTRL1
TT-F02S1-E	TT1102S1E	CF1-TT1102S1E	CF1_TT1102S1E	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	75	76								S4	2	3	4	SFO-DCS-001	SFO-CTRL1
TT-F02S1-F	TT1102S1F	CF1-TT1102S1F	CF1_TT1102S1F	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	77	78								S4	3	5	6	SFO-DCS-001	SFO-CTRL1
TT-F02S2-C	TT1102S2C	CF1-TT1102S2C	CF1_TT1102S2C	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	79	80								S4	4	7	8	SFO-DCS-001	SFO-CTRL1
TT-F02S2-E	TT1102S2E	CF1-TT1102S2E	CF1_TT1102S2E	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	81	82								S4	5	9	10	SFO-DCS-001	SFO-CTRL1
TT-F02S2-F	TT1102S2F	CF1-TT1102S2F	CF1_TT1102S2F	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	83	84								S4	6	11	12	SFO-DCS-001	SFO-CTRL1
TT-F16A1-1	TT1216A11	CF1-TT1216A11	CF1_TT1216A11	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	85	86								S4	7	13	14	SFO-DCS-001	SFO-CTRL1
TT-F16A2-1	TT1216A21	CF1-TT1216A21	CF1_TT1216A21	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	87	88								S4	8	15	16	SFO-DCS-001	SFO-CTRL1
LT-F78C	LT1478C	CF1-LT1478C	CF1_LT1478C	Level Transmitter	Differential Pressure	AI	0-4750mmH2O (0-100%)	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	89	90								S4	9	17	18	SFO-DCS-001	SFO-CTRL1
PT-SAC/R-2	PT1400R2	CF1-PT1400R2	CF1_PT1400R2	Pressure Transmitter & Indicator	Gauge	AI	0-20 barg	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	91	92								S4	10	19	20	SFO-DCS-001	SFO-CTRL1
TT-F81/16-1	TT121161	CF1-TT121161	CF1_TT121161	Temperature Transmitter & Indicator	temperature differential	AI	0-150 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	93	94								S4	11	21	22	SFO-DCS-001	SFO-CTRL1
TT-MPF16A/S-1	TT1116A-1	CF1-TT1116A-1	CF1_TT1116A_1	Temperature Transmitter & Indicator		AI		4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	95	96								S4	12	23	24	SFO-DCS-001	SFO-CTRL1
TT-F12	TT1412	CF1-TT1412	CF1_TT1412	Temperature Transmitter & Indicator		AI		4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	97	98								S4	13	25	26	SFO-DCS-001	SFO-CTRL1
TT-F13	TT1413	CF1-TT1413	CF1_TT1413	Temperature Transmitter & Indicator		AI		4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	99	100								S4	14	27	28	SFO-DCS-001	SFO-CTRL1
FT-307	FT307	CF1-FT307	CF1_FT307	Flow Transmitter		AI		4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	101	102								S4	15	29	30	SFO-DCS-001	SFO-CTRL1
~~FT-1329~~	~~FT1329~~	~~CF1-FT1329~~	~~CF1_FT1329~~	~~Flow Transmitter~~		~~AI~~		~~4-20 mA HART~~	~~2 wire~~	CF1-RIO-001	TB-AI	103	104								S4	16	31	32	SFO-DCS-001	SFO-CTRL1
FT-1536	FT1536	CF1-FT1536	CF1_FT1536	Flow Transmitter		AI		4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	105	106								S5	1	1	2	SFO-DCS-001	SFO-CTRL1
FT-1537	FT1537	CF1-FT1537	CF1_FT1537	Flow Transmitter		AI		4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	107	108								S5	2	3	4	SFO-DCS-001	SFO-CTRL1
FT-1490	FT1490	CF1-FT1490	CF1_FT1490	Flow Transmitter	6508-02	AI		4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	109	110								S5	3	5	6	SFO-DCS-001	SFO-CTRL1
FT-1491	FT1491	CF1-FT1491	CF1_FT1491	Flow Transmitter	6508-02	AI		4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	111	112								S5	4	7	8	SFO-DCS-001	SFO-CTRL1
~~FT-1666~~	~~FT1666~~	~~CF1-FT1666~~	~~CF1_FT1666~~	~~Flow Transmitter~~	~~6511-02~~	~~AI~~		~~4-20 mA HART~~	~~2 wire~~	CF1-RIO-001	TB-AI	113	114								S5	5	9	10	SFO-DCS-001	SFO-CTRL1
FT-1667	FT1667	CF1-FT1667	CF1_FT1667	Flow Transmitter	6511-02	AI		4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	115	116								S5	6	11	12	SFO-DCS-001	SFO-CTRL1
LT-1403	LT1403	CF1-LT1403	CF1_LT1403	Level Tansmitter		AI		4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	117	118								S5	7	13	14	SFO-DCS-001	SFO-CTRL1
~~TT-1275~~	~~TT1275~~	~~CF1-TT1275~~	~~CF1_TT1275~~	~~Temperature Transmitter~~		~~AI~~		~~4-20 mA HART~~	~~2 wire~~	CF1-RIO-001	TB-AI	119	120								S5	8	15	16	SFO-DCS-001	SFO-CTRL1
TT-1728	TT1728	CF1-TT1728	CF1_TT1728	Temperature Transmitter		AI		4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	121	122								S5	9	17	18	SFO-DCS-001	SFO-CTRL1
TT-1264	TT1264	CF1-TT1264	CF1_TT1264	Temperature Transmitter		AI		4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	123	124								S5	10	19	20	SFO-DCS-001	SFO-CTRL1
TT-H01	TTH01	CF1-TTH01	CF1_TTH01		RTD	AI	0 - 100 DegC	4-20 mA HART	2 wire	CF1-RIO-001	TB-AI	125	126								S5	11	21	22	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI	127	128								S5	12	23	24	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI	129	130								S5	13	25	26	SFO-DCS-001	SFO-CTRL1

Emerson Automation Solutiont - Confidential and Proprietary

										RIO CABINET															SYSTEM CABINET	
										Marshalling						Relay					DELTA V				DELTA V	
Vendor's tags	Wilmar's Tags	Emerson Database Tags	Module Name	Description	Type	IO Type	Range Proposed (kg/H)	Signal Type	Electrical Connection	Cabinet Name	TB Name	Term. (+)	Term. (-)	24V(+) Term.	24V(-) Term.	Term. (+)	Term. (-)	Name	Term. (+)	Term. (-)	Slot	Channel	Term. (+)	Term. (-)	Cabinet Name	Controller
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI	131	132								S5	14	27	28	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI	133	134								S5	15	29	30	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AI	135	136								S5	16	31	32	SFO-DCS-001	SFO-CTRL1
TCV-F21A-1	TCV1021A1	CF1-TCV1021A1	CF1_TT1021A1	Control Valve	Electro-pneumatic	AO	0 - 100%	4-20 mA HART	2 wire	CF1-RIO-001	TB-AO	1	2								S6	1	1	2	SFO-DCS-001	SFO-CTRL1
TCV-F21C-1	TCV1321C1	CF1-TCV1321C1	CF1_TT1321C1	Control Valve	Electro-pneumatic	AO	0 - 100%	4-20 mA HART	2 wire	CF1-RIO-001	TB-AO	3	4								S6	2	3	4	SFO-DCS-001	SFO-CTRL1
TCV-F21ST-S	TCV1321ST	CF1-TCV1321ST	CF1_TT1321ST1	Control Valve	Electro-pneumatic	AO	0 - 100%	4-20 mA HART	2 wire	CF1-RIO-001	TB-AO	5	6								S6	3	5	6	SFO-DCS-001	SFO-CTRL1
TCV-PF50/02A-1	TCV1052A1	CF1-TCV1052A1	CF1_TT1050A1	Control Valve	Electro-pneumatic	AO	0 - 100%	4-20 mA HART	2 wire	CF1-RIO-001	TB-AO	7	8								S6	4	7	8	SFO-DCS-001	SFO-CTRL1
TCV-PF50/02S2-1	TCV115021	CF1-TCV115021	CF1_TT1150S21	Control Valve	Electro-pneumatic	AO	0 - 100%	4-20 mA HART	2 wire	CF1-RIO-001	TB-AO	9	10								S6	5	9	10	SFO-DCS-001	SFO-CTRL1
TCV-PF50/02S1-1	TCV115011	CF1-TCV115011	CF1_TT1150S11	Control Valve	Electro-pneumatic	AO	0 - 100%	4-20 mA HART	2 wire	CF1-RIO-001	TB-AO	11	12								S6	6	11	12	SFO-DCS-001	SFO-CTRL1
TCV-F21D-1	TCV1421D1	CF1-TCV1421D1	CF1_TT1421D1	Control Valve	Electro-pneumatic	AO	0 - 100%	4-20 mA HART	2 wire	CF1-RIO-001	TB-AO	13	14								S6	7	13	14	SFO-DCS-001	SFO-CTRL1
PCV-F16A1-HPR	PCV1216AS1	CF1-PCV1216AS1	CF1_PT1216AS2	Control Valve	Electro-pneumatic	AO	0 - 100%	4-20 mA HART	2 wire	CF1-RIO-001	TB-AO	15	16								S6	8	15	16	SFO-DCS-001	SFO-CTRL1
PCV-F16A2-HPR	PCV1216AS2	CF1-PCV1216AS2	CF1_PT1216AS4	Control Valve	Electro-pneumatic	AO	0 - 100%	4-20 mA HART	2 wire	CF1-RIO-001	TB-AO	17	18								S7	1	1	2	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AO	19	20								S7	2	3	4	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AO	21	22								S7	3	5	6	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AO	23	24								S7	4	7	8	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AO	25	26								S7	5	9	10	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AO	27	28								S7	6	11	12	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AO	29	30								S7	7	13	14	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-001	TB-AO	31	32								S7	8	15	16	SFO-DCS-001	SFO-CTRL1
XV-F02A-FIW	V1002AIW-ZO	CF1-V1002AIW-ZO	CF1_V1002AIW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	1	2								S1	1	1	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-FIW	V1002AIW-ZC	CF1-V1002AIW-ZC	CF1_V1002AIW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	3	4								S1	2	2	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-FHW	V1002AHW-ZO	CF1-V1002AHW-ZO	CF1_V1002AHW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	5	6								S1	3	3	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-FHW	V1002AHW-ZC	CF1-V1002AHW-ZC	CF1_V1002AHW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	7	8								S1	4	4	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-FO	V1002AFO-ZO	CF1-V1002AFO-ZO	CF1_V1002AFO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	9	10								S1	5	5	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-FO	V1002AFO-ZC	CF1-V1002AFO-ZC	CF1_V1002AFO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	11	12								S1	6	6	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-RTHW	V1002THW-ZO	CF1-V1002THW-ZO	CF1_V1002THW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	13	14								S1	7	7	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-RTHW	V1002THW-ZC	CF1-V1002THW-ZC	CF1_V1002THW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	15	16								S1	8	8	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-DW	V11021DW-ZO	CF1-V11021DW-ZO	CF1_V11021DW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	17	18								S1	9	9	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-DW	V11021DW-ZC	CF1-V11021DW-ZC	CF1_V11021DW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	19	20								S1	10	10	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-DW	V1102DW-ZO	CF1-V1102DW-ZO	CF1_V1102DW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	21	22								S1	11	11	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-DW	V1102DW-ZC	CF1-V1102DW-ZC	CF1_V1102DW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	23	24								S1	12	12	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-FHW	V1102S1FW-ZO	CF1-V1102S1FW-ZO	CF1_V1102S1FW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	25	26								S1	13	13	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-FHW	V1102S1FW-ZC	CF1-V1102S1FW-ZC	CF1_V1102S1FW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	27	28								S1	14	14	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-RTIW	V1102S1RW-ZO	CF1-V1102S1RW-ZO	CF1_V1102S1RW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	29	30								S1	15	15	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-RTIW	V1102S1RW-ZC	CF1-V1102S1RW-ZC	CF1_V1102S1RW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	31	32								S1	16	16	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-RTIW	V1102S2RW-ZO	CF1-V1102S2RW-ZO	CF1_V1102S2RW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	33	34								S1	17	17	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-RTIW	V1102S2RW-ZC	CF1-V1102S2RW-ZC	CF1_V1102S2RW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	35	36								S1	18	18	NA	SFO-DCS-001	SFO-CTRL1
XV-F21B-DO1	V1316A2D1-ZO	CF1-V1316A2D1-ZO	CF1_V1316A2D1	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	37	38								S1	19	19	NA	SFO-DCS-001	SFO-CTRL1
XV-F21B-DO1	V1316A2D1-ZC	CF1-V1316A2D1-ZC	CF1_V1316A2D1	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	39	40								S1	20	20	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-BA	V1321CBA-ZO	CF1-V1321CBA-ZO	CF1_V1321CBA	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	41	42								S1	21	21	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-BA	V1321CBA-ZC	CF1-V1321CBA-ZC	CF1_V1321CBA	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	43	44								S1	22	22	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-FC	V1216A1FC-ZO	CF1-V1216A1FC-ZO	CF1_V1216A1FC	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	45	46								S1	23	23	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-FC	V1216A1FC-ZC	CF1-V1216A1FC-ZC	CF1_V1216A1FC	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	47	48								S1	24	24	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-FO	V1216A1FO-ZO	CF1-V1216A1FO-ZO	CF1_V1216A1FO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	49	50								S1	25	25	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-FO	V1216A1FO-ZC	CF1-V1216A1FO-ZC	CF1_V1216A1FO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	51	52								S1	26	26	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-FIW	V1321FIW-ZO	CF1-V1321FIW-ZO	CF1_V1321FIW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	53	54								S1	27	27	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-FIW	V1321FIW-ZC	CF1-V1321FIW-ZC	CF1_V1321FIW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	55	56								S1	28	28	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-RTIW	V1321RTIW-ZO	CF1-V1321RTIW-ZO	CF1_V1321RTIW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	57	58								S1	29	29	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-RTIW	V1321RTIW-ZC	CF1-V1321RTIW-ZC	CF1_V1321RTIW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	59	60								S1	30	30	NA	SFO-DCS-001	SFO-CTRL1
XV-F21D-S	V1421DS-ZO	CF1-V1421DS-ZO	CF1_V1421DS	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	61	62								S1	31	31	NA	SFO-DCS-001	SFO-CTRL1
XV-F21D-S	V1421DS-ZC	CF1-V1421DS-ZC	CF1_V1421DS	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	63	64								S1	32	32	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-BA	V13460VBA-ZO	CF1-V13460VBA-ZO	CF1_V13460VBA	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	65	66								S2	1	1	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-BA	V13460VBA-ZC	CF1-V13460VBA-ZC	CF1_V13460VBA	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	67	68								S2	2	2	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-DO	V13460VDO-ZO	CF1-V13460VDO-ZO	CF1_V13460VDO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	69	70								S2	3	3	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-DO	V13460VDO-ZC	CF1-V13460VDO-ZC	CF1_V13460VDO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	71	72								S2	4	4	NA	SFO-DCS-001	SFO-CTRL1
XV-F78/16/1-R1	V12161R1-ZO	CF1-V12161R1-ZO	CF1_V12161R1	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	73	74								S2	5	5	NA	SFO-DCS-001	SFO-CTRL1
XV-F78/16/1-R1	V12161R1-ZC	CF1-V12161R1-ZC	CF1_V12161R1	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	75	76								S2	6	6	NA	SFO-DCS-001	SFO-CTRL1
XV-F78/16/1-R2	V12161R2-ZO	CF1-V12161R2-ZO	CF1_V12161R2	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	77	78								S2	7	7	NA	SFO-DCS-001	SFO-CTRL1
XV-F78/16/1-R2	V12161R2-ZC	CF1-V12161R2-ZC	CF1_V12161R2	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	79	80								S2	8	8	NA	SFO-DCS-001	SFO-CTRL1
XV-F78TR-FIW	V11TRFIW-ZO	CF1-V11TRFIW-ZO	CF1_V11TRFIW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	81	82								S2	9	9	NA	SFO-DCS-001	SFO-CTRL1
XV-F78TR-FIW	V11TRFIW-ZC	CF1-V11TRFIW-ZC	CF1_V11TRFIW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	83	84								S2	10	10	NA	SFO-DCS-001	SFO-CTRL1
XV-F78TR-FHW	V11TRFHW-ZO	CF1-V11TRFHW-ZO	CF1_V11TRFHW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	85	86								S2	11	11	NA	SFO-DCS-001	SFO-CTRL1
XV-F78TR-FHW	V11TRFHW-ZC	CF1-V11TRFHW-ZC	CF1_V11TRFHW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	87	88								S2	12	12	NA	SFO-DCS-001	SFO-CTRL1
XV-F78TR-RTIW	V11TRTIW-ZO	CF1-V11TRTIW-ZO	CF1_V11TRTIW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	89	90								S2	13	13	NA	SFO-DCS-001	SFO-CTRL1
XV-F78TR-RTIW	V11TRTIW-ZC	CF1-V11TRTIW-ZC	CF1_V11TRTIW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	91	92								S2	14	14	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-FHW	V1216FHW-ZO	CF1-V1216FHW-ZO	CF1_V1216FHW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	93	94								S2	15	15	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-FHW	V1216FHW-ZC	CF1-V1216FHW-ZC	CF1_V1216FHW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	95	96								S2	16	16	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-FIW	V1216FIW-ZO	CF1-V1216FIW-ZO	CF1_V1216FIW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	97	98								S2	17	17	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-FIW	V1216FIW-ZC	CF1-V1216FIW-ZC	CF1_V1216FIW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	99	100								S2	18	18	NA	SFO-DCS-001	SFO-CTRL1
XV-F82A-B	V1082AB-ZO	CF1-V1082AB-ZO	CF1_V1082AB	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	101	102								S2	19	19	NA	SFO-DCS-001	SFO-CTRL1
XV-F82A-B	V1082AB-ZC	CF1-V1082AB-ZC	CF1_V1082AB	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	103	104								S2	20	20	NA	SFO-DCS-001	SFO-CTRL1
XV-F82B-DO	V1382BDO-ZO	CF1-V1382BDO-ZO	CF1_V1382BDO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	105	106								S2	21	21	NA	SFO-DCS-001	SFO-CTRL1
XV-F82B-DO	V1382BDO-ZC	CF1-V1382BDO-ZC	CF1_V1382BDO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	107	108								S2	22	22	NA	SFO-DCS-001	SFO-CTRL1
XV-F82B-DO1	V13BDO1-ZO	CF1-V13BDO1-ZO	CF1_V13BDOB	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	109	110								S2	23	23	NA	SFO-DCS-001	SFO-CTRL1
XV-F82B-DO1	V13BDO1-ZC	CF1-V13BDO1-ZC	CF1_V13BDOB	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	111	112								S2	24	24	NA	SFO-DCS-001	SFO-CTRL1
XV-F82C-DO	V1382CDO-ZO	CF1-V1382CDO-ZO	CF1_V1382CDO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	113	114								S2	25	25	NA	SFO-DCS-001	SFO-CTRL1
XV-F82C-DO	V1382CDO-ZC	CF1-V1382CDO-ZC	CF1_V1382CDO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	115	116								S2	26	26	NA	SFO-DCS-001	SFO-CTRL1
XV-F82C-FO	V1382CFO-ZO	CF1-V1382CFO-ZO	CF1_V1382CFO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	117	118								S2	27	27	NA	SFO-DCS-001	SFO-CTRL1
XV-F82C-FO	V1382CFO-ZC	CF1-V1382CFO-ZC	CF1_V1382CFO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	119	120								S2	28	28	NA	SFO-DCS-001	SFO-CTRL1
XV-F82ST-BA	V1382STBA-ZO	CF1-V1382STBA-ZO	CF1_V1382STBA	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	121	122								S2	29	29	NA	SFO-DCS-001	SFO-CTRL1
XV-F82ST-BA	V1382STBA-ZC	CF1-V1382STBA-ZC	CF1_V1382STBA	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	123	124								S2	30	30	NA	SFO-DCS-001	SFO-CTRL1
XV-F82ST-COIL	V1382ST-ZO	CF1-V1382ST-ZO	CF1_V1382ST	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	125	126								S2	31	31	NA	SFO-DCS-001	SFO-CTRL1
XV-F82ST-COIL	V1382ST-ZC	CF1-V1382ST-ZC	CF1_V1382ST	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	127	128								S2	32	32	NA	SFO-DCS-001	SFO-CTRL1
XV-F82ST-DO	V1382STDO-ZO	CF1-V1382STDO-ZO	CF1_V1382STDO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	129	130								S3	1	1	NA	SFO-DCS-001	SFO-CTRL1
XV-F82ST-DO	V1382STDO-ZC	CF1-V1382STDO-ZC	CF1_V1382STDO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	131	132								S3	2	2	NA	SFO-DCS-001	SFO-CTRL1
XV-F82ST-RO	V1382STRO-ZO	CF1-V1382STRO-ZO	CF1_V1382STRO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	133	134								S3	3	3	NA	SFO-DCS-001	SFO-CTRL1
XV-F82ST-RO	V1382STRO-ZC	CF1-V1382STRO-ZC	CF1_V1382STRO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	135	136								S3	4	4	NA	SFO-DCS-001	SFO-CTRL1
XV-F78C-RT	V1478CRT-ZO	CF1-V1478CRT-ZO	CF1_V1478CRT	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	137	138								S3	5	5	NA	SFO-DCS-001	SFO-CTRL1
XV-F78C-RT	V1478CRT-ZC	CF1-V1478CRT-ZC	CF1_V1478CRT	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	139	140								S3	6	6	NA	SFO-DCS-001	SFO-CTRL1
XV-F78D	V1478D-ZO	CF1-V1478D-ZO	CF1_V1478D	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	141	142								S3	7	7	NA	SFO-DCS-001	SFO-CTRL1
XV-F78D	V1478D-ZC	CF1-V1478D-ZC	CF1_V1478D	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	143	144								S3	8	8	NA	SFO-DCS-001	SFO-CTRL1
XV-F78D-RT	V1478DRT-ZO	CF1-V1478DRT-ZO	CF1_V1478DRT	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	145	146								S3	9	9	NA	SFO-DCS-001	SFO-CTRL1
XV-F78D-RT	V1478DRT-ZC	CF1-V1478DRT-ZC	CF1_V1478DRT	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	147	148								S3	10	10	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-RTHW	V148THW-ZO	CF1-V148THW-ZO	CF1_V148THW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	149	150								S3	11	11	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-RTHW	V148THW-ZC	CF1-V148THW-ZC	CF1_V148THW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	151	152								S3	12	12	NA	SFO-DCS-001	SFO-CTRL1
XV-PF01A-D	V1001AD-ZO	CF1-V1001AD-ZO	CF1_V1001AD	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	153	154								S3	13	13	NA	SFO-DCS-001	SFO-CTRL1
XV-PF01A-D	V1001AD-ZC	CF1-V1001AD-ZC	CF1_V1001AD	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	155	156								S3	14	14	NA	SFO-DCS-001	SFO-CTRL1
XV-PF01A-R	V1001AR-ZO	CF1-V1001AR-ZO	CF1_V1001AR	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	157	158								S3	15	15	NA	SFO-DCS-001	SFO-CTRL1
XV-PF01A-R	V1001AR-ZC	CF1-V1001AR-ZC	CF1_V1001AR	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	159	160								S3	16	16	NA	SFO-DCS-001	SFO-CTRL1
XV-PF01A/B-BA	V1001A-ZO	CF1-V1001A-ZO	CF1_V1001A	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	161	162								S3	17	17	NA	SFO-DCS-001	SFO-CTRL1
XV-PF01A/B-BA	V1001A-ZC	CF1-V1001A-ZC	CF1_V1001A	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	163	164								S3	18	18	NA	SFO-DCS-001	SFO-CTRL1
XV-PF02A-BY	V1102ABY-ZO	CF1-V1102ABY-ZO	CF1_V1102ABY	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	165	166								S3	19	19	NA	SFO-DCS-001	SFO-CTRL1
XV-PF02A-BY	V1102ABY-ZC	CF1-V1102ABY-ZC	CF1_V1102ABY	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	167	168								S3	20	20	NA	SFO-DCS-001	SFO-CTRL1
XV-PF02A-DO	V1002DO-ZO	CF1-V1002DO-ZO	CF1_V1002DO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	169	170								S3	21	21	NA	SFO-DCS-001	SFO-CTRL1
XV-PF02A-DO	V1002DO-ZC	CF1-V1002DO-ZC	CF1_V1002DO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	171	172								S3	22	22	NA	SFO-DCS-001	SFO-CTRL1
XV-PF02A-DO1	V1102ADO1-ZO	CF1-V1102ADO1-ZO	CF1_V1102ADO1	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	173	174								S3	23	23	NA	SFO-DCS-001	SFO-CTRL1
XV-PF02A-DO1	V1102ADO1-ZC	CF1-V1102ADO1-ZC	CF1_V1102ADO1	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	175	176								S3	24	24	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-BA	V1002ABA-ZO	CF1-V1002ABA-ZO	CF1_V1002ABA	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	177	178								S3	25	25	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-BA	V1002ABA-ZC	CF1-V1002ABA-ZC	CF1_V1002ABA	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	179	180								S3	26	26	NA	SFO-DCS-001	SFO-CTRL1
XV-PF16A/S-D01	V1116SAD1-ZO	CF1-V1116SAD1-ZO	CF1_V1116SAD1	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	181	182								S3	27	27	NA	SFO-DCS-001	SFO-CTRL1
XV-PF16A/S-D01	V1116SAD1-ZC	CF1-V1116SAD1-ZC	CF1_V1116SAD1	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	183	184								S3	28	28	NA	SFO-DCS-001	SFO-CTRL1
XV-PF16A/S-D02	V1116SAD2-ZO	CF1-V1116SAD2-ZO	CF1_V1116SAD2	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	185	186								S3	29	29	NA	SFO-DCS-001	SFO-CTRL1
XV-PF16A/S-D02	V1116SAD2-ZC	CF1-V1116SAD2-ZC	CF1_V1116SAD2	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	187	188								S3	30	30	NA	SFO-DCS-001	SFO-CTRL1
XV-PF16A/S-R	V1116ASR-ZO	CF1-V1116ASR-ZO	CF1_V1116ASR	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	189	190								S3	31	31	NA	SFO-DCS-001	SFO-CTRL1
XV-PF16A/S-R	V1116ASR-ZC	CF1-V1116ASR-ZC	CF1_V1116ASR	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	191	192								S3	32	32	NA	SFO-DCS-001	SFO-CTRL1
XV-PF16A/S-RO	V1116ASRO-ZO	CF1-V1116ASRO-ZO	CF1_V1116ASRO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	193	194								S4	1	1	NA	SFO-DCS-001	SFO-CTRL1
XV-PF16A/S-RO	V1116ASRO-ZC	CF1-V1116ASRO-ZC	CF1_V1116ASRO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	195	196								S4	2	2	NA	SFO-DCS-001	SFO-CTRL1
LSH-F460V-1	LSH1360V1	CF1-LSH1360V1	CF1_LSH1360V1	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	197	198	+		A1	A2(comm)	RDI1-01	14	11(comm)	S4	3	3	NA	SFO-DCS-001	SFO-CTRL1
LSH-F78B-1	LSH1478B1	CF1-LSH1478B1	CF1_LSH1478B1	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	199	200	+		A1	A2	RDI1-02	14	11	S4	4	4	NA	SFO-DCS-001	SFO-CTRL1
LSH-F78D-1	LSH1478D1	CF1-LSH1478D1	CF1_LSH1478D1	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	201	202	+		A1	A2	RDI1-03	14	11	S4	5	5	NA	SFO-DCS-001	SFO-CTRL1
LSH-F82B-1	LSH1382B1	CF1-LSH1382B1	CF1_LSH1382B1	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	203	204	+		A1	A2	RDI1-04	14	11	S4	6	6	NA	SFO-DCS-001	SFO-CTRL1
LSH-F82C-1	LSH1382C1	CF1-LSH1382C1	CF1_LSH1382C1	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	205	206	+		A1	A2	RDI1-05	14	11	S4	7	7	NA	SFO-DCS-001	SFO-CTRL1
LSH-F82ST-1	LSH1382ST	CF1-LSH1382ST	CF1_LSH1382ST	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	207	208	+		A1	A2	RDI1-06	14	11	S4	8	8	NA	SFO-DCS-001	SFO-CTRL1
LSM-F460V-1	LSM1360V1	CF1-LSM1360V1	CF1_LSM1360V1	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	209	210	+		A1	A2	RDI1-07	14	11	S4	9	9	NA	SFO-DCS-001	SFO-CTRL1
LSL-F460V-1	LSL1360V1	CF1-LSL1360V1	CF1_LSL1360V1	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	211	212	+		A1	A2	RDI1-08	14	11	S4	10	10	NA	SFO-DCS-001	SFO-CTRL1
LSL-F78B-1	LSL1478B1	CF1-LSL1478B1	CF1_LSL1478B1	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	213	214	+		A1	A2	RDI1-09	14	11	S4	11	11	NA	SFO-DCS-001	SFO-CTRL1
LSL-F78C	LSL1478C	CF1-LSL1478C	CF1_LSL1478C	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	215	216	+		A1	A2	RDI1-10	14	11	S4	12	12	NA	SFO-DCS-001	SFO-CTRL1
LSL-F78D-1	LSL1478D1	CF1-LSL1478D1	CF1_LSL1478D1	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	217	218	+		A1	A2	RDI1-11	14	11	S4	13	13	NA	SFO-DCS-001	SFO-CTRL1
LSL-F82B-1	LSL1382B1	CF1-LSL1382B1	CF1_LSL1382B1	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	219	220	+		A1	A2	RDI1-12	14	11	S4	14	14	NA	SFO-DCS-001	SFO-CTRL1
LSL-F82C-1	LSL1382C1	CF1-LSL1382C1	CF1_LSL1382C1	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	221	222	+		A1	A2	RDI1-13	14	11	S4	15	15	NA	SFO-DCS-001	SFO-CTRL1
LSL-F82ST-1	LSL1382ST	CF1-LSL1382ST	CF1_LSL1382ST	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	223	224	+		A1	A2	RDI1-14	14	11	S4	16	16	NA	SFO-DCS-001	SFO-CTRL1
LSH-F09S-1	LSH1109S1	CF1-LSH1109S1	CF1_LSH1109S1	Level Switch	Capacitance	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	225	226	+		A1	A2	RDI1-15	14	11	S4	17	17	NA	SFO-DCS-001	SFO-CTRL1
LSL-F09S-1	LSL1109S1	CF1-LSL1109S1	CF1_LSL1109S1	Level Switch	Capacitance	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	227	228	+		A1	A2	RDI1-16	14	11	S4	18	18	NA	SFO-DCS-001	SFO-CTRL1
LSH-F02A-1	LSH1002A1	CF1-LSH1002A1	CF1_LSH1002A1	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	229	230	+		A1	A2	RDI1-17	14	11	S4	19	19	NA	SFO-DCS-001	SFO-CTRL1
FS-1276	FSL1276	CF1-FSL1276	CF1_FSL1276	Flow Switch	6503-05	DI				CF1-RIO-002	TB-DI	231	232								S4	20	20	NA	SFO-DCS-001	SFO-CTRL1
SV-1403A	SV1403A-ZO	CF1-SV1403A-ZO	CF1_SV1403A	On-Off Valve	Valve open indication	DI				CF1-RIO-002	TB-DI	233	234								S4	21	21	NA	SFO-DCS-001	SFO-CTRL1
SV-1403A	SV1403A-ZC	CF1-SV1403A-ZC	CF1_SV1403A	On-Off Valve	Valve close indication	DI				CF1-RIO-002	TB-DI	235	236								S4	22	22	NA	SFO-DCS-001	SFO-CTRL1
SV-1403B	SV1403B-ZO	CF1-SV1403B-ZO	CF1_SV1403B	On-Off Valve	Valve open indication	DI				CF1-RIO-002	TB-DI	237	238								S4	23	23	NA	SFO-DCS-001	SFO-CTRL1

										RIO CABINET															SYSTEM CABINET	
										Marshalling						Relay					DELTA V				DELTA V	
Vendor's tags	Wilmar's Tags	Emerson Database Tags	Module Name	Description	Type	IO Type	Range Proposed (kg/H)	Signal Type	Electrical Connection	Cabinet Name	TB Name	Term. (+)	Term. (-)	24V(+) Term.	24V(-) Term.	Term. (+)	Term. (-)	Name	Term. (+)	Term. (-)	Slot	Channel	Term. (+)	Term. (-)	Cabinet Name	Controller
SV-1403B	SV1403B-ZC	CF1-SV1403B-ZC	CF1_SV1403B	On-Off Valve	Valve close indication	DI				CF1-RIO-002	TB-DI	239	240								S4	24	24	NA	SFO-DCS-001	SFO-CTRL1
LSLL-307	LSLL307	CF1-LSLL307	CF1_LSLL307	Level Switch		DI				CF1-RIO-002	TB-DI	241	242								S4	25	25	NA	SFO-DCS-001	SFO-CTRL1
LS-904	LSH904	CF1-LSH904	CF1_LSH904	Level Switch		DI				CF1-RIO-002	TB-DI	243	244								S4	26	26	NA	SFO-DCS-001	SFO-CTRL1
LSHH-1403	LSHH1403	CF1-LSHH1403	CF1_LSHH1403	Level Switch		DI				CF1-RIO-002	TB-DI	245	246								S4	27	27	NA	SFO-DCS-001	SFO-CTRL1
LSLL-1403	LSLL1403	CF1-LSLL1403	CF1_LSLL1403	Level Switch		DI				CF1-RIO-002	TB-DI	247	248								S4	28	28	NA	SFO-DCS-001	SFO-CTRL1
PS-8017	PSL8017	CF1-PSL8017	CF1_PSL8017	Pressure Switch		DI				CF1-RIO-002	TB-DI	249	250								S4	29	29	NA	SFO-DCS-001	SFO-CTRL1
PS-809	PSL809	CF1-PSL809	CF1_PSL809	Pressure Switch	6508-02	DI				CF1-RIO-002	TB-DI	251	252								S4	30	30	NA	SFO-DCS-001	SFO-CTRL1
PS-1106	PSL1106	CF1-PSL1106	CF1_PSL1106	Pressure Switch	6511-02	DI				CF1-RIO-002	TB-DI	253	254								S4	31	31	NA	SFO-DCS-001	SFO-CTRL1
LSH-F78/16-1	LSH127816	CF1-LSH127816	CF1_LSH127816	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-002	TB-DI	255	256	+		A1	A2(comm)	RDI1-18	14	11(comm)	S4	32	32	NA	SFO-DCS-001	SFO-CTRL1
XV-F021S2-DW	V1121S2DW-ZO	CF1-V1121S2DW-ZO	CF1_V1121S2DW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	257	258								S5	1	1	NA	SFO-DCS-001	SFO-CTRL1
XV-F021S2-DW	V1121S2DW-ZC	CF1-V1121S2DW-ZC	CF1_V1121S2DW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	259	260								S5	2	2	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-FHW	V1102S2FW-ZO	CF1-V1102S2FW-ZO	CF1_V1102S2FW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	261	262								S5	3	3	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-FHW	V1102S2FW-ZC	CF1-V1102S2FW-ZC	CF1_V1102S2FW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	263	264								S5	4	4	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-DO	V1002ADO-ZO	CF1-V1002ADO-ZO	CF1_V1002ADO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	265	266								S5	5	5	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-DO	V1002ADO-ZC	CF1-V1002ADO-ZC	CF1_V1002ADO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	267	268								S5	6	6	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-RTIW	V1002TIW-ZO	CF1-V1002TIW-ZO	CF1_V1002TIW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	269	270								S5	7	7	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-RTIW	V1002TIW-ZC	CF1-V1002TIW-ZC	CF1_V1002TIW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	271	272								S5	8	8	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-FW	V1321CFW-ZO	CF1-V1321CFW-ZO	CF1_V1321CFW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	273	274								S5	9	9	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-FW	V1321CFW-ZC	CF1-V1321CFW-ZC	CF1_V1321CFW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	275	276								S5	10	10	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-LPC	V1321LPC-ZO	CF1-V1321LPC-ZO	CF1_V1321LPC	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	277	278								S5	11	11	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-LPC	V1321LPC-ZC	CF1-V1321LPC-ZC	CF1_V1321LPC	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	279	280								S5	12	12	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-RTW	V1321RTW-ZO	CF1-V1321RTW-ZO	CF1_V1321RTW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	281	282								S5	13	13	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-RTW	V1321RTW-ZC	CF1-V1321RTW-ZC	CF1_V1321RTW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	283	284								S5	14	14	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-S	V1321CS-ZO	CF1-V1321CS-ZO	CF1_V1321CS	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	285	286								S5	15	15	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-S	V1321CS-ZC	CF1-V1321CS-ZC	CF1_V1321CS	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	287	288								S5	16	16	NA	SFO-DCS-001	SFO-CTRL1
XV-F21ST-DO1	V1321DO1-ZO	CF1-V1321DO1-ZO	CF1_V1321DO1	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	289	290								S5	17	17	NA	SFO-DCS-001	SFO-CTRL1
XV-F21ST-DO1	V1321DO1-ZC	CF1-V1321DO1-ZC	CF1_V1321DO1	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	291	292								S5	18	18	NA	SFO-DCS-001	SFO-CTRL1
XV-F21ST-DO2	V1321DO2-ZO	CF1-V1321DO2-ZO	CF1_V1321DO2	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	293	294								S5	19	19	NA	SFO-DCS-001	SFO-CTRL1
XV-F21ST-DO2	V1321DO2-ZC	CF1-V1321DO2-ZC	CF1_V1321DO2	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	295	296								S5	20	20	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-DO1	V13460DO1-ZO	CF1-V13460DO1-ZO	CF1_V13460DO1	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	297	298								S5	21	21	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-DO1	V13460DO1-ZC	CF1-V13460DO1-ZC	CF1_V13460DO1	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	299	300								S5	22	22	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-FO	V13460FO-ZO	CF1-V13460FO-ZO	CF1_V13460FO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	301	302								S5	23	23	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-FO	V13460FO-ZC	CF1-V13460FO-ZC	CF1_V13460FO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	303	304								S5	24	24	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-R	V13460VR-ZO	CF1-V13460VR-ZO	CF1_V13460VR	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	305	306								S5	25	25	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-R	V13460VR-ZC	CF1-V13460VR-ZC	CF1_V13460VR	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-002	TB-DI	307	308								S5	26	26	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-002	TB-DI	309	310								S5	27	27	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-002	TB-DI	311	312								S5	28	28	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-002	TB-DI	313	314								S5	29	29	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-002	TB-DI	315	316								S5	30	30	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-002	TB-DI	317	318								S5	31	31	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-002	TB-DI	319	320								S5	32	32	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-FIW	V1002AIW-SY	CF1-V1002AIW-SY	CF1_V1002AIW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	1	2			14	11	RDO1-01	A1	A2 (COMM)	S6	1	1	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-FHW	V1002AHW-SY	CF1-V1002AHW-SY	CF1_V1002AHW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	3	4			14	11	RDO1-02	A1	A2	S6	2	2	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-FO	V1002AFO-SY	CF1-V1002AFO-SY	CF1_V1002AFO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	5	6			14	11	RDO1-03	A1	A2	S6	3	3	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-RTHW	V1002THW-SY	CF1-V1002THW-SY	CF1_V1002THW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	7	8			14	11	RDO1-04	A1	A2	S6	4	4	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-DW	V11021DW-SY	CF1-V11021DW-SY	CF1_V11021DW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	9	10			14	11	RDO1-05	A1	A2	S6	5	5	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-DW	V1102DW-SY	CF1-V1102DW-SY	CF1_V1102DW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	11	12			14	11	RDO1-06	A1	A2	S6	6	6	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-FHW	V1102S1FW-SY	CF1-V1102S1FW-SY	CF1_V1102S1FW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	13	14			14	11	RDO1-07	A1	A2	S6	7	7	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-RTIW	V1102S1RW-SY	CF1-V1102S1RW-SY	CF1_V1102S1RW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	15	16			14	11	RDO1-08	A1	A2	S6	8	8	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-RTIW	V1102S2RW-SY	CF1-V1102S2RW-SY	CF1_V1102S2RW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	17	18			14	11	RDO1-09	A1	A2	S6	9	9	NA	SFO-DCS-001	SFO-CTRL1
XV-F21B-DO1	V1316A2D1-SY	CF1-V1316A2D1-SY	CF1_V1316A2D1	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	19	20			14	11	RDO1-10	A1	A2	S6	10	10	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-BA	V1321CBA-SY	CF1-V1321CBA-SY	CF1_V1321CBA	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	21	22			14	11	RDO1-11	A1	A2	S6	11	11	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-FC	V1216A1FC-SY	CF1-V1216A1FC-SY	CF1_V1216A1FC	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	23	24			14	11	RDO1-12	A1	A2	S6	12	12	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-FO	V1216A1FO-SY	CF1-V1216A1FO-SY	CF1_V1216A1FO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	25	26			14	11	RDO1-13	A1	A2	S6	13	13	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-FIW	V1321FIW-SY	CF1-V1321FIW-SY	CF1_V1321FIW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	27	28			14	11	RDO1-14	A1	A2	S6	14	14	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-RTIW	V1321RTIW-SY	CF1-V1321RTIW-SY	CF1_V1321RTIW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	29	30			14	11	RDO1-15	A1	A2	S6	15	15	NA	SFO-DCS-001	SFO-CTRL1
XV-F21D-S	V1421DS-SY	CF1-V1421DS-SY	CF1_V1421DS	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	31	32			14	11	RDO1-16	A1	A2	S6	16	16	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-BA	V13460VBA-SY	CF1-V13460VBA-SY	CF1_V13460VBA	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	33	34			14	11	RDO1-17	A1	A2	S6	17	17	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-DO	V13460VDO-SY	CF1-V13460VDO-SY	CF1_V13460VDO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	35	36			14	11	RDO1-18	A1	A2	S6	18	18	NA	SFO-DCS-001	SFO-CTRL1
XV-F78/16/1-R1	V12161R1-SY	CF1-V12161R1-SY	CF1_V12161R1	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	37	38			14	11	RDO1-19	A1	A2	S6	19	19	NA	SFO-DCS-001	SFO-CTRL1
XV-F78/16/1-R2	V12161R2-SY	CF1-V12161R2-SY	CF1_V12161R2	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	39	40			14	11	RDO1-20	A1	A2	S6	20	20	NA	SFO-DCS-001	SFO-CTRL1
XV-F78TR-FIW	V11TRFIW-SY	CF1-V11TRFIW-SY	CF1_V11TRFIW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	41	42			14	11	RDO1-21	A1	A2	S6	21	21	NA	SFO-DCS-001	SFO-CTRL1
XV-F78TR-FHW	V11TRFHW-SY	CF1-V11TRFHW-SY	CF1_V11TRFHW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	43	44			14	11	RDO1-22	A1	A2	S6	22	22	NA	SFO-DCS-001	SFO-CTRL1
XV-F78TR-RTIW	V11TRTIW-SY	CF1-V11TRTIW-SY	CF1_V11TRTIW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	45	46			14	11	RDO1-23	A1	A2	S6	23	23	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-FHW	V1216FHW-SY	CF1-V1216FHW-SY	CF1_V1216FHW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	47	48			14	11	RDO1-24	A1	A2	S6	24	24	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-FIW	V1216FIW-SY	CF1-V1216FIW-SY	CF1_V1216FIW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	49	50			14	11	RDO1-25	A1	A2	S6	25	25	NA	SFO-DCS-001	SFO-CTRL1
XV-F82A-B	V1082AB-SY	CF1-V1082AB-SY	CF1_V1082AB	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	51	52			14	11	RDO1-26	A1	A2	S6	26	26	NA	SFO-DCS-001	SFO-CTRL1
XV-F82B-DO	V1382BDO-SY	CF1-V1382BDO-SY	CF1_V1382BDO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	53	54			14	11	RDO1-27	A1	A2	S6	27	27	NA	SFO-DCS-001	SFO-CTRL1
XV-F82B-DO1	V13BDO1-SY	CF1-V13BDO1-SY	CF1_V13BDOB	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	55	56			14	11	RDO1-28	A1	A2	S6	28	28	NA	SFO-DCS-001	SFO-CTRL1
XV-F82C-DO	V1382CDO-SY	CF1-V1382CDO-SY	CF1_V1382CDO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	57	58			14	11	RDO1-29	A1	A2	S6	29	29	NA	SFO-DCS-001	SFO-CTRL1
XV-F82C-FO	V1382CFO-SY	CF1-V1382CFO-SY	CF1_V1382CFO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	59	60			14	11	RDO1-30	A1	A2	S6	30	30	NA	SFO-DCS-001	SFO-CTRL1
XV-F82ST-BA	V1382STBA-SY	CF1-V1382STBA-SY	CF1_V1382STBA	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	61	62			14	11	RDO1-31	A1	A2	S6	31	31	NA	SFO-DCS-001	SFO-CTRL1
XV-F82ST-COIL	V1382ST-SY	CF1-V1382ST-SY	CF1_V1382ST	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	63	64			14	11	RDO1-32	A1	A2	S6	32	32	NA	SFO-DCS-001	SFO-CTRL1
XV-F82ST-DO	V1382STDO-SY	CF1-V1382STDO-SY	CF1_V1382STDO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	65	66			14	11	RDO1-33	A1	A2	S7	1	1	NA	SFO-DCS-001	SFO-CTRL1
XV-F82ST-RO	V1382STRO-SY	CF1-V1382STRO-SY	CF1_V1382STRO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	67	68			14	11	RDO1-34	A1	A2	S7	2	2	NA	SFO-DCS-001	SFO-CTRL1
XV-F78C-RT	V1478CRT-SY	CF1-V1478CRT-SY	CF1_V1478CRT	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	69	70			14	11	RDO1-35	A1	A2	S7	3	3	NA	SFO-DCS-001	SFO-CTRL1
XV-F78D	V1478D-SY	CF1-V1478D-SY	CF1_V1478D	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	71	72			14	11	RDO1-36	A1	A2	S7	4	4	NA	SFO-DCS-001	SFO-CTRL1
XV-F78D-RT	V1478DRT-SY	CF1-V1478DRT-SY	CF1_V1478DRT	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	73	74			14	11	RDO1-37	A1	A2	S7	5	5	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-RTHW	V148THW-SY	CF1-V148THW-SY	CF1_V148THW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	75	76			14	11	RDO1-38	A1	A2	S7	6	6	NA	SFO-DCS-001	SFO-CTRL1
XV-PF01A-D	V1001AD-SY	CF1-V1001AD-SY	CF1_V1001AD	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	77	78			14	11	RDO1-39	A1	A2	S7	7	7	NA	SFO-DCS-001	SFO-CTRL1
XV-PF01A-R	V1001AR-SY	CF1-V1001AR-SY	CF1_V1001AR	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	79	80			14	11	RDO1-40	A1	A2	S7	8	8	NA	SFO-DCS-001	SFO-CTRL1
XV-PF01A/B-BA	V1001A-SY	CF1-V1001A-SY	CF1_V1001A	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	81	82			14	11	RDO1-41	A1	A2	S7	9	9	NA	SFO-DCS-001	SFO-CTRL1
XV-PF02A-BY	V1102ABY-SY	CF1-V1102ABY-SY	CF1_V1102ABY	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	83	84			14	11	RDO1-42	A1	A2	S7	10	10	NA	SFO-DCS-001	SFO-CTRL1
XV-PF02A-DO	V1002DO-SY	CF1-V1002DO-SY	CF1_V1002DO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	85	86			14	11	RDO1-43	A1	A2	S7	11	11	NA	SFO-DCS-001	SFO-CTRL1
XV-PF02A-DO1	V1102ADO1-SY	CF1-V1102ADO1-SY	CF1_V1102ADO1	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	87	88			14	11	RDO1-44	A1	A2	S7	12	12	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-BA	V1002ABA-SY	CF1-V1002ABA-SY	CF1_V1002ABA	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	89	90			14	11	RDO1-45	A1	A2	S7	13	13	NA	SFO-DCS-001	SFO-CTRL1
XV-PF16A/S-D01	V1116SAD1-SY	CF1-V1116SAD1-SY	CF1_V1116SAD1	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	91	92			14	11	RDO1-46	A1	A2	S7	14	14	NA	SFO-DCS-001	SFO-CTRL1
XV-PF16A/S-D02	V1116SAD2-SY	CF1-V1116SAD2-SY	CF1_V1116SAD2	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	93	94			14	11	RDO1-47	A1	A2	S7	15	15	NA	SFO-DCS-001	SFO-CTRL1
XV-PF16A/S-R	V1116ASR-SY	CF1-V1116ASR-SY	CF1_V1116ASR	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	95	96			14	11	RDO1-48	A1	A2	S7	16	16	NA	SFO-DCS-001	SFO-CTRL1
XV-PF16A/S-RO	V1116ASRO-SY	CF1-V1116ASRO-SY	CF1_V1116ASRO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	97	98			14	11	RDO1-49	A1	A2	S7	17	17	NA	SFO-DCS-001	SFO-CTRL1
SV-1403A	SV1403A-SY	CF1-SV1403A-SY	CF1_SV1403A	On-Off Valve	Valve open command	DO				CF1-RIO-002	TB-DO	99	100			14	11	RDO1-50	A1	A2	S7	18	18	NA	SFO-DCS-001	SFO-CTRL1
SV-1403B	SV1403B-SY	CF1-SV1403B-SY	CF1_SV1403B	On-Off Valve	Valve open command	DO				CF1-RIO-002	TB-DO	101	102			14	11	RDO1-51	A1	A2	S7	19	19	NA	SFO-DCS-001	SFO-CTRL1
XV-F021S2-DW	V1121S2DW-SY	CF1-V1121S2DW-SY	CF1_V1121S2DW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	103	104			14	11	RDO1-52	A1	A2	S7	20	20	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-FHW	V1102S2FW-SY	CF1-V1102S2FW-SY	CF1_V1102S2FW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	105	106			14	11	RDO1-53	A1	A2	S7	21	21	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-DO	V1002ADO-SY	CF1-V1002ADO-SY	CF1_V1002ADO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	107	108			14	11	RDO1-54	A1	A2	S7	22	22	NA	SFO-DCS-001	SFO-CTRL1
XV-F02A-RTIW	V1002TIW-SY	CF1-V1002TIW-SY	CF1_V1002TIW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	109	110			14	11	RDO1-55	A1	A2	S7	23	23	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-FW	V1321CFW-SY	CF1-V1321CFW-SY	CF1_V1321CFW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	111	112			14	11	RDO1-56	A1	A2	S7	24	24	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-LPC	V1321LPC-SY	CF1-V1321LPC-SY	CF1_V1321LPC	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	113	114			14	11	RDO1-57	A1	A2	S7	25	25	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-RTW	V1321RTW-SY	CF1-V1321RTW-SY	CF1_V1321RTW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	115	116			14	11	RDO1-58	A1	A2	S7	26	26	NA	SFO-DCS-001	SFO-CTRL1
XV-F21C-S	V1321CS-SY	CF1-V1321CS-SY	CF1_V1321CS	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	117	118			14	11	RDO1-59	A1	A2	S7	27	27	NA	SFO-DCS-001	SFO-CTRL1
XV-F21ST-DO1	V1321DO1-SY	CF1-V1321DO1-SY	CF1_V1321DO1	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	119	120			14	11	RDO1-60	A1	A2	S7	28	28	NA	SFO-DCS-001	SFO-CTRL1
XV-F21ST-DO2	V1321DO2-SY	CF1-V1321DO2-SY	CF1_V1321DO2	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	121	122			14	11	RDO1-61	A1	A2	S7	29	29	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-DO1	V13460DO1-SY	CF1-V13460DO1-SY	CF1_V13460DO1	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	123	124			14	11	RDO1-62	A1	A2	S7	30	30	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-FO	V13460FO-SY	CF1-V13460FO-SY	CF1_V13460FO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	125	126			14	11	RDO1-63	A1	A2	S7	31	31	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-R	V13460VR-SY	CF1-V13460VR-SY	CF1_V13460VR	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-002	TB-DO	127	128			14	11	RDO1-64	A1	A2 (COMM)	S7	32	32	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1	V1102S1-ZO	CF1-V1102S1-ZO	CF1_V1102S1	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	1	2								S1	1	1	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1	V1102S1-ZC	CF1-V1102S1-ZC	CF1_V1102S1	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	3	4								S1	2	2	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S-B	V1102SB-ZO	CF1-V1102SB-ZO	CF1_V1102SB	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	5	6								S1	3	3	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S-B	V1102SB-ZC	CF1-V1102SB-ZC	CF1_V1102SB	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	7	8								S1	4	4	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-BA	V1102S1BA-ZO	CF1-V1102S1BA-ZO	CF1_V1102S1BA	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	9	10								S1	5	5	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-BA	V1102S1BA-ZC	CF1-V1102S1BA-ZC	CF1_V1102S1BA	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	11	12								S1	6	6	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-FO	V1102S1FO-ZO	CF1-V1102S1FO-ZO	CF1_V1102S1FO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	13	14								S1	7	7	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-FO	V1102S1FO-ZC	CF1-V1102S1FO-ZC	CF1_V1102S1FO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	15	16								S1	8	8	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-H0	V1102S1HO-ZO	CF1-V1102S1HO-ZO	CF1_V1102S1HO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	17	18								S1	9	9	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-H0	V1102S1HO-ZC	CF1-V1102S1HO-ZC	CF1_V1102S1HO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	19	20								S1	10	10	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-H1	V1102SH1-ZO	CF1-V1102SH1-ZO	CF1_V1102SH1	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	21	22								S1	11	11	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-H1	V1102SH1-ZC	CF1-V1102SH1-ZC	CF1_V1102SH1	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	23	24								S1	12	12	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-H2	V1102SH2-ZO	CF1-V1102SH2-ZO	CF1_V1102SH2	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	25	26								S1	13	13	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-H2	V1102SH2-ZC	CF1-V1102SH2-ZC	CF1_V1102SH2	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	27	28								S1	14	14	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-V2	V1102S1V2-ZO	CF1-V1102S1V2-ZO	CF1_V1102S1V2	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	29	30								S1	15	15	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-V2	V1102S1V2-ZC	CF1-V1102S1V2-ZC	CF1_V1102S1V2	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	31	32								S1	16	16	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2	V1102S2-ZO	CF1-V1102S2-ZO	CF1_V1102S2	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	33	34								S1	17	17	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2	V1102S2-ZC	CF1-V1102S2-ZC	CF1_V1102S2	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	35	36								S1	18	18	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-B	V1102S2B-ZO	CF1-V1102S2B-ZO	CF1_V1102S2B	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	37	38								S1	19	19	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-B	V1102S2B-ZC	CF1-V1102S2B-ZC	CF1_V1102S2B	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	39	40								S1	20	20	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-BA	V1102S2BA-ZO	CF1-V1102S2BA-ZO	CF1_V1102S2BA	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	41	42								S1	21	21	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-BA	V1102S2BA-ZC	CF1-V1102S2BA-ZC	CF1_V1102S2BA	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	43	44								S1	22	22	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-FO	V1102S2FO-ZO	CF1-V1102S2FO-ZO	CF1_V1102S2FO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	45	46								S1	23	23	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-FO	V1102S2FO-ZC	CF1-V1102S2FO-ZC	CF1_V1102S2FO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	47	48								S1	24	24	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-H0	V1102S2HO-ZO	CF1-V1102S2HO-ZO	CF1_V1102S2HO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	49	50								S1	25	25	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-H0	V1102S2HO-ZC	CF1-V1102S2HO-ZC	CF1_V1102S2HO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	51	52								S1	26	26	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-H1	V1102S2H1-ZO	CF1-V1102S2H1-ZO	CF1_V1102S2H1	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	53	54								S1	27	27	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-H1	V1102S2H1-ZC	CF1-V1102S2H1-ZC	CF1_V1102S2H1	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	55	56								S1	28	28	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-H2	V1102S2H2-ZO	CF1-V1102S2H2-ZO	CF1_V1102S2H2	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	57	58								S1	29	29	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-H2	V1102S2H2-ZC	CF1-V1102S2H2-ZC	CF1_V1102S2H2	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	59	60								S1	30	30	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-V2	V1102S2V2-ZO	CF1-V1102S2V2-ZO	CF1_V1102S2V2	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	61	62								S1	31	31	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-V2	V1102S2V2-ZC	CF1-V1102S2V2-ZC	CF1_V1102S2V2	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	63	64								S1	32	32	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-BA	V12161BA-ZO	CF1-V12161BA-ZO	CF1_V12161BA	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	65	66								S2	1	1	NA	SFO-DCS-001	SFO-CTRL1

										RIO CABINET															SYSTEM CABINET	
										Marshalling						Relay					DELTA V				DELTA V	
Vendor's tags	Wilmar's Tags	Emerson Database Tags	Module Name	Description	Type	IO Type	Range Proposed (kg/H)	Signal Type	Electrical Connection	Cabinet Name	TB Name	Term. (+)	Term. (-)	24V(+) Term.	24V(-) Term.	Term. (+)	Term. (-)	Name	Term. (+)	Term. (-)	Slot	Channel	Term. (+)	Term. (-)	Cabinet Name	Controller
XV-F16A1-BA	V12161BA-ZC	CF1-V12161BA-ZC	CF1_V12161BA	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	67	68								S2	2	2	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-COH	V1216A1CH-ZO	CF1-V1216A1CH-ZO	CF1_V1216A1CH	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	69	70								S2	3	3	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-COH	V1216A1CH-ZC	CF1-V1216A1CH-ZC	CF1_V1216A1CH	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	71	72								S2	4	4	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-COL	V1216A1CL-ZO	CF1-V1216A1CL-ZO	CF1_V1216A1CL	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	73	74								S2	5	5	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-COL	V1216A1CL-ZC	CF1-V1216A1CL-ZC	CF1_V1216A1CL	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	75	76								S2	6	6	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-DO	V1216A1DO-ZO	CF1-V1216A1DO-ZO	CF1_V1216A1DO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	77	78								S2	7	7	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-DO	V1216A1DO-ZC	CF1-V1216A1DO-ZC	CF1_V1216A1DO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	79	80								S2	8	8	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-DOH	V1216A1DH-ZO	CF1-V1216A1DH-ZO	CF1_V1216A1DH	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	81	82								S2	9	9	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-DOH	V1216A1DH-ZC	CF1-V1216A1DH-ZC	CF1_V1216A1DH	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	83	84								S2	10	10	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-DOL	V1216A1OL-ZO	CF1-V1216A1OL-ZO	CF1_V1216A1OL	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	85	86								S2	11	11	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-DOL	V1216A1OL-ZC	CF1-V1216A1OL-ZC	CF1_V1216A1OL	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	87	88								S2	12	12	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-F01	V1216A1F1-ZO	CF1-V1216A1F1-ZO	CF1_V1216A1F1	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	89	90								S2	13	13	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-F01	V1216A1F1-ZC	CF1-V1216A1F1-ZC	CF1_V1216A1F1	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	91	92								S2	14	14	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-F02	V1216A1F2-ZO	CF1-V1216A1F2-ZO	CF1_V1216A1F2	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	93	94								S2	15	15	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-F02	V1216A1F2-ZC	CF1-V1216A1F2-ZC	CF1_V1216A1F2	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	95	96								S2	16	16	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-BA	V12162BA-ZO	CF1-V12162BA-ZO	CF1_V12162BA	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	97	98								S2	17	17	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-BA	V12162BA-ZC	CF1-V12162BA-ZC	CF1_V12162BA	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	99	100								S2	18	18	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-COH	V1216A2CH-ZO	CF1-V1216A2CH-ZO	CF1_V1216A2CH	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	101	102								S2	19	19	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-COH	V1216A2CH-ZC	CF1-V1216A2CH-ZC	CF1_V1216A2CH	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	103	104								S2	20	20	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-COL	V1216A2CL-ZO	CF1-V1216A2CL-ZO	CF1_V1216A2CL	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	105	106								S2	21	21	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-COL	V1216A2CL-ZC	CF1-V1216A2CL-ZC	CF1_V1216A2CL	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	107	108								S2	22	22	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-DO	V1216A2DO-ZO	CF1-V1216A2DO-ZO	CF1_V1216A2DO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	109	110								S2	23	23	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-DO	V1216A2DO-ZC	CF1-V1216A2DO-ZC	CF1_V1216A2DO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	111	112								S2	24	24	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-DOH	V1216A2DH-ZO	CF1-V1216A2DH-ZO	CF1_V1216A2DH	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	113	114								S2	25	25	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-DOH	V1216A2DH-ZC	CF1-V1216A2DH-ZC	CF1_V1216A2DH	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	115	116								S2	26	26	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-DOL	V1216A2DL-ZO	CF1-V1216A2DL-ZO	CF1_V1216A2DL	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	117	118								S2	27	27	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-DOL	V1216A2DL-ZC	CF1-V1216A2DL-ZC	CF1_V1216A2DL	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	119	120								S2	28	28	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-FC	V1216A2FC-ZO	CF1-V1216A2FC-ZO	CF1_V1216A2FC	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	121	122								S2	29	29	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-FC	V1216A2FC-ZC	CF1-V1216A2FC-ZC	CF1_V1216A2FC	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	123	124								S2	30	30	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-FO	V1216A2FO-ZO	CF1-V1216A2FO-ZO	CF1_V1216A2FO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	125	126								S2	31	31	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-FO	V1216A2FO-ZC	CF1-V1216A2FO-ZC	CF1_V1216A2FO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	127	128								S2	32	32	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-F01	V1216A2F1-ZO	CF1-V1216A2F1-ZO	CF1_V1216A2F1	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	129	130								S3	1	1	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-F01	V1216A2F1-ZC	CF1-V1216A2F1-ZC	CF1_V1216A2F1	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	131	132								S3	2	2	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-F02	V1261A2F2-ZO	CF1-V1261A2F2-ZO	CF1_V1261A2F2	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	133	134								S3	3	3	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-F02	V1261A2F2-ZC	CF1-V1261A2F2-ZC	CF1_V1261A2F2	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	135	136								S3	4	4	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-RCO	V1216A2RC-ZO	CF1-V1216A2RC-ZO	CF1_V1216A2RC	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	137	138								S3	5	5	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-RCO	V1216A2RC-ZC	CF1-V1216A2RC-ZC	CF1_V1216A2RC	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	139	140								S3	6	6	NA	SFO-DCS-001	SFO-CTRL1
LSH-F02S1	LSH1102S1	CF1-LSH1102S1	CF1_LSH1102S1	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-003	TB-DI	141	142	+		A1	A2(comm)	RDI1-01	14	11(comm)	S3	7	7	NA	SFO-DCS-001	SFO-CTRL1
LSH-F02S1-1	LSH11S11	CF1-LSH11S11	CF1_LSH11S11	Level Switch		DI		PNP	3 wire PNP	CF1-RIO-003	TB-DI	143	144	+		A1	A2	RDI1-02	14	11	S3	8	8	NA	SFO-DCS-001	SFO-CTRL1
LSH-F02S2	LSH1102S2	CF1-LSH1102S2	CF1_LSH1102S2	Level Switch	Tuning Fork	DI		PNP	3 wire PNP	CF1-RIO-003	TB-DI	145	146	+		A1	A2	RDI1-03	14	11	S3	9	9	NA	SFO-DCS-001	SFO-CTRL1
LSH-F02S2-1	LSH1102S3	CF1-LSH1102S3	CF1_LSH1102S3	Level Switch		DI		PNP	3 wire PNP	CF1-RIO-003	TB-DI	147	148	+		A1	A2(comm)	RDI1-04	14	11(comm)	S3	10	10	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-BC	V1216A1BC-ZO	CF1-V1216A1BC-ZO	CF1_V1216A1BC	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	149	150								S3	11	11	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-BC	V1216A1BC-ZC	CF1-V1216A1BC-ZC	CF1_V1216A1BC	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	151	152								S3	12	12	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-RCO	V1216A1RC-ZO	CF1-V1216A1RC-ZO	CF1_V1216A1RC	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	153	154								S3	13	13	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-RCO	V1216A1RC-ZC	CF1-V1216A1RC-ZC	CF1_V1216A1RC	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	155	156								S3	14	14	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-BC	V1216A2BC-ZO	CF1-V1216A2BC-ZO	CF1_V1216A2BC	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	157	158								S3	15	15	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-BC	V1216A2BC-ZC	CF1-V1216A2BC-ZC	CF1_V1216A2BC	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	159	160								S3	16	16	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-S	VS3460VS-ZO	CF1-VS3460VS-ZO	CF1_VS3460VS	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	161	162								S3	17	17	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-S	VS3460VS-ZC	CF1-VS3460VS-ZC	CF1_VS3460VS	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	163	164								S3	18	18	NA	SFO-DCS-001	SFO-CTRL1
XV-F57CK-DA	V1357CKD-ZO	CF1-V1357CKD-ZO	CF1_V1357CKD	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	165	166								S3	19	19	NA	SFO-DCS-001	SFO-CTRL1
XV-F57CK-DA	V1357CKD-ZC	CF1-V1357CKD-ZC	CF1_V1357CKD	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	167	168								S3	20	20	NA	SFO-DCS-001	SFO-CTRL1
XV-F78/16/2-R1	V12162R1-ZO	CF1-V12162R1-ZO	CF1_V12162R1	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	169	170								S3	21	21	NA	SFO-DCS-001	SFO-CTRL1
XV-F78/16/2-R1	V12162R1-ZC	CF1-V12162R1-ZC	CF1_V12162R1	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	171	172								S3	22	22	NA	SFO-DCS-001	SFO-CTRL1
XV-F78/16/2-R2	V12162R2-ZO	CF1-V12162R2-ZO	CF1_V12162R2	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	173	174								S3	23	23	NA	SFO-DCS-001	SFO-CTRL1
XV-F78/16/2-R2	V12162R2-ZC	CF1-V12162R2-ZC	CF1_V12162R2	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	175	176								S3	24	24	NA	SFO-DCS-001	SFO-CTRL1
XV-F78B-F	V1482BF-ZO	CF1-V1482BF-ZO	CF1_V1482BF	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	177	178								S3	25	25	NA	SFO-DCS-001	SFO-CTRL1
XV-F78B-F	V1482BF-ZC	CF1-V1482BF-ZC	CF1_V1482BF	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	179	180								S3	26	26	NA	SFO-DCS-001	SFO-CTRL1
XV-F78D-F	V1478DF-ZO	CF1-V1478DF-ZO	CF1_V1478DF	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	181	182								S3	27	27	NA	SFO-DCS-001	SFO-CTRL1
XV-F78D-F	V1478DF-ZC	CF1-V1478DF-ZC	CF1_V1478DF	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	183	184								S3	28	28	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-RTW	V148TIW-ZO	CF1-V148TIW-ZO	CF1_V148TIW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	185	186								S3	29	29	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-RTW	V148TIW-ZC	CF1-V148TIW-ZC	CF1_V148TIW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	187	188								S3	30	30	NA	SFO-DCS-001	SFO-CTRL1
XV-F82B-DO2	V13BDO2-ZO	CF1-V13BDO2-ZO	CF1_V13BDO2	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	189	190								S3	31	31	NA	SFO-DCS-001	SFO-CTRL1
XV-F82B-DO2	V13BDO2-ZC	CF1-V13BDO2-ZC	CF1_V13BDO2	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	191	192								S3	32	32	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-BY	V1002S1BY-ZO	CF1-V1002S1BY-ZO	CF1_V1002S1BY	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	193	194								S4	1	1	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-BY	V1002S1BY-ZC	CF1-V1002S1BY-ZC	CF1_V1002S1BY	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	195	196								S4	2	2	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-BY	V1102S2BY-ZO	CF1-V1102S2BY-ZO	CF1_V1102S2BY	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	197	198								S4	3	3	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-BY	V1102S2BY-ZC	CF1-V1102S2BY-ZC	CF1_V1102S2BY	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	199	200								S4	4	4	NA	SFO-DCS-001	SFO-CTRL1
XV-F82B-R	V1382BR-ZO	CF1-V1382BR-ZO	CF1_V1382BR	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	201	202								S4	5	5	NA	SFO-DCS-001	SFO-CTRL1
XV-F82B-R	V1382BR-ZC	CF1-V1382BR-ZC	CF1_V1382BR	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	203	204								S4	6	6	NA	SFO-DCS-001	SFO-CTRL1
XV-F82C-DOC	V1382CDOC-ZO	CF1-V1382CDOC-ZO	CF1_V1382CDOC	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	205	206								S4	7	7	NA	SFO-DCS-001	SFO-CTRL1
XV-F82C-DOC	V1382CDOC-ZC	CF1-V1382CDOC-ZC	CF1_V1382CDOC	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	207	208								S4	8	8	NA	SFO-DCS-001	SFO-CTRL1
XV-F82C-RO	V1382CRO-ZO	CF1-V1382CRO-ZO	CF1_V1382CRO	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	209	210								S4	9	9	NA	SFO-DCS-001	SFO-CTRL1
XV-F82C-RO	V1382CRO-ZC	CF1-V1382CRO-ZC	CF1_V1382CRO	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	211	212								S4	10	10	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-RTIW	V148RTIW-ZO	CF1-V148RTIW-ZO	CF1_V148RTIW	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	213	214								S4	11	11	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-RTIW	V148RTIW-ZC	CF1-V148RTIW-ZC	CF1_V148RTIW	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	215	216								S4	12	12	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S-BA	V1102SBA-ZO	CF1-V1102SBA-ZO	CF1_V1102SBA	Actuator Valve	Valve open indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	217	218								S4	13	13	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S-BA	V1102SBA-ZC	CF1-V1102SBA-ZC	CF1_V1102SBA	Actuator Valve	Valve close indication	DI		NPN/PNP	2 wire	CF1-RIO-003	TB-DI	219	220								S4	14	14	NA	SFO-DCS-001	SFO-CTRL1
PF1078B	PU1478	CF1-PU1478	CF1_PU1478	Cold Pump	Motor run feedback	DI		DI Dry Contact	2 wire	CF1-RIO-003	TB-DI	221	222								S4	15	15	NA	SFO-DCS-001	SFO-CTRL1
PF1078B	PU1478	CF1-PU1478	CF1_PU1478	Cold Pump	Motor trip feedback	DI		DI Dry Contact	2 wire	CF1-RIO-003	TB-DI	223	224								S4	16	16	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	225	226								S4	17	17	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	227	228								S4	18	18	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	229	230								S4	19	19	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	231	232								S4	20	20	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	233	234								S4	21	21	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	235	236								S4	22	22	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	237	238								S4	23	23	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	239	240								S4	24	24	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	241	242								S4	25	25	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	243	244								S4	26	26	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	245	246								S4	27	27	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	247	248								S4	28	28	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	249	250								S4	29	29	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	251	252								S4	30	30	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	253	254								S4	31	31	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DI	255	256								S4	32	32	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1	V1102S1-SY	CF1-V1102S1-SY	CF1_V1102S1	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	1	2			14	11	RDO1-01	A1	A2 (COMM)	S6	1	1	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S-B	V1102SB-SY	CF1-V1102SB-SY	CF1_V1102SB	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	3	4			14	11	RDO1-02	A1	A2	S6	2	2	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-BA	V1102S1BA-SY	CF1-V1102S1BA-SY	CF1_V1102S1BA	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	5	6			14	11	RDO1-03	A1	A2	S6	3	3	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-FO	V1102S1FO-SY	CF1-V1102S1FO-SY	CF1_V1102S1FO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	7	8			14	11	RDO1-04	A1	A2	S6	4	4	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-H0	V1102S1HO-SY	CF1-V1102S1HO-SY	CF1_V1102S1HO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	9	10			14	11	RDO1-05	A1	A2	S6	5	5	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-H1	V1102SH1-SY	CF1-V1102SH1-SY	CF1_V1102SH1	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	11	12			14	11	RDO1-06	A1	A2	S6	6	6	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-H2	V1102SH2-SY	CF1-V1102SH2-SY	CF1_V1102SH2	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	13	14			14	11	RDO1-07	A1	A2	S6	7	7	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-V2	V1102S1V2-SY	CF1-V1102S1V2-SY	CF1_V1102S1V2	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	15	16			14	11	RDO1-08	A1	A2	S6	8	8	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2	V1102S2-SY	CF1-V1102S2-SY	CF1_V1102S2	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	17	18			14	11	RDO1-09	A1	A2	S6	9	9	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-B	V1102S2B-SY	CF1-V1102S2B-SY	CF1_V1102S2B	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	19	20			14	11	RDO1-10	A1	A2	S6	10	10	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-BA	V1102S2BA-SY	CF1-V1102S2BA-SY	CF1_V1102S2BA	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	21	22			14	11	RDO1-11	A1	A2	S6	11	11	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-FO	V1102S2FO-SY	CF1-V1102S2FO-SY	CF1_V1102S2FO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	23	24			14	11	RDO1-12	A1	A2	S6	12	12	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-H0	V1102S2HO-SY	CF1-V1102S2HO-SY	CF1_V1102S2HO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	25	26			14	11	RDO1-13	A1	A2	S6	13	13	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-H1	V1102S2H1-SY	CF1-V1102S2H1-SY	CF1_V1102S2H1	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	27	28			14	11	RDO1-14	A1	A2	S6	14	14	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-H2	V1102S2H2-SY	CF1-V1102S2H2-SY	CF1_V1102S2H2	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	29	30			14	11	RDO1-15	A1	A2	S6	15	15	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-V2	V1102S2V2-SY	CF1-V1102S2V2-SY	CF1_V1102S2V2	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	31	32			14	11	RDO1-16	A1	A2	S6	16	16	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-BA	V12161BA-SY	CF1-V12161BA-SY	CF1_V12161BA	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	33	34			14	11	RDO1-17	A1	A2	S6	17	17	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-COH	V1216A1CH-SY	CF1-V1216A1CH-SY	CF1_V1216A1CH	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	35	36			14	11	RDO1-18	A1	A2	S6	18	18	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-COL	V1216A1CL-SY	CF1-V1216A1CL-SY	CF1_V1216A1CL	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	37	38			14	11	RDO1-19	A1	A2	S6	19	19	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-DO	V1216A1DO-SY	CF1-V1216A1DO-SY	CF1_V1216A1DO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	39	40			14	11	RDO1-20	A1	A2	S6	20	20	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-DOH	V1216A1DH-SY	CF1-V1216A1DH-SY	CF1_V1216A1DH	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	41	42			14	11	RDO1-21	A1	A2	S6	21	21	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-DOL	V1216A1OL-SY	CF1-V1216A1OL-SY	CF1_V1216A1OL	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	43	44			14	11	RDO1-22	A1	A2	S6	22	22	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-F01	V1216A1F1-SY	CF1-V1216A1F1-SY	CF1_V1216A1F1	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	45	46			14	11	RDO1-23	A1	A2	S6	23	23	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-F02	V1216A1F2-SY	CF1-V1216A1F2-SY	CF1_V1216A1F2	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	47	48			14	11	RDO1-24	A1	A2	S6	24	24	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-BA	V12162BA-SY	CF1-V12162BA-SY	CF1_V12162BA	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	49	50			14	11	RDO1-25	A1	A2	S6	25	25	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-COH	V1216A2CH-SY	CF1-V1216A2CH-SY	CF1_V1216A2CH	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	51	52			14	11	RDO1-26	A1	A2	S6	26	26	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-COL	V1216A2CL-SY	CF1-V1216A2CL-SY	CF1_V1216A2CL	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	53	54			14	11	RDO1-27	A1	A2	S6	27	27	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-DO	V1216A2DO-SY	CF1-V1216A2DO-SY	CF1_V1216A2DO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	55	56			14	11	RDO1-28	A1	A2	S6	28	28	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-DOH	V1216A2DH-SY	CF1-V1216A2DH-SY	CF1_V1216A2DH	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	57	58			14	11	RDO1-29	A1	A2	S6	29	29	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-DOL	V1216A2DL-SY	CF1-V1216A2DL-SY	CF1_V1216A2DL	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	59	60			14	11	RDO1-30	A1	A2	S6	30	30	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-FC	V1216A2FC-SY	CF1-V1216A2FC-SY	CF1_V1216A2FC	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	61	62			14	11	RDO1-31	A1	A2	S6	31	31	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-FO	V1216A2FO-SY	CF1-V1216A2FO-SY	CF1_V1216A2FO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	63	64			14	11	RDO1-32	A1	A2	S6	32	32	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-F01	V1216A2F1-SY	CF1-V1216A2F1-SY	CF1_V1216A2F1	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	65	66			14	11	RDO1-33	A1	A2	S7	1	1	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-F02	V1261A2F2-SY	CF1-V1261A2F2-SY	CF1_V1261A2F2	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	67	68			14	11	RDO1-34	A1	A2	S7	2	2	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-RCO	V1216A2RC-SY	CF1-V1216A2RC-SY	CF1_V1216A2RC	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	69	70			14	11	RDO1-35	A1	A2	S7	3	3	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-BC	V1216A1BC-SY	CF1-V1216A1BC-SY	CF1_V1216A1BC	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	71	72			14	11	RDO1-36	A1	A2	S7	4	4	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A1-RCO	V1216A1RC-SY	CF1-V1216A1RC-SY	CF1_V1216A1RC	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	73	74			14	11	RDO1-37	A1	A2	S7	5	5	NA	SFO-DCS-001	SFO-CTRL1
XV-F16A2-BC	V1216A2BC-SY	CF1-V1216A2BC-SY	CF1_V1216A2BC	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	75	76			14	11	RDO1-38	A1	A2	S7	6	6	NA	SFO-DCS-001	SFO-CTRL1
XV-F460V-S	VS3460VS-SY	CF1-VS3460VS-SY	CF1_VS3460VS	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	77	78			14	11	RDO1-39	A1	A2	S7	7	7	NA	SFO-DCS-001	SFO-CTRL1
XV-F57CK-DA	V1357CKD-SY	CF1-V1357CKD-SY	CF1_V1357CKD	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	79	80			14	11	RDO1-40	A1	A2	S7	8	8	NA	SFO-DCS-001	SFO-CTRL1
XV-F78/16/2-R1	V12162R1-SY	CF1-V12162R1-SY	CF1_V12162R1	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	81	82			14	11	RDO1-41	A1	A2	S7	9	9	NA	SFO-DCS-001	SFO-CTRL1
XV-F78/16/2-R2	V12162R2-SY	CF1-V12162R2-SY	CF1_V12162R2	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	83	84			14	11	RDO1-42	A1	A2	S7	10	10	NA	SFO-DCS-001	SFO-CTRL1

										RIO CABINET																SYSTEM CABINET	
												Marshalling				Relay					DELTA V					DELTA V	
Vendor's tags	Wilmar's Tags	Emerson Database Tags	Module Name	Description	Type	IO Type	Range Proposed (kg/H)	Signal Type	Electrical Connection	Cabinet Name	TB Name	Term. (+)	Term. (-)	24V(+) Term.	24V(-) Term.	Term. (+)	Term. (-)	Name	Term. (+)	Term. (-)	Slot	Channel	Term. (+)	Term. (-)	Cabinet Name	Controller
XV-F78B-F	V1482BF-SY	CF1-V1482BF-SY	CF1_V1482BF	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	85	86			14	11	RDO1-43	A1	A2	S7	11	11	NA	SFO-DCS-001	SFO-CTRL1
XV-F78D-F	V1478DF-SY	CF1-V1478DF-SY	CF1_V1478DF	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	87	88			14	11	RDO1-44	A1	A2	S7	12	12	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-RTW	V148TIW-SY	CF1-V148TIW-SY	CF1_V148TIW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	89	90			14	11	RDO1-45	A1	A2	S7	13	13	NA	SFO-DCS-001	SFO-CTRL1
XV-F82B-DO2	V13BDO2-SY	CF1-V13BDO2-SY	CF1_V13BDO2	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	91	92			14	11	RDO1-46	A1	A2	S7	14	14	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S1-BY	V1002S1BY-SY	CF1-V1002S1BY-SY	CF1_V1002S1BY	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	93	94			14	11	RDO1-47	A1	A2	S7	15	15	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S2-BY	V1102S2BY-SY	CF1-V1102S2BY-SY	CF1_V1102S2BY	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	95	96			14	11	RDO1-48	A1	A2	S7	16	16	NA	SFO-DCS-001	SFO-CTRL1
XV-F82B-R	V1382BR-SY	CF1-V1382BR-SY	CF1_V1382BR	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	97	98			14	11	RDO1-49	A1	A2	S7	17	17	NA	SFO-DCS-001	SFO-CTRL1
XV-F82C-DOC	V1382CDOC-SY	CF1-V1382CDOC-SY	CF1_V1382CDOC	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	99	100			14	11	RDO1-50	A1	A2	S7	18	18	NA	SFO-DCS-001	SFO-CTRL1
XV-F82C-RO	V1382CRO-SY	CF1-V1382CRO-SY	CF1_V1382CRO	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	101	102			14	11	RDO1-51	A1	A2	S7	19	19	NA	SFO-DCS-001	SFO-CTRL1
XV-F81/16-RTIW	V148RTIW-SY	CF1-V148RTIW-SY	CF1_V148RTIW	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	103	104			14	11	RDO1-52	A1	A2	S7	20	20	NA	SFO-DCS-001	SFO-CTRL1
XV-F02S-BA	V1102SBA-SY	CF1-V1102SBA-SY	CF1_V1102SBA	Actuator Valve	Valve open command	DO		24VDC Wet Supply	2 wire	CF1-RIO-003	TB-DO	105	106			14	11	RDO1-53	A1	A2	S7	21	21	NA	SFO-DCS-001	SFO-CTRL1
PF1078B	PU1478	CF1-PU1478	CF1_PU1478	Cold Pump	Motor start command	DO		24VDC Wet supply	2 wire	CF1-RIO-003	TB-DO	107	108			14	11	RDO1-54	A1	A2	S7	22	22	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DO	109	110			14	11	RDO1-55	A1	A2	S7	23	23	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DO	111	112			14	11	RDO1-56	A1	A2	S7	24	24	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DO	113	114			14	11	RDO1-57	A1	A2	S7	25	25	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DO	115	116			14	11	RDO1-58	A1	A2	S7	26	26	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DO	117	118			14	11	RDO1-59	A1	A2	S7	27	27	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DO	119	120			14	11	RDO1-60	A1	A2	S7	28	28	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DO	121	122			14	11	RDO1-61	A1	A2	S7	29	29	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DO	123	124			14	11	RDO1-62	A1	A2	S7	30	30	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DO	125	126			14	11	RDO1-63	A1	A2	S7	31	31	NA	SFO-DCS-001	SFO-CTRL1
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	SPARE	CF1-RIO-003	TB-DO	127	128			14	11	RDO1-64	A1	A2 (COMM)	S7	32	32	NA	SFO-DCS-001	SFO-CTRL1