

万用表：福禄克17B
整板状态测量

Multimeter: fluke 17b whole board state measurement

Ultra Wide Angle Camera
超广角摄像头

	OL	OL	GND	OL	OL	GND	539	681	GND	427	580	
GND												500
	OL	GND	OL	OL	GND	OL	735	GND	341	405	400	

Wide angle camera

广角摄像头

	682	529	GND	574	516	513	GND	OL	OL	GND	OL	OL	GND	
GND														502
	283	737	GND	341	OL	513	434	GND	OL	OL	GND	OL	531	

Upper antenna

上天线

	OL	GND	GND	GND	GND	GND	GND	GND	GND	GND	GND	
GND												GND
	GND	GND	GND	361	GND	GND	GND	GND	GND	GND	361	

Telephoto camera

长焦摄像头

	GND	OL	OL	GND	OL	OL	GND	GND	273	335	GND	528	683	
628														GND
	630	GND	OL	OL	GND	OL	OL	572	512	341	425	514	514	

Earphone line

听筒排线

	444	444	763	763	295	341	GND	GND	GND	GND	606	341	408	672	
596															GND
	596	596	596	341	545	1995	491	497	491	497	334	334	665	668	

Touch base

触摸座

	358	342	342	342	342	342	GND	465	363	517	
GND											GND
	342	342	342	342	342	369	466	342	508	546	

Lattice projection
点阵投影

	487	
	320	320
	513	515
	749	483
	625	GND
	343	498
	320	504
	320	320
	492	

Power on, auxiliary mic flash
开机，副麦克风
闪光灯

	OL	
	361	GND
	338	GND
	339	666
	610	713
	683	662
	627	662
	637	412
	581	580
	GND	

front camera
前置摄像头

	530	
	OL	530
	GND	GND
	OL	343
	OL	GND
	GND	333
	OL	341
	OL	OL
	GND	282
	333	GND
	560	

红外像头

Infrared image head

	629	
	398	680
	429	OL
	422	682
	GND	GND
	453	283
	442	340
	GND	512
	440	512
	440	342
	GND	

Battery holder 1

电池座1

	GND	742	300	
		GND	GND	GND

Display base

显示座

	307	305	OL	759	374	591	282	636	452	447	340	321	GND	417	420	GND	413	417	
275																			GND
	307	307	GND	714	OL	OL	OL	340	368	GND	418	423	GND	417	420	GND	417	420	

Lower antenna

下天线

		361	GND	401	GND	630	
GND							GND
		362	GND	GND	GND	GND	

Tail insertion (Including wireless charging, volume + -, mute, battery holder 2)

尾插

(包含无线充电、音量+-、静音、无线充电、电池座2)

	671	663	674	668	296	375	427	363	374	376	339	GND	GND	GND	654	370	371	373	371	370	625	442	405	513	358	806	443	379	
GND																													379
	669	705	675	705	296	GND	493	GND	339	682	336	336	337	337	GND	340	371	GND	398	GND	442	86	GND	664	664	660	660	GND	