

chapter-8

July 15, 2025

0.1 Overview

Measurements of EMG and force were taken in a forearm exercise. The data is divided in two types of muscle activity: intermittent and fatigue. In this Python notebook, we will analyze the intermittent data. The fatigue program has already been explained in a previous notebook (Ch. 5). The recordings to be analyzed can be found in our GitHub repository (<https://github.com/emckiernan/electrophys>). Before carrying out this analysis practical, students should first do the ‘Graphing and exploring EMG data’ and ‘Filtering and analyzing EMG data’ practicals from this series.

0.2 Setting up the notebook

We begin by setting up the Jupyter notebook and importing the Python modules for plotting figures, reading the data and analyzing it.

```
[2]: %pip install pandas;
```

```
Requirement already satisfied: pandas in
/opt/homebrew/Cellar/jupyterlab/4.4.4/libexec/lib/python3.13/site-packages
(2.3.1)
Requirement already satisfied: numpy>=1.26.0 in
/opt/homebrew/lib/python3.13/site-packages (from pandas) (2.2.5)
Requirement already satisfied: python-dateutil>=2.8.2 in
/opt/homebrew/Cellar/jupyterlab/4.4.4/libexec/lib/python3.13/site-packages (from
pandas) (2.9.0.post0)
Requirement already satisfied: pytz>=2020.1 in
/opt/homebrew/Cellar/jupyterlab/4.4.4/libexec/lib/python3.13/site-packages (from
pandas) (2025.2)
Requirement already satisfied: tzdata>=2022.7 in
/opt/homebrew/Cellar/jupyterlab/4.4.4/libexec/lib/python3.13/site-packages (from
pandas) (2025.2)
Requirement already satisfied: six>=1.5 in
/opt/homebrew/Cellar/jupyterlab/4.4.4/libexec/lib/python3.13/site-packages (from
python-dateutil>=2.8.2->pandas) (1.17.0)
Note: you may need to restart the kernel to use updated packages.
```

```
[1]: import os
import scipy as sc
from scipy import signal
```

```

from scipy.optimize import curve_fit
import scipy.io.wavfile
import numpy as np
import matplotlib.pyplot as plt
from numpy.fft import fft, ifft
import wave
import pandas as pd

```

```

[15]: # command to view figures in Jupyter notebook
      %matplotlib inline

      # commands to create high-resolution figures with large labels
      %config InlineBackend.figure_formats = {'png', 'retina'}
      plt.rcParams['axes.labelsize'] = 14 # fontsize for figure labels
      plt.rcParams['font.size'] = 14 # fontsize for figure numbers

```

0.3 Importing data

```

[36]: sr_fatigue_l, fatigue_l = scipy.io.wavfile.read("./data/
      ↪S1_EMG_leftHand_gripFatigue.wav", "r")
      sr_fatigue_r, fatigue_r = scipy.io.wavfile.read("./data/
      ↪S1_EMG_rightHand_gripFatigue.wav", "r")

```

```

[37]: sr_interm_l, interm_l = scipy.io.wavfile.read("./data/
      ↪S1_EMG_leftHand_gripIntermittent.wav", "r")
      sr_interm_r, interm_r = scipy.io.wavfile.read("./data/
      ↪S1_EMG_rightHand_gripIntermittent.wav", "r")

```

```

[38]: # Read the csv file of the force recordings
      force=pd.read_csv("./data/EMG_Force.csv")

```

```

[39]: f_time=force["Time"].to_numpy()
      f_fatigue_l= force["Left_hand_fatigue"].to_numpy()
      f_fatigue_l= f_fatigue_l[~np.isnan(f_fatigue_l)]
      f_fatigue_r=force["Right_hand_fatigue"].to_numpy()
      f_fatigue_r= f_fatigue_r[~np.isnan(f_fatigue_r)]
      f_interm_l=force["Left_hand_intermittent"].to_numpy()
      f_interm_l=f_interm_l[~np.isnan(f_interm_l)]
      f_interm_r=force["Right_hand_intermittent"].to_numpy()
      f_interm_r=f_interm_r[~np.isnan(f_interm_r)]

```


0.4 Plotting the data

```


[46]: plt.figure(figsize=(18,6))
      plt.title("Force: Fatigue")

```


```
plt.plot(np.linspace(0,len(fatigue_r)/
    ↳sr_fatigue_r,num=len(fatigue_r)),fatigue_r,label="Fatigue R")
plt.plot(np.linspace(0,len(fatigue_l)/
    ↳sr_fatigue_l,num=len(fatigue_l)),fatigue_l,label="Fatigue L")
plt.legend()
plt.xlabel('Time (s)')
plt.ylabel('Voltage (uncalibrated)')
plt.show;
```



```
[47]: plt.figure(figsize=(18,6))
plt.title("Force: Fatigue")
plt.plot(f_time[0:len(f_fatigue_r)],f_fatigue_r,label="Fatigue R")
plt.plot(f_time[0:len(f_fatigue_l)],f_fatigue_l,label="Fatigue L")
plt.legend()
plt.xlabel('Time (s)')
plt.ylabel('Force')
plt.show;
```




```
[48]: plt.figure(figsize=(18,6))
plt.title("ECG: Intermittent")
plt.plot(np.linspace(0,len(inter_m_l)/
    ↳sr_inter_m_l,num=len(inter_m_l)),inter_m_l,label="Intermittent L")
plt.plot(np.linspace(0,len(inter_m_r)/
    ↳sr_inter_m_r,num=len(inter_m_r)),inter_m_r,label="Intermittent R")
plt.legend()
plt.xlabel('Time (s)')
plt.ylabel('Voltage (uncalibrated)')
plt.show;
```



```
[49]: plt.figure(figsize=(18,6))
plt.title("Force: Intermittent")
plt.plot(f_time[0:len(f_inter_m_r)],f_inter_m_l,label="Intermittent L")
plt.plot(f_time[0:len(f_inter_m_l)],f_inter_m_r,label="Intermittent R")
plt.legend()

plt.xlabel('Time (s)')
plt.ylabel('Force (N)')
plt.show;
```




0.5 Graphing the intermittent measurements

```
[50]: #The EMG data is larger than the force data.  
# First we need to adjust both arrays.  
# The offset is calculated  
offset_i_l=abs(f_time[len(f_intermitent_l)-1]-len(intermitent_l)/  
    ↳sr_intermitent_l)
```

```
[51]: # We establish a delay time.  
#Feel free to play with this value until you are certain that both lines  
    ↳coincide  
a_i_l=1.58
```


```
[56]: # Plot the left hand intermittent data  
plt.figure(figsize=(18,6))  
plt.title("Intermittent: Left")  
plt.plot(np.  
    ↳linspace(-a_i_l,offset_i_l-a_i_l+f_time[len(f_interm_l)-1]),num=len(inter_m_l),inter_m_l,lab  
plt.plot(f_time[0:len(f_interm_l)],max(inter_m_l)*f_interm_l/  
    ↳max(f_interm_l),label="Force")  
#plt.xlim(0,10)  
plt.xlabel('Time (s)')  
plt.ylabel('Voltage (uncalibrated)')  
plt.legend()  
plt.show;
```



```
[57]: # The offset is calculated  
offset_i_r=abs(f_time[len(f_intermitent_r)-1]-len(intermitent_r)/  
    ↳sr_intermitent_r)
```

```
[58]: # We establish a delay time.
#Feel free to play with this value until you are certain that both lines
      ↪coincide
a_i_r=1
```

```
[60]: # Plot the left hand intermittent data
plt.figure(figsize=(18,6))
plt.title("Intermittent: Right")
plt.plot(np.linspace(-0.
      ↪9,offset_i_r-a_i_r+f_time[len(f_interm_r)-1]],num=len(inter_m_r)),inter_m_r,label="EMG")
plt.plot(f_time[0:len(f_interm_r)],max(inter_m_r)*f_interm_r/
      ↪max(f_interm_r),label="Force")
#plt.xlim(0,10)
plt.xlabel('Time (s)')
plt.ylabel('Voltage (uncalibrated)')
plt.legend()
plt.show;
```




0.6 Graphing the fatigue measurments

```
[61]: # The offset is calculated
offset_f_l=abs(f_time[len(f_fatigue_l)-1])-len(fatigue_l)/sr_fatigue_l
```

```
[62]: # We establish a delay time.
#Feel free to play with this value until you are certain that both lines
      ↪coincide
a_f_l=1.15
```

```
[64]: # Plot the left hand fatigue data
plt.figure(figsize=(18,6))
plt.title("Fatigue: Left")
```


```
plt.plot(np.
    ↳ linspace(-a_f_l,offset_f_l-a_f_l+f_time[len(f_fatigue_l)-1],num=len(fatigue_l)),fatigue_l,l
plt.plot(f_time[0:len(f_fatigue_l)],max(fatigue_l)*f_fatigue_l/
    ↳ max(f_fatigue_l),label="Force")
plt.legend()
#plt.xlim(0,10)
plt.xlabel('Time (s)')
plt.ylabel('Voltage (uncalibrated)')
plt.show;
```



```
[66]: # The offset is calculated
offset_f_r=abs(f_time[len(f_fatigue_r)-1]-len(fatigue_r)/sr_fatigue_r)
```

```
[67]: # We establish a delay time.
#Feel free to play with this value until you are certain that both lines
    ↳ coincide
a_f_r=6.3
```

```
[69]: # Plot the right hand fatigue data
plt.figure(figsize=(18,6))
plt.title("Fatigue: Right")
plt.plot(np.
    ↳ linspace(-a_f_r,offset_f_r-a_f_r+f_time[len(f_fatigue_r)-1],num=len(fatigue_r)),fatigue_r,l
plt.plot(f_time[0:len(f_fatigue_r)],6*f_fatigue_r,label="Force")
plt.xlabel('Time (s)')
plt.ylabel('Voltage (uncalibrated)')
plt.legend()
#plt.xlim(0,10)
plt.show;
```



0.7 Filtering the signals

```
[70]: # Function to delete the 60Hz noise from a given signal
def filtering(x,sr):
    X=fft(x)

    # calculate the frequency
    N = len(X)
    n = np.arange(N)
    T = N/sr
    freq = n/T

    # Get the one-sided specturm
    n_oneside = N//2
    # get the one side frequency
    f_oneside = freq[:n_oneside]

    # normalize the amplitude
    X_oneside =X[:n_oneside]/n_oneside

    # Filter out the 60 Hz noise
    for i in range(int(55*T),int(65*T)+1):
        X[i]=0
        X[-i-1]=0
    X2=ifft(X).real
    return X2

    #plt.figure(figsize=(18,6))
    #plt.plot(np.linspace(0,T,num=N),X2)
    #plt.stem(f_oneside, abs(X_oneside), linefmt='b',markerfmt=" ",
    ↪basefmt="-b")
    #plt.xlabel('Freq (Hz)')
    #plt.ylabel('Normalized FFT Amplitude |X(freq)|')
```

```
#plt.xlim(10,400)
#plt.show()
```

```
[71]: interm_l=filtering(interm_l,sr_interm_l)
```

```
[72]: interm_r=filtering(interm_r,sr_interm_r)
```

```
[73]: fatigue_l=filtering(fatigue_l,sr_fatigue_l)
```

```
[74]: fatigue_r=filtering(fatigue_r,sr_fatigue_r)
```


0.8 Finding the activation limits in the intermittent signal

0.8.1 First derivative function

One way to find the beginning and ending of the signal is by analyzing concavities. To do this we must first find the first derivative of the function.

```
[75]: #Function to find the first derivative
def der1(array):
    r=[0]
    for i in range(1,len(array)):
        r.append(array[i]-array[i-1])
    return(r)
```


```
[76]: plt.figure(figsize=(18,6))
plt.title("Force: Intermittent")
plt.plot(f_time[0:len(f_interm_l)],f_interm_l,label="Intermittent L")
plt.legend()
plt.xlabel('Time (s)')
plt.ylabel('Force (N)')
plt.show;
```



Now we compute the first derivative to the array graphed above.

```
[77]: f_interm_l_prime=der1(f_interm_l)
```

```
[78]: plt.figure(figsize=(18,6))
plt.title("Force: Intermittent Left")
plt.plot(f_time[:len(f_interm_l)],f_interm_l,label="Intermittent L")
plt.plot(f_time[:len(f_interm_l)],f_interm_l_prime,label="Intermittent L'")
plt.legend()
plt.xlabel('Time (s)')
plt.ylabel('Force (N)')
plt.show;
```




0.8.2 Second derivative function

Now we compute the second derivative

```
[82]: f_interm_l_2prime=der1(f_interm_l_prime)
```

```
[83]: plt.figure(figsize=(18,6))
plt.title("Force: Intermittent Left")
plt.plot(f_time[:len(f_interm_l)],f_interm_l,label="Intermittent L")
plt.plot(f_time[:len(f_interm_l)],f_interm_l_2prime,label="Intermittent L''")
plt.legend()
plt.xlabel('Time (s)')
plt.ylabel('Force (N)')
plt.show;
```




Notice how we only care about the peaks, so we will compute them in the next section.

0.8.3 Inflection points

```
[84]: def local_max(x,y):
    r=[[],[]]
    for i in range(1,len(y)-1):
        if y[i]>y[i-1]:
            if y[i]>y[i+1]:
                r[0].append(x[i])
                r[1].append(y[i])
    return r
```

```
[85]: f_interm_l_ip=local_max(f_time[:len(f_interm_l)],f_interm_l_prime)
```

```
[86]: plt.figure(figsize=(18,6))
plt.title("Force: Intermittent Left")
plt.plot(f_time[:len(f_interm_l)],f_interm_l,label="Intermittent L")
plt.plot(f_time[:len(f_interm_l)],f_interm_l_prime,label="Intermittent L'")
plt.scatter(f_interm_l_ip[0],f_interm_l_ip[1],label="Inflection points")
plt.legend()
plt.xlabel('Time (s)')
plt.ylabel('Force (N)')
plt.show;
```




Notice that we have too many inflection points that occur due to noise, so we will filter out all the points that are above zero.

```
[87]: def local_max(x,y):
    r=[[ ],[ ]]
    for i in range(1,len(y)-1):
        if y[i]>7.5:
            if y[i]>y[i-1]:
                if y[i]>y[i+1]:
                    r[0].append(x[i])
                    r[1].append(y[i])
    return r

[88]: f_interm_l_ip=local_max(f_time[:len(f_interm_l)],f_interm_l_prime)

[89]: plt.figure(figsize=(18,6))
plt.title("Force: Intermittent Left")
plt.plot(f_time[:len(f_interm_l)],f_interm_l,label="Intermittent L")
plt.plot(f_time[:len(f_interm_l)],f_interm_l_prime,label="Intermittent L'")
plt.scatter(f_interm_l_ip[0],f_interm_l_ip[1],label="Inflection points")
plt.xlim(0,20)
plt.ylim(0,50)
plt.grid()
plt.xlabel('Time (s)')
plt.ylabel('Force (N)')
plt.legend()
plt.show;
```





0.8.4 Limits with threshold:

```
[90]: def pa_beginning(x,y,threshold=5):
        r=[[ ],[ ],[ ]]
        for i in range(0,len(y)-1):
            if y[i+1]>threshold:
                if y[i]<threshold:
                    r[0].append(x[i])
                    r[1].append(y[i])
                    r[2].append(i)
        return(r)
```

```
[91]: f_interm_l_pab=pa_beginning(f_time,f_interm_l_prime,threshold=4)
```

```
[92]: plt.figure(figsize=(18,6))
plt.title("Force: Intermittent Left")
plt.plot(f_time[:601],f_interm_l,label="Intermittent L")
plt.plot(f_time[:601],f_interm_l_prime,label="Intermittent L'")
plt.scatter(f_interm_l_pab[0],f_interm_l_pab[1],label="Inflection points")
plt.xlim(0,20)
plt.ylim(0,50)
plt.grid()
plt.xlabel('Time (s)')
plt.ylabel('Force (N)')
plt.legend()
plt.show;
```




```
[93]: def pa_ending(x,y,threshold=-5):
        r=[[ ],[ ],[ ]]
        for i in range(0,len(y)-1):
            if y[i+1]>threshold:
                if y[i]<threshold:
                    r[0].append(x[i+1])
                    r[1].append(y[i+1])
                    r[2].append(i+1)
        return(r)
```

```
[94]: f_interm_l_pae=pa_ending(f_time,f_interm_l_prime,threshold=-6)
```

```
[107]: plt.figure(figsize=(18,6))
plt.title("Force: Intermittent Left")
plt.plot(f_time[0:601],f_interm_l,label="Intermittent L")
plt.plot(f_time[0:601],f_interm_l_prime,label="Intermittent L'")

plt.scatter(f_interm_l_pab[0],f_interm_l_pab[1],label="Start")
plt.scatter(f_interm_l_pae[0],f_interm_l_pae[1],label="End")
plt.xlim(0,20)
plt.ylim(-8,20)
plt.grid()
plt.xlabel('Time (s)')
plt.ylabel('Force (N)')
plt.legend()
plt.show;
```




```
[105]: def segments_th(x,y,threshold=6):
r=[[[]],[[]],[[]],[[]],[[]]]
start=False
for i in range(1,len(y)):
    if start==False:
        if y[i]>threshold:
            if y[i-1]<threshold:
                r[0][0].append(x[i])
                r[0][1].append(y[i])
                r[0][2].append(i)
                start=True
    if start==True:
        if y[i]<threshold:
            if y[i-1]>threshold:
                r[1][0].append(x[i-1])
                r[1][1].append(y[i-1])
                r[1][2].append(i-1)
                start=False
return(r)
```


```
[106]: segments_l=segments_th(f_time[:601],f_interm_l)
segments_r=segments_th(f_time[:len(f_interm_r)],f_interm_r)
```

```
[108]: plt.figure(figsize=(18,6))
plt.title("Force: Intermittent Left")
plt.plot(f_time[:601],f_interm_l,label="Intermittent L")
plt.scatter(segments_l[0][0],segments_l[0][1],label="Start")
plt.scatter(segments_l[1][0],segments_l[1][1],label="End")
#plt.xlim(0,20)
plt.xlabel('Time (s)')
plt.ylabel('Force (N)')
plt.grid()
```

```
plt.legend()
plt.show;
```



```
[109]: plt.figure(figsize=(18,6))
plt.title("Force: Intermittent Right")
plt.plot(f_time[:len(f_interm_r)],f_interm_r,label="Intermittent R")
plt.scatter(segments_r[0][0],segments_r[0][1],label="Start")
plt.scatter(segments_r[1][0],segments_r[1][1],label="End")
#plt.xlim(0,20)
plt.grid()
plt.xlabel('Time (s)')
plt.ylabel('Force (N)')
plt.legend()
plt.show;
```




0.9 Segmenting the EMG

```
[110]: def find_in(array,x):  
        for i in range(1,len(array)):  
            if array[i]>=x:  
                if array[i-1]<x:  
                    return(i)  
        print("Error: Value not found")  
        return("Error")
```

```
[111]: Time_a=np.linspace(-1.  
        ↪45,offset_i_l-a_i_l+f_time[len(f_interm_l-1)],num=len(inter_m_l))  
Time_b=np.linspace(-0.  
        ↪9,offset_i_r-a_i_r+f_time[len(f_interm_r-1)],num=len(inter_m_r))
```

```
[113]: plt.figure(figsize=(18,6))  
plt.title("Intermittent: Left")  
plt.plot(Time_a,inter_m_l,label="EMG")  
plt.plot(f_time[:601],max(inter_m_l)*f_inter_m_l/max(f_inter_m_l),label="Force")  
#plt.scatter(segments[0][0],100*segments[0][1],label="Start")  
#plt.scatter(segments[1][0],100*segments[1][1],label="End")  
plt.xlim(0,10)  
plt.ylim(-5000,5000)  
plt.xlabel('Time (s)')  
plt.ylabel('Force (N)')  
plt.legend()  
plt.show;
```




```
[115]: plt.figure(figsize=(18,6))  
plt.title("Intermittent: Right")  
plt.plot(Time_b,inter_m_r,label="EMG")  
plt.plot(f_time[:len(f_inter_m_r)],max(inter_m_r)*f_inter_m_r/  
        ↪max(f_inter_m_r),label="Force")
```

```

#plt.scatter(segments[0][0],100*segments[0][1],label="Start")
#plt.scatter(segments[1][0],100*segments[1][1],label="End")
plt.xlim(0,10)
plt.ylim(-5000,5000)
plt.xlabel('Time (s)')
plt.ylabel('Force (N)')
plt.legend()
plt.show;

```



0.10 Muscle fiber recruitment: Frequency analysis

0.10.1 Main frequency comparison

The first value we are going to look into is the main frequency of each segment. This might give us a clue of the amount of muscle fibers that are getting activated. We expect to find higher frequencies when the force is greater, though the correlation is not always perfect.

```

[116]: #First we define a function that calculates the fft of a given segment
# and returns the frequency at which a maxima is obtained
def mainFreq(i,side="l"):
    if side=="l":
        Pa=interm_l[find_in(Time_a,segments_l[0][0][i]):
↪find_in(Time_a,segments_l[1][0][i])]
        #plt.figure(figsize=(18,6))
        #plt.subplot(121)
        #plt.plot(Time_a[find_in(Time_a,segments_l[0][0][i]):
↪find_in(Time_a,segments_l[1][0][i])],Pa)
        #plt.xlabel("Time(s)")
        #plt.ylabel("EMG Amplitude (uV)")
        #plt.title("EMG")
    else:
        Pa=interm_r[find_in(Time_b,segments_r[0][0][i]):
↪find_in(Time_b,segments_r[1][0][i])]

```

```

        #plt.figure(figsize=(18,6))
        #plt.subplot(121)
        #plt.plot(Time_b[find_in(Time_b,segments_r[0][0][i]):
↪find_in(Time_b,segments_r[1][0][i])],Pa)
        #plt.xlabel("Time(s)")
        #plt.ylabel("EMG Amplitude (uV)")
        #plt.title("EMG")

        #The fft is calculated
        X = fft(Pa)
        N = len(X)
        n = np.arange(N)
        freq = n/(Time_a[-1]-Time_a[0])

        # Get the one-sided specturm
        n_oneside = N//2
        # get the one side frequency
        f_oneside = freq[:n_oneside]

        # normalize the amplitude
        X_oneside =X[:n_oneside]/n_oneside

        main_freq=freq[np.argmax(X_oneside)]

        #plt.subplot(122)
        #plt.stem(f_oneside, abs(X_oneside), linefmt='b',markerfmt=" ",
↪basefmt="-b")
        #plt.xlabel('Freq (Hz)')
        #plt.ylabel('Normalized FFT Amplitude |X(freq)|')
        #plt.tight_layout()
        #plt.xlim(0,100)
        #plt.show()
        return(main_freq)

```

```
[117]: np.shape(segments_r)
```

```
[117]: (2, 3, 33)
```


```
[118]: freq_req_l=[]
for i in range(0,37):
    freq_req_l.append(mainFreq(i))
```

```
[119]: freq_req_r=[]
for i in range(0,33):
    freq_req_r.append(mainFreq(i,side="r"))
```


Each segment is classified by the intensity of the force produced. Each of the 4 measurments consisted in 3 sets of pulses (S1, S2 and S3). The force produced was meant to be similar in every

pulse of a given set. The first set (s1) corresponds to the lowest force pulses, while the third and last set (S3) corresponds to the higher force pulses.

```
[120]: plt.figure(figsize=(18,6))
plt.scatter(np.linspace(0,60,num=37)[:17],freq_req_l[:17],label="S1")
plt.scatter(np.linspace(0,60,num=37)[17:27],freq_req_l[17:27],label="S2")
plt.scatter(np.linspace(0,60,num=37)[27:],freq_req_l[27:],label="S3")
plt.legend()
plt.title('Analysis: Left')
plt.ylabel('Main Frequency (Hz)')
plt.xlabel('Time (s)')
plt.show;
```



```
[122]: plt.figure(figsize=(18,6))
plt.scatter(np.linspace(0,60,num=33)[:16],freq_req_r[:16],label="S1")
plt.scatter(np.linspace(0,60,num=33)[16:25],freq_req_r[16:25],label="S2")
plt.scatter(np.linspace(0,60,num=33)[25:],freq_req_r[25:],label="S3")
plt.legend()
plt.title('Analysis: Right')
plt.ylabel('Main Frequency (Hz)')
plt.xlabel('Time (s)')
plt.show;
```

From the graphs above we can conclude that the most relevant frequency isn't a significant number. No strong correlation can be found between the force produced and the frequency of the EMG based on this analysis. This might be due to two reasons. Either the measurements do not have enough resolution to properly identify the muscle fiber recruitment, or the shape of the spectrogram cannot be accurately described by the main frequency component. In the first case we would need to repeat the experiment again and get new measurements with a more precise detector. If the second case is true, we should find a new way to classify the shape of the spectrogram.

0.10.2 Spectrogram

```
[123]: f_r,t_r,sxx_r = sc.signal.spectrogram(interim_r,sr_interim_r,nperseg=sr_interim_r//
      ↪2, scaling='spectrum')
```

```
[124]: f_l,t_l,sxx_l = sc.signal.spectrogram(interim_l,sr_interim_l,nperseg=sr_interim_l//
      ↪2, scaling='spectrum')
```


```
[127]: f_r = f_r[:401]
      sxx_r = sxx_r[:401]

      fig = plt.figure(figsize=(30,15),dpi=50)
      ax1 = plt.subplot(211)
      plt.pcolormesh(np.log(sxx_r),cmap='jet')
      plt.xticks([])
      plt.ylabel('Frequency (Hz)')
      plt.title('Spectrogram - Rectified EMG')

      ax2 = plt.subplot(212)
      plt.plot(np.arange(0,len(interim_r))/sr_interim_r,interim_r,lw=.1)
      plt.ylabel('Voltage (uncalibrated)')
      plt.xlabel('Time (sec)')
      plt.xlim(t_r[0],t_r[-1])
```

```
# adding an independent axis for the colorbar:
fig.subplots_adjust(right=0.8)
cbar_ax = fig.add_axes([.81, .5, 0.025, 0.4])
plt.colorbar(label='log($Voltage^2$)',cax=cbar_ax,)

plt.draw()
```




```
[128]: f_l = f_l[:401]
sxx_l = sxx_l[:401]

fig = plt.figure(figsize=(30,15),dpi=50)
ax1 = plt.subplot(211)
plt.pcolormesh(np.log(sxx_l),cmap='jet')
plt.xticks([])
plt.ylabel('Frequency (Hz)')
plt.title('Spectrogram - Rectified EMG')

ax2 = plt.subplot(212)
plt.plot(np.arange(0,len(interim_l))/sr_interim_l,interim_l,lw=.1)
plt.ylabel('Voltage (uncalibrated)')
plt.xlabel('Time (s)')
plt.xlim(t_l[0],t_l[-1])

# adding an independent axis for the colorbar:
fig.subplots_adjust(right=0.8)
cbar_ax = fig.add_axes([.81, .5, 0.025, 0.4])
plt.colorbar(label='log($Voltage^2$)',cax=cbar_ax,)
```

```
plt.draw()
```



From the spectrogram we can see that the main frequency isn't as important as the distribution of the spectrogram. In pulses of greater force, the spectrogram of the signal appears to be wider (more high frequency components). From these observations we see that the signal could be described by the mean root squared of the values in the corresponding segment.

0.10.3 Average frequency in spectrogram of each segment

```
[129]: def rms_freq(i,side="l"):  
    if side=="l":  
        Pa=interm_l[find_in(Time_a,segments_l[0][0][i]):  
↪find_in(Time_a,segments_l[1][0][i])]  
    else:  
        Pa=interm_r[find_in(Time_b,segments_r[0][0][i]):  
↪find_in(Time_b,segments_r[1][0][i])]  
  
    #The fft is calculated  
    X = fft(Pa)  
    N = len(X)  
    n = np.arange(N)  
    freq = n/(Time_a[-1]-Time_a[0])  
  
    # Get the one-sided spectrum  
    n_oneside = N//2  
    # get the one side frequency
```

```

f_oneside = freq[:n_oneside]

# normalize the amplitude
X_oneside = X[:n_oneside]/n_oneside

#First we compute the area under the curve of the spectrogram in log scale
area=0.
for i in range(0,n_oneside):
    area+=np.log(abs(X_oneside[i]))

#Now we must find the value i at which the area under the curve is the half
↳ of the total area
area2=0.
for i in range(0,n_oneside):
    if area2>(area/2):
        area2+=np.log(abs(X_oneside[i]))
    else:
        return freq[i]

```

```


[130]: freq_rms_l=[]
for i in range(0,37):
    freq_rms_l.append(rms_freq(i))

```

```


[131]: plt.figure(figsize=(18,6))
plt.scatter(np.linspace(0,60,num=37)[:17],freq_rms_l[:17],label="S1")
plt.scatter(np.linspace(0,60,num=37)[17:27],freq_rms_l[17:27],label="S2")
plt.scatter(np.linspace(0,60,num=37)[27:],freq_rms_l[27:],label="S3")
plt.legend()
plt.title('Analysis: Left')
plt.ylabel('Average Frequency (Hz)')
plt.xlabel('Time (s)')
plt.show;

```



```
[133]: freq_rms_r=[]
for i in range(0,33):
    freq_rms_r.append(rms_freq(i,side="r"))
```

```
[134]: plt.figure(figsize=(18,6))
plt.scatter(np.linspace(0,60,num=33)[:16],freq_rms_r[:16],label="S1")
plt.scatter(np.linspace(0,60,num=33)[16:25],freq_rms_r[16:25],label="S2")
plt.scatter(np.linspace(0,60,num=33)[25:],freq_rms_r[25:],label="S3")
plt.legend()
plt.title('Analysis: right')
plt.ylabel('Average Frequency (Hz)')
plt.xlabel('Time (s)')
plt.show;
```



0.11 Average frequency vs force produced

```
[135]: # For every segment of the force array, we append the maximum value to the
        ↪array f_interm_l_max
f_interm_l_max=[]
for i in range(0,len(segments_l[0][0])):
    f_interm_l_max.append(max(f_interm_l[segments_l[0][2][i]:
        ↪segments_l[1][2][i]]))
```


```
[136]: len(f_interm_l_max)
```

```
[136]: 37
```


```
[137]: # For every segment of the force array, we append the maximum value to the
        ↪array f_interm_r_max
f_interm_r_max=[]
for i in range(0,len(segments_r[0][0])):
```

```
f_interm_r_max.append(max(f_interm_r[segments_r[0][2][i]:
↪segments_r[1][2][i]]))
```

```
[138]: plt.figure(figsize=(18,6))
plt.scatter(f_interm_l_max[:17],freq_rms_l[:17],label="S1")
plt.scatter(f_interm_l_max[17:27],freq_rms_l[17:27],label="S2")
plt.scatter(f_interm_l_max[27:],freq_rms_l[27:],label="S3")
plt.legend()
plt.title('Analysis: Left')
plt.ylabel('Average Frequency (Hz)')
plt.xlabel("Force max (N)")
plt.show;
```



```
[140]: plt.figure(figsize=(18,6))
plt.scatter(f_interm_r_max[:16],freq_rms_r[:16],label="S1")
plt.scatter(f_interm_r_max[16:25],freq_rms_r[16:25],label="S2")
plt.scatter(f_interm_r_max[25:],freq_rms_r[25:],label="S3")
plt.legend()
plt.title('Analysis: Right')
plt.ylabel('Average Frequency (Hz)')
plt.xlabel("Force max (N)")
plt.show;
```



0.12 Rectification and envelope

0.12.1 Envelope method 1: Low-pass filter

```
[141]: interm_r_abs=abs(interm_r)
       interm_l_abs=abs(interm_l)
```


```
[142]: def envelope(x,sr,lf=15):
       X=fft(x)

       # calculate the frequency
       N = len(X)
       T = N/sr


       # Filter out the 60 Hz noise
       for i in range(int(lf*T),len(X)-int(lf*T)):
           X[i]=0
       X2=ifft(X).real
       return X2
```

```
[143]: interm_l_env=envelope(interm_l_abs,sr_interm_l)
       interm_r_env=envelope(interm_r_abs,sr_interm_r)
```

```
[144]: plt.figure(figsize=(18,6))
       plt.plot(Time_a,interm_l_abs,label="Rectified signal")
       plt.plot(Time_a,interm_l_env,label="Envelope")
       plt.legend()
       plt.title("Envelope: Low-pass filter (Left)")
       plt.xlabel("Time (s)")
       plt.ylabel('Voltage (uncalibrated)')
       plt.show()
```



```
[145]: plt.figure(figsize=(18,6))
plt.plot(Time_b,interm_r_abs,label="Rectified signal")
plt.plot(Time_b,interm_r_env,label="Envelope")
plt.legend()
plt.title("Envelope: Low-pass filter (right)")
plt.xlabel("Time (s)")
plt.ylabel('Voltage (uncalibrated)')
plt.show()
```



0.12.2 Envelope method 2: Local max in a time window

```
[148]: def envelope_2(x,y,s=6000):
    # x: Time array
    # y: Voltage array
    # s: Time window (# of values in a single time window)
    x2=[]
    y2=[]
```



```

for i in range(0,-1+len(x)//s):
    x2.append(max(x[s*i:s*(i+1)]))
    y2.append(y[s*i])
return(x2,y2)

```

```


[149]: #The envelope is calculated for each hand
interm_l_env2,time_l_env=envelope_2(inter_m_l_abs,Time_a)
interm_r_env2,time_r_env=envelope_2(inter_m_r_abs,Time_b)

```

```

[150]: #Plot left hand envelope and EMG
plt.figure(figsize=(18,6))
plt.plot(time_l_env,interm_l_env2,label="Envelope")
plt.plot(Time_a,interm_l,label="EMG")
plt.legend()
plt.xlim(0,10)
plt.title("Envelope: Local maxima (left)")
plt.xlabel("Time (s)")
plt.ylabel('Voltage (uncalibrated)')
plt.show()


```



```

[151]: #Plot right hand envelope and EMG
plt.figure(figsize=(18,6))
plt.plot(time_r_env,interm_r_env2,label="Envelope")
plt.plot(Time_b,interm_r,label="EMG")
plt.legend()
plt.title("Envelope: Local maxima (right)")
plt.xlabel("Time (s)")
plt.ylabel('Voltage (uncalibrated)')
plt.show()

```




0.12.3 Envelope method 3: Root mean squared in a time window

```
[152]: def envelope_rms(x,s=3000):
        x2 = np.power(x,2)
        window = np.ones(s)/float(s)
        return np.sqrt(np.convolve(x2, window, 'same'))
```


Breaking it down, the `np.power(a, 2)` part makes a new array with the same dimension as `a`, but where each value is squared. `np.ones(window_size)/float(window_size)` produces an array of length `window_size` where each element is `1/window_size`.

```
[153]: interm_l_rms=envelope_rms(interm_l_abs)
        interm_r_rms=envelope_rms(interm_r_abs)
```

```
[154]: #Plot left hand envelope and EMG
plt.figure(figsize=(18,6))
plt.plot(Time_a,interm_l_abs,label="Rectified signal")
plt.plot(Time_a,3*interm_l_rms,label="Envelope")
plt.legend()
#plt.xlim(0,10)
plt.title("Envelope: Local maxima (left)")
plt.xlabel("Time (s)")
plt.ylabel('Voltage (uncalibrated)')
plt.show()
```



```
[155]: #Plot left hand envelope and EMG
plt.figure(figsize=(18,6))
plt.plot(Time_b,interm_r_abs,label="Rectified signal")
plt.plot(Time_b,3*interm_r_rms,label="Envelope")
plt.legend()
#plt.xlim(0,10)
plt.title("Envelope: Local maxima (left)")
plt.xlabel("Time (s)")
plt.ylabel('Voltage (uncalibrated)')
plt.show()
```




0.13 Enveloped EMG signal vs Force signal

```
[156]: # Plot enveloped EMG and the Force signal
plt.figure(figsize=(18,6))
plt.plot(Time_a,5*interm_l_rms,label="Envelope")
```

```

plt.plot(f_time[:len(f_interm_l)],max(inter_m_l)*f_interm_l/
↪max(f_interm_l),label="Force(scaled)")
plt.legend()
plt.title("Envelope vs Force (left)")
plt.xlabel("Time (s)")
plt.ylabel('Voltage (uncalibrated)')
#plt.xlim(0,10)
plt.show()


```



```

[157]: plt.figure(figsize=(18,6))
plt.plot(Time_b,5*inter_r_rms,label="Envelope")
plt.plot(f_time[:len(f_interm_r)],max(inter_r_env2)*f_interm_r/
↪max(f_interm_r),label="Force")
plt.legend()
#plt.xlim(50,60)
plt.title("Envelope vs Force (right)")
plt.xlabel("Time (s)")
plt.ylabel('Voltage (uncalibrated)')
plt.show()


```



Base line compensation


```
[158]: baseLine_l=min(interml_rms[6000:len(interml_rms)-6000])
```

```
[159]: plt.figure(figsize=(18,6))
plt.plot(Time_a,5*(interml_rms-baseLine_l),label="Envelope")
plt.plot(f_time[:len(f_interml)],max(interml_env2-baseLine_l)*f_interml/
↪max(f_interml),label="Force")
plt.legend()
#plt.xlim(20,30)
plt.title("Envelope vs Force with baseline compensation (left)")
plt.xlabel("Time (s)")
plt.ylabel('Voltage (uncalibrated)')
plt.show()
```



```
[160]: baseLine_r=min(intermr_rms[6000:len(intermr_rms)-6000])
```

```
[161]: plt.figure(figsize=(18,6))
plt.plot(Time_b,5*(intermr_rms-baseLine_r),label="Envelope")
plt.plot(f_time[:len(f_intermr)],max(intermr_env2-baseLine_r)*f_intermr/
↪max(f_intermr),label="Force")
plt.legend()
#plt.xlim(20,30)
plt.title("Envelope vs Force with baseline compensation (right)")
plt.xlabel("Time (s)")
plt.ylabel('Voltage (uncalibrated)')
plt.show()
```



Notice that with the MSR method we have borderline effects in the left hand, as well as deformations in the resting periods, which amplifies noise. So, we will use the envelope obtained with method 2: local maxima. Method 2 does not affect the borders of each impulse and helps to keep the amplitude of the signal constant. Despite the fact that the MSR method proved to be less useful in this case, it is very useful when enveloping EEG signals or fatigue EMG signals. It is important to know the limitations of each technique we use, as well as their pros and cons.

0.14 Impulse amplitude: EMG vs Force

```
[163]: # Define a new array of corrected envelopes
interm_l_c=interm_l_env2-baseLine_l
f_time_l=f_time[:len(f_interm_l)]
interm_r_c=interm_r_env2-baseLine_r
f_time_r=f_time[:len(f_interm_r)]

[164]: # Segmentation of the EMG envelope by thresholds
segments_l_c=segments_th(time_l_env,interm_l_c,threshold=500)
segments_r_c=segments_th(time_r_env,interm_r_c,threshold=500)

[166]: # For every segment of the EMG envelope, we append the maximum value to the
↳array interm_l_max
j=0
start=False
interm_l_max=[]
for i in range(0,len(time_l_env)):
    if j==len(segments_l[1][0]):
        break
    if start==True:
        if time_l_env[i]>segments_l[1][0][j]:
            #print(index,i)
            interm_l_max.append(max(intermediate_l_c[index:i]))
            start=False
        j+=1
```

```

if start==False:
    if j!=37:
        if time_l_env[i]>segments_l[0][0][j]:
            start=True
            index=i

```

```


[170]: # For every segment of the EMG envelope, we append the maximum value to the
        ↪ array intermitent_r_max
j=0
start=False
interm_r_max=[]
for i in range(0,len(time_r_env)):
    if j==len(segments_l[1][0]):
        break
    if start==True:
        if time_r_env[i]>segments_r[1][0][j]:
            #print(index,i)
            interm_r_max.append(max(interm_r_c[index:i]))
            start=False
            j+=1
    if start==False:
        if j!=33:
            if time_r_env[i]>segments_r[0][0][j]:
                start=True
                index=i

```


```

[171]: plt.figure(figsize=(18,6))
plt.scatter(interm_l_max[:17],f_interm_l_max[:17],label="S1")
plt.scatter(interm_l_max[17:27],f_interm_l_max[17:27],label="S2")
plt.scatter(interm_l_max[27:],f_interm_l_max[27:],label="S3")
plt.legend()
plt.title("Impulse amplitude: EMG vs Force (left)")
plt.xlabel("EMG envelope max")
plt.ylabel("Force max (N)")
plt.show;

```



```
[172]: plt.figure(figsize=(18,6))
plt.scatter(inter_r_max[:16],f_inter_r_max[:16],label="S1")
plt.scatter(inter_r_max[16:25],f_inter_r_max[16:25],label="S2")
plt.scatter(inter_r_max[25:],f_inter_r_max[25:],label="S3")
plt.legend()
plt.title("Impulse amplitude: EMG vs Force (right)")
plt.xlabel("EMG envelope max")
plt.ylabel("Force max (N)")
plt.show;
plt.show;
```



0.15 Curve fitting

As can be seen in the previous graphs, the force produced has a logarithmic(ish) response to the amplitude of the signals in the muscles that produced it. So, now we will try to fit a logarithmic function to the curve.

```
[182]: #First we define the log function.
def logarithmic(x,a,b,c):
    return a*np.log(x + b)+c
```

In the previous function we have 3 trainable parameters: a, b and c

```
[183]: # these are the same as the scipy defaults
initialParameters = np.array([1.0, -500.0, -300.0])
```

```
[184]: # curve fit the test data
fittedParameters_l, pcov_l = curve_fit(logarithmic, interm_l_max,
    ↪ f_interm_l_max, initialParameters)
```



```
/var/folders/n6/xcj3j4lx6lb8r4wj_86v5cnr0000gn/T/ipykernel_56516/1045232656.py:3
: RuntimeWarning: invalid value encountered in log
    return a*np.log(x + b)+c
```

```
[185]: modelPredictions_l = logarithmic(interterm_l_max, *fittedParameters_l)

absError_l = modelPredictions_l - f_interterm_l_max

SE_l = np.square(absError_l) # squared errors
MSE_l = np.mean(SE_l) # mean squared errors
RMSE_l = np.sqrt(MSE_l) # Root Mean Squared Error, RMSE
Rsquared_l = 1.0 - (np.var(absError_l) / np.var(f_interterm_l_max))

print('Parameters:', fittedParameters_l)
print('RMSE:', RMSE_l)
print('R-squared:', Rsquared_l)
```

```
Parameters: [ 54.31161914 -519.81028461 -350.89252246]
RMSE: 9.372192092606587
R-squared: 0.9465566888298268
```


```
[186]: def bubblesort(elements):
    elements2=np.zeros([2,len(elements[0])])
    # Looping from size of array from last index[-1] to index [0]
    cont=0
    for i in range(0,len(elements[0])):
        for j in range(0,len(elements[0])):
            if elements[0,j]==min(elements[0]):
                elements2[:,cont]=elements[:,j]
                elements[0,j]=max(elements[0])+1
                elements[1,j]=0
                cont+=1
                break
    return elements2
```

```
[187]: PA_fit_l=np.array([interterm_l_max,modelPredictions_l])
```

```
[188]: PA_fit_l=bubblesort(PA_fit_l)
```

```
[189]: plt.figure(figsize=(18,6))
plt.scatter(interterm_l_max[:17],f_interterm_l_max[:17],label="S1")
plt.scatter(interterm_l_max[17:27],f_interterm_l_max[17:27],label="S2")
plt.scatter(interterm_l_max[27:],f_interterm_l_max[27:],label="S3")
plt.plot(PA_fit_l[0],PA_fit_l[1],label="Log fit")
plt.legend()
plt.title("EMG vs Force (left)")
plt.xlabel("EMG envelope max")
```

```
plt.ylabel("Force max (N)")
plt.show;
```



```
[192]: # curve fit the test data
fittedParameters_r, pcov_r = curve_fit(logarithmic, interm_r_max,
    ↪ f_interm_r_max, initialParameters)

modelPredictions_r = logarithmic(interm_r_max, *fittedParameters_r)

absError_r = modelPredictions_r - f_interm_r_max

SE_r = np.square(absError_r) # squared errors
MSE_r = np.mean(SE_r) # mean squared errors
RMSE_r = np.sqrt(MSE_r) # Root Mean Squared Error, RMSE
Rsquared_r = 1.0 - (np.var(absError_r) / np.var(f_interm_r_max))

print('Parameters:', fittedParameters_r)
print('RMSE:', RMSE_r)
print('R-squared:', Rsquared_r)
```

```
Parameters: [ 47.92615244  21.07684969 -332.47485898]
RMSE: 10.640590096617057
R-squared: 0.8976560657623052
```

```
[194]: PA_fit_r=np.array([interm_r_max,modelPredictions_r])
```

```
[195]: PA_fit_r=bubblesort(PA_fit_r)
```

```
[196]: plt.figure(figsize=(18,6))
plt.scatter(interm_r_max[:17],f_interm_r_max[:17],label="S1")
plt.scatter(interm_r_max[17:27],f_interm_r_max[17:27],label="S2")
plt.scatter(interm_r_max[27:],f_interm_r_max[27:],label="S3")
plt.plot(PA_fit_r[0],PA_fit_r[1],label="Log fit")
```

```
plt.legend()
plt.title("EMG vs Force (right)")
plt.xlabel("EMG envelope max")
plt.ylabel("Force max (N)")
plt.show;
```

