Daybook — Android Kiosk Checklist

Aim: a tablet that boots into Daybook, cannot leave the page, stays awake, reconnects automatically, and shows the 5 PM reminder banner. See ANDROID-KIOSK-GUIDE.md for details.

1. Network

- [ ] Tablet on Wi-Fi
- [ ] WireGuard (or Tailscale) installed
- [ ] Tunnel imported / signed in
- [ ] Android → VPN → WireGuard → **Always-on VPN** + **Block connections without VPN**
- [ ] Test URL loads: `http://<NAS_WG_IP>:8484/login`

2. Fully Kiosk Browser

- [ ] Fully Kiosk Browser installed and opened once
- [ ] Start URL: `http://<NAS_WG_IP>:8484/kiosk?eink=1` (e-ink) or `/kiosk` (LCD)
- [ ] JavaScript and cookies enabled
- [ ] Landscape orientation
- [ ] Logged in once with the username and password
- [ ] Kiosk Mode / Lock enabled, settings PIN set
- [ ] Start on Boot / Autostart enabled
- [ ] Keep Screen On enabled
- [ ] Restart App on Crash enabled
- [ ] Reload on Reconnect / network error enabled
- [ ] Status bar / navigation bar hidden if available
- [ ] Website whitelist (PRO): only `http://<NAS_WG_IP>:8484/*`

3. Android settings

- [ ] Fully set as **Home app**
- [ ] Battery → **Unrestricted** for Fully
- [ ] Screen lock → None (Fully has its own PIN)
- [ ] Stay awake while charging
- [ ] Screen timeout long / Never
- [ ] Play Store auto-update off for Fully
- [ ] Date & time automatic
- [ ] Charger connected

4. Test before handing it over

- [ ] Reboot → returns to Daybook by itself
- [ ] Wi-Fi drop → reconnects and reloads
- [ ] Home button → Daybook only
- [ ] No way to reach Settings/other apps without PIN
- [ ] Toggle No-show → Done + notes → undo
- [ ] Overnight → still on the kiosk
- [ ] After 5 PM with an outstanding session → banner appears
- [ ] Clear the session → banner disappears

> **No email is involved.** The tablet is the reminder surface. After the configured time (default 5 PM) a banner appears while sessions are unconfirmed. Adjust the 3-day threshold and time in Daybook → Settings.

If something breaks

Browser error: VPN down → reconnect WireGuard; Fully reloads.

Login screen: log in again; cookie lasts 90 days. Don't clear cookies on exit.

Stale day: tap Refresh in e-ink mode / wait 5 minutes; check tablet clock.

App closes: battery optimisation still on; set Unrestricted.

Lost settings PIN: clear Fully's app data and reconfigure.