Acme Retail Group

Transportation EDI Implementation Guide
Version 4.0 - Motor Carrier Partners
Issued October 6, 2026

Revision history

Version	Date	Changes
4.0	2026-10-06	New EDI Coordinator; ISA13 now starts at 5000; MS1 optional.
3.2	2026-09-01	Test AS2 URL added; ISA13 starting number set.

1. Introduction

This guide describes how carriers exchange X12 transportation documents with Acme Retail Group.

Trading Partner Code: ACMERETAIL
Trading Partner Name: Acme Retail Group

EDI Coordinator: Priya Raman
Email: edi-ops@acmeretail.example
Phone: +1 312 555 0177

All times in this guide are Central Time (America/Chicago).

2. Communications

2.1 Connection method

Acme exchanges all documents over AS2 (Applicability Statement 2). FTP and VAN connections are not offered.

Acme AS2 Identifier: ACMERETAILAS2
Carrier AS2 Identifier: TRENOVA-AS2

Production AS2 URL: https://as2.acmeretail.example/as2/receive
Test AS2 URL: https://as2-test.acmeretail.example/as2/receive

MDN: synchronous, signed.
Signing algorithm: SHA-256. Encryption algorithm: AES-256 (CBC).

2.2 Certificates

Certificates are exchanged by email with the EDI Coordinator before testing starts.

For the test environment, the keystore password: Acme#Test2026 is sent separately.

Begin in the test environment; Acme moves the connection to production after certification.

3. Envelopes

3.1 Interchange (ISA)

ISA05/ISA06 Acme interchange sender: qualifier 01 (DUNS), ID 007912345

ISA07/ISA08 Carrier interchange receiver: qualifier 02 (SCAC), ID TRNV

ISA12 Interchange version 00401. ISA15 usage indicator: T during testing, P in production.

3.2 Functional group (GS)

GS02 Application Sender Code: ACMERETAIL
GS03 Application Receiver Code: TRNV
GS08 Version: 004010

3.3 Delimiters

Element separator: * (asterisk). Segment terminator: ~ (tilde). Sub-element separator: > (greater than).

3.4 Control numbers

Carrier interchange control numbers (ISA13) must start at 5000 and increase by one.

4. Transaction sets

4.1 Documents exchanged

Acme sends the 204 Motor Carrier Load Tender to the carrier.

The carrier answers each tender with a 990 Response to a Load Tender within 2 hours.

The carrier sends the 214 Transportation Carrier Shipment Status Message for every pickup and delivery.

The carrier invoices with the 210 Motor Carrier Freight Details and Invoice.

4.2 Acknowledgments

Acme expects a 997 Functional Acknowledgment for every 990, 214 and 210 within 4 hours.

Acme returns a 997 for each document it receives. Acme does not support the 999 Implementation Acknowledgment.

5. 204 Load Tender requirements

B2 Beginning Segment is mandatory. B2-02 Standard Carrier Alpha Code is mandatory. B2-04 Shipment Identification Number is mandatory.

B2A Set Purpose is mandatory. B2A-01 codes: 00 Original, 01 Cancellation, 04 Change.

L11 with qualifier BM (Bill of Lading) is mandatory.

S5 Stop Off Details is mandatory for every stop.

6. 214 Shipment Status requirements

AT7 Shipment Status Details is mandatory. AT7-01 codes: X3 Arrived at Pickup, AF Departed Pickup, X1 Arrived at Delivery, D1 Delivered.

MS1 Equipment Location is optional; send it when the equipment location is known.

K1 Remarks is not used.

7. Code lists

7.1 Stop reason codes (S5-02): CL Complete Load, CU Complete Unload.

7.2 Service levels (L5): STD Standard, EXP Expedited.

8. Invoicing notes

Detention and other accessorial charges are billed on the 210 with the Acme charge codes listed in Appendix B.

Appendix B is distributed separately to certified carriers.

9. Sample 204

```
ISA*00*          *00*          *01*007912345      *02*TRNV           *261014*0930*U*00401*000000
123*0*T*>~
GS*SM*ACMERETAIL*TRNV*20261014*0930*123*X*004010~
ST*204*0001~
B2**TRNV**ACM-55821**PP~
B2A*00~
L11*BOL-77812*BM~
S5*1*CL~
N1*SH*ACME DC 14~
S5*2*CU~
N1*CN*ACME STORE 220~
SE*9*0001~
GE*1*123~
IEA*1*000000123~
```