connice

Bluetooth headset FCC ID:2AAIH-MS02

muses 2 INSTRUCTION

Call -

Answer a call

Press the Multifunction button once.

End a call

Press the Multifunction button once.

Reject a call

Press and hold the Multifunction button for about 2

Redial the last call


Double-press the Multifunction button in standby mode. The mobile phone will redial the last call number.

MIC mute on/off

Press the Volume button "-" for about 2 seconds to mute on/off.

Start here

Following items are included



Switch between the Headset and phone

Press the Volume button "+" for about 2 seconds during a call, the call will be switched to the mobile phone, redo this operation again, the call will be switched back to the Headset.

Voice dial (Need phone support)

Press the Volume button "+" and "-" in standby mode, wait for phone prompt and then tell the phone to dial the name of a stored contact.

End current call and answer new call


When a new call rings during a call, press the Multifunction button to answer new call and end current call simultaneously.

On hold current call and answer new call

When a new call rings during a call, hold the Multifunction button for 2 seconds to hold current call and answer new call. To switch between held call and active call, Hold the multifunction button for 2 seconds.

Product overview





Music -

(Need media player support)

Music play / pause

Press Multifunction button to play / pause music.

Trackbac

Press the Volume button "+" for 2 seconds to skip track back.

Trackforward

Press the Volume button "-" for 2 seconds to skip track forward.

Switch Music and Call

When a call rings during a music playing, the music automatically pauses to allow you to answer or ignore the call. Once the call is ignored or ends, the music is resumed.

Basic operation

Volume adjust

Press the Volume button "+" or "-" to turn volume up or down, you hear "beep" voice prompts once reach the maximum or minimum.

LED indicator and voice prompts


Instruction	LED STOTUS	voice prompts & Alerts
Power on	Stays blue for 2 seconds	Power on
Power off	Stays red for 2 seconds	Power off
Pairing	Flashes red and blue alternately	Pairing

Instruction LED status Voice prompts & Alerts Standby Flashes blue twice every 5 seconds Connection successful Incoming call Flashes blue continuously Vibration alerts Battery low Flashes red twice every 5 seconds Battery low

More features

Battery Indicator

When the Headset is connected to a device with iOS system, a battery indicator will appear at the upper right of the system, indicating battery status of the



Pairing

Pair one phone


- Turn on Bluetooth headset, press and hold the Multifunction button for about 5 seconds, the LED indicator flashes red and blue alternately. Voice prompts "Pairing".
- Activate Bluetooth on your phone and set it to search for new devices.

 Select "Muses2". If you phone asks, enter 0000 (four zeros) for the passcode or accept the connection. The LED indicator stops flashing red and blue once successfully paired. Voice prompts "Connection successful".

Charging

Your new Headset has enough power to pair and make a few calls.

When battery is low, you will hear the voice prompt "Battery low". It takes 2.5 hours to fully charge the Headset. While charging, the battery indicator light is red, the indicator light stays blue once charging is complete.



Pair another phone

Multipoint technology enables you to pair another phone and take a call from either.

To pair with another mobile phone, follow the steps for "Pair One Phone" . After pairing successfully, restart the Headset to connect to 2 paired mobile phone automatically.



Power off


Switch the power button to Off position to turn off the Headset. (Note: Power off the Headset to save power when not in use.)

Clear paired list

Turn on the Headset, connect it to a USB charger of USB, press and hold the Volume button "+" and "-" simultaneously for about 5 seconds, LED flashes 5 times, paired list is cleared. (Note: The Headset automatically enter pairing mode when power on the first time after clear paired list)

NFC Pairing


Turn on Bluetooth headset, after 5 seconds, hold an NFC device against the NFC zone of the Headset. The LED indicator flashes red and blue, you hear voice prompts "Pairing", the LED indicator stops flashing red and blue once successfully paired, you hear voice prompts "Connection successful".



NFC detection area

Hardware reset

Turn on Bluetooth headset, press and hold the Multifunction button, connect the Headset to a USB charger, hardware reset is done. (Note: The Headset automatically power off, please switch the power button to off then on to power on the Headset)



This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.