

CINCH Systems

RF-FOB-PANIC-319

FCC 15.231:2018 Low Power Radio

Report # CINC0029







NVLAP LAB CODE: 200881-0

CERTIFICATE OF TEST



Last Date of Test: October 11, 2018 CINCH Systems Model: RF-FOB-PANIC-319

Radio Equipment Testing

Standards

Specification	Method
FCC 15.231:2018	ANSI C63.10:2013

Results

Method Clause Test Description		Applied	Results	Comments
6.2	Powerline Conducted Emissions	No	N/A	Not required for a battery powered EUT.
6.5, 6.6	Field Strength of Fundamental	Yes	Pass	
6.5, 6.6	Spurious Radiated Emissions	Yes	Pass	
6.9.2	Occupied Bandwidth	Yes	Pass	
7.5	Duty Cycle	Yes	Pass	

Deviations From Test Standards

None

Approved By:

Matt Nuernberg, Operations Manager

Product compliance is the responsibility of the client; therefore, the tests and equipment modes of operation represented in this report were agreed upon by the client, prior to testing. The results of this test pertain only to the sample(s) tested. The specific description is noted in each of the individual sections of the test report supporting this certificate of test. This report reflects only those tests from the referenced standards shown in the certificate of test. It does not include inspection or verification of labels, identification, marking or user information. As indicated in the Statement of Work sent with the quotation, Element's standard process is to always use the latest published version of the test methods even when earlier versions are cited in the test specification. Issuance of a purchase order was de facto acceptance of this approach. Otherwise, the client would have advised Element in writing of the specific version of the test methods they wanted applied to the subject testing.

Report No. CINC0029 2/22

REVISION HISTORY



Revision Number	Description	Date (yyyy-mm-dd)	Page Number
00	None		

Report No. CINC0029 3/22

ACCREDITATIONS AND AUTHORIZATIONS



United States

FCC - Designated by the FCC as a Telecommunications Certification Body (TCB). Certification chambers, Open Area Test Sites, and conducted measurement facilities are listed with the FCC.

A2LA - Accredited by A2LA to ISO / IEC 17065 as a product certifier. This allows Element to certify transmitters to FCC and IC specifications.

NVLAP - Each laboratory is accredited by NVLAP to ISO 17025

Canada

ISED - Recognized by Innovation, Science and Economic Development Canada as a Certification Body (CB). Certification chambers and Open Area Test Sites are filed with ISED.

European Union

European Commission - Within Element, we have a EU Notified Body validated for the EMCD and RED Directives.

Australia/New Zealand

ACMA - Recognized by ACMA as a CAB for the acceptance of test data.

Korea

MSIT / RRA - Recognized by KCC's RRA as a CAB for the acceptance of test data.

Japan

VCCI - Associate Member of the VCCI. Conducted and radiated measurement facilities are registered.

Taiwan

BSMI - Recognized by BSMI as a CAB for the acceptance of test data.

NCC - Recognized by NCC as a CAB for the acceptance of test data.

Singapore

IDA – Recognized by IDA as a CAB for the acceptance of test data.

Israel

MOC - Recognized by MOC as a CAB for the acceptance of test data.

Hong Kong

OFCA – Recognized by OFCA as a CAB for the acceptance of test data.

Vietnam

MIC – Recognized by MIC as a CAB for the acceptance of test data.

SCOPE

For details on the Scopes of our Accreditations, please visit: https://www.nwemc.com/emc-testing-accreditations

Report No. CINC0029 4/22


FACILITIES







California Labs OC01-17 41 Tesla Irvine, CA 92618 (949) 861-8918	Minnesota Labs MN01-10 9349 W Broadway Ave. Brooklyn Park, MN 55445 (612)-638-5136	New York Labs NY01-04 4939 Jordan Rd. Elbridge, NY 13060 (315) 554-8214	Oregon Labs EV01-12 6775 NE Evergreen Pkwy #400 Hillsboro, OR 97124 (503) 844-4066	Texas Labs TX01-09 3801 E Plano Pkwy Plano, TX 75074 (469) 304-5255	Washington Labs NC01-05 19201 120 th Ave NE Bothell, WA 98011 (425)984-6600		
(0.10) 00.1 00.10	(0.12) 000 0.00		LAP	(100) 001 0000	(.==)== : ====		
			 I				
NVLAP Lab Code: 200676-0	NVLAP Lab Code: 200881-0	NVLAP Lab Code: 200761-0	NVLAP Lab Code: 200630-0	NVLAP Lab Code:201049-0	NVLAP Lab Code: 200629-0		
	Innovation, Science and Economic Development Canada						
2834B-1, 2834B-3	2834E-1, 2834E-3	N/A	2834D-1, 2834D-2	2834G-1	2834F-1		
	BSMI						
SL2-IN-E-1154R	SL2-IN-E-1152R	N/A	SL2-IN-E-1017	SL2-IN-E-1158R	SL2-IN-E-1153R		
VCCI							
A-0029	A-0109	N/A	A-0108	A-0201	A-0110		
	Recognized Phase I CAB for ACMA, BSMI, IDA, KCC/RRA, MIC, MOC, NCC, OFCA						
US0158	US0175	N/A	US0017	US0191	US0157		



Report No. CINC0029 5/22

MEASUREMENT UNCERTAINTY



Measurement Uncertainty

When a measurement is made, the result will be different from the true or theoretically correct value. The difference is the result of tolerances in the measurement system that cannot be completely eliminated. To the extent that technology allows us, it has been our aim to minimize this error. Measurement uncertainty is a statistical expression of measurement error qualified by a probability distribution.

A measurement uncertainty estimation has been performed for each test per our internal quality document WP 342. The estimation is used to compare the measured result with its "true" or theoretically correct value. The expanded measurement uncertainty (K=2) for each test is on each data sheet. Our measurement data meets or exceeds the measurement uncertainty requirements of the applicable specification; therefore, the test data can be compared directly to the specification limit to determine compliance. The calculations for estimating measurement uncertainty are based upon ETSI TR 100 028 (or CISPR 16-4-2 as applicable), and are available upon request.

The following table represents the Measurement Uncertainty (MU) budgets for each of the tests that may be contained in this report.


Test	+ MU	<u>- MU</u>
Frequency Accuracy (Hz)	0.0007%	-0.0007%
Amplitude Accuracy (dB)	1.2 dB	-1.2 dB
Conducted Power (dB)	0.3 dB	-0.3 dB
Radiated Power via Substitution (dB)	0.7 dB	-0.7 dB
Temperature (degrees C)	0.7°C	-0.7°C
Humidity (% RH)	2.5% RH	-2.5% RH
Voltage (AC)	1.0%	-1.0%
Voltage (DC)	0.7%	-0.7%
Field Strength (dB)	5.2 dB	-5.2 dB
AC Powerline Conducted Emissions (dB)	2.4 dB	-2.4 dB

Report No. CINC0029 6/22


Test Setup Block Diagrams




Antenna Port Conducted Measurements



Near Field Test Fixture Measurements



Spurious Radiated Emissions



Report No. CINC0029 7/22

PRODUCT DESCRIPTION



Client and Equipment Under Test (EUT) Information

Company Name:	CINCH Systems		
Address:	Suite 300 12075 43rd Street NE		
City, State, Zip:	St. Michael, MN 55376		
Test Requested By:	Jibril Aga		
Model:	RF-FOB-PANIC-319		
First Date of Test:	October 11, 2018		
Last Date of Test:	October 11, 2018		
Receipt Date of Samples:	October 11, 2018		
Equipment Design Stage:	Production		
Equipment Condition:	No Damage		
Purchase Authorization:	Verified		

Information Provided by the Party Requesting the Test

Functional Description of the EUT:	
Low power radio with one antenna type operating at 319.5 MHz	

Testing Objective:

To demonstrate compliance to FCC 15.231 specifications.

Report No. CINC0029 8/22

CONFIGURATIONS



Configuration CINC0029-1

EUT			
Description	Manufacturer	Model/Part Number	Serial Number
Keyfob	CINCH Systems	RF-FOB-PANIC-319	0348139

Configuration CINC0029-2

EUT			
Description	Manufacturer	Model/Part Number	Serial Number
Keyfob	CINCH Systems	RF-FOB-PANIC-319	03C46DE

Configuration CINC0029-3

EUT			
Description	Manufacturer	Model/Part Number	Serial Number
Keyfob	CINCH Systems	RF-FOB-PANIC-319	0348139

Report No. CINC0029 9/22

MODIFICATIONS



Equipment Modifications

Item	Date	Test	Modification	Note	Disposition of EUT
		Field Strength of	Tested as	No EMI suppression	EUT remained at
1	2018-10-11	Fundamental	delivered to	devices were added or	Element following
		i unuamentai	Test Station.	modified during this test.	the test.
			Tested as	No EMI suppression	EUT remained at
2	2018-10-11	Duty Cycle	delivered to	devices were added or	Element following
			Test Station.	modified during this test.	the test.
		Occupied	Tested as	No EMI suppression	EUT remained at
3	2018-10-11	Bandwidth	delivered to	devices were added or	Element following
		Danuwiuin	Test Station.	modified during this test.	the test.
		Spurious	Tested as	No EMI suppression	Scheduled testing
4	2018-10-11	Radiated	delivered to	devices were added or	was completed.
		Emissions	Test Station.	modified during this test.	was completed.

Report No. CINC0029 10/22

FIELD STRENGTH OF FUNDAMENTAL



PSA-ESCI 2018.07.27

Testing was performed using the mode(s) of operation and configuration(s) noted within the report. The individuals and/or the organization requesting the test provided the modes, configurations and settings used to complete the evaluation. The actual test parameters are specified in the test data, this includes items such as investigated frequency range (scanned) and test levels. The testing methods and performance specifications, as well as the test site used for the evaluation are indicated in the test data. The test data represents the configuration / operating mode/ model that produced the highest emission levels as compared to the specification limit.

MODES OF OPERATION

Transmitting at 319.5 MHz, CW

POWER SETTINGS INVESTIGATED

Battery

CONFIGURATIONS INVESTIGATED

CINC0029 - 3

FREQUENCY RANGE INVESTIGATED

SAMPLE CALCULATIONS

Radiated Emissions: Field Strength = Measured Level + Antenna Factor + Cable Factor - Amplifier Gain + Distance Adjustment Factor + External Attenuation

TEST EQUIPMENT

Description	Manufacturer	Model	ID	Last Cal.	Interval
Analyzer - Spectrum Analyzer	Agilent	E4440A	AAX	26-Mar-2018	12 mo
Cable	Element	Biconilog Cable	MNX	24-Feb-2018	12 mo
Antenna - Biconilog	ETS Lindgren	3142D	AXO	15-Dec-2017	24 mo

TEST DESCRIPTION

To derive average emission measurements, a duty cycle correction factor was utilized:

Duty Cycle = On time/100 milliseconds (or the period, whichever is less)

Where "On time" = N1L1 +N2L2 +....

Where N1 is the number of type 1 pulses, L1 is length of type 1 pulses, N2 is the number of type 2 pulses, L2 is the length of type 2 pulses, etc.

Therefore, Duty Cycle = (N1L1 +N2L2 +...)/100mS or T, whichever is less. (Where T is the period of the pulse train.)

The measured values for the EUT's pulse train are as follows:

Period = <100> mSec

Pulsewidth of Type 1 Pulse = <0.6635> mSec

Pulsewidth of Type 2 Pulse = <0.4484> mSec

Pulsewidth of Type 3 Pulse = <0.1233> mSec

Number of Type 1 Pulses = <1>

Number of Type 2 Pulses = <1>

Number of Type 3 Pulses = <58>

Duty Cycle = $20 \log [((1)(0.6635) + (1)(0.4484) + (58)(0.1233))/100] = <-21.66 > dB$

The duty cycle correction factor of <-21.66> dB was added to the peak readings to mathematically derive the average levels. Peak measurements were made with a resolution bandwidth of 100kHz and a video bandwidth of 300kHz.

Report No. CINC0029 11/22

FIELD STRENGTH OF FUNDAMENTAL



				EmiR5 2018.09.26 PSA-ESCI 2018.07.27
Work Order:	CINC0029	Date:	11-Oct-2018	2 0
Project:	None	Temperature:	20.3 °C	Drevor Buls
Job Site:	MN09	Humidity:	38.8% RH	Drevo C vines
Serial Number:	0348139	Barometric Pres.:	1018 mbar	Tested by: Andrew Rogstad, Trevor Buls
EUT:	RF-FOB-PANIC-319	<u> </u>		
Configuration:	3			
Customer:	CINCH Systems			
Attendees:	Jibril Aga			
EUT Power:	Battery			
Operating Mode:	Transmitting at 319.5	MHz, CW		
Deviations:	None			
Comments:	See data comments f	or EUT orientation		
Test Specifications			Test Metho	od
ECC 15 221:2019			VNSI Ces	10.2012

ANSI C63.10:2013

FCC 15.231:2018

Run# Test Distance (m) Antenna Height(s) Results 3 1 to 4(m) Pass 100 90 80 70 60 dBuV/m 50 40 30 20 10 0 319.0 319.1 319.2 319.3 319.4 319.5 319.6 319.7 319.8 320.0 319.9 MHz QP ■ PK ◆ AV

Freq (MHz)	Amplitude (dBuV)	Factor (dB)	Antenna Height (meters)	Azimuth (degrees)	Duty Cycle Correction Factor (meters)	External Attenuation (dB)	Polarity/ Transducer Type	Detector	Distance Adjustment (dB)	Adjusted (dBuV/m)	Spec. Limit (dBuV/m)	Compared to Spec. (dB)	Comments
319.505	66.5	19.5	1.0	360.0	0.0	0.0	Horz	PK	0.0	86.0	95.9	-9.9	EUT horz
319.505	66.5	19.5	1.0	360.0	-21.7	0.0	Horz	AV	0.0	64.3	75.9	-11.6	EUT horz
319.507	62.5	19.5	1.7	360.0	0.0	0.0	Vert	PK	0.0	82.0	95.9	-13.9	EUT on side
319.503	62.4	19.5	1.6	92.0	0.0	0.0	Vert	PK	0.0	81.9	95.9	-14.0	EUT vert
319.507	62.5	19.5	1.7	360.0	-21.7	0.0	Vert	AV	0.0	60.3	75.9	-15.6	EUT on side
319.503	62.4	19.5	1.6	92.0	-21.7	0.0	Vert	AV	0.0	60.2	75.9	-15.7	EUT vert
319.505	59.0	19.5	1.3	187.0	0.0	0.0	Horz	PK	0.0	78.5	95.9	-17.4	EUT vert
319.503	58.8	19.5	2.2	261.0	0.0	0.0	Horz	PK	0.0	78.3	95.9	-17.6	EUT on side
319.505	59.0	19.5	1.3	187.0	-21.7	0.0	Horz	AV	0.0	56.8	75.9	-19.1	EUT vert
319.503	58.8	19.5	2.2	261.0	-21.7	0.0	Horz	AV	0.0	56.6	75.9	-19.3	EUT on side
319.505	47.6	19.5	1.4	242.0	0.0	0.0	Vert	PK	0.0	67.1	95.9	-28.8	EUT horz
319.505	47.6	19.5	1.4	242.0	-21.7	0.0	Vert	AV	0.0	45.4	75.9	-30.5	EUT horz

Report No. CINC0029 12/22

SPURIOUS RADIATED EMISSIONS



PSA-ESCI 2018.07.27

Testing was performed using the mode(s) of operation and configuration(s) noted within the report. The individuals and/or the organization requesting the test provided the modes, configurations and settings used to complete the evaluation. The actual test parameters are specified in the test data, this includes items such as investigated frequency range (scanned) and test levels. The testing methods and performance specifications, as well as the test site used for the evaluation are indicated in the test data. The test data represents the configuration / operating mode/ model that produced the highest emission levels as compared to the specification limit.

MODES OF OPERATION

Transmitting at 319.5 MHz, CW

POWER SETTINGS INVESTIGATED

Battery

CONFIGURATIONS INVESTIGATED

CINC0029 - 3

FREQUENCY RANGE INVESTIGATED

	Start Frequency 30 MHz	Stop Frequency	3195 MHz
--	------------------------	----------------	----------

SAMPLE CALCULATIONS

Radiated Emissions: Field Strength = Measured Level + Antenna Factor + Cable Factor - Amplifier Gain + Distance Adjustment Factor + External Attenuation

TEST EQUIPMENT

Description	Manufacturer	Model	ID	Last Cal.	Interval
Attenuator	Coaxicom	3910-10	AWZ	26-Sep-2018	12 mo
Amplifier - Pre-Amplifier	Miteq	AMF-3D-00100800-32-13P	AVX	24-Feb-2018	12 mo
Cable	Element	Double Ridge Guide Horn Cables	MNV	24-Feb-2018	12 mo
Antenna - Double Ridge	ETS-Lindgren	3115	AJQ	14-Nov-2016	24 mo
Amplifier - Pre-Amplifier	Miteq	AM-1064-9079 and SA18E-10	AOO	24-Feb-2018	12 mo
Cable	Element	Biconilog Cable	MNX	24-Feb-2018	12 mo
Antenna - Biconilog	ETS Lindgren	3142D	AXO	15-Dec-2017	24 mo
Analyzer - Spectrum Analyzer	Agilent	E4440A	AAX	26-Mar-2018	12 mo

TEST DESCRIPTION

The highest gain antenna of each type to be used with the EUT was tested. The EUT was configured for the required transmit frequency in each operational band and the modes as showed in the data sheets.

For each configuration, the spectrum was scanned throughout the specified range as part of the exploratory investigation of the emissions. These "pre-scans" are not included in the report. Final measurements on individual emissions were then made and included in this test report.

The individual emissions from the EUT were maximized by rotating the EUT on a turntable, adjusting the position of the EUT and EUT antenna in three orthogonal axis, and adjusting the measurement antenna height and polarization (per ANSI C63.10). A preamp and high pass filter (and notch filter) were used for this test in order to provide sufficient measurement sensitivity.

Measurements were made with the required detectors and annotated on the data for each individual point using the following annotation:

QP = Quasi-Peak Detector

PK = Peak Detector

AV = RMS Detector

To derive average emission measurements, a duty cycle correction factor was utilized:

Duty Cycle = On time/100 milliseconds (or the period, whichever is less)

Where "On time" = N1L1 +N2L2 +....

Report No. CINC0029 13/22

SPURIOUS RADIATED EMISSIONS



PSA-ESCI 2018.07.27

Where N1 is the number of type 1 pulses, L1 is length of type 1 pulses, N2 is the number of type 2 pulses, L2 is the length of type 2 pulses, etc.

Therefore, Duty Cycle = (N1L1 +N2L2 +...)/100mS or T, whichever is less. Where T is the period of the pulse train.

The measured values for the EUT's pulse train are as follows:

Period = <100> mSec
Pulsewidth of Type 1 Pulse = <0.6635> mSec
Pulsewidth of Type 2 Pulse = <0.4484> mSec
Pulsewidth of Type 3 Pulse = <0.1233> mSec
Number of Type 1 Pulses = <1>
Number of Type 2 Pulses = <1>
Number of Type 3 Pulses = <58>

Duty Cycle = $20 \log [((1)(0.6635) + (1)(0.4484) + (58)(0.1233))/100] = <-21.66 > dB$

The duty cycle correction factor of <-21.66> dB was added to the peak readings to mathematically derive the average levels. Peak measurements were made with a resolution bandwidth of 100kHz and a video bandwidth of 300kHz for measurements at or below 1GHz. Above 1GHz, a resolution bandwidth of 1MHz and a video bandwidth of 3MHz was used.

Report No. CINC0029 14/22

SPURIOUS RADIATED EMISSIONS



W	ork Order:	CINC	0029		Date:	11-00	t-2018		-	EmiR5 2018.09.26	- 0	PSA-ESCI 2018.07.27	1
	Project:	No	ne	Ter	nperature:	20.3	3 °C	1		~ 1.	3 W.	D_	
0	Job Site:	MN		Darrer	Humidity:		% RH	\ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \	evo	Amalucii D	material T	uan Deile	J
Seria	I Number:	0348 RF-FOB-P		Barome	etric Pres.:	1018	mbar		ested by:	Andrew Ro	gstad, Tre	vor Buls	-
Conf	iguration:	3											-
		CINCH Sys	stems										-
	Attendees:												_
	UT Power:		ng at 319.5	MHz CW									-
Operat	ing Mode:	Tranomita	ig at 010.0	1411 12, 044									
D	eviations:	None											=
		Niere											_
C	omments:	None											
													_
Test Spec	ifications						Test Meth	od					-
FCC 15.23	31:2018						ANSI C63.	10:2013					_
													_
Run #	7	Test Dis	stance (m)	3	Antenna	Height(s)		1 to 4(m)		Results	Pa	ass	-
Γ													
80												++	
											<u> </u>		
70					111111	+						+	
60													
		_				┥╟					┸		
50											٠. "		
ے 50													
w//\ngp				<u> </u>									
4 0 +			•	- -					•				
·								<u> </u>					
30							<u> </u>		•				
20							ľ						
10													
0 10)			100	·	'		1000	'			10000	
				.00		MHz							
										■ PK	◆ AV	• QP	
			Antenna		Duty Cycle Correction	External	Polarity/ Transducer		Distance			Compared to	
Freq	Amplitude	Factor	Height	Azimuth	Factor	Attenuation	Type	Detector	Adjustment	Adjusted	Spec. Limit	Spec.	
(MHz)	(dBuV)	(dB)	(meters)	(degrees)	(dB)	(dB)			(dB)	(dBuV/m)	(dBuV/m)	(dB)	Comments
1597.575	70.1	-6.8	1.0	166.0	0.0	0.0	Vert	PK	0.0	63.3	74.0	-10.7	EUT on side EUT horz
1597.490 1597.575	69.4 70.1	-6.8 -6.8	1.0 1.0	330.0 166.0	0.0 -21.7	0.0 0.0	Horz Vert	PK AV	0.0 0.0	62.6 41.6	74.0 54.0	-11.4 -12.4	EUT norz EUT on side
1597.490	69.4	-6.8	1.0	330.0	-21.7	0.0	Horz	AV	0.0	40.9	54.0	-13.1	EUT horz
958.514 639.010	32.5 37.6	13.2 7.9	1.4 1.2	30.0 136.0	0.0 0.0	10.0 10.0	Horz Horz	PK PK	0.0 0.0	55.7 55.5	75.9 75.9	-20.2 -20.4	EUT horz EUT horz
958.522	31.2	13.2	1.1	66.0	0.0	10.0	Vert	PK	0.0	54.4	75.9	-21.5	EUT on side
1278.135 639.008	62.3 36.3	-8.0 7.9	2.6 1.0	271.0 0.0	0.0 0.0	0.0 10.0	Horz Vert	PK PK	0.0 0.0	54.3 54.2	75.9 75.9	-21.6 -21.7	EUT horz EUT on side
958.514	32.5	13.2	1.4	30.0	-21.7	10.0	Horz	AV	0.0	34.0	55.9	-21.9	EUT horz
639.010 958.522	37.6 31.2	7.9 13.2	1.2 1.1	136.0 66.0	-21.7 -21.7	10.0 10.0	Horz Vert	AV AV	0.0 0.0	33.8 32.7	55.9 55.9	-22.1 -23.2	EUT horz EUT on side
1278.135	62.3	-8.0	2.6	271.0	-21.7	0.0	Horz	AV	0.0	32.6	55.9	-23.3	EUT horz
639.008 639.022	36.3 33.7	7.9 7.9	1.0 1.8	0.0 353.0	-21.7 0.0	10.0 10.0	Vert Vert	AV PK	0.0 0.0	32.5 51.6	55.9 75.9	-23.4 -24.3	EUT on side EUT vert
1278.030	58.3	7.9 -8.0	1.8	13.0	0.0	0.0	Vert	PK PK	0.0	51.6	75.9 75.9	-24.3 -25.6	EUT on side
639.010	32.2	7.9	1.4	76.0	0.0	10.0	Horz	PK	0.0	50.1	75.9	-25.8	EUT vert
639.022 639.008	33.7 31.5	7.9 7.9	1.8 3.9	353.0 85.0	-21.7 0.0	10.0 10.0	Vert Horz	AV PK	0.0 0.0	29.9 49.4	55.9 75.9	-26.0 -26.5	EUT vert EUT on side
1278.030	58.3	-8.0	1.0	13.0	-21.7	0.0	Vert	AV	0.0	28.6	55.9	-27.3	EUT on side
639.010 639.008	32.2 31.5	7.9 7.9	1.4 3.9	76.0 85.0	-21.7 -21.7	10.0 10.0	Horz Horz	AV AV	0.0 0.0	28.4 27.7	55.9 55.9	-27.5 -28.2	EUT vert EUT on side
639.019	27.5	7.9	1.0	35.0	0.0	10.0	Vert	PK	0.0	45.4	75.9	-30.5	EUT horz
639.019	27.5	7.9	1.0	35.0	-21.7	10.0	Vert	AV	0.0	23.7	55.9	-32.2	EUT horz

Report No. CINC0029

OCCUPIED BANDWIDTH



XMit 2017.12.13

Testing was performed using the mode(s) of operation and configuration(s) noted within the report. The individuals and/or the organization requesting the test provided the modes, configurations and settings used to complete the evaluation. The actual test parameters are specified in the test data, this includes items such as investigated frequency range (scanned) and test levels. The testing methods and performance specifications, as well as the test site used for the evaluation are indicated in the test data.

TEST EQUIPMENT

Description	Manufacturer	Model	ID	Last Cal.	Cal. Due
Analyzer - Spectrum Analyzer	Agilent	E4440A	AAX	26-Mar-2018	26-Mar-2019
Cable	Element	Biconilog Cable	MNX	24-Feb-2018	24-Feb-2019
Antenna - Biconilog	ETS Lindgren	3142D	AXO	15-Dec-2017	15-Dec-2019

TEST DESCRIPTION

The measurement was made in a radiated configuration of the fundamental with the carrier fully maximized for its highest radiated power. The EUT was transmitting at its maximum data rate.

The 20 dB occupied bandwidth is required to be no wider than 0.25% of the center frequency for devices operating above 70 MHz and below 900 MHz.

Report No. CINC0029 16/22

OCCUPIED BANDWIDTH



							XMit 2017.12.13
EUT:	RF-FOB-PANIC-319				Work Order:	CINC0029	
Serial Number:	0348139				Date:	11-Oct-18	
	CINCH Systems				Temperature:		
Attendees:	Jibril Aga				Humidity:		
Project:	None				Barometric Pres.:		
	Andrew Rogstad, Trevor	Buls		Power: Battery	Job Site:	MN09	
TEST SPECIFICATI	IONS			Test Method			
FCC 15.231:2018				ANSI C63.10:2013			
COMMENTS							
Transmitting at 319	9.508 MHz modulated						
DEVIATIONS FROM	II TEST STANDARD						
None							
Configuration #	2	Signature	J	veror Buls			
					-20 OB (kHz)	Limit (kHz)	Result
319.5 MHz					33.779	798	Pass

Report No. CINC0029 17/22


OCCUPIED BANDWIDTH



319.5 MHz

-20 OB (kHz) Limit (kHz) Result

33.779 798 Pass



Report No. CINC0029 18/22



XMit 2017.12.13

Testing was performed using the mode(s) of operation and configuration(s) noted within the report. The individuals and/or the organization requesting the test provided the modes, configurations and settings used to complete the evaluation. The actual test parameters are specified in the test data, this includes items such as investigated frequency range (scanned) and test levels. The testing methods and performance specifications, as well as the test site used for the evaluation are indicated in the test data.

TEST EQUIPMENT

Description	Manufacturer	Model	ID	Last Cal.	Cal. Due
Analyzer - Spectrum Analyzer	Agilent	E4440A	AAX	26-Mar-2018	26-Mar-2019
Cable	Element	Biconilog Cable	MNX	24-Feb-2018	24-Feb-2019
Antenna - Biconilog	ETS Lindgren	3142D	AXO	15-Dec-2017	15-Dec-2019

TEST DESCRIPTION

The measurement was made in a radiated configuration of the fundamental with the carrier fully maximized for its highest radiated power. For software controlled or pre-programmed devices, the manufacturer shall declare the duty cycle class or classes for the equipment under test. For manually operated or event dependant devices, with or without software controlled functions, the manufacturer shall declare whether the device once triggered, follows a pre-programmed cycle, or whether the transmission is constant until the trigger is released or manually reset. The manufacturer shall also give a description of the application for the device and include a typical usage pattern. The typical usage pattern as declared by the manufacturer shall be used to determine the duty cycle and hence the duty class.

Where an acknowledgement is required, the additional transmitter on-time shall be included and declared by the manufacturer.

To derive average emission measurements, a duty cycle correction factor was utilized:

Duty Cycle = On time/100 milliseconds (or the period, whichever is less)

Where "On time" = N1L1 +N2L2 +....

Where N1 is the number of type 1 pulses, L1 is length of type 1 pulses, N2 is the number of type 2 pulses, L2 is the length of type 2 pulses, etc.

Therefore, Duty Cycle = (N1L1 +N2L2 +...)/100mS or T, whichever is less. (Where T is the period of the pulse train.)

The measured values for the EUT's pulse train are as follows:

```
Period = <_100_> mSec

Pulsewidth of Type 1 Pulse = <_.6635_> mSec

Pulsewidth of Type 2 Pulse = <_.4484_> mSec

Pulsewidth of Type 3 Pulse = <_.1233_> mSec

Number of Type 1 Pulses = <_1_>

Number of Type 2 Pulses = <_1_>

Number of Type 3 Pulses = <_58_>
```

Duty Cycle = $20 \log [((1)(.6635) + (1)(.4484) + (58)(.1233))/100] = <-21.66 > dB$

Report No. CINC0029 19/22




Result
Result N/A


Report No. CINC0029 20/22



100 ms Number of Type 1 Pulse Number of Type 2 Pulse Number of Type 3 Pulse Type 1 Pulses length (ms) Type 2 Pulses length (ms) Type 3 Pulses length (ms) DCCF 0.6635 0.4484 58 -21.66



			5 s			
Number of	Type 1 Pulse	Number of	Type 2 Pulse	Number of	Type 3 Pulse	
Type 1 Pulses	length (ms)	Type 2 Pulses	length (ms)	Type 3 Pulses	length (ms)	DCCF
N/A	N/A	N/A	N/A	N/A	N/A	N/A




Report No. CINC0029 21/22

Mit 2017.12.1



XMit 2017.12.1

			10 s			
Number of	Type 1 Pulse	Number of	Type 2 Pulse	Number of	Type 3 Pulse	
Type 1 Pulses	length (ms)	Type 2 Pulses	length (ms)	Type 3 Pulses	length (ms)	DCCF
N/A	N/A	N/A	N/A	N/A	N/A	N/A



Report No. CINC0029 22/22