					Serial NO.	
					Version	V1.0
Fi	le name				Page No.	Page 1/Page 6
		tomo-				
		tomer:	E-898			
	Mod	del Name: S	tereo Wireless	s (Blueto	oth) Head	dset
	Custome	er Approval				

		Product Specifications		
Product Model	ME-898	Serial No.		
Product Name	Stereo Wireless Bluetooth Headset	Page No.	Page /Page 6	

# 1. Product Image



# **2.** Product Specifications&Features

Bluetooth	W	
Protocol	Version 4.0	
Operating Frequency	ISM 2.4to 2.48GHz	
Power Transmissio	Class 2	
Connective Range	About 10m	
Voltage and Built-in	3.7V 370mAh/502533	
USB Charging	MICRO USB 5PIN	
Charging Time	≤4H	
Standby Current	≤10mA	
Working Current	≤25mA	
Play Time	≥10H	
Standby Time	≥12day	
Speaker	Diameter 40mm 32ohm 115dB 30mW 20-20000Hz	
microphone	-42dB+/-3dB	
Dimensions	195*165*79mm	
Weight	0. 242kg	

		Product Specifications		
Product Model	ME-898	Serial No.		
Product Name	Stereo Wireless Bluetooth Headset	Page No.	Page /Page 6	

# **3.** Button Operation and LED Display:

	ME-898 Bluetooth Headset Instructions					
Function	Operation	<b>Functional Descriptions</b>	LED Status	Tone	Voice prompt	
Bluetooth on	Long Press MFB about 3 seconds	When the headset is OFF, press MFB about 3 seconds.	The red and the blue lights alternately flash.	On music		
Bluetooth off	Long Press MFB about 3 seconds	When the headset is ON, press MFB about 3 seconds.	The red and the blue lights alternately flash.	Off music		
Pair			When the red and the blue lights alternately flash, it is connecting ,after pairing the blue light slowly.			
Play	Press MFB	When the headset music is Pausing, press MFB to play music.		/		
Pause	Press MFB	When the headset music is Playing, press MFB to pause music.		/		
Volume +	Press VOL+	When the headset music is Playing or phones Talking, long press VOL+ 3 seconds to increase the volume.				
Volume -	Press VOL-	When the headset music is Playing or phones Talking, long press VOL- 3 seconds to decrease the volume.				
Next	Press NEXT	When the headset is in the music mode, press NEXT to skip to the next.		/		
Previous	Press PREV	When the headset is in the music mode, press PREV to skip to the next.		/		
Answer a call	Press MFB	When the phone calling, press MFB button to answer the call.				
Reject a call	Press MFB about 2 seconds	When the phone calling, press the MFB button about 2seconds to reject the call.		/		
End a call	Press MFB	When the headset is in the phone mode, press MFB to end the call.				

		Product Specifications		
Product Model	ME-898	Serial No.		
Product Name	Stereo Wireless Bluetooth Headset	Page No.	Page /Page 6	

D 11 1 1 1 1		When the headset is in standby			
Redial the last call	Press MFB twice	mode, press MFB twice to redial			
Call		the last call.			
Cancel the	Press MFB	When the headset is in dialing,			
dialing	TICSS WII D	press MFB to end the call.			
Connected	Press MFB Aft	ter turn the headset on and not			
twice again .	paired, please Press MFB (This is second times to			/	
twice again.	connected for your n	nobile.			
				/	
Calls			The blue light flashes.		
Low Battery	3.2V to alarm, under	23 OV to shutdown			
Alarm	5.2 v to ararm, under	3.0 v to shutdown.			
Charge	When the headphon	es is charging the red light is on. V	When the headphones are	fully charged	is show blue
Charge	light.				

## 4, Operation steps

#### 4. 1 Start Using

Before using your Bluetooth headset, please refer to the following steps:

- 1. Charge the battery fully before you use the headphones for the first time.
- 2. You can use a computer to charge, or any device that is USB supported like a general 5V USB adapter etc. When the headphones is charging the red light is on. When the headphones are fully charged is show blue light and the charging cable can be removed.
- 3. During pairing, make sure that the Bluetooth headset and your phone are within 0.5 meters.
- 4. Make sure that the Bluetooth headphones and the phone are within 10 meters when in use.

#### 4.2 Turning on and off

- 1. To turn on: Press MFB about 3 seconds ,when the red and the blue lights alternately flash. You will hear "On music" .
- 2. To turn OFF: Press MFB for at least 3 seconds ,when the red and the blue lights alternately flash. You will hear "Off music" .

### 4.3 Pairing your phone using Bluetooth

- 1. Make sure the headphones is turned off.
- 2. During pairing, make sure that the Bluetooth headphones and your phone are within 0.5 meters.
- 3. Put your headphones in pairing mode by pressing MFB for approx. 3 seconds, when the red and the blue lights alternately flash, after pairing the blue light slowly.
- 4. Follow the instructions that came with your phone or device. If your phone requires a pass code, press 0000. If the headphones have been paired successfully, after pairing the blue light slowly.

#### 4.4 Reconnecting the headphones

- 1. Using your headphones: Press MFB for 3 seconds to reconnect. Select "Accept connection" on your phone if prompted.
- 2. Using your phone: check the list of paired devices on your phone, select ME-898 to connect.

#### Tips:

1. When the Bluetooth is disconnected or removed, and the symbol  $\Omega$  is not visible on the phone screen, please reconnect

		Product Specifications		
Product Model	ME-898	Serial No.		
Product Name	Stereo Wireless Bluetooth Headset	Page No.	Page /Page 6	

the headphone according to the right steps.

- 2. If the Bluetooth connection is lost for more than 15 minutes, the headphones will go into power-saving (shutdown) mode. If you want to restore the connection, press MFB or use the phone to reconnect.
- 3. When you turn the headphones back on it will automatically connect with the phone that was last used. You have two options to reconnect:
- 1. Using your headphones: Press MFB for 3 seconds to reconnect. Select "Accept connection" on your phone if prompted.
- 2. Using your phone: check the list of paired devices on your phone, select ME-898 to connect.

### **4.5 Removing Connection**

- 1. Turn off your headphones or your phone.
- 2. Disconnect using your phone menu.

Remark: If the headphone and your phone out of 10 meters, it will be disconnected. For most of Bluetooth mobile phone will automatically connected within 15 minutes. If it is disconnected over 15 minutes, the headset will go into shutdown mode.

#### 4.6 Using phone functions with your Bluetooth headphones

1. To answer a call

When the phone calling, press MFB button to answer the call.

2. To finish a call

Press MFB or press the 'End Call' button from your phone.

3. Redial last number

Press MFB twice to dial the last number your phone called.

4. Stop dialing/calling

When you dial a number by mistake, or the other person doesn't answer, press MFB to stop calling.

5. Reject a call

Press MFB for about 2 seconds to reject the call.

#### **4.7** Listening to music

- 1. Choose a song from your phone and press PLAY. If you want to pause or resume the music, press PLAY.
- 2. When playing a song, press the VOL+ or VOL- button to adjust the volume.
- 3. Press the PREV button to skip back to the previous song and press the NEXT button to skip forward to the next song
- 4. If you answer a call while listening to music, the music will stop playing, and will continue after the call ends. The same thing happens when making calls.

#### 4.9 Using your headphones with wires

Insert the 3.5mm jack cable into the hole on the left side of the headphones.

Use your computer or other device to play songs, etc.

Tips! The Bluetooth volume control doesn't work when connecting through a wire, use your computer/mobile phone to adjust the volume.

		Product Specifications		
Product Model	ME-898	Serial No.		
Product Name	Stereo Wireless Bluetooth Headset	Page No.	Page /Page 6	

#### **FCC WARNING**

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.