
- 71.00 mm

BT820 蓝牙立体声耳机

MM

00

05



使用说明书

欢迎使用BT820蓝牙耳机

在使用你的立体声蓝牙耳机之前,请遵循以下步骤:

- 1. 请确保你的蓝牙耳机已完全充电。 2. 首次使用蓝牙耳机前,建议先将电池充满电。请将已充满电 的蓝牙耳机与具有蓝牙功能的手机配对连接。

启动蓝牙耳机

启动蓝牙耳机,请按住多功能 ▶Ⅲ/€ 键3秒,听到"嘟" 声提示声,表示已开机,蓝灯闪亮。关于配接功能,请参阅 "蓝牙配对"一节。

关闭蓝牙耳机

在开机状态下,请按住多功能 ▶Ⅱ/€ 键约4秒,直到指示 对连续内炼。 注意: 如果您有一段时间将不使用蓝牙耳机时,建议您关闭耳机 并关闭手机的蓝牙功能。

首次使用和配接蓝牙耳机前,请检查你的手机是否具有 蓝牙功能,在你的手机用户指南或包装上能看到此信息。 下步将会提供具有蓝牙功能的移动电话配接说明,蓝牙耳机的配对程序和手机的不同型号而定,欲知更多信息,请向您的 手机制造商或代理商查询。

蓝牙配对

- 1. 请将蓝牙耳机和移动电话放在容易看见的位置及相距离1米
- 2. 蓝牙耳机处于关机状态; 3. 请按多功能 ▶Ⅱ/ 键约6秒直至蓝牙耳机听到"嘟嘟"两声提示音,红蓝灯交替闪烁,即进入配对状态;

- 打开你的手机蓝牙功能,在搜索到的蓝牙设备中选择 "BT820",这时蓝牙耳机和手机会自动开始连接,连接上时指示灯转为蓝色隔4秒闪一次;
 某些型号的手机在配对时会要求输入配对密码,本耳机的预编
- 6. 如果手机与本蓝牙耳机已连接成功,则长按多功能 ▶॥/♂ 键

使用您的蓝牙耳机 接听来电/拒接来电

当有来电时,您能通过蓝牙耳机聆听到铃声讯号,按一下多功能 ▶Ⅱ/♂ 键可接听来电,或使用手机接听键接听来电。若您想拒接来电,在响铃过程中,长按多功能 ▶Ⅱ/♂ 键2秒松开即可

终止诵话

通话过程中,若想终止通话,请按一下多功能 ▶Ⅱ/ ¢ 键,或使用手机挂机键终止通话。

最后一个号码重拨

在待机状态下,双击多功能 ▶Ⅱ/ℰ 键

蓝牙耳机在与手机连接后,在播放音乐过程中,短按多功 能 ▶॥/♂ 键, 音乐会暂停, 再按一下多功能 ▶॥/♂ 键则恢复播放。

在播放音乐过程中,短按 ━┃◀◀ 键,耳机会自动播放上一曲

下一曲

在播放音乐过程中,短按 ▶▶|+ 键,耳机会自动播放下一曲


在通话过程中或播放音乐时,长按住或短按 ▶▶1+ 键, 音量随之增大,当音量调到最大时蓝牙耳机会发出"嘟"的 一声提示音

减小音量

在通话过程中或播放音乐时,长按住或短按 ━┃◀◀ 键, 音量随之减小,当音量调到最小时蓝牙耳机会发出"嘟"的一声提示音

外接音频输入

当插上3.5MM耳机线时,这时蓝牙耳机外接3.5MM的音频信号,会断开蓝牙连接的声音,手机会通过耳机线播放音乐。



产品清单

	牙耳机1个
	克充电线1条
3.	5MM耳机线1条
说	明书1本

Stereo **Bluetooth Headphones** BT820



Thanks for using BT820 Bluetooth headphone

Before using stereo Bluetooth headset, please check bellow's points firstly. Make sure the built-in battery is fully charged.

For headphone charging:
Use the USB cable to connect the computer, When charging, the power light in headphone is red, (DC 5V for charging). This device is not attached adapter sales together

Turn on Bluetooth headphone:
Please press the headphone 's multifunction key ►II/⟨* for 3 seconds, hear "beep" sounds, which means headphone turns on, at the same time,

Turn off Bluetooth headphone:

Under the working status, press the headphone's multifunction key ► II / \(\c^2\) for about 4 seconds, the indicator light flashes continuously. The headphone

(Note: if you don't use the Bluetooth headphone, please turn off).

Bluetooth headphone and mobilephone's pairing: First time pairing with mobile phone, please check if Bluetooth function in

mobile phone is turned on. Please put Bluetooth headphone and mobile phone in the place where it is

easy to see, the distance is 1 meter's range.

New pairing

headphone's password is "0000".)

For Bluetooth headphone with Mobile phone:

1. Press the headphone 's multifunction key ▶ II / ⟨° for about 6 seconds, till the Bluetooth headphone to hear "beep" 2-times sound , red and blue light flashing alternately, means on the pairing status.

2. Open your mobile phone Bluetooth function, search the Bluetooth

headphone's model code "BT820", the Bluetooth headphone and mobile phones will start automatically pairing, if connected successfully, then the LED light indicator turns blue, and flash every 4 seconds. (Some old mobile phone requires input matching password when pairing, the

Repeated pairing

For Bluetooth headphone with Mobile phone:

If the mobile phone and the headphone had connected before, then press the headphone 's multifunction button \(\big|\lambda\lambda\rangle\) for 3 seconds, it will be connecting automatically, the LED indicator light blue flashes per every 0.5 seconds. If headphone searched the mobile phone successfully, it will

Connecting with the other devices if under the connect status:

The Bluetooth headphone is in connecting at a Bluetooth device. If the user wants to change connecting to other Bluetooth devices press the headphone's multifunction key $\bullet \parallel \parallel / \epsilon^*$ for about 2 seconds, hear "beep" sounds, the LED indicator turns flashing in red and blue colour, then you can connect to other Bluetooth devices.

Use Bluetooth headphone for phone call:

Answer the call / rejecting calls

When there is an incoming call, you can hear the mobile phone's phone call sounds signal through the Bluetooth headphone, press the headphone's multifunction key > II / to answer the call, or use mobile phone key to answer the call, if you want to reject the call, press the headphone's multifunction key III/6° for about 2 seconds, you can reject the call.

During a call, to end the call, press the headphone's multifunction ►II /

key, or use a mobile phone to terminate the call as usual. 3. Phone numbers re-dial In the standby mode, double click the headphone's multifunction > II / C

key to re-dial last phone number as phone calling.

Music status

 Play / pause for music
 When bluetooth for headphones and mobilephone's connection well, and user begins to play music, press key ►II/ short time for pause and

2. Pre / Next song playing.

Press key —|44 for Pre. song and key for ▶▶|+ next song.

Volume control:

1. Increase the volume

During a call, or when the music is playing, press the headphone's key -|◀◀ , the volume increases, when the volume to the maximum, the Bluetooth


2. Reduce the volume

During a call, or when the music is playing, press the headphone's key ▶►I+, the volume decreases, when the volume to the minimum, the Blueto headphone will have a been sound to remind

External audio input

When plug in 3.5MM audio cable, then the Bluetooth function will be disconnected automatically, the headphone will play 3.5MM signal

Operation Instruction



Parts List

. 4. 10 =.01	
Bluetooth Headphone	1PCS
3.5 to 3.5 jackcable	1PCS
Micro USB cable	1PCS
Hear Manual	1000



User Manual

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference

in a residential installation. This equipment generates uses and can radiate radio frequency energy and,

if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that

interference will not occur in a particular installation. If this equipment

does cause harmful interference to radio or television reception, which can be determined

by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

-Reorient or relocate the receiving antenna.

- -Increase the separation between the equipment and receiver.
- -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- -Consult the dealer or an experienced radio/TV technician for help.