

# **Radio Test Report**

# FCC ID: 2ADZVCMPTWLTX

This report concerns (check one) : ☐ Original Grant ☐ Class II Change

Project No. : 1412C180 Equipment : Cycle Computer Model Name : CMPT WL-TX

**Applicant**: Pending System GmbH & Co. KG

Address : Ludwig-Hüttner-Str.5-7 D-95679 Waldershof

**GERMANY** 

Date of Receipt : Dec. 23, 2014

**Date of Test** : Dec. 23, 2014~ Jan. 05, 2015

**Issued Date** : Jan. 06, 2015 **Tested by** : BTL Inc.

Testing Engineer : Yavid Mao

(David Mao)

Technical Manager :

(Leo Hung)

**Authorized Signatory** 

(Steven Lu)

# BTLINC

No.3, Jinshagang 1st Road, Shixia, Dalang Town, Dongguan, Guangdong, China.

TEL: +86-769-8318-3000 FAX: +86-769-8319-6000

Report No.: BTL-FCCP-1-1412C180 Page 1 of 29



#### **Declaration**

**BTL** represents to the client that testing is done in accordance with standard procedures as applicable and that test instruments used has been calibrated with the standards traceable to National Measurement Laboratory (**NML**) of **R.O.C.**, or National Institute of Standards and Technology (**NIST**) of **U.S.A.** 

**BTL**'s reports apply only to the specific samples tested under conditions. It is manufacture's responsibility to ensure that additional production units of this model are manufactured with the identical electrical and mechanical components. **BTL** shall have no liability for any declarations, inferences or generalizations drawn by the client or others from **BTL** issued reports.

**BTL**'s reports must not be used by the client to claim product endorsement by the authorities or any agency of the Government.

This report is the confidential property of the client. As a mutual protection to the clients, the public and **BTL-self**, extracts from the test report shall not be reproduced except in full with **BTL**'s authorized written approval.

BTL's laboratory quality assurance procedures are in compliance with the ISO Guide 17025 requirements, and accredited by the conformity assessment authorities listed in this test report.

#### Limitation

For the use of the authority's logo is limited unless the Test Standard(s)/Scope(s)/Item(s) mentioned in this test report is (are) included in the conformity assessment authorities acceptance respective.

Report No.: BTL-FCCP-1-1412C180 Page 2 of 29



# **Table of Contents**

REPO	ORT ISSUED HISTORY	4			
1	CERTIFICATION	5			
2	SUMMARY OF TEST RESULTS	6			
2.1 TI	EST FACILITY	7			
2.2 M	EASUREMENT UNCERTAINTY	7			
3	GENERAL INFORMATION	8			
3.1	GENERAL DESCRIPTION OF EUT	8			
3.2	DESCRIPTION OF TEST MODES	9			
3.3	BLOCK DIAGRAM SHOWING THE CONFIGURATION OF SYSTEM TESTED	10			
3.4	DESCRIPTION OF SUPPORT UNITS	11			
4	CONDUCTED EMISSION	12			
4.1	LIMITS	12			
4.2	TEST PROCEDURES	12			
4.3	TEST SETUP LAYOUT	13			
4.4	DEVIATION FROM TEST STANDARD	13			
4.5	EUT OPERATING CONDITIONS	13			
4.6	TEST RESULTS	13			
5	RADIATED EMISSION	14			
5.1	LIMITS	14			
5.2	TEST PROCEDURE	15			
5.3	DEVIATION FROM TEST STANDARD	15			
5.4	TEST SETUP	16			
5.5	EUT OPERATING CONDITIONS	16			
5.6	TEST RESULTS (BELOW 30MHz)	16			
5.7	TEST RESULTS (30MHz-1GHz)	17			
6. 20I	DB SPECTRUM BANDWIDTH MEASUREMENT	18			
6.1. L	IMIT OF 20dB BANDWIDTH MEASUREMENT	18			
6.2.Tl	EST PROCEDURES	18			
6.3. T	EST SETUP LAYOUT	18			
6.4. T	EST DEVIATION	18			
6.5. EUT OPERATION DURING TEST					
6.6. T	EST RESULT	18			
7	MEASUREMENT INSTRUMENTS LIST	19			
8	EUT TEST PHOTO	20			
ATTACHMENT A - CONDUCTED EMISSION					
ATTACHMENT B - RADIATED EMISSION (BELOW 30MHZ)					
ATTACHMENT C - RADIATED EMISSION (30 MHZ TO 1 GHZ)					
ATTACHMENT D - 20DB SPECTRUM BANDWIDTH MEASUREMENT					

Report No.: BTL-FCCP-1-1412C180 Page 3 of 29



# **REPORT ISSUED HISTORY**

Issue No.	Description	Issued Date
BTL-FCCP-1-1412C180	Original Issue.	Jan. 06, 2015

Report No.: BTL-FCCP-1-1412C180 Page 4 of 29



#### 1 CERTIFICATION

Equipment : Cycle Computer Brand Name : CUBE; RFR Model Name : CMPT WL-TX

Applicant : Pending System GmbH & Co. KG

Manufacturer: DONGGUAN RESOURCEFUL MIND ELECTRONICS LTD.

NO. 7 DONG HUAN ROAD, HUANGNIU PU IND. ZONE, DONG GUAN,

Address : CHINA

Factory : DONGGUAN RESOURCEFUL MIND ELECTRONICS LTD.

Address : NO. 7 DONG HUAN ROAD, HUANGNIU PU IND. ZONE, DONG GUAN,

Address . CHINA

Date of Test : Dec. 23, 2014~ Jan. 05, 2015

Standards : FCC Part 15, Subpart C(15.209): 2013

ANSI C63.4: 2009

The above equipment has been tested and found compliance with the requirement of the relative standards by BTL Inc..

The test data, data evaluation, and equipment configuration contained in our test report (Ref No. BTL-FCCP-1-1406175) were obtained utilizing the test procedures, test instruments, test sites that has been accredited by the Authority of TAF according to the ISO-17025 quality assessment standard and technical standard(s).

Report No.: BTL-FCCP-1-1412C180 Page 5 of 29



## **2 SUMMARY OF TEST RESULTS**

Test procedures according to the technical standards:

Standard Section	Test Item	Result
15.207	Conducted emission	N/A
15.209	Radiated Emission	PASS

NOTE:

1.	N/A:	denotes	test is	s not	app	licable	in	this	Test	Re	port
----	------	---------	---------	-------	-----	---------	----	------	------	----	------

Report No.: BTL-FCCP-1-1412C180 Page 6 of 29



#### 2.1 TEST FACILITY

The test facilities used to collect the test data in this report is **DG-CB03** at the location of No.3, Jinshagang 1st Road, Shixia, Dalang Town, Dong Guan, Guangdong, China.523792 BTL's test firm number for FCC: 319330

#### 2.2 MEASUREMENT UNCERTAINTY

Where relevant, the following measurement uncertainty levels have been estimated for tests performed on the EUT as specified in CISPR 16-4-2:

The reported uncertainty of measurement  $\mathbf{y} \pm \mathbf{U}$ , where expended uncertainty  $\mathbf{U}$  is based on a standard uncertainty multiplied by a coverage factor of  $\mathbf{k=2}$ , providing a level of confidence of approximately 95 %.

#### A. Radiated Measurement:

Test Site	Method	Measurement Frequency Range	Ant. H / V	U , (dB)	Note
		9KHz~30MHz	V	3.79	
	CISPR	9KHz~30MHz	Н	3.57	
DG-CB03		30MHz ~ 200MHz	V	3.82	
DG-CB03		30MHz ~ 200MHz	Η	3.60	
		200MHz ~ 1,000MHz	V	3.86	
		200MHz ~ 1,000MHz	Н	3.94	

Report No.: BTL-FCCP-1-1412C180 Page 7 of 29



## **3 GENERAL INFORMATION**

#### 3.1 GENERAL DESCRIPTION OF EUT

Equipment	Cycle Computer
Brand Name	CUBE; RFR
Model Name	CMPT WL-TX
Model Difference	N/A
Product Description	Operation Frequency   120 kHz   Antenna Designation   LOOP Antenna
Power Source	Supplied from battery
Power Rating	DC 3V

#### Note:

1. For a more detailed features description, please refer to the manufacturer's specifications or the User's Manual.

Report No.: BTL-FCCP-1-1412C180 Page 8 of 29



#### 3.2 DESCRIPTION OF TEST MODES

To investigate the maximum EMI emission characteristics generates from EUT, the test system was pre-scanning tested base on the consideration of following EUT operation mode or test configuration mode which possible have effect on EMI emission level. Each of these EUT operation mode(s) or test configuration mode(s) mentioned above was evaluated respectively.

Pretest Test Mode	Description
Mode 1	120 KHz Transmit

Radiated emission test					
Final Test Mode	Description				
Mode 1	120 KHz Transmit				

Report No.: BTL-FCCP-1-1412C180 Page 9 of 29



3.3 BLOC	K DIAGRAM SHOWING THE CONFIGURATION OF SYSTEM TESTED	
	EUT TX	

Report No.: BTL-FCCP-1-1412C180



#### 3.4 DESCRIPTION OF SUPPORT UNITS

The EUT has been tested as an independent unit together with other necessary accessories or support units. The following support units or accessories were used to form a representative test configuration during the tests.

Item	Equipment	Mfr/Brand	Model/Type No.	FCC ID	Series No.	Note
-	-	-	-		-	-

Item	Shielded Type	Ferrite Core	Length	Note
-		-		-

N	ote

(1) The support equipment was authorized by Declaration of Conformity (DOC).

Report No.: BTL-FCCP-1-1412C180 Page 11 of 29



Page 12 of 29

#### 4 CONDUCTED EMISSION

#### 4.1 LIMITS

FREQUENCY	Class A	(dBuV)	Class B (dBuV)		
(MHz)	Quasi-peak	Average	Quasi-peak	Average	
0.15 - 0.5	79.00	66.00	66 - 56 *	56 - 46 *	
0.50 - 5.0	73.00	60.00	56.00	46.00	
5.0 - 30.0	73.00	60.00	60.00	50.00	

#### NOTE:

- 1. The tighter limit applies at the band edges.
- 2. The limit of " \* " marked band means the limitation decreases linearly with the logarithm of the frequency in the range.
- The test result calculated as following:
   Measurement Value = Reading Level + Correct Factor
   Correct Factor = Insertion Loss + Cable Loss + Attenuator Factor(if use)
   Margin Level = Measurement Value Limit Value

#### **4.2 TEST PROCEDURES**


- a. The EUT was placed 0.8 meters from the horizontal ground plane with EUT being connected to the power mains through a line impedance stabilization network (LISN). All other support equipments powered from additional LISN(s). The LISN provide 50 Ohm/ 50uH of coupling impedance for the measuring instrument.
- b. Interconnecting cables that hang closer than 40 cm to the ground plane shall be folded back and forth in the center forming a bundle 30 to 40 cm long.
- c. I/O cables that are not connected to a peripheral shall be bundled in the center. The end of the cable may be terminated, if required, using the correct terminating impedance. The overall length shall not exceed 1 m.
- d. LISN at least 80 cm from nearest part of EUT chassis.
- e. For the actual test configuration, please refer to the related Item -EUT Test Photos.

#### NOTE:

- a. Reading in which marked as Peak, QP or AVG means measurements by using are Quasi-Peak or Average Mode with Detector BW=9 kHz (6 dB Bandwidth).
- b. All readings are Peak Mode value unless otherwise stated QP or AVG in column of Note. If the Peak or QP Mode Measured value compliance with the QP Limits and lower than AVG Limits, the EUT shall be deemed to meet both QP & AVG Limits and then only Peak or QP Mode was measured, but AVG Mode didn't perform.



#### **4.3 TEST SETUP LAYOUT**



#### 4.4 DEVIATION FROM TEST STANDARD

No deviation

#### 4.5 EUT OPERATING CONDITIONS

The EUT used during radiated and/or conducted emission measurement was designed to exercise in a manner similar to a typical use.

Temperature: 24°C Relative Humidity: 59%

#### 4.6 TEST RESULTS

Please refer to the Attachment A.

Report No.: BTL-FCCP-1-1412C180 Page 13 of 29



#### **5 RADIATED EMISSION**

#### 5.1 LIMITS

FCC Part 15.209								
Frequency	Field Streng Limitation	•	Field Strength Limitation at 3m Measurement Dist					
(MHz)	(uV/m)	Dist	(uV/m)	(dBuV/m)				
0.009 - 0.490	2400 / F(KHz)	300m	10000 * 2400/F(KHz)	20log 2400/F(KHz) + 80				
0.490 - 1.705	24000 / F(KHz)	30m	100 * 24000/F(KHz)	20log 24000/F(KHz) + 40				
1.705 – 30.00	30	30m	100* 30	20log 30 + 40				
30.0 – 88.0	100	3m	100	20log 100				
88.0 – 216.0	150	3m	150	20log 150				
216.0 – 960.0	200	3m	200	20log 200				
Above 960.0	500	3m	500	20log 500				

#### NOTE:

- (1) The tighter limit shall apply at the boundary between two frequency range.
- (2) Limitation expressed in dBuV/m is calculated by 20log Emission Level (uV/m).
- (3) If measurement is made at 3m distance, then F.S Limitation at 3m distance is adjusted by using the formula of  $L_{d1} = L_{d2} * (d_2/d_1)^2$ .

Example:

F.S Limit at 30m distance is 30uV/m , then F.S Limitation at 3m distance is adjusted as  $L_{d1}=L_{1}=30uV/m^{*}$  (10) $^{2}=100^{*}$  30 uV/m

(4) The test result calculated as following:

Measurement Value = Reading Level + Correct Factor

Correct Factor = Insertion Loss + Cable Loss + Attenuator Factor(if use)

Margin Level = Measurement Value - Limit Value

Report No.: BTL-FCCP-1-1412C180



#### **5.2 TEST PROCEDURE**

- a. The measuring distance of at 3 m shall be used for measurements at frequency up to 1GHz. For frequencies above 1GHz, any suitable measuring distance may be used.
- b. The EUT was placed on the top of a rotating table 0.8 meters above the ground at a 3m or 10 meter open area test site. The table was rotated 360 degrees to determine the position of the highest radiation.
- c. The height of the equipment or of the substitution antenna shall be 0.8 m; the height of the test antenna shall vary between 1 m to 4 m. Both horizontal and vertical polarizations of the antenna are set to make the measurement.
- d. The initial step in collecting radiated emission data is a spectrum analyzer peak detector mode pre-scanning the measurement frequency range. Significant peaks are then marked and then Quasi Peak detector mode re-measured.
- e. If the Peak Mode measured value compliance with and lower than Quasi Peak Mode Limit, the EUT shall be deemed to meet QP Limits and then no additional QP Mode measurement performed.
- f. For the actual test configuration, please refer to the related Item –EUT Test Photos.

#### NOTE:

- a. Reading in which marked as QP or Peak means measurements by using are Quasi-Peak Mode with Detector BW=120 kHz.
- b. All readings are Peak unless otherwise stated QP in column of Note. Peak denotes that the Peak reading compliance with the QP Limits and then QP Mode measurement didn't perform.
- c. new battery is used during all test
- d. The EUT was pre-tested on positioned of each 3 axis. The worst case was found positioned on X-plane. Therefore only the test data of this X-plane was used for radiated emission measurement test.


#### 5.3 DEVIATION FROM TEST STANDARD

No deviation


Report No.: BTL-FCCP-1-1412C180 Page 15 of 29



#### **5.4 TEST SETUP**



#### 30MHz-1GHz



### 5.5 EUT OPERATING CONDITIONS

The EUT tested system was configured as the statements of 4.1.5 Unless otherwise a special operating condition is specified in the follows during the testing.

Below 30MHz:

Temperature: 22°C Relative Humidity: 61%

30MHz-1GHz:

Temperature: 25°C Relative Humidity: 54%

#### 5.6 TEST RESULTS (BELOW 30MHz)

Please refer to the Attachment B.

Report No.: BTL-FCCP-1-1412C180 Page 16 of 29



5.7 TEST RESULTS (30MHz-1GHz)	
Please refer to the Attachment C.	

Report No.: BTL-FCCP-1-1412C180



#### 6. 20dB SPECTRUM BANDWIDTH MEASUREMENT


#### **6.1. LIMIT OF 20DB BANDWIDTH MEASUREMENT**

The 20dB bandwidth shall be specified in operating frequency band.

#### **6.2.TEST PROCEDURES**

The bandwidth of the fundamental frequency was measured by spectrum analyzer with 10kHz RBW and 10kHz VBW. The 20dB bandwidth is defined as the total spectrum the power of which is higher than peak power minus 20dB.

#### **6.3. TEST SETUP LAYOUT**



#### **6.4. TEST DEVIATION**

There is no deviation with the original standard.

#### **6.5. EUT OPERATION DURING TEST**

The EUT was programmed to be in continuously transmitting mode.

#### 6.6. TEST RESULT

Please refer to the Attachment D.

Report No.: BTL-FCCP-1-1412C180 Page 18 of 29



## 7 MEASUREMENT INSTRUMENTS LIST

	Radiated Emission Measurement Instruments List								
Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until				
1	Antenna	Schwarbeck	VULB9160	9160-3232	Mar. 29, 2015				
2	Amplifier	HP	8447D	2944A09673	Mar. 29, 2015				
3	Receiver	AGILENT	N9038A	MY52130039	Sep. 30, 2015				
4	Test Cable	N/A	C-01_CB03	N/A	Jul. 01, 2015				
5	Controller	СТ	SC100	N/A	N/A				
6	Active Loop Antenna	R&S	HFH2-Z2	830749/020	Mar. 29, 2015				
7	EMI Test Receiver	R&S	ESCI	100895	Mar. 29, 2015				
8	Measurement Software	Farad	EZ-EMC Ver.NB-03A1-0 1	N/A	N/A				

	20dB Bandwidth Measurement							
Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until			
1	Spectrum Analyzer	R&S	FSP 40	100185	Oct. 22, 2015			

Report No.: BTL-FCCP-1-1412C180 Page 19 of 29




# **8 EUT TEST PHOTO**

# Radiated emission test photos

Below 30MHz





Report No.: BTL-FCCP-1-1412C180 Page 20 of 29



# Radiated emission test photos 30MHz-1G





Report No.: BTL-FCCP-1-1412C180 Page 21 of 29



# **ATTACHMENT A - CONDUCTED EMISSION**

**Test Mode: N/A** 

Note: "N/A" denotes test is not applicable to this device.

Report No.: BTL-FCCP-1-1412C180 Page 22 of 29



ATTACHMENT B - RADIATED EMISSION (BELOW 30MHz)

Report No.: BTL-FCCP-1-1412C180 Page 23 of 29



Test Voltage:	DC 3V
Test Mode:	TX Mode

Freq.	Ant.	Reading(RA)	Corr.Factor(CF)	Measured(FS)	Limits	Margin	Note
(MHz)	0°/90°	(dBuV)	(dB)	(dBuV/m)	(dBuV/m)	(dB)	11010
0.0135	0°	1.35	24.30	25.65	125.00	-99.35	AVG
0.0135	0°	7.15	24.30	31.45	145.00	-113.55	PEAK
0.1200	0°	20.26	21.08	41.34	106.02	-64.68	AVG
0.1200	0°	27.61	21.08	48.69	126.02	-77.33	PEAK
0.2400	0°	10.28	20.42	30.70	100.00	-69.30	AVG
0.2400	0°	15.37	20.42	35.79	120.00	-84.21	PEAK
0.1100	0°	3.99	21.24	25.23	106.78	-81.55	AVG
0.1100	0°	9.02	21.24	30.26	126.78	-96.52	PEAK
0.4986	0°	17.36	19.80	37.16	73.65	-36.49	QP
1.7367	0°	19.87	19.53	39.40	69.54	-30.14	QP


Freq.	Ant.	Reading(RA)	Corr.Factor(CF)	Measured(FS)	Limits	Margin	Note
(MHz)	0°/90°	(dBuV)	(dB)	(dBuV/m)	(dBuV/m)	(dB)	
0.0112	90°	2.53	24.30	26.83	126.62	-99.79	AVG
0.0112	90°	8.01	24.30	32.31	146.62	-114.31	PEAK
0.1203	90°	19.35	21.08	40.43	106.00	-65.57	AVG
0.1203	90°	25.64	21.08	46.72	126.00	-79.28	PEAK
0.2420	90°	8.53	20.42	28.95	99.93	-70.98	AVG
0.2420	90°	14.16	20.42	34.58	119.93	-85.35	PEAK
0.1100	90°	2.36	21.24	23.60	106.78	-83.18	AVG
0.1100	90°	8.12	21.24	29.36	126.78	-97.42	PEAK
0.4974	90°	17.45	19.81	37.26	73.67	-36.41	QP
1.7685	90°	18.63	19.52	38.15	69.54	-31.39	QP

#### Remark

- (1) The amplitude of spurious emissions which are attenuated by more than 20 dB below the permissible value has no need to be reported.
- (2) Distance extrapolation factor = 40 log (specific distance / test distance) (dB);.
- (3) Limit line = specific limits (dBuV) + distance extrapolation factor..

Report No.: BTL-FCCP-1-1412C180 Page 24 of 29






Report No.: BTL-FCCP-1-1412C180 Page 25 of 29



Test Voltage	DC 3V
Test Mode	120 KHz Transmit

#### **Polarization: Vertical**




No.	Mk	. Freq.	Reading Level	Correct Factor	Measure- ment	Limit	Over			
		MHz	dBuV	dB	dBuV/m	dBuV/m	dB	Detector	Comment	
1		62.9800	36.30	-23.17	13.13	40.00	-26.87	peak		
2		115.3600	35.04	-22.19	12.85	43.50	-30.65	peak		
3		155.1300	33.91	-21.94	11.97	43.50	-31.53	peak		
4		371.4400	29.21	-13.31	15.90	46.00	-30.10	peak		
5		580.9600	29.71	-9.24	20.47	46.00	-25.53	peak		
6	*	725.4900	29.41	-6.30	23.11	46.00	-22.89	peak		

Report No.: BTL-FCCP-1-1412C180 Page 26 of 29



Test Voltage	DC 3V
Test Mode	120 KHz Transmit

#### **Polarization: Horizontal**



No.	Mk	. Freq.	Reading Level	Correct Factor	Measure- ment	Limit	Over		
-		MHz	dBuV	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1		62.9800	34.25	-23.17	11.08	40.00	-28.92	peak	
2		321.9700	29.02	-15.23	13.79	46.00	-32.21	peak	
3		413.1500	28.69	-13.22	15.47	46.00	-30.53	peak	
4		534.4000	28.97	-10.65	18.32	46.00	-27.68	peak	
5		699.3000	29.46	-6.31	23.15	46.00	-22.85	peak	
6	*	858.3800	29.06	-4.84	24.22	46.00	-21.78	peak	

Report No.: BTL-FCCP-1-1412C180 Page 27 of 29




ATTACHMENT D - 20dB SPEC MEASUREMI	

Report No.: BTL-FCCP-1-1412C180 Page 28 of 29



**Test Mode: TX Mode** 

Frequency	20dB Bandwidth	99% OBW	Test Result
(kHz)	(kHz)	(kHz)	
120	6.320	8.200	Complies



Report No.: BTL-FCCP-1-1412C180 Page 29 of 29