


# USER MANUAL

## M100

### About Your Headset

**Talk Time:** 6hs  
**Music Time:** 6hs  
**Standby Time:** 120hs  
**Bluetooth Version:** 4.1  
**Profile:** AVRCP/A2DP/HSP/HFP  
**Chip:** CSR  
**Technology:** CVC noise reduction  
**Operation Distance:** 10m  
**Weight:** 10g

1. charge port
2. multi-function button
3. power on/ off
4. volume +/-
5. led indicator
6. built-in microphone



#### Charging power attention

1. Please use the original charger.
2. Please do not use it when you charging the headset

#### Volume control

UP/down :press once, the volume go down or up a little

#### Music control

Last track: press up button for three seconds  
Next track: press down button for three seconds

#### Indicator Shows:

Pairing: blue and red light flash  
Turn off: red light flash  
Call coming: blue light flash continuously, then headset report the coming phone number  
Charging : Red light is on when charging, it goes out after a full charge, and blue light is on

#### Use of Multi-functional Button:

Take or end a call control (tap once)  
Reject call (tap twice)  
Play/pause songs (tap once)  
Enter pairing mode (press for 5 seconds)  
Manually connect the lost connection (tap once)

### Before Using the Bluetooth Headset

Carefully read the instructions, understand the various functions of the headset button, make sure the Bluetooth headset has power, charged before first use at least 1 hour.

#### Enters Pairing Mode:

1. When first use the headset, turn on and then step onto pairing mode, you can pair the headset with your phone settings now. Once lost connection or you want to pair a new phone. Need to press the function key for 5 seconds to enter pairing mode again.
2. Turn off other Bluetooth devices to avoid interference.

#### Paired with Phones :

1. Turn on the Bluetooth device on your phone, then use your phone to add / search / discover new Bluetooth devices
2. Bluetooth devices will be displayed on the phone, select and press "M100". If required a password, enter "0000", you can see the "-----" on the screen
3. Different phones have different settings menu

Iphone: setting> general> bluetooth> turn on

Smart phones : setting> options> bluetooth : turn on> search device

#### Connect the mobile phone profiles

After paired, you can make the selection, connect with profiles "Call audio" and "Media Audio" from the paired Bluetooth devices list (the model you paired -settings -profiles selection)

#### Bluetooth control the mobile phone calls

When the call coming, short press is answer the call, long press 2 minutes is reject the call, after answer the call, then short press is end the call

#### Multi-point Connection:

1. Open Bluetooth headset and pair with the first phone A
2. Open the Bluetooth of second phone B, hold on the MFB button of headset until flash red and blue light alternately and then connect with phone B.
3. Re-turn on Bluetooth headset, then the headset paired with two phones(some phones need to tap once the connect of phone A)



### APP Appliance (APP Only Support Phones with 4.0 + Android System) :

#### I.Installation

1. Install the XJWD.APK by scan the two-dimension code
2. After installation, pull power display icon out of Widget to the desktop (if the phone don't support the function of Widget, the power display and reporting time function of headset will lost)
3. Mobile TTS voice settings : Mobile Applications -> Settings -> Language & Input -> Text-to-Speech (TTS) output. If there is no Chinese TTS engine inside the phone, you can go online to download the software, "iFly Speech + " and installation.

#### II.Function

1. Photo taking : After bluetooth headset connected with phones, click the APP icon on the desktop, double click volume keys of headset to control camera. After taking pictures, you can find the photos in the folder DCIM / Camera file.
2. Voice report time function: In the main screen or black screen mode, double click the volume keys remote control of headset, then headset will report the current time of phones.
3. Power display: pull the power display icon out of widget, then the power can be display.
4. Read Out SMS  
When a new SMS is received, the headset can automatically report the name of message sender and the content of SMS, if can't find the sender name in contacts, the headset will report the phone number.(Some phones have to turn on the automatically report function in setting, for example, setting<< smart voice )

#### III. The TTS Software Installation ( iFly Speech + )

1. Mobile application market -> Search " iFly Speech + " Click to download.
2. Set APK Language: APP language is according with the system language ( Chinese or English )

#### Sound Tips:

When the Bluetooth headset beyond the effective distance, headset beeps or lose connection. When the Bluetooth headset power is low, the headset beeps.

#### Re-connect:

When beyond the effective range, the headset will loss the connection. When step into the effective range, press the MFB button once or click the connection of Bluetooth device of phone

#### Redial:

When headset is standby, press MFB button twice, it will redial the last call number.

## FCC Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:  
-- Reorient or relocate the receiving antenna.  
-- Increase the separation between the equipment and receiver.  
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.  
-- Consult the dealer or an experienced radio/TV technician for help

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation