

EMISSIONS TEST REPORT

Report Number: 102085252BOX-001c Project Number: G102085252

Report Issue Date: 6/05/2015

Product Designation: Modular Device (RF Card)

Standards: FCC 47CFR Part 15 Subpart C Section 15.231 (2015)

RSS-210 Issue 8 December 2010 RSS-Gen Issue 4 November 2014 ICES-003 Issue 5 August 2012

Tested by:
Intertek Testing Services NA, Inc.
70 Codman Hill Road
Boxborough, MA 01719
USA

Client: IntelliSAW 100 Burtt Road Andover, MA 01810 USA

Report prepared by

Report reviewed by

Vathana Ven / Staff Engineer, EMC

Michael F. Murphy / Sr. Staff Engineer, EMC

This report is for the exclusive use of Intertek's Client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this report. Only the Client is authorized to permit copying or distribution of this report and then only in its entirety. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek. The observations and test results in this report are relevant only to the sample tested. This report by itself does not imply that the material, product, or service is or has ever been under an Intertek certification program.

1 **Introduction and Conclusion**

The tests indicated in section 2.0 were performed on the product constructed as described in section 4.0. The remaining test sections are the verbatim text from the actual data sheets used during the investigation. These test sections include the test name, the specified test Method, a list of the actual Test Equipment Used, documentation Photos, Results and raw Data. No additions, deviations, or exclusions have been made from the standard(s) unless specifically noted.

Based on the results of our investigation, we have concluded the product tested Comply with the requirements of the standard(s) indicated. The results obtained in this test report pertain only to the item(s) tested.

2 **Test Summary**

Section	Test full name	Result
3	Client Information	
4	Description of Equipment Under Test	
5	System Setup and Method	
6	Fundamental Field Strength and Conducted Output Power (CFR47 Part 15 Subpart C Section 15.231(e), RSS-210 Annex I)	Pass
7	Occupied Bandwidth (CFR47 Part 15 Subpart C Sections 15.215, 15.231(c), RSS-Gen Section 6.6)	Pass
8	Radiated Spurious Emissions (CFR47 Part 15 Subpart C Sections 15.205, 15.209, and 15.231(e), RSS-210 Annex I, RSS-Gen)	Pass
9	Duty Cycle (CFR47 Part 15 Section 15.35 and Subpart C Section 15.231(b)(2), RSS-Gen Section 6.10)	Pass
10	Automatically Limiting Operation (CFR47 Part 15 Subpart C Section 15.231(e), RSS-210 A1.1.5)	Pass
11	AC Line-Conducted Emissions (CFR47 FCC Part 15 Subpart C 15.207, ICES-003)	Pass
12	Receiver Radiated Spurious Emissions (CFR47 Part 15 Subpart B Sections 15.205, 5.209, ICES-003)	Pass
13	Revision History	-

Non-Specific EMC Report Shell Rev. May 2014 Page 2 of 110

3 **Client Information**

This EUT was tested at the request of:

Client: IntelliSAW

> 100 Burtt Road Andover, MA 01810

USA

Contact: Jonathan P. Murray Telephone: +1.978.409.1534 x204 Email: jmurray@intellisaw.com

Description of Equipment Under Test

Manufacturer: IntelliSAW

> 100 Burtt Road Andover, MA 01810

USA

Equipment Under Test						
Description	Manufacturer	Model Number	Serial Number			
Modular Device (RF Card)	IntelliSAW	400.00152.0001	08150695			

Receive Date:	04/09/2015 & 06/01/2015
Received Condition:	Good
Type:	Production

Description of Equipment Under Test (provided by client)

The IntelliSAW RF card is a circuit board assembly integral to multiple current and future products. It is not sold to third parties and is therefore eligible for certain exceptions as a Limited Modular Approval. The module was tested with a PIFA patch antenna and a 17 cm monopole antenna.

400.00152.0001 (ASSEMBLY, INTERROGATOR RF BOARD, PARTIAL DISCHARGE, SMA)

Equipment Under Test Power Configuration							
Rated Voltage Rated Current Rated Frequency Number of Phase							
	IntelliSAW RF Module						
4.3 to 5.5 Vdc	500 mA	N/A	N/A				
IS485 host equipment							
24 Vdc	125 mA	N/A	N/A				

Notes: All tests except CEMI – Cotek 80 ~ 265 Vac/dc class II power supply (meets class A CEMI) CEMI test of module: Agilent E3620 120Vac variable DC supply. Module-only, 5 Vdc; IS485 host unit 24 Vdc.

Operating modes of the EUT:

No.	Descriptions of EUT Exercising
1	The EUT was programmed to transmit between 425-445 MHz with a 100% duty cycle. Lab tests – TX power at operating limits of the hardware for all spurious emissions Site field test – +6.5 dBm conducted power limited by setting PA = 7 and PPS = 8
2	Device was in Rx/idle mode

Non-Specific EMC Report Shell Rev. May 2014 Page 3 of 110

Software used by the EUT:

Ī	No.	Descriptions of EUT Exercising
	1	None
ſ	•	

System Setup and Method


	Cables							
ID	Description	Length (m)	Shielding	Ferrites	Termination			
1	Two DC wires	10m	N/A	N/A	24VDC supply			

Support Equipment						
Description	Manufacturer	Model Number	Serial Number			
24 VDC Class II power supply	PHOENIX CONTAC	UNO- PS/1AC/24DC/100W	3039923677			
RS-45 converter	SerialGrear	USBG-COMi-SI-M	239694			
Host device	IntelleSaw	IS485-24-TPH	46140572			
Variable power supply	Agilent	E3620A	MY40005590			

5.1 Method:

Configuration as required by FCC 47 CFR PT 15.231(e), ANSI C63.10:2009, ICES-003, RSS-Gen, RSS-210.

5.2 EUT Block Diagram (Intertek Lab)



5.3 **National Grid**

The Nasonville Substation in Burrillville, RI comprises one ANSI/IEEE C37.20 outdoor switchgear, representing a typical installation under FCC Part 15.201(c) and FCC Part 15.31(d). The site has safety constraints due to overhead high voltage equipment. These concerns prevent measurements along several radials, as outlined below.

Fifteen safe measurement locations were chosen that allow measurement of 15 of the 16 radials. This

Client: IntelliSAW, Product Designation: Modular Device (RF Card)

report details measurements of this switchgear, a 1980 installation of ABB equipment.




Figure 1 shows the measurement locations and safety concerns of the site.

For this test site, radials SE (135°) cannot be measured within an acceptable radial distance because of serious safety concerns. The presence of overhead 115kV lines prevent the use of a 4.5 meter tall mast structure due to risk of electrocution. The remaining 15 radials will be made between 3 and 10 meters, as needed to avoid obstacles.

System passed with a nominal conducted power of 6.5dBm (PA = 7, PPS = 8). Settings PA=7, PPS=8 are found to be compliant over all locations.

PPS	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
PA=0	-13.43	-13	-12.26	-11.4	-11.2	-10.5	-9.44	-8.8	-8.8	-8.06	-7.8	-7.63	-7.26	-7.36	-7.2	-7.06
PA=1	-10.57	-10.3	-9.3	-8.5	-8.2	-7.45	-6.4	-5.61	-5.61	-4.85	-4.45	-4.2	-3.96	-3.92	-3.8	-3.67
PA=2	-8.08	-7.6	-6.77	-6	-5.7	-4.52	-3.75	-2.88	-2.88	-2	-1.57	-1.22	-0.9	-0.79	-0.66	-0.5
PA=3	-5.79	-5.2	-4.44	-3.6	-3.3	-2.47	-1.4	-0.5	-0.5	0.46	1	1.42	1.81	1.94	2.07	2.28
PA=4	-3.86	-3.2	-2.47	-1.7	-1.27	-0.45	0.7	1.64	1.64	2.62	3.26	3.74	4.15	4.43	4.64	4.84
PA=5	-2.17	-1.55	-0.8	0	0.44	1.31	2.5	3.46	3.46	4.52	5.2	5.82	6.41	6.7	6.95	7.32
PA=6	-0.67	-0.12	0.7	1.5	1.9	2.8	4	5.02	5.02	5.18	6.9	7.57	8.25	8.66	9.02	9.43
PA=7	0.58	1.21	2	2.8	3.26	4.14	5.4	6.48	6.5	7.66	8.44	9.15	9.94	10.31	10.71	11.33

The 17cm monopole with nominal gain 3.2 dBi is mounted on the left wall of a cable compartment (right photo, red outline). The grounding cables are removed after servicing before energizing the system. The PIFA antenna with a nominal gain of 3.5 dBi is located on the door of the switchgear, facing inwards.

Page 5 of 110 Client: IntelliSAW, Product Designation: Modular Device (RF Card)





Figure 1 shows the two antennas, mounted to optimally read the passive sensors.

The selected antenna positions are optimal for measuring the passive sensors in typical locations. The primary radiation sources outside the switchgear will be the door seal and the louvered ventilation slots. The ventilation slots are covered with a metal mesh filter, already installed in the picture above. In most cases this filter is present.



Figure 2 shows cabinet 127W44 in the lineup of the switchgear.




Figure 3 shows an internal view of the digital device hosting the transmitter (red outline), which is located in a secured building, inside a secured enclosure integral to the switchgear.

Fundamental Field Strength and Output power

6.1 Method

Tests are performed in accordance with FCC 47 CFR PT 15.231(e), RSS-210 and ANSI C63.10:2009. Test points were selected for testing as shown in the block diagram. The receiving antenna polarity varied between vertical and horizontal. The emissions were maximized by raising receiving antenna up and down from 1 meter to 4 meters.

TEST SITE: National Grid Substation

All testing took place at Nasonville National Grid Substation in Burrillville, RI.

TEST SITE: 10m ALSE

The 10m ALSE is 13m (Length) x 21m (Depth) x 10m (Height) with the effective size in terms of space from the tips of the absorber is 12m (Length) x 20m (Depth) x 8.5m (Height). This chamber achieves broadband performance using a unique arrangement of hybrid and ferrite tile absorber. This chamber has a built in 3m diameter turntable (Embedded type). The metal structure of the table makes electrical connection around the entire circumference of the turntable to the ground plane with a metal brush type connection. The turntable is located on one end of the chamber and the antennas are mounted 3 and 10 meters away at the other end of the chamber on the adjustable an Antenna Mast. The antenna mast is a non-conductive bore sighted type with remote control of antenna height and polarization. The Antenna Mast and the turntable can be remotely controlled through the controller located in the adjacent Control room. A wooden table 80 cm high is used for table-top equipment.

Measurement Uncertainty

For radiated emissions, U_{lab} (3.5 dB at 3m and 3.5 dB at 10m below 1 GHz, and 4.2 dB at 3m above 1 GHz) < U_{CISPR} (5.2 dB), which is the reference value in CISPR 16-4-2 Table 1, hence the compliance of the product is only based on the measured value, and no measurement uncertainty correction is required, based on CISPR 22 and CISPR 11 (for 2006 and later revisions) Clause 11.

Page 8 of 110 Client: IntelliSAW, Product Designation: Modular Device (RF Card)

Sample Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

FS = RA + AF + CF - AG

Where $FS = Field Strength in dB\mu V/m$

RA = Receiver Amplitude (including preamplifier) in dBµV

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB AG = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows.

Assume a receiver reading of 52.0 dB_µV is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32 dBμV/m. This value in dB_μV/m was converted to its corresponding level in μV/m.

 $RA = 52.0 dB\mu V$ AF = 7.4 dB/mCF = 1.6 dB $AG = 29.0 \, dB$ $FS = 32 dB\mu V/m$

To convert from dB_μV to μV or mV the following was used:

UF =
$$10^{(NF/20)}$$
 where UF = Net Reading in μ V NF = Net Reading in dB μ V

Example:

FS = RA + AF + CF - AG =
$$52.0 + 7.4 + 1.6 - 29.0 = 32.0$$
 UF = $10^{(32 \, dB_{\mu}V \, / \, 20)} = 39.8 \, \mu V/m$

Non-Specific EMC Report Shell Rev. May 2014 Page 9 of 110

6.2 **Test Equipment Used**

Test equipment used on 06/01/2015

Asset	Description	Manufacturer	Model	Serial	Cal Date	Cal Due
MAN1'	Digital 4 Line Barometer	Mannix	0ABA116	MAN1	08/29/2014	08/29/2016
ANT1C'	BROADBAND ANTENNA	Compliance Design	B300	00668	11/04/2014	11/04/2015
147149'	Spectrum Analyzer	Hewlett Packard	8591E	3346A02258	07/05/2014	07/05/2015
CBLEMC3'	2" BNC Cable	Hewlett Packard	10503A	3	04/02/2015	04/02/2016

Test equipment used on 4/09/2015

Asset	Description	Manufacturer	Model	Serial	Cal Date	Cal Due
145128'	EMI Receiver (20 Hz - 40 Ghz)	Rohde & Schwarz	ESIB 40	839283/001	03/17/2014	03/17/2015
145-410'	Cables 145-400 145-403 145-405 145-406 145-407	Huber + Suhner	10m Track A Cables	multiple	10/04/2014	10/04/2015
145106'	Bilog Antenna (30MHz - 5GHz)	Sunol Sciences	JB5	A111003	10/24/2014	10/24/2015
Dav004'	Weather Station	Davis Instruments	7400	PE80529A61A	10/06/2014	10/06/2015

Software Utilized:

Name	Manufacturer	Version
EMI Boxborough.xls	Intertek	08/27/2010

6.3 Results:

The sample tested was found to Comply

(e) Intentional radiators may operate at a periodic rate exceeding that specified in paragraph (a) of this section and may be employed for any type of operation, including operation prohibited in paragraph (a) of this section, provided the intentional radiator complies with the provisions of paragraphs (b) through (d) of this section, except the field strength table in paragraph (b) of this section is replaced by the following:

Fundamental frequency (MHz)	Field strength of fundamental (microvolts/meter)	Field strength of spurious emission (microvolts/meter)
40.66-40.70	1,000	100
70-130	500	50
130-174	500 to 1,500 ¹	50 to 150 ¹
174-260	1,500	150
260-470	1,500 to 5,000 ¹	150 to 500 ¹
Above 470	5,000	500

¹Linear interpolations.

Page 10 of 110 Client: IntelliSAW, Product Designation: Modular Device (RF Card)

6.4 Setup Photographs:
































6.5 Test Data:

Position 1 Radiated Emissions at 8 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw

Antenna & Cables: N Bands: N, LF, HF, SHF

Model #: Switchgears (425 to 442 MHz)

Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 Filter: NONE

Project #: G102085252 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3
PreAmp: None Test Distance (m): 8

PreAmp Used? (Y or N): N Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS: NF = Noise Floor. RB = Restricted Band: Bandwidth denoted as RBW/VBW

Peak: F	PK Quasi-P	eak: QP Av	erage: AVG	RMS: RM	S; NF = Noise	se Floor, RE	s = Restricte	d Band; Ba	ndwidth den	oted as RB	W/VBW
	Ant.			Antenna	Cable	Pre-amp	Distance				
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB	
	Position 1	at 8 meters. C	Output Power	Setting: 6.5	dBm, AVG =	Peak Readin	gs - Average	Factor of 20	dB from 10%	6 duty cycle	
А	distance facto	or of 8.52 dB	was added t	o the reading	s (shown as	negative) to	compensate t	for testing at	8 meters inst	ead of 3 met	ers
				Reseat th	ne screen a	nd tightened	the door				
Max PK	V	434.000	48.08	21.58	0.72	0.00	-8.52	78.90	92.87	-13.97	120/300 kHz
AVG	V	434.000	28.08	21.58	0.72	0.00	-8.52	58.90	72.87	-13.96	120/300 kHz
Max PK	Н	434.000	48.97	22.34	0.72	0.00	-8.52	80.55	92.87	-12.32	120/300 kHz
AVG	Н	434.000	28.97	22.34	0.72	0.00	-8.52	60.55	72.87	-12.31	120/300 kHz
Max PK	V	445.000	40.86	23.00	0.74	0.00	-8.52	73.12	93.22	-20.10	120/300 kHz
AVG	V	445.000	20.86	23.00	0.74	0.00	-8.52	53.12	73.22	-20.11	120/300 kHz
Max PK	Н	445.000	40.28	22.20	0.74	0.00	-8.52	71.74	93.22	-21.48	120/300 kHz
AVG	Н	445.000	20.28	22.20	0.74	0.00	-8.52	51.74	73.22	-21.49	120/300 kHz
Max PK	Н	425.000	52.37	22.00	0.71	0.00	-8.52	83.60	92.57	-8.97	120/300 kHz
AVG	Н	425.000	32.37	22.00	0.71	0.00	-8.52	63.60	72.57	-8.97	120/300 kHz
Max PK	V	425.000	42.97	21.60	0.71	0.00	-8.52	73.80	92.57	-18.77	120/300 kHz
AVG	V	425.000	22.97	21.60	0.71	0.00	-8.52	53.80	72.57	-18.77	120/300 kHz

Position 2 Radiated Emissions at 8 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw

Antenna & Cables: N Bands: N, LF, HF, SHF

Model #: Switchgears (425 to 442 MHz)

Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 Filter: NONE

Project #: G102085252 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3
PreAmp: None Test Distance (m): 8

PreAmp Used? (Y or N): N Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK, Quasi-Peak: QP, Average: AVG, RMS: RMS: NF = Noise Floor, RB = Restricted Band: Bandwidth denoted as RBW/VBW

Peak: F	PK Quasi-P	eak: QP Av	erage: AVG	RMS: RM	S; NF = Noise	se Floor, RB	B = Restricte	d Band; Ba	ndwidth den	oted as RB\	W/VBW
	Ant.			Antenna	Cable	Pre-amp	Distance				
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB	
	Position 2	at 8 meters. C	Output Power	Setting: 6.5	dBm, AVG =	Peak Readin	gs - Average	Factor of 20	dB from 10%	6 duty cycle	
A	distance facto	or of 8.52 dB	was added t	o the reading	s (shown as	negative) to	compensate t	for testing at	8 meters inst	ead of 3 met	ers
				Reseat th	ne screen a	nd tightened	I the door				
Max PK	٧	434.000	42.74	21.58	0.72	0.00	-8.52	73.56	92.87	-19.31	120/300 kHz
AVG	V	434.000	22.74	21.58	0.72	0.00	-8.52	53.56	72.87	-19.30	120/300 kHz
Max PK	Ι	434.000	44.99	22.34	0.72	0.00	-8.52	76.57	92.87	-16.30	120/300 kHz
AVG	Ι	434.000	24.99	22.34	0.72	0.00	-8.52	56.57	72.87	-16.29	120/300 kHz
Max PK	V	445.000	37.50	23.00	0.74	0.00	-8.52	69.76	93.22	-23.46	120/300 kHz
AVG	V	445.000	17.50	23.00	0.74	0.00	-8.52	49.76	73.22	-23.47	120/300 kHz
Max PK	Ι	445.000	46.63	22.20	0.74	0.00	-8.52	78.09	93.22	-15.13	120/300 kHz
AVG	Ι	445.000	26.63	22.20	0.74	0.00	-8.52	58.09	73.22	-15.14	120/300 kHz
Max PK	Ι	425.000	48.11	22.00	0.71	0.00	-8.52	79.34	92.57	-13.23	120/300 kHz
AVG	Η	425.000	28.11	22.00	0.71	0.00	-8.52	59.34	72.57	-13.23	120/300 kHz
Max PK	V	425.000	45.25	21.60	0.71	0.00	-8.52	76.08	92.57	-16.49	120/300 kHz
AVG	V	425.000	25.25	21.60	0.71	0.00	-8.52	56.08	72.57	-16.49	120/300 kHz

Position 3 Radiated Emissions at 8 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw

Antenna & Cables: N Bands: N, LF, HF, SHF

Model #: Switchgears (425 to 442 MHz)

Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 Filter: NONE

Project #: G102085252 Date(s): 06/02/15

425.000

17.64

21.60

0.71

AVG

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3
PreAmp: None Test Distance (m): 8

PreAmp Used? (Y or N): N Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: F	^o K Quasi-P	eak: QP Av	erage: AVG	RMS: RM	S; NF = Noi:	se Floor, RE	B = Restricte	ed Band; Ba	ndwidth den	oted as RB	W/VBW
	Ant.			Antenna	Cable	Pre-amp	Distance				
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB	
	Position 3	at 8 meters. C	Output Power	Setting: 6.5	dBm, AVG =	Peak Readin	gs - Average	Factor of 20	dB from 10%	6 duty cycle	
A	distance facto	or of 8.52 dB	was added t	o the reading	ıs (shown as	negative) to	compensate	for testing at	8 meters inst	ead of 3 met	ers
				Reseat tl	ne screen a	nd tightened	I the door				
Max PK	٧	434.000	39.14	21.58	0.72	0.00	-8.52	69.96	92.87	-22.91	120/300 kHz
AVG	٧	434.000	19.14	21.58	0.72	0.00	-8.52	49.96	72.87	-22.90	120/300 kHz
Max PK	Η	434.000	44.85	22.34	0.72	0.00	-8.52	76.43	92.87	-16.44	120/300 kHz
AVG	Η	434.000	24.85	22.34	0.72	0.00	-8.52	56.43	72.87	-16.43	120/300 kHz
Max PK	V	445.000	37.00	23.00	0.74	0.00	-8.52	69.26	93.22	-23.96	120/300 kHz
AVG	>	445.000	17.00	23.00	0.74	0.00	-8.52	49.26	73.22	-23.97	120/300 kHz
Max PK	Η	445.000	37.96	22.20	0.74	0.00	-8.52	69.42	93.22	-23.80	120/300 kHz
AVG	Η	445.000	17.96	22.20	0.74	0.00	-8.52	49.42	73.22	-23.81	120/300 kHz
Max PK	Η	425.000	46.17	22.00	0.71	0.00	-8.52	77.40	92.57	-15.17	120/300 kHz
AVG	Ι	425.000	26.17	22.00	0.71	0.00	-8.52	57.40	72.57	-15.17	120/300 kHz
Max PK	V	425.000	37.64	21.60	0.71	0.00	-8.52	68.47	92.57	-24.10	120/300 kHz

0.00

48.47

-8.52

72.57

-24.10

120/300 kHz

Position 4 Radiated Emissions at 8 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw

Antenna & Cables: N Bands: N, LF, HF, SHF

Model #: Switchgears (425 to 442 MHz)

Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 Filter: NONE

Project #: G102085252 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3
PreAmp: None Test Distance (m): 8

PreAmp Used? (Y or N): N Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS: NF = Noise Floor. RB = Restricted Band: Bandwidth denoted as RBW/VBW

Peak: F	'N Quasi-P	eak: QP Av	erage: AvG	KINS: KINS	5; $NF = NOS$	se Floor, RE	= Restricte	a Bana; Bai	nawiath aen	oted as RB	W/VBW
	Ant.			Antenna	Cable	Pre-amp	Distance				
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB	
	Position 4	at 8 meters. C	Output Power	Setting: 6.5	dBm, AVG =	Peak Readin	gs - Average	Factor of 20	dB from 10%	duty cycle	
A	distance facto	or of 8.52 dB	was added t	o the reading	s (shown as	negative) to	compensate t	for testing at	8 meters inst	ead of 3 met	ers
				Reseat th	ne screen a	nd tightened	the door				
Max PK	V	434.000	44.64	21.58	0.72	0.00	-8.52	75.46	92.87	-17.41	120/300 kHz
AVG	V	434.000	24.64	21.58	0.72	0.00	-8.52	55.46	72.87	-17.40	120/300 kHz
Max PK	Н	434.000	40.79	22.34	0.72	0.00	-8.52	72.37	92.87	-20.50	120/300 kHz
AVG	Н	434.000	20.79	22.34	0.72	0.00	-8.52	52.37	72.87	-20.49	120/300 kHz
Max PK	V	445.000	40.65	23.00	0.74	0.00	-8.52	72.91	93.22	-20.31	120/300 kHz
AVG	V	445.000	20.65	23.00	0.74	0.00	-8.52	52.91	73.22	-20.32	120/300 kHz
Max PK	Н	445.000	38.92	22.20	0.74	0.00	-8.52	70.38	93.22	-22.84	120/300 kHz
AVG	Н	445.000	18.92	22.20	0.74	0.00	-8.52	50.38	73.22	-22.85	120/300 kHz
Max PK	Ι	425.000	46.20	22.00	0.71	0.00	-8.52	77.43	92.57	-15.14	120/300 kHz
AVG	Ι	425.000	26.20	22.00	0.71	0.00	-8.52	57.43	72.57	-15.14	120/300 kHz
Max PK	V	425.000	42.00	21.60	0.71	0.00	-8.52	72.83	92.57	-19.74	120/300 kHz
AVG	V	425.000	22.00	21.60	0.71	0.00	-8.52	52.83	72.57	-19.74	120/300 kHz

Position 5 Radiated Emissions at 8 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw

Antenna & Cables: N Bands: N, LF, HF, SHF

Model #: Switchgears (425 to 442 MHz)

Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 Filter: NONE

Project #: G102085252 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3
PreAmp: None Test Distance (m): 8

PreAmp Used? (Y or N): N Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS: NF = Noise Floor. RB = Restricted Band: Bandwidth denoted as RBW/VBW

Peak: F	'N Quasi-P	eak: QP Av	erage: AvG	KIVIS: KIVIS	5; $NF = NOS$	se Floor, RE	= Restricte	a Bana; Bai	nawiath den	oted as RB	VV/VBVV
	Ant.			Antenna	Cable	Pre-amp	Distance				
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB	
	Position 5	at 8 meters. C	Output Power	Setting: 6.5	dBm, AVG =	Peak Readin	gs - Average	Factor of 20	dB from 10%	duty cycle	
A	distance facto	or of 8.52 dB	was added t	o the reading	s (shown as	negative) to	compensate t	for testing at	8 meters inst	ead of 3 met	ers
				Reseat th	ne screen a	nd tightened	the door				
Max PK	V	434.000	38.20	21.58	0.72	0.00	-8.52	69.02	92.87	-23.85	120/300 kHz
AVG	V	434.000	18.20	21.58	0.72	0.00	-8.52	49.02	72.87	-23.84	120/300 kHz
Max PK	Н	434.000	44.40	22.34	0.72	0.00	-8.52	75.98	92.87	-16.89	120/300 kHz
AVG	Н	434.000	24.40	22.34	0.72	0.00	-8.52	55.98	72.87	-16.88	120/300 kHz
Max PK	V	445.000	34.26	23.00	0.74	0.00	-8.52	66.52	93.22	-26.70	120/300 kHz
AVG	V	445.000	14.26	23.00	0.74	0.00	-8.52	46.52	73.22	-26.71	120/300 kHz
Max PK	Н	445.000	40.95	22.20	0.74	0.00	-8.52	72.41	93.22	-20.81	120/300 kHz
AVG	Н	445.000	20.95	22.20	0.74	0.00	-8.52	52.41	73.22	-20.82	120/300 kHz
Max PK	Н	425.000	46.10	22.00	0.71	0.00	-8.52	77.33	92.57	-15.24	120/300 kHz
AVG	Ι	425.000	26.10	22.00	0.71	0.00	-8.52	57.33	72.57	-15.24	120/300 kHz
Max PK	V	425.000	35.97	21.60	0.71	0.00	-8.52	66.80	92.57	-25.77	120/300 kHz
AVG	V	425.000	15.97	21.60	0.71	0.00	-8.52	46.80	72.57	-25.77	120/300 kHz

Position 6 Radiated Emissions at 8 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw

Antenna & Cables: N Bands: N, LF, HF, SHF

Model #: Switchgears (425 to 442 MHz)

Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 Filter: NONE

Project #: G102085252 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3
PreAmp: None Test Distance (m): 8

PreAmp Used? (Y or N): N Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK, Quasi-Peak: QP, Average: AVG, RMS: RMS: NF = Noise Floor, RB = Restricted Band: Bandwidth denoted as RBW/VBW

Peak: F	PK Quasi-P	eak: QP Av	erage: AVG	RMS: RM	S; NF = Noise	se Floor, RB	B = Restricte	d Band; Ba	ndwidth den	oted as RB\	W/VBW
	Ant.			Antenna	Cable	Pre-amp	Distance				
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB	
	Position 6	at 8 meters. C	Output Power	Setting: 6.5	dBm, AVG =	Peak Readin	gs - Average	Factor of 20	dB from 10%	6 duty cycle	
A	distance facto	or of 8.52 dB	was added t	o the reading	s (shown as	negative) to	compensate t	for testing at	8 meters inst	ead of 3 met	ers
				Reseat tl	ne screen a	nd tightened	I the door				
Max PK	٧	434.000	37.90	21.58	0.72	0.00	-8.52	68.72	92.87	-24.15	120/300 kHz
AVG	V	434.000	17.90	21.58	0.72	0.00	-8.52	48.72	72.87	-24.14	120/300 kHz
Max PK	Ι	434.000	40.44	22.34	0.72	0.00	-8.52	72.02	92.87	-20.85	120/300 kHz
AVG	Ι	434.000	20.44	22.34	0.72	0.00	-8.52	52.02	72.87	-20.84	120/300 kHz
Max PK	V	445.000	34.68	23.00	0.74	0.00	-8.52	66.94	93.22	-26.28	120/300 kHz
AVG	٧	445.000	14.68	23.00	0.74	0.00	-8.52	46.94	73.22	-26.29	120/300 kHz
Max PK	Ι	445.000	36.72	22.20	0.74	0.00	-8.52	68.18	93.22	-25.04	120/300 kHz
AVG	Ι	445.000	16.72	22.20	0.74	0.00	-8.52	48.18	73.22	-25.05	120/300 kHz
Max PK	Ι	425.000	43.00	22.00	0.71	0.00	-8.52	74.23	92.57	-18.34	120/300 kHz
AVG	Ι	425.000	23.00	22.00	0.71	0.00	-8.52	54.23	72.57	-18.34	120/300 kHz
Max PK	V	425.000	41.96	21.60	0.71	0.00	-8.52	72.79	92.57	-19.78	120/300 kHz
AVG	V	425.000	21.96	21.60	0.71	0.00	-8.52	52.79	72.57	-19.78	120/300 kHz

Position 7 Radiated Emissions at 13.106 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw

Antenna & Cables: N Bands: N, LF, HF, SHF

Model #: Switchgears (425 to 442 MHz)

Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 Filter: NONE

Project #: G102085252 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3
PreAmp: None Test Distance (m): 13.106

PreAmp Used? (Y or N): N Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS: NF = Noise Floor RB = Restricted Band: Bandwidth denoted as RBW/VBW

Peak: F	PK Quasi-P	eak: QP Av	erage: AVG	RMS: RM	S; NF = Noise	se Floor, RB	B = Restricte	ed Band; Bai	ndwidth den	oted as RB\	W/VBW
	Ant.			Antenna	Cable	Pre-amp	Distance				
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB	
P	osition 7 at 1	3.106 meters	. Output Pow	er Setting: 9.	15 dBm, AV	G = Peak Rea	adings - Aver	age Factor of	20 dB from	10% duty cyc	le
A dista	ance factor o	f 12.81 dB w	as added to t	the readings	(shown as ne	gative) to co	mpensate for	testing at 13	.106 meters	instead of 3 r	neters
				Reseat th	ne screen a	nd tightened	I the door				
Max PK	V	434.000	40.19	21.58	0.72	0.00	-12.81	75.30	92.87	-17.57	120/300 kHz
AVG	V	434.000	20.19	21.58	0.72	0.00	-12.81	55.30	72.87	-17.57	120/300 kHz
Max PK	Ι	434.000	40.91	22.34	0.72	0.00	-12.81	76.78	92.87	-16.09	120/300 kHz
AVG	Ι	434.000	20.91	22.34	0.72	0.00	-12.81	56.78	72.87	-16.09	120/300 kHz
Max PK	V	445.000	38.53	23.00	0.74	0.00	-12.81	75.07	93.22	-18.15	120/300 kHz
AVG	V	445.000	18.53	23.00	0.74	0.00	-12.81	55.07	73.22	-18.15	120/300 kHz
Max PK	Ι	445.000	37.82	22.20	0.74	0.00	-12.81	73.56	93.22	-19.66	120/300 kHz
AVG	Ι	445.000	17.82	22.20	0.74	0.00	-12.81	53.56	73.22	-19.66	120/300 kHz
Max PK	Ι	425.000	42.19	22.00	0.71	0.00	-12.81	77.71	92.57	-14.86	120/300 kHz
AVG	Н	425.000	22.19	22.00	0.71	0.00	-12.81	57.71	72.57	-14.86	120/300 kHz
Max PK	V	425.000	43.61	21.60	0.71	0.00	-12.81	78.73	92.57	-13.84	120/300 kHz
AVG	V	425.000	23.61	21.60	0.71	0.00	-12.81	58.73	72.57	-13.84	120/300 kHz

Position 8 Radiated Emissions at 8 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw Antenna & Cables: Ν Bands: N, LF, HF, SHF Model #: Switchgears (425 to 442 MHz) Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 NONE Filter:

Project #: G102085252 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3 PreAmp: None Test Distance (m): 8

> PreAmp Used? (Y or N): Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS: NF = Noise Floor. RB = Restricted Band: Bandwidth denoted as RBW/VBW

Peak: F	r Quasi-P	eak: QP Av	erage: AvG	KINIS: KINIS	5; $NF = NOS$	se Floor, RE	s = Restricte	a Bana; Ba	nawiath aen	oted as RB	W/VBW
	Ant.			Antenna	Cable	Pre-amp	Distance				
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB	
	Position 8 a	it 8 meters. O	utput Power	Setting: 9.15	dBm, AVG =	Peak Readir	ngs - Average	e Factor of 20	dB from 109	% duty cycle	
A	distance facto	or of 8.52 dB	was added t	o the reading	s (shown as	negative) to	compensate	for testing at	8 meters inst	ead of 3 met	ers
				Reseat th	ne screen a	nd tightened	the door				
Max PK	V	434.000	42.69	21.58	0.72	0.00	-8.52	73.51	92.87	-19.36	120/300 kHz
AVG	V	434.000	22.69	21.58	0.72	0.00	-8.52	53.51	72.87	-19.35	120/300 kHz
Max PK	Н	434.000	43.91	22.34	0.72	0.00	-8.52	75.49	92.87	-17.38	120/300 kHz
AVG	Н	434.000	23.91	22.34	0.72	0.00	-8.52	55.49	72.87	-17.37	120/300 kHz
Max PK	V	445.000	38.48	23.00	0.74	0.00	-8.52	70.74	93.22	-22.48	120/300 kHz
AVG	V	445.000	18.48	23.00	0.74	0.00	-8.52	50.74	73.22	-22.49	120/300 kHz
Max PK	Н	445.000	42.46	22.20	0.74	0.00	-8.52	73.92	93.22	-19.30	120/300 kHz
AVG	Н	445.000	22.46	22.20	0.74	0.00	-8.52	53.92	73.22	-19.31	120/300 kHz
Max PK	Н	425.000	45.92	22.00	0.71	0.00	-8.52	77.15	92.57	-15.42	120/300 kHz
AVG	Н	425.000	25.92	22.00	0.71	0.00	-8.52	57.15	72.57	-15.42	120/300 kHz
Max PK	V	425.000	43.38	21.60	0.71	0.00	-8.52	74.21	92.57	-18.36	120/300 kHz
AVG	V	425.000	23.38	21.60	0.71	0.00	-8.52	54.21	72.57	-18.36	120/300 kHz

Page 33 of 110 Non-Specific EMC Report Shell Rev. May 2014

Client: IntelliSAW, Product Designation: Modular Device (RF Card)

Position 9 Radiated Emissions at 8 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw Antenna & Cables: Ν Bands: N, LF, HF, SHF Model #: Switchgears (425 to 442 MHz) Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 NONE Filter:

Project #: G102085252 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3 PreAmp: None Test Distance (m): 8

> PreAmp Used? (Y or N): Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

AVC DMC DMC NE Naiss Els

Peak: F	PK Quasi-P	eak: QP Av	erage: AVG	RMS: RM	S; NF = Nois	se Floor, RB	s = Restricte	d Band; Ba	ndwidth den	oted as RB	W/VBW
	Ant.			Antenna	Cable	Pre-amp	Distance				
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB	
	Position 9 a	it 8 meters. O	utput Power	Setting: 9.15	dBm, AVG =	Peak Readir	ngs - Average	e Factor of 20	dB from 109	% duty cycle	
A	distance facto	or of 8.52 dB	was added t	o the reading	ıs (shown as	negative) to	compensate	for testing at	8 meters inst	ead of 3 met	ers
				Reseat tl	ne screen a	nd tightened	I the door				
Max PK	V	434.000	45.29	21.58	0.72	0.00	-8.52	76.11	92.87	-16.76	120/300 kHz
AVG	V	434.000	25.29	21.58	0.72	0.00	-8.52	56.11	72.87	-16.75	120/300 kHz
Max PK	Ι	434.000	49.72	22.34	0.72	0.00	-8.52	81.30	92.87	-11.57	120/300 kHz
AVG	Ι	434.000	29.72	22.34	0.72	0.00	-8.52	61.30	72.87	-11.56	120/300 kHz
Max PK	٧	445.000	44.20	23.00	0.74	0.00	-8.52	76.46	93.22	-16.76	120/300 kHz
AVG	٧	445.000	24.20	23.00	0.74	0.00	-8.52	56.46	73.22	-16.77	120/300 kHz
Max PK	Н	445.000	43.72	22.20	0.74	0.00	-8.52	75.18	93.22	-18.04	120/300 kHz
AVG	Ι	445.000	23.72	22.20	0.74	0.00	-8.52	55.18	73.22	-18.05	120/300 kHz
Max PK	Ι	425.000	50.50	22.00	0.71	0.00	-8.52	81.73	92.57	-10.84	120/300 kHz
AVG	Ι	425.000	30.50	22.00	0.71	0.00	-8.52	61.73	72.57	-10.84	120/300 kHz
Max PK	V	425.000	46.95	21.60	0.71	0.00	-8.52	77.78	92.57	-14.79	120/300 kHz
AVG	V	425.000	26.95	21.60	0.71	0.00	-8.52	57.78	72.57	-14.79	120/300 kHz

Page 34 of 110 Non-Specific EMC Report Shell Rev. May 2014

Client: IntelliSAW, Product Designation: Modular Device (RF Card)

Position 10 Radiated Emissions at 8 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw

Antenna & Cables: N Bands: N, LF, HF, SHF

Model #: Switchgears (425 to 442 MHz)

Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 Filter: NONE

Project #: G102014290 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3
PreAmp: None Test Distance (m): 8

PreAmp Used? (Y or N): N Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS: NF = Noise Floor. RB = Restricted Band: Bandwidth denoted as RBW/VBW

Peak: F	'N Quasi-P	eak: QP Av	erage: AvG	KIVIS: KIVIS	5; $NF = NOS$	se Floor, RE	= Restricte	a Bana; Bai	nawiath aen	oted as RB	VV/VBVV
	Ant.			Antenna	Cable	Pre-amp	Distance				
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB	
	Position 10	at 8 meters. C	Output Power	Setting: 9.15	dBm, AVG =	= Peak Readi	ngs - Averag	e Factor of 2	0 dB from 10	% duty cycle	
A	distance facto	or of 8.52 dB	was added t	o the reading	s (shown as	negative) to	compensate t	for testing at	8 meters inst	ead of 3 met	ers
				Reseat th	ne screen a	nd tightened	the door				
Max PK	V	434.000	44.74	21.58	0.72	0.00	-8.52	75.56	92.87	-17.31	120/300 kHz
AVG	V	434.000	24.74	21.58	0.72	0.00	-8.52	55.56	72.87	-17.30	120/300 kHz
Max PK	Н	434.000	45.60	22.34	0.72	0.00	-8.52	77.18	92.87	-15.69	120/300 kHz
AVG	Н	434.000	25.60	22.34	0.72	0.00	-8.52	57.18	72.87	-15.68	120/300 kHz
Max PK	V	445.000	43.75	23.00	0.74	0.00	-8.52	76.01	93.22	-17.21	120/300 kHz
AVG	V	445.000	23.75	23.00	0.74	0.00	-8.52	56.01	73.22	-17.22	120/300 kHz
Max PK	Н	445.000	41.38	22.20	0.74	0.00	-8.52	72.84	93.22	-20.38	120/300 kHz
AVG	Н	445.000	21.38	22.20	0.74	0.00	-8.52	52.84	73.22	-20.39	120/300 kHz
Max PK	Н	425.000	40.65	22.00	0.71	0.00	-8.52	71.88	92.57	-20.69	120/300 kHz
AVG	Н	425.000	20.65	22.00	0.71	0.00	-8.52	51.88	72.57	-20.69	120/300 kHz
Max PK	V	425.000	46.47	21.60	0.71	0.00	-8.52	77.30	92.57	-15.27	120/300 kHz
AVG	V	425.000	26.47	21.60	0.71	0.00	-8.52	57.30	72.57	-15.27	120/300 kHz

Position 11 Radiated Emissions at 8 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw

Antenna & Cables: N Bands: N, LF, HF, SHF

Model #: Switchgears (425 to 442 MHz)

Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 Filter: NONE

Project #: G102014290 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3
PreAmp: None Test Distance (m): 8

PreAmp Used? (Y or N): N Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS: NF = Noise Floor. RB = Restricted Band: Bandwidth denoted as RBW/VBW

Peak: F	'N Quasi-P	eak: QP Av	erage: AvG	KINS: KINS	5; $NF = NOS$	se Floor, RE	= Restricte	a Bana; Bai	nawiath aen	oted as RB	W/VBW
	Ant.			Antenna	Cable	Pre-amp	Distance				
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB	
	Position 11	at 8 meters. C	Output Power	Setting: 9.15	dBm, AVG =	= Peak Readi	ngs - Averag	e Factor of 2	0 dB from 10	% duty cycle	
A	distance facto	or of 8.52 dB	was added t	o the reading	s (shown as	negative) to	compensate t	for testing at	8 meters inst	ead of 3 met	ers
				Reseat th	ne screen a	nd tightened	the door				
Max PK	V	434.000	49.34	21.58	0.72	0.00	-8.52	80.16	92.87	-12.71	120/300 kHz
AVG	V	434.000	29.34	21.58	0.72	0.00	-8.52	60.16	72.87	-12.70	120/300 kHz
Max PK	Н	434.000	55.26	22.34	0.72	0.00	-8.52	86.84	92.87	-6.03	120/300 kHz
AVG	Н	434.000	35.26	22.34	0.72	0.00	-8.52	66.84	72.87	-6.02	120/300 kHz
Max PK	V	445.000	45.17	23.00	0.74	0.00	-8.52	77.43	93.22	-15.79	120/300 kHz
AVG	V	445.000	25.17	23.00	0.74	0.00	-8.52	57.43	73.22	-15.80	120/300 kHz
Max PK	Н	445.000	50.28	22.20	0.74	0.00	-8.52	81.74	93.22	-11.48	120/300 kHz
AVG	Н	445.000	30.28	22.20	0.74	0.00	-8.52	61.74	73.22	-11.49	120/300 kHz
Max PK	Н	425.000	55.96	22.00	0.71	0.00	-8.52	87.19	92.57	-5.38	120/300 kHz
AVG	Ι	425.000	35.96	22.00	0.71	0.00	-8.52	67.19	72.57	-5.38	120/300 kHz
Max PK	V	425.000	46.95	21.60	0.71	0.00	-8.52	77.78	92.57	-14.79	120/300 kHz
AVG	V	425.000	26.95	21.60	0.71	0.00	-8.52	57.78	72.57	-14.79	120/300 kHz

Position 12 Radiated Emissions at 6.25 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw

Antenna & Cables: N Bands: N, LF, HF, SHF

Model #: Switchgears (425 to 442 MHz)

Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 Filter: NONE

Project #: G102014290 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3
PreAmp: None Test Distance (m): 6.25

PreAmp Used? (Y or N): N Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: F	Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS; NF = Noise Floor, RB = Restricted Band; Bandwidth denoted as RBW/VBW											
	Ant.			Antenna	Cable	Pre-amp	Distance					
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth	
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB		
F	Position 12 at 6.25 meters. Output Power Setting: 9.15 dBm, AVG = Peak Readings - Average Factor of 20 dB from 10% duty cycle											
A di	stance factor	of 6.38 dB v	vas added to	the readings	(shown as n	egative) to co	mpensate fo	r testing at 6.	.25 meters in	stead of 3 me	eters	
				Reseat tl	ne screen a	nd tightened	the door					
Max PK	V	434.000	45.90	21.58	0.72	0.00	-6.38	74.58	92.87	-18.29	120/300 kHz	
AVG	V	434.000	25.90	21.58	0.72	0.00	-6.38	54.58	72.87	-18.29	120/300 kHz	
Max PK	Н	434.000	59.98	22.34	0.72	0.00	-6.38	89.42	92.87	-3.45	120/300 kHz	
AVG	Н	434.000	39.98	22.34	0.72	0.00	-6.38	69.42	72.87	-3.45	120/300 kHz	
Max PK	V	445.000	50.21	23.00	0.74	0.00	-6.38	80.32	93.22	-12.90	120/300 kHz	
AVG	V	445.000	30.21	23.00	0.74	0.00	-6.38	60.32	73.22	-12.90	120/300 kHz	
Max PK	Н	445.000	53.83	22.20	0.74	0.00	-6.38	83.14	93.22	-10.08	120/300 kHz	
AVG	Н	445.000	33.83	22.20	0.74	0.00	-6.38	63.14	73.22	-10.08	120/300 kHz	
Max PK	Н	425.000	54.00	22.00	0.71	0.00	-6.38	83.09	92.57	-9.48	120/300 kHz	
AVG	Н	425.000	34.00	22.00	0.71	0.00	-6.38	63.09	72.57	-9.48	120/300 kHz	
Max PK	V	425.000	52.44	21.60	0.71	0.00	-6.38	81.13	92.57	-11.44	120/300 kHz	
AVG	V	425.000	32.44	21.60	0.71	0.00	-6.38	61.13	72.57	-11.44	120/300 kHz	

Position 13 Radiated Emissions at 8 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw Antenna & Cables: Ν Bands: N, LF, HF, SHF Model #: Switchgears (425 to 442 MHz) Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 NONE Filter:

Project #: G102014290 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3 PreAmp: None Test Distance (m): 8

> PreAmp Used? (Y or N): Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS; NF = Noise Floor, RB = Restricted Band; Bandwidth denoted as RBW/VBW

I can. I	reak. FR Quasi-reak. QF Average. AVG Kivis, NI = Noise Floor, NB = Restricted Band, Bandwidth denoted as NBW/VBW											
	Ant.			Antenna	Cable	Pre-amp	Distance					
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth	
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB		
	Position 13 at 8 meters. Output Power Setting: 9.15 dBm, AVG = Peak Readings - Average Factor of 20 dB from 10% duty cycle											
А	A distance factor of 8.52 dB was added to the readings (shown as negative) to compensate for testing at 8 meters instead of 3 meters											
				Reseat tl	ne screen a	nd tightened	I the door					
Max PK	V	434.000	49.32	21.58	0.72	0.00	-8.52	80.14	92.87	-12.73	120/300 kHz	
AVG	V	434.000	29.32	21.58	0.72	0.00	-8.52	60.14	72.87	-12.72	120/300 kHz	
Max PK	Н	434.000	59.34	22.34	0.72	0.00	-8.52	90.92	92.87	-1.95	120/300 kHz	
AVG	Н	434.000	39.34	22.34	0.72	0.00	-8.52	70.92	72.87	-1.94	120/300 kHz	
Max PK	V	445.000	52.72	23.00	0.74	0.00	-8.52	84.98	93.22	-8.24	120/300 kHz	
AVG	V	445.000	32.72	23.00	0.74	0.00	-8.52	64.98	73.22	-8.25	120/300 kHz	
Max PK	Н	445.000	51.41	22.20	0.74	0.00	-8.52	82.87	93.22	-10.35	120/300 kHz	
AVG	Н	445.000	31.41	22.20	0.74	0.00	-8.52	62.87	73.22	-10.36	120/300 kHz	
Max PK	Н	425.000	56.89	22.00	0.71	0.00	-8.52	88.12	92.57	-4.45	120/300 kHz	
AVG	Н	425.000	36.89	22.00	0.71	0.00	-8.52	68.12	72.57	-4.45	120/300 kHz	
Max PK	V	425.000	57.36	21.60	0.71	0.00	-8.52	88.19	92.57	-4.38	120/300 kHz	
AVG	V	425.000	37.36	21.60	0.71	0.00	-8.52	68.19	72.57	-4.38	120/300 kHz	

Position 14 Radiated Emissions at 8 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw

Antenna & Cables: N Bands: N, LF, HF, SHF

Model #: Switchgears (425 to 442 MHz)

Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 Filter: NONE

Project #: G102014290 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3
PreAmp: None Test Distance (m): 8

PreAmp Used? (Y or N): N Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK, Quasi-Peak: QP, Average: AVG, RMS: RMS: NF = Noise Floor, RB = Restricted Band: Bandwidth denoted as RBW/VBW

Peak: F	Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS; NF = Noise Floor, RB = Restricted Band; Bandwidth denoted as RBW/VBW										
	Ant.			Antenna	Cable	Pre-amp	Distance				
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB	
	Position 14 at 8 meters. Output Power Setting: 6.5 dBm, AVG = Peak Readings - Average Factor of 20 dB from 10% duty cycle										
A	A distance factor of 8.52 dB was added to the readings (shown as negative) to compensate for testing at 8 meters instead of 3 meters										
	Reseat the screen and tightened the door										
Notes	: Due to nor	n-compliant	on this side,	the output	power settir	ig was dropp	oed to 6.5 d	Bm and con	tinued testir	ng with this	setting
Max PK	V	434.000	52.73	21.58	0.72	0.00	-8.52	83.55	92.87	-9.32	120/300 kHz
AVG	V	434.000	32.73	21.58	0.72	0.00	-8.52	63.55	72.87	-9.31	120/300 kHz
Max PK	Ι	434.000	55.30	22.34	0.72	0.00	-8.52	86.88	92.87	-5.99	120/300 kHz
AVG	Ι	434.000	35.30	22.34	0.72	0.00	-8.52	66.88	72.87	-5.98	120/300 kHz
Max PK	V	445.000	51.71	23.00	0.74	0.00	-8.52	83.97	93.22	-9.25	120/300 kHz
AVG	V	445.000	31.71	23.00	0.74	0.00	-8.52	63.97	73.22	-9.26	120/300 kHz
Max PK	Η	445.000	55.46	22.20	0.74	0.00	-8.52	86.92	93.22	-6.30	120/300 kHz
AVG	Ι	445.000	35.46	22.20	0.74	0.00	-8.52	66.92	73.22	-6.31	120/300 kHz
Max PK	Ι	425.000	60.80	22.00	0.71	0.00	-8.52	92.03	92.57	-0.54	120/300 kHz
AVG	Ι	425.000	40.80	22.00	0.71	0.00	-8.52	72.03	72.57	-0.54	120/300 kHz
Max PK	V	425.000	57.98	21.60	0.71	0.00	-8.52	88.81	92.57	-3.76	120/300 kHz
AVG	V	425.000	37.98	21.60	0.71	0.00	-8.52	68.81	72.57	-3.76	120/300 kHz

Position 15 Radiated Emissions at 6.55 meters

Test Site: Nasonville National Grid in Nasonville, RI

Company: Intellisaw

Antenna & Cables: N Bands: N, LF, HF, SHF

Model #: Switchgears (425 to 442 MHz)

Antenna: ANT1-10mV 11-04-2015.txt ANT1-10mH 11-04-2015.txt

Serial #: 8150695 Cable(s): CBLEMC3 04-02-16.txt NONE.

Engineers: Kouma Sinn Location: National Grid Barometer: MAN1 Filter: NONE

Project #: G102014290 Date(s): 06/02/15

Standard: FCC Part 15 Subpart C Section 15.231e Temp/Humidity/Pressure: 12C 74% 1010mbar

Receiver: 147-149 Limit Distance (m): 3
PreAmp: None Test Distance (m): 6.55


PreAmp Used? (Y or N): N Voltage/Frequency: Powered from substation Frequency Range: 425 MHz, 434MHz & 445 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS: NF = Noise Floor RB = Restricted Band: Bandwidth denoted as RBW/VBW

Peak: F	Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS; NF = Noise Floor, RB = Restricted Band; Bandwidth denoted as RBW/VBW										
	Ant.			Antenna	Cable	Pre-amp	Distance				
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB	
	Position 15 at 6.55 meters. Output Power Setting: 6.5 dBm, AVG = Peak Readings - Average Factor of 20 dB from 10% duty cycle										
A di	stance factor	of 8.52 dB w	vas added to	the readings	(shown as n	egative) to co	mpensate fo	r testing at 6	.55 meters in:	stead of 3 me	eters
				Reseat tl	ne screen a	nd tightened	I the door				
Max PK	V	434.000	53.30	21.58	0.72	0.00	-6.78	82.38	92.87	-10.49	120/300 kHz
AVG	V	434.000	33.30	21.58	0.72	0.00	-6.78	62.38	72.87	-10.48	120/300 kHz
Max PK	Η	434.000	59.52	22.34	0.72	0.00	-6.78	89.36	92.87	-3.51	120/300 kHz
AVG	Η	434.000	39.52	22.34	0.72	0.00	-6.78	69.36	72.87	-3.50	120/300 kHz
Max PK	V	445.000	45.17	23.00	0.74	0.00	-6.78	75.69	93.22	-17.53	120/300 kHz
AVG	V	445.000	25.17	23.00	0.74	0.00	-6.78	55.69	73.22	-17.54	120/300 kHz
Max PK	Η	445.000	56.15	22.20	0.74	0.00	-6.78	85.87	93.22	-7.35	120/300 kHz
AVG	Η	445.000	36.15	22.20	0.74	0.00	-6.78	65.87	73.22	-7.36	120/300 kHz
Max PK	Η	425.000	60.69	22.00	0.71	0.00	-6.78	90.18	92.57	-2.39	120/300 kHz
AVG	Н	425.000	40.69	22.00	0.71	0.00	-6.78	70.18	72.57	-2.39	120/300 kHz
Max PK	V	425.000	58.14	21.60	0.71	0.00	-6.78	87.23	92.57	-5.34	120/300 kHz
AVG	V	425.000	38.14	21.60	0.71	0.00	-6.78	67.23	72.57	-5.34	120/300 kHz

Antenna Port Conducted Power at 425 MHz




Date: 10.APR.2015 17:29:57

Output power for frequency 425MHz is 11.69 dB(m)

Output power = -8.11+19.8 (cable loss + attenuator factor)


Client: IntelliSAW, Product Designation: Modular Device (RF Card)

Antenna Port Conducted Power at 434 MHz



Output power for frequency 434 MHz is 11.24 dB(m)

Antenna Port Conducted Power at 445 MHz



Output power for frequency 445 MHz is 10.97 d(Bm)

Test Personnel:	Vathana Ven	Test Date:	04/09/2015
	Kouma Sinn 43		06/02/2015
Supervising/Reviewing Engineer:			
(Where Applicable)	N/A		
Product Standard:	FCC Part 15 Subpart C, RSS-210 Powered from 24VDC Host	Limit Applied:	Section 15.231(e)
Pretest Verification w/	1 GWCICCI HOIN 24V DO FIOSI	Ambient Temperature:	See data tables
Ambient Signals or BB Source:	Ambient Signals	Relative Humidity:	See data tables
		Atmospheric Pressure:	See data tables

Deviations, Additions, or Exclusions: None

7 Occupied Bandwidth

7.1 Method

Tests are performed in accordance with FCC 47CFR Part 15 Subpart C Section 15.231(c), ANSI C63.10:2009, RSS-Gen.

TEST SITE: 10m ALSE

The 10m ALSE is 13m (Length) x 21m (Depth) x 10m (Height) with the effective size in terms of space from the tips of the absorber is 12m (Length) x 20m (Depth) x 8.5m (Height). This chamber achieves broadband performance using a unique arrangement of hybrid and ferrite tile absorber. This chamber has a built in 3m diameter turntable (Embedded type). The metal structure of the table makes electrical connection around the entire circumference of the turntable to the ground plane with a metal brush type connection. The turntable is located on one end of the chamber and the antennas are mounted 3 and 10 meters away at the other end of the chamber on the adjustable an Antenna Mast. The antenna mast is a non-conductive bore sighted type with remote control of antenna height and polarization. The Antenna Mast and the turntable can be remotely controlled through the controller located in the adjacent Control room. A wooden table 80 cm high is used for table-top equipment.

7.2 Test Equipment Used:

Asset	Description	Manufacturer	Model	Serial	Cal Date	Cal Due
145128'	EMI Receiver (20 Hz - 40 Ghz)	Rohde & Schwarz	ESIB 40	839283/001	03/14/2015	03/14/2016
145-410'	Cables 145-400 145-403 145-405 145-406 145-407	Huber + Suhner	10m Track A Cables	multiple	10/04/2014	10/04/2015
145106'	Bilog Antenna (30MHz - 5GHz)	Sunol Sciences	JB5	A111003	10/24/2014	10/24/2015
Dav004'	Weather Station	Davis Instruments	7400	PE80529A61A	10/06/2014	10/06/2015

Software Utilized:

Name	Manufacturer	Version
None		


7.3 Results:

The sample tested was found to Comply. The bandwidth of the emission shall be no wider than 0.25% of the center frequency for devices operating above 70 MHz and below 900 MHz. For devices operating above 900 MHz, the emission shall be no wider than 0.5% of the center frequency. Bandwidth is determined at the points 20 dB down from the modulated carrier. Therefore the bandwidth must not exceed 1.06 MHz for 425 MHz, 1.09 MHz for 434 MHz, and 1.11 MHz for 445 MHz.

Non-Specific EMC Report Shell Rev. May 2014 Page 44 of 110


Issued: 06/05/2015 Report Number: 102085252BOX-001c

7.4 **Setup Photograph:**



Page 45 of 110


7.5 Plots/Data:



Date: 10.APR.2015 17:34:01


Page 46 of 110

Report Number: 102085252BOX-001c Issued: 06/05/2015




Date: 9.APR.2015 19:09:38

99% Power Bandwidth




Report Number: 102085252BOX-001c Issued: 06/05/2015




20 dB Bandwidth






99% Power Bandwidth

Report Number: 102085252BOX-001c Issued: 06/05/2015



20 dB Bandwidth



99% Power Bandwidth

Test Personnel: Supervising/Reviewing	Vathana Ven	Test Date:	04/28/2015
Engineer:			
(Where Applicable)	N/A		
Product Standard:	FCC Part 15 Subpart C, RSS-Gen	Limit Applied:	Section 15.231(c)
Input Voltage:	Powered from 24VDC Host		
Pretest Verification w/		Ambient Temperature:	22 °C
Ambient Signals or			
	Ambient Signals	Relative Humidity:	10 %
		Atmospheric Pressure:	1007 mbars

Page 52 of 110 Client: IntelliSAW, Product Designation: Modular Device (RF Card)

Radiated and Spurious Emissions 8

8.1 Method

Tests are performed in accordance with FCC 47CFR Part 15 Subpart C Section 15.231(e), ANSI C63.10:2009, RSS-210

TEST SITE: 10m ALSE

The 10m ALSE is 13m (Length) x 21m (Depth) x 10m (Height) with the effective size in terms of space from the tips of the absorber is 12m (Length) x 20m (Depth) x 8.5m (Height). This chamber achieves broadband performance using a unique arrangement of hybrid and ferrite tile absorber. This chamber has a built in 3m diameter turntable (Embedded type). The metal structure of the table makes electrical connection around the entire circumference of the turntable to the ground plane with a metal brush type connection. The turntable is located on one end of the chamber and the antennas are mounted 3 and 10 meters away at the other end of the chamber on the adjustable an Antenna Mast. The antenna mast is a non-conductive bore sighted type with remote control of antenna height and polarization. The Antenna Mast and the turntable can be remotely controlled through the controller located in the adjacent Control room. A wooden table 80 cm high is used for table-top equipment.

Measurement Uncertainty

For radiated emissions, U_{tab} (3.5 dB at 3m and 3.5 dB at 10m below 1 GHz, and 4.2 dB at 3m above 1 GHz) $< U_{CISPR}$ (5.2 dB), which is the reference value in CISPR 16-4-2 Table 1, hence the compliance of the product is only based on the measured value, and no measurement uncertainty correction is required, based on CISPR 22 and CISPR 11 (for 2006 and later revisions) Clause 11.

Non-Specific EMC Report Shell Rev. May 2014 Page 53 of 110

Sample Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

FS = RA + AF + CF - AG

Where $FS = Field Strength in dB\mu V/m$

RA = Receiver Amplitude (including preamplifier) in dBµV

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB AG = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows.

Assume a receiver reading of 52.0 dB_µV is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32 dBμV/m. This value in dB_μV/m was converted to its corresponding level in μV/m.

 $RA = 52.0 dB\mu V$ AF = 7.4 dB/mCF = 1.6 dB $AG = 29.0 \, dB$ $FS = 32 dB\mu V/m$

To convert from dB_μV to μV or mV the following was used:

UF =
$$10^{(NF/20)}$$
 where UF = Net Reading in μ V NF = Net Reading in dB μ V

Example:

FS = RA + AF + CF - AG =
$$52.0 + 7.4 + 1.6 - 29.0 = 32.0$$
 UF = $10^{(32 \, dB_{\mu}V \, / \, 20)} = 39.8 \, \mu V/m$

Non-Specific EMC Report Shell Rev. May 2014 Page 54 of 110

8.2 **Test Equipment Used:**

Asset	Description	Manufacturer	Model	Serial	Cal Date	Cal Due
145128'	EMI Receiver (20 Hz - 40 Ghz)	Rohde & Schwarz	ESIB 40	839283/001	03/14/2015	03/14/2016
145-410'	Cables 145-400 145-403 145-405 145-406 145-407	Huber + Suhner	10m Track A Cables	multiple	10/04/2014	10/04/2015
145106'	Bilog Antenna (30MHz - 5GHz)	Sunol Sciences	JB5	A111003	10/24/2014	10/24/2015
Dav004'	Weather Station	Davis Instruments	7400	PE80529A61A	10/06/2014	10/06/2015
REA003'	1GHz High Pass Filter	Reactel, Inc	7HS-1G/10G-S11	06-1	12/30/2013	12/30/2015
145-416'	Cables 145-400 145-402 145-404 145-408	Huber + Suhner	3m Track B cables	multiple	10/04/2014	10/04/2015
145014'	Preamplifier (1 GHz to 26.5 GHz)	Hewlett Packard	8449B	3008A00232	05/05/2014	05/05/2015
ETS002'	1-18GHz DRG Horn Antenna	ETS Lindgren	3117	00143260	04/10/2015	04/10/2016

Software Utilized:

Name	Manufacturer	Version
EMI Boxborough	Intertek	8/27/2010
C5	TESEQ	Build 5.26.46.46

8.3 Results:

The sample tested was found to Comply.


(e) Intentional radiators may operate at a periodic rate exceeding that specified in paragraph (a) of this section and may be employed for any type of operation, including operation prohibited in paragraph (a) of this section, provided the intentional radiator complies with the provisions of paragraphs (b) through (d) of this section, except the field strength table in paragraph (b) of this section is replaced by the following:


Fundamental frequency (MHz)	Field strength of fundamental (microvolts/meter)	Field strength of spurious emission (microvolts/meter)
40.66-40.70	1,000	100
70-130	500	50
130-174	500 to 1,500 ¹	50 to 150 ¹
174-260	1,500	150
260-470	1,500 to 5,000 ¹	150 to 500 ¹
Above 470	5,000	500

¹Linear interpolations.

Page 55 of 110 Client: IntelliSAW, Product Designation: Modular Device (RF Card)

8.4 Setup Photographs:





Report Number: 102085252BOX-001c Issued: 06/05/2015

8.5 Plots/Data:

Radiated Emissions

Company: Intellisaw Antenna & Cables: Ν Bands: N, LF, HF, SHF Model #: 400.00152.0001 Antenna: 145106 10mh 10-21-15.txt 145106 10mh 10-21-15.txt

Serial #: 08150695 Cable(s): 145-410 10M Track A Cables 9Mfz to 2 Gftz REDUCED POINTS 10-04-15.bs NONE.

Engineers: Vathana Ven Location: 10M Barometer: DAV004 Filter: NONE

Project #: 500592446 Date(s): 04/09/15

Standard: FCC Part 15 Subpart C, 15.231e, RSS-210 Temp/Humidity/Pressure: 21 deg C 29% 1017 mB

Receiver: R&S ESI (145-128) 03-14-2016 Limit Distance (m): 3 PreAmp: NONE. Test Distance (m): 10

Voltage/Frequency: 5VDC Frequency Range: PreAmp Used? (Y or N): Ν 30-1000 MHz Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB) Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS; NF = Noise Floor, RB = Restricted Band; Bandwidth denoted as RBW/VBW

	Ant.			Antenna	Cable	Pre-amp	Distance					
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth	
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB		FCC IC
	F=	425 MHz, X	Axis, PPS	= 15 and P/	4 = 7, Anten	na (IA-MM-	17, 17cm m	onopole ant	enna, +3.2 d	dBi)		
PK	V	45.000	34.16	10.60	1.07	0.00	-10.46	56.28	72.57	-16.29	120/300 kHz	
AVG	V	45.000	14.16	10.60	1.07	0.00	-10.46	36.28	52.57	-16.29	120/300 kHz	
PK	V	55.000	32.87	7.00	1.18	0.00	-10.46	51.51	72.57	-21.06	120/300 kHz	
AVG	V	55.000	12.87	7.00	1.18	0.00	-10.46	31.51	52.57	-21.06	120/300 kHz	
PK	V	850.000	25.75	21.90	4.76	0.00	-10.46	62.87	72.57	-9.70	120/300 kHz	Noise Floor
AVG	V	850 000	5.75	21 90	4 76	0.00	-10 46	42 87	52 57	-9 70	120/300 kHz	Noise Floor

Page 58 of 110 Non-Specific EMC Report Shell Rev. May 2014

Client: IntelliSAW, Product Designation: Modular Device (RF Card)

Report Number: 102085252BOX-001c Issued: 06/05/2015

Radiated Emissions

Company: Intellisaw

Antenna & Cables: N Bands: N, LF, HF, SHF

Model #: 400.00152.0001 Antenna: 145106 10mh 10-21-15.txt 145106 10mh 10-21-15.txt

Serial #: 08150695 Cable(s): 10.419 IMT THAN A CAMB MADE IN THE ACCOUNT PROMET SOME OF THE ACCOUNT PRO

Engineers: Vathana Ven Location: 10M Barometer: DAV004 Filter: NONE

Project #: 500592446 Date(s): 04/09/15

Standard: FCC Part 15 Subpart C, 15.231e, RSS-210 Temp/Humidity/Pressure: 21 deg C 29% 1017 mB

Receiver: R&S ESI (145-128) 03-14-2016 Limit Distance (m): 3
PreAmp: NONE. Test Distance (m): 10

PreAmp Used? (Y or N): N Voltage/Frequency: 5VDC Frequency Range: 30-1000 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS; NF = Noise Floor, RB = Restricted Band; Bandwidth denoted as RBW/VBW

	Ant.			Antenna	Cable	Pre-amp	Distance					
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth	
Туре	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB		FCC IC
F = 425 MHz, X-Axis, PPS = 15 and PA = 7, Antenna (IA-MM-TPD, PIFA Patched Inverted F antenna)												
PK	V	45.000	33.50	10.60	1.07	0.00	-10.46	55.62	72.57	-16.95	120/300 kHz	
AVG	V	45.000	13.50	10.60	1.07	0.00	-10.46	35.62	52.57	-16.95	120/300 kHz	
PK	V	55.000	32.87	7.00	1.18	0.00	-10.46	51.51	72.57	-21.06	120/300 kHz	
AVG	V	55.000	12.87	7.00	1.18	0.00	-10.46	31.51	52.57	-21.06	120/300 kHz	
PK	V	850.000	25.75	21.90	4.76	0.00	-10.46	62.87	72.57	-9.70	120/300 kHz	Noise Floor
AVG	V	850.000	5.75	21.90	4.76	0.00	-10.46	42.87	52.57	-9.70	120/300 kHz	Noise Floor

Report Number: 102085252BOX-001c Issued: 06/05/2015

Radiated Emissions

 Company: Intellisaw
 Antenna & Cables:
 N
 Bands: N, LF, HF, SHF

 Model #: 400.00152.0001
 Antenna: 145106 10mh 10-21-15.txt
 145106 10mh 10-21-15.txt
 145106 10mh 10-21-15.txt

Serial #: 08150695 Cable(s): 165-101 DOM TIEGO A CABBRE BRIDE 2 CHARLES CONTROL OF CONTR

Engineers: Vathana Ven Location: 10M Barometer: DAV004 Filter: NONE

Project #: 500592446 Date(s): 04/09/15

Standard: FCC Part 15 Subpart C, 15.231e, RSS-210 Temp/Humidity/Pressure: 21 deg C 29% 1017 mB

Receiver: R&S ESI (145-128) 03-14-2016 Limit Distance (m): 3
PreAmp: NONE. Test Distance (m): 10

PreAmp Used? (Y or N): N Voltage/Frequency: 5VDC Frequency Range: 30-1000 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS; NF = Noise Floor, RB = Restricted Band; Bandwidth denoted as RBW/VBW

Todit. The Quadrit date Quarter Two age. And Thine, This are the controlled balla, Ballamath deliced at the William												
	Ant.			Antenna	Cable	Pre-amp	Distance					
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth	
Туре	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB		FCC IC
	F =	434 MHz, X	-Axis, PPS	= 15 and P/	A = 7, Anten	na (IA-MM-	17, 17cm m	onopole ant	enna, +3.2 d	dBi)		
PK	V	45.000	31.69	10.60	1.07	0.00	-10.46	53.81	72.87	-19.06	120/300 kHz	
AVG	V	45.000	11.69	10.60	1.07	0.00	-10.46	33.81	52.87	-19.06	120/300 kHz	
PK	V	55.000	32.23	7.00	1.18	0.00	-10.46	50.87	72.87	-22.00	120/300 kHz	
AVG	V	55.000	12.23	7.00	1.18	0.00	-10.46	30.87	52.87	-22.00	120/300 kHz	
PK	V	868.000	25.99	21.80	4.79	0.00	-10.46	63.03	72.87	-9.84	120/300 kHz	Noise Floor
AVG	V	868.000	5.99	21.80	4.79	0.00	-10.46	43.03	52.87	-9.84	120/300 kHz	Noise Floor

Report Number: 102085252BOX-001c Issued: 06/05/2015

Radiated Emissions

Company: Intellisaw Antenna & Cables: Ν Bands: N, LF, HF, SHF

Model #: 400.00152.0001 Antenna: 145106 10mh 10-21-15.txt 145106 10mh 10-21-15.txt

Serial #: 08150695 $Cable(s): \ \ _{\text{145-410 10M Track A Cables SMMz to 2 GHz REDUCED POINTS 10-04-15 ad}} \quad NONE.$

Engineers: Vathana Ven Location: 10M Barometer: DAV004 Filter: NONE

Project #: 500592446 Date(s): 04/09/15

Standard: FCC Part 15 Subpart C, 15.231e, RSS-210 Temp/Humidity/Pressure: 21 deg C 29% 1017 mB

Receiver: R&S ESI (145-128) 03-14-2016 Limit Distance (m): 3 PreAmp: NONE. Test Distance (m): 10

> PreAmp Used? (Y or N): Ν Voltage/Frequency: 5VDC Frequency Range: 30-1000 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS; NF = Noise Floor, RB = Restricted Band; Bandwidth denoted as RBW/VBW

	Ant.			Antenna	Cable	Pre-amp	Distance					
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth	
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB		FCC IC
F = 434 MHz, X-Axis, PPS = 15 and PA = 7, Antenna (IA-MM-TPD, PIFA Patched Inverted F antenna)												
PK	V	45.000	31.81	10.60	1.07	0.00	-10.46	53.93	72.87	-18.94	120/300 kHz	
AVG	V	45.000	12.00	10.60	1.07	0.00	-10.46	34.12	52.87	-18.75	120/300 kHz	
PK	٧	55.000	32.23	7.00	1.18	0.00	-10.46	50.87	72.87	-22.00	120/300 kHz	
AVG	V	55.000	12.23	7.00	1.18	0.00	-10.46	30.87	52.87	-22.00	120/300 kHz	
PK	V	868.000	25.99	21.80	4.79	0.00	-10.46	63.03	72.87	-9.84	120/300 kHz	Noise Floor
AVG	V	868.000	5.99	21.80	4.79	0.00	-10.46	43.03	52.87	-9.84	120/300 kHz	Noise Floor

Page 61 of 110 Non-Specific EMC Report Shell Rev. May 2014

Client: IntelliSAW, Product Designation: Modular Device (RF Card)

Report Number: 102085252BOX-001c Issued: 06/05/2015

Radiated Emissions

 Company: Intellisaw
 Antenna & Cables:
 N
 Bands: N, LF, HF, SHF

 Model #: 400.00152.0001
 Antenna: 145106 10mh 10-21-15.txt
 145106 10mh 10-21-15.txt
 145106 10mh 10-21-15.txt

Model #: 400.00152.0001 Antenna: 145106 10mh 10-21-15.txt 145106 10mh 10-21-15.txt 145106 10mh 10-21-15.txt Serial #: 08150695 Cable(s): 16-45 081 08150695 NONE.

Engineers: Vathana Ven Location: 10M Barometer: DAV004 Filter: NONE

Project #: 500592446 Date(s): 04/09/15

Standard: FCC Part 15 Subpart C, 15.231e, RSS-210 Temp/Humidity/Pressure: 21 deg C 29% 1017 mB

Receiver: R&S ESI (145-128) 03-14-2016 Limit Distance (m): 3
PreAmp: NONE. Test Distance (m): 10

PreAmp Used? (Y or N): N Voltage/Frequency: 5VDC Frequency Range: 30-1000 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS: NF = Noise Floor, RB = Restricted Band: Bandwidth denoted as RBW/VBW

r can. r	reak. Fit Quasi-reak. Qr Average. Avg Kivio. Kivio, Nr = Noise Floor, Nb = Restricted band, bandwidth defloted as KbW/VbW													
	Ant.			Antenna	Cable	Pre-amp	Distance							
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth			
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB		FCC	IC	
	F =	445 MHz, X	Axis, PPS	= 15 and PA	A = 7, Anten	na (IA-MM-	17, 17cm m	onopole ant	enna, +3.2 o	dBi)				
PK	V	45.000	33.20	10.60	1.07	0.00	-10.46	55.32	73.22	-17.90	120/300 kHz			
AVG	V	45.000	13.20	10.60	1.07	0.00	-10.46	35.32	53.22	-17.90	120/300 kHz			
PK	V	55.000	31.92	7.00	1.18	0.00	-10.46	50.56	73.22	-22.66	120/300 kHz			
AVG	V	55.000	11.92	7.00	1.18	0.00	-10.46	30.56	53.22	-22.66	120/300 kHz			
PK	V	890.000	25.59	21.90	4.82	0.00	-10.46	62.76	73.22	-10.46	120/300 kHz	Noise Floor		
AVG	V	890.000	5.59	21.90	4.82	0.00	-10.46	42.76	53.22	-10.46	120/300 kHz	Noise Floor		

Report Number: 102085252BOX-001c Issued: 06/05/2015

Radiated Emissions

Company: Intellisaw Antenna & Cables: Bands: N, LF, HF, SHF Ν Model #: 400.00152.0001 Antenna: 145106 10mh 10-21-15.txt 145106 10mh 10-21-15.txt

Serial #: 08150695 Cable(s): 145-410 50M Track A Cables SMHz to 2 GHz REDUCED POINTS 10-04-15:84 NONE.

Engineers: Vathana Ven Location: 10M Barometer: DAV004 Filter: NONE

Project #: 500592446 Date(s): 04/09/15

Standard: FCC Part 15 Subpart C, 15.231e, RSS-210 Temp/Humidity/Pressure: 21 deg C 29% 1017 mB

Receiver: R&S ESI (145-128) 03-14-2016 Limit Distance (m): 3 PreAmp: NONE. Test Distance (m): 10

> PreAmp Used? (Y or N): Voltage/Frequency: 5VDC Frequency Range: 30-1000 MHz

Net = Reading (dBuV/m) + Antenna Factor (dB1/m) + Cable Loss (dB) - Preamp Factor (dB) - Distance Factor (dB)

Peak: PK Quasi-Peak: QP Average: AVG RMS: RMS; NF = Noise Floor, RB = Restricted Band; Bandwidth denoted as RBW/VBW

	Ant.			Antenna	Cable	Pre-amp	Distance					
Detector	Pol.	Frequency	Reading	Factor	Loss	Factor	Factor	Net	Limit	Margin	Bandwidth	
Type	(V/H)	MHz	dB(uV)	dB(1/m)	dB	dB	dB	dB(uV/m)	dB(uV/m)	dB		FCC IC
	F =	445 MHz, X	-Axis, PPS :	= 15 and PA	. = 7, Anteni	na (IA-MM-1	PD, PIFA F	Patched Inve	rted F anter	nna)		
PK	٧	45.000	33.20	10.60	1.07	0.00	-10.46	55.32	73.22	-17.90	120/300 kHz	
AVG	V	45.000	13.20	10.60	1.07	0.00	-10.46	35.32	53.22	-17.90	120/300 kHz	
PK	V	55.000	31.92	7.00	1.18	0.00	-10.46	50.56	73.22	-22.66	120/300 kHz	
AVG	V	55.000	11.92	7.00	1.18	0.00	-10.46	30.56	53.22	-22.66	120/300 kHz	
PK	>	890.000	25.59	21.90	4.82	0.00	-10.46	62.76	73.22	-10.46	120/300 kHz	Noise Floor
AVG	V	890.000	5.59	21.90	4.82	0.00	-10.46	42.76	53.22	-10.46	120/300 kHz	Noise Floor

Page 63 of 110 Non-Specific EMC Report Shell Rev. May 2014

Client: IntelliSAW, Product Designation: Modular Device (RF Card)

1-4.5 GHz

Test Information


Test Details

User Entry Radiated - FCC15.231(e) @ 3m IntelliSaw_Q500592446 Test: Project:

Test Notes: 120VAC/60Hz, 425 MHz both antennas, X-Axis, worst-case

Temperature: Humidity: 21 deg C 29%, 1017 mB Vathana Ven 9 Apr 2015 23 : 49 Tested by: Test Started:

Prescan Emission Graph



Measured Peak Value

Measured Quasi Peak Value

Measured Average Value

Maximum Value of Mast and Turntable

Swept Peak Data

Swept Quasi Peak Data

Swept Average Data

Emissions Test Data

Trace1: Measured Peak


Frequency (Hz)	Level (dBuV/m)	AF	PA+CL	Limit (dBuV/m)	Margin (dBuV/m)	Hor (), Ver ()	Azimuth (deg)(Deg)	Mast Height(m)	RBW(Hz)	Comment
1.27499666 G	43.65	28.685	-27.800	72.570	-28.92		160	1.53	1 M	
1.738383434 G	45.68	29.339	-26.815	72.570	-26.89	1	109	2.40	1 M	
3.829144957 G	50.83	33.594	-23.933	72.570	-21.74	Ì	333	1.20	1 M	
4.093934536 G	51.82	33.463	-23.194	72.570	-20.75		164	2.51	1 M	
2.55011356 G	52.92	32.515	-25.850	72.570	-19.65		28	2.88	1 M	
2.12510354 G	56.66	31.269	-26.015	72.570	-15.91		266	2.05	1 M	
2.975317301 G	60.52	32.905	-25.127	72.570	-12.05		51	2.30	1 M	
3.40008016 G	66.86	32.966	-24.908	72.570	-5.71		105	2.17	1 M	

Trace3: Measured Average


Frequency (Hz)	Level (dBuV/m)	AF	PA+CL	Limit (dBuV/m)	Margin(dBuV/m)	Hor (), Ver ()	Azimuth (deg)(Deg)	Mast Height(m)	RBW(Hz)	Comment
1.27499666 G	23.65	28.685	-27.800	52.570	-28.92		160	1.53	1 M	
1.738383434 G	25.68	29.339	-26.815	52.570	-26.89		109	2.40	1 M	
3.829144957 G	30.83	33.594	-23.933	52.570	-21.74		333	1.20	1 M	
4.093934536 G	31.82	33.463	-23.194	52.570	-20.75		164	2.51	1 M	
2.55011356 G	32.92	32.515	-25.850	52.570	-19.65		28	2.88	1 M	
2.12510354 G	36.66	31.269	-26.015	52.570	-15.91		266	2.05	1 M	
2.975317301 G	40.52	32.905	-25.127	52.570	-12.05		51	2.30	1 M	
3.40008016 G	46.86	32.966	-24.908	52.570	-5.71		105	2.17	1 M	

Non-Specific EMC Report Shell Rev. May 2014 Client: IntelliSAW, Product Designation: Modular Device (RF Card) Additional Information


Azimuth Plots





7 Totaliacs 7 Emilia




Turntable Plots

















All Polarities




Non-Specific EMC Report Shell Rev. May 2014 Client: IntelliSAW, Product Designation: Modular Device (RF Card)


Azimuth (Degrees)







All Polarities





Non-Specific EMC Report Shell Rev. May 2014


Client: IntelliSAW, Product Designation: Modular Device (RF Card)

Page 67 of 110


Azimuth (Degrees)







All Polarities



Non-Specific EMC Report Shell Rev. May 2014 Client: IntelliSAW, Product Designation: Modular Device (RF Card)

Azimuth (Degrees)

Test Information


Test Details

User Entry Radiated - FCC15.231e @ 3m IntelliSaw_Q500592446 Test: Project:

Test Notes: Temperature: 120VAC/60Hz, Both antennas, 434 MHz, X-Axis, worst-case

21 deg C 38%, 994 mB Humidity: Tested by: Test Started: Vathana Ven 10 Apr 2015 17 : 32 Additional Information

Prescan Emission Graph



- Measured Peak Value
- Measured Quasi Peak Value
- Measured Average Value
- Maximum Value of Mast and Turntable

- Swept Peak Data
- Swept Quasi Peak Data
- Swept Average Data

Emissions Test Data


Trace1: Measured Peak

Frequency (Hz)	Level (dBuV/m)	AF	PA+CL	Limit (dBuV/m)	Margin (dBuV/m)	Hor (), Ver ()	Azimuth (deg)(Deg)	Mast Height(m)	RBW(Hz)	Comment
1.736212425 G	47.53	29.318	-26.823	72.870	-25.34	1	30	2.76	1 M	
3.473132933 G	49.00	32.984	-24.905	72.870	-23.87	1	0	1.09	1 M	
2.606800267 G	49.81	32.588	-25.681	72.870	-23.06		8	1.80	1 M	
2.169899799 G	52.13	31.286	-25.971	72.870	-20.74		292	1.32	1 M	
4.377682031 G	55.31	33.626	-23.629	72.870	-17.56		21	2.53	1 M	
3.037822311 G	56.68	32.966	-25.105	72.870	-16.19	1	287	2.04	1 M	
3.890567802 G	60.50	33.670	-23.781	72.870	-12.37		360	1.09	1 M	
1.301863727 G	65.69	28.874	-27.576	72.870	-7.18		150	1.09	1 M	


Trace3: Measured Average

Frequency (Hz)	Level (dBuV/m)	AF	PA+CL	Limit (dBuV/m)	Margin (dBuV/m)	Hor (), Ver ()	Azimuth (deg)(Deg)	Mast Height(m)	RBW(Hz)	Comment
1.736212425 G	27.53	29.318	-26.823	52.870	-25.34	1	30	2.76	1 M	
3.473132933 G	29.00	32.984	-24.905	52.870	-23.87	İ	0	1.09	1 M	
2.606800267 G	29.81	32.588	-25.681	52.870	-23.06	İ	8	1.80	1 M	
2.169899799 G	32.13	31.286	-25.971	52.870	-20.74		292	1.32	1 M	
4.377682031 G	35.31	33.626	-23.629	52.870	-17.56		21	2.53	1 M	
3.037822311 G	36.68	32.966	-25.105	52.870	-16.19		287	2.04	1 M	
3.890567802 G	40.50	33.670	-23.781	52.870	-12.37		360	1.09	1 M	
1.301863727 G	45.69	28.874	-27.576	52.870	-7.18		150	1.09	1 M	


Azimuth Plots





Turntable Plot (1.736212425 GHz)




Turntable Plots











































Test Information

Test Details

User Entry Radiated - FCC15.231e @ 3m Test: Project: IntelliSaw_Q500592446


Test Notes: Temperature: 120VAC/60Hz, Both antennas, 445 MHz, X-Axis, worst-case

21 deg C 38%, 994 mB Humidity: Vathana Ven 10 Apr 2015 18:29 Tested by: Test Started:

Additional Information

Comment

Prescan Emission Graph



Measured Peak Value

Measured Quasi Peak Value

Measured Average Value Maximum Value of Mast and Turntable Swept Peak Data

Swept Quasi Peak Data

Swept Average Data

Emissions Test Data

Trace1: Measured Peak

Frequency (Hz)	Level (dBuV/m)	AF	PA+CL	Limit (dBuV/m)	Margin (dBuV/m)	Hor (), Ver ()	Azimuth (deg)(Deg)	Mast Height(m)	RBW(Hz)	Comment
1.332732131 G	43.97	28.823	-27.486	73.220	-29.25		187	1.19	1 M	
3.550627922 G	49.67	33.042	-24.420	73.220	-23.55		50	1.80	1 M	
2.669812959 G	51.88	32.519	-25.522	73.220	-21.34	Ì	317	2.29	1 M	
2.22490982 G	53.82	31.306	-26.041	73.220	-19.40	İ	192	2.52	1 M	
3.114856379 G	56.86	32.979	-25.220	73.220	-16.36	Ì	249	3.12	1 M	
1 77993988 G	59 56	29.739	-26 674	73 220	-13 66		195	1 09	1 M	


Trace3: Measured Average


Frequency (Hz)	Level (dBuV/m)	AF	PA+CL	Limit (dBuV/m)	Margin (dBuV/m)	Hor (), Ver ()	Azimuth (deg)(Deg)	Mast Height(m)	RBW(Hz)
1.332732131 G	23.97	28.823	-27.486	53.220	-29.25		187	1.19	1 M
3.550627922 G	29.67	33.042	-24.420	53.220	-23.55		50	1.80	1 M
2.669812959 G	31.88	32.519	-25.522	53.220	-21.34	ĺ	317	2.29	1 M
2.22490982 G	33.82	31.306	-26.041	53.220	-19.40		192	2.52	1 M
3.114856379 G	36.86	32.979	-25.220	53.220	-16.36	ĺ	249	3.12	1 M
1.77993988 G	39.56	29.739	-26.674	53.220	-13.66		195	1.09	1 M

Non-Specific EMC Report Shell Rev. May 2014 Page 74 of 110


Client: IntelliSAW, Product Designation: Modular Device (RF Card)


Azimuth Plots







Turntable Plots

























Turntable Plot (3.550627922 GHz)

Level (dBuV/m)





Vathana Ver Test Personnel: Supervising/Reviewing Engineer: (Where Applicable)

Input Voltage:

FCC Part 15 Subpart C, RSS-210 Powered from 24VDC Host

Pretest Verification w/ Ambient Signals or BB Source:

Product Standard:

Ambient Signals

Test Date: 04/09/2015

Limit Applied: Section 15.231(e), RSS-210

Ambient Temperature: See data tables

Relative Humidity: See data tables

Atmospheric Pressure: See data tables

9 Duty Cycle

9.1 Method

Tests are performed in accordance with FCC 47CFR Part 15 Subpart C Section 15.231(c), ANSI C63.10:2009, RSS-Gen Section 6.10.

TEST SITE: 10m ALSE

The 10m ALSE is 13m (Length) x 21m (Depth) x 10m (Height) with the effective size in terms of space from the tips of the absorber is 12m (Length) x 20m (Depth) x 8.5m (Height). This chamber achieves broadband performance using a unique arrangement of hybrid and ferrite tile absorber. This chamber has a built in 3m diameter turntable (Embedded type). The metal structure of the table makes electrical connection around the entire circumference of the turntable to the ground plane with a metal brush type connection. The turntable is located on one end of the chamber and the antennas are mounted 3 and 10 meters away at the other end of the chamber on the adjustable an Antenna Mast. The antenna mast is a non-conductive bore sighted type with remote control of antenna height and polarization. The Antenna Mast and the turntable can be remotely controlled through the controller located in the adjacent Control room. A wooden table 80 cm high is used for table-top equipment.

9.2 Test Equipment Used:

Asset	Description	Manufacturer	Model	Serial	Cal Date	Cal Due
145128'	EMI Receiver (20 Hz - 40 Ghz)	Rohde & Schwarz	ESIB 40	839283/001	03/14/2015	03/14/2016
145-410'	Cables 145-400 145-403 145-405 145-406 145-407	Huber + Suhner	10m Track A Cables	multiple	10/04/2014	10/04/2015
145106'	Bilog Antenna (30MHz - 5GHz)	Sunol Sciences	JB5	A111003	10/24/2014	10/24/2015
Dav004'	Weather Station	Davis Instruments	7400	PE80529A61A	10/06/2014	10/06/2015


Software Utilized:

Name	Manufacturer	Version
None		


9.3 Results:

There is no limit on duty cycle, it is used to obtain the average value of emissions. The duty cycle average factor was determined to be 20 dB.


9.4 Setup Photograph:



9.5 Plots/Data:



Report Number: 102085252BOX-001c Issued: 06/05/2015



Issued: 06/05/2015 Report Number: 102085252BOX-001c

Test Personnel:	Vathana Ven	Test Date:	04/09/2015
Supervising/Reviewing			
Engineer: (Where Applicable)	N/A		
Product Standard:	FCC Part 15 Subpart C, RSS-Gen	Limit Applied:	N/A
Input Voltage:	Powered from 24VDC Host		
Pretest Verification w/		Ambient Temperature:	21 °C
Ambient Signals or			
BB Source:	Ambient Signals	Relative Humidity:	38 %
		Atmospheric Pressure:	994 mbars

10 Automatically Limiting Operation

10.1 Method

Tests are performed in accordance with FCC 47CFR Part 15 Subpart C Section 15.231(e), ANSI C63.10:2009, RSS-210.

TEST SITE: 10m ALSE

The 10m ALSE is 13m (Length) x 21m (Depth) x 10m (Height) with the effective size in terms of space from the tips of the absorber is 12m (Length) x 20m (Depth) x 8.5m (Height). This chamber achieves broadband performance using a unique arrangement of hybrid and ferrite tile absorber. This chamber has a built in 3m diameter turntable (Embedded type). The metal structure of the table makes electrical connection around the entire circumference of the turntable to the ground plane with a metal brush type connection. The turntable is located on one end of the chamber and the antennas are mounted 3 and 10 meters away at the other end of the chamber on the adjustable an Antenna Mast. The antenna mast is a non-conductive bore sighted type with remote control of antenna height and polarization. The Antenna Mast and the turntable can be remotely controlled through the controller located in the adjacent Control room. A wooden table 80 cm high is used for table-top equipment.

10.2 Test Equipment Used:

Asset	Description	Manufacturer	Model	Serial	Cal Date	Cal Due
ROS001'	Spectrum Analyzer 20Hz - 40 GHz	Rohde & Schwartz	FSEK-30	100225	05/19/2014	05/19/2015
CBLSHF203'	Cable, SMA - SMA, < 18GHz	Sucoflex (Huber Suhn	104PE	CBLSHF203	06/03/2004	06/03/2015
WEI8'	Attenuator	Weinschel Corp	47-10-34	BD8309	04/02/2015	04/02/2016
Dav004'	Weather Station	Davis Instruments	7400	PE80529A61A	10/06/2014	10/06/2015

Software Utilized:

Name	Manufacturer	Version
None		


10.3 Results:

The sample tested was found to Comply.


In addition, devices operated under the provisions of this paragraph shall be provided with a means for automatically limiting operation so that the duration of each transmission shall not be greater than one second and the silent period between transmissions shall be at least 30 times the duration of the transmission but in no case less than 10 seconds.

Page 83 of 110 Client: IntelliSAW, Product Designation: Modular Device (RF Card)

10.4 Setup Photograph:




10.5 Plots/Data:



Date: 1.JAN.1997 00:52:11

Report Number: 102085252BOX-001c Issued: 06/05/2015



Date: 1.JAN.1997 00:53:23

Report Number: 102085252BOX-001c Issued: 06/05/2015

Test Personnel: Vathana Ven Test Date: 04/09/2015 Supervising/Reviewing Engineer: (Where Applicable) FCC Part 15 Subpart C, RSS-210 Powered from 24VDC Host Product Standard: Limit Applied: Section 15.231(e), RSS-210 Input Voltage: Ambient Temperature: 21 °C Pretest Verification w/ Ambient Signals or BB Source: Ambient Signals Relative Humidity: 38 % Atmospheric Pressure: 994 mbars

Non-Specific EMC Report Shell Rev. May 2014 Page 87 of 110

11 AC Mains Conducted Emissions

11.1 Method

Tests are performed in accordance with FCC 47CFR Part 15 Subpart B, ANSI C63.10:2009, ICES-003.

TEST SITE: 10m ALSE

<u>The EMC Lab</u> has one Semi-anechoic Chamber and one Shielded Chamber. AC Mains Power is available at 120, 230, and 277 Single Phase; 208, 400, and 480 3-Phase. Large reference ground-planes are installed in the general lab area to facilitate EMC work not requiring a shielded environment.

The 10m ALSE is 13m (Length) x 21m (Depth) x 10m (Height) with the effective size in terms of space from the tips of the absorber is 12m (Length) x 20m (Depth) x 8.5m (Height). This chamber achieves broadband performance using a unique arrangement of hybrid and ferrite tile absorber. This chamber has a built in 3m diameter turntable (Embedded type). The metal structure of the table makes electrical connection around the entire circumference of the turntable to the ground plane with a metal brush type connection. A Styrofoam table 80 cm high is used for table-top equipment.

Measurement Uncertainty

Measurement	Frequency Range	Expanded Uncertainty (k=2)	Ucispr
AC Line Conducted			
Emissions	150 kHz - 30 MHz	2.8	3.4
Telco Port Emissions	150 kHz - 30 MHz	3.2	5

Sample Calculations

The following is how net line-conducted readings were determined:

NF = RF + LF + CF + AF

Where NF = Net Reading in $dB\mu V$

RF = Reading from receiver in $dB\mu V$

LF = LISN or ISN Correction Factor in dB

CF = Cable Correction Factor in dB

AF = Attenuator Loss Factor in dB

To convert from dB μ V to μ V or mV the following was used:

UF =
$$10^{(NF/20)}$$
 where UF = Net Reading in μV
NF = Net Reading in $dB\mu V$

Example:

NF = RF + LF + CF + AF = 28.5 + 0.2 + 0.4 + 20.0 = 49.1 dB
$$\mu V$$
 UF = $10^{(49.1~dB \mu V \ / \ 20)}$ = 285.1 $\mu V/m$

Alternately, when C5 Software is used, the "Level" includes all losses and gains and is compared directly in the "Margin" column to the "Limit". "TF" is the Transducer Factor; in this case LISN or ISN loss.

Report Number: 102085252BOX-001c Issued: 06/05/2015

11.2 Test Equipment Used:

Asset	Description	Manufacturer	Model	Serial	Cal Date	Cal Due
				PE80529A61		
DAV004	Weather Station	Davis Instruments	7400	Α	10/06/2014	10/06/2015
145128	EMI Receiver (20 Hz - 40 Ghz)	Rohde & Schwarz	ESIB 40	839283/001	03/14/2015	03/14/2016
LISN32	LISN - CISPR16 Compliant 9kHz-30MHz	Com-Power	LI-215A	191955	03/18/2015	03/18/2016
DS27	Attenuator, 20dB	Mini Circuits	20dB, 50 ohm	DS27	10/01/2014	10/01/2015
CBLBNC1						
0	25 ft, 50 Ohm BNC Cable	Pomona	RG 58 C/U	CBLBNC10	10/04/2014	10/04/2015

Software Utilized:

Name	Manufacturer	Version
C5	TESEQ	Build 5.26.46.46

11.3 Results:

The sample tested was found to Comply.

11.4 Setup Photographs:



With Agilent variable power supply




11.5 Plots/Data:

Test Information

User Entry LISN - FCC15 Class B Test Details IntelliSaw_G102014290 120VAC/60Hz, 24VDC Project: Test Notes: 22 deg C 37%, 1013 mB Vathana Ven 4 Jun 2015 17 : 12 Temperature: Humidity: Tested by: Test Started:

Additional Information

Prescan Emission Graph



Measured Peak Value Measured Quasi Peak Value Measured Average Value Maximum Value of Mast and Turntable

Swept Quasi Peak Data Swept Average Data

Swept Peak Data

Emissions Test Data

Trace2: Measured Quasi Peak

	acaas ca							
Frequency(Hz)	Level(dBuV)	TF	PA+CL	Limit(dBuV)	Margin(dBuV)	RBW(Hz)	Comment	LINE
20.02004008 M	21.29	0.110	21.174	60.000	-38.71	9 k		L1
160.220440882 k	28.22	0.070	20.460	65.453	-37.23	9 k		L1
414.028056112 k	22.29	0.030	20.589	57.567	-35.28	9 k		L1
194.288577154 k	28.80	0.056	20.508	63.851	-35.05	9 k		L1
497.49498998 k	21.07	0.030	20.589	56.042	-34.97	9 k		L1
209.619238477 k	28.26	0.048	20.521	63.220	-34.96	9 k		L1
270.941883768 k	28.11	0.040	20.570	61.089	-32.98	9 k		L1
333.967935872 k	26.40	0.033	20.570	59.352	-32.95	9 k		L1

Trace3: Measured Average

Frequency(Hz)	Level(dBuV)	TF	PA+CL	Limit(dBuV)	Margin(dBuV)	RBW(Hz)	Comment	LINE
20.02004008 M	17.30	0.110	21.174	50.000	-32.70	9 k		L1
160.220440882 k	22.92	0.070	20.460	55.453	-32.53	9 k		L1
194.288577154 k	24.25	0.056	20.508	53.851	-29.60	9 k		L1
270.941883768 k	22.65	0.040	20.570	51.089	-28.44	9 k		L1
333.967935872 k	21.06	0.033	20.570	49.352	-28.29	9 k		L1
414.028056112 k	23.01	0.030	20.589	47.567	-24.55	9 k		L1
497.49498998 k	21.90	0.030	20.589	46.042	-24.14	9 k		L1
209.619238477 k	35.34	0.048	20.521	53.220	-17.88	9 k		L1

Page 92 of 110 Non-Specific EMC Report Shell Rev. May 2014

Client: IntelliSAW, Product Designation: Modular Device (RF Card)


Test Information

User Entry LISN - FCC15 Class B IntelliSaw_G102014290 Test Details Test: Project:

Test Notes: 120VAC/60Hz, Module with switch power supply

22 deg C 37%, 1013 mB Vathana Ven 4 Jun 2015 17 : 59 Temperature: Humidity: Tested by: Test Started:

Prescan Emission Graph



Measured Peak Value Measured Quasi Peak Value

> Measured Average Value Maximum Value of Mast and Turntable

Swept Peak Data Swept Quasi Peak Data __ Swept Average Data

Additional Information

Emissions Test Data

Frequency(Hz)	Level(dBuV)	TF	PA+CL	Limit(dBuV)	Margin(dBuV)	RBW(Hz)	Comment	LINE
19.97995992 M	21.28	0.110	21.156	60.000	-38.72	9 k		L1
436.172344689 k	22.65	0.030	20.579	57.134	-34.49	9 k		N
543.486973948 k	22.30	0.030	20.598	56.000	-33.70	9 k		N
335.671342685 k	27.30	0.033	20.573	59.310	-32.01	9 k		N
272.645290581 k	29.85	0.040	20.570	61.037	-31.19	9 k		N
250.501002004 k	32.76	0.040	20.557	61.741	-28.98	9 k		N
195.991983968 k	36.20	0.054	20.498	63.779	-27.58	9 k		N
163.627254509 k	41.11	0.066	20.460	65.278	-24.17	9 k		N

rraces. Measured A	average							
Frequency(Hz)	Level(dBuV)	TF	PA+CL	Limit(dBuV)	Margin(dBuV)	RBW(Hz)	Comment	LINE
19.97995992 M	16.53	0.110	21.156	50.000	-33.47	9 k		L1
163.627254509 k	27.22	0.066	20.460	55.278	-28.06	9 k		N
195.991983968 k	27.24	0.054	20.498	53.779	-26.54	9 k		N
250.501002004 k	25.40	0.040	20.557	51.741	-26.34	9 k		N
543.486973948 k	19.67	0.030	20.598	46.000	-26.33	9 k		N
436.172344689 k	21.06	0.030	20.579	47.134	-26.07	9 k		N
335.671342685 k	23.34	0.033	20.573	49.310	-25.97	9 k		N
272.645290581 k	26.41	0.040	20.570	51.037	-24.63	9 k		N

Page 93 of 110 Client: IntelliSAW, Product Designation: Modular Device (RF Card)

Report Number: 102085252BOX-001c Issued: 06/05/2015

Vathana VenVFV 06/04/2015 Test Date: Test Personnel: Supervising/Reviewing Engineer: (Where Applicable) FCC Part 15, ICES003 Product Standard: Limit Applied: Class B Input Voltage: 120VAC/60Hz Pretest Verification w/ Ambient Temperature: 22 °C Ambient Signals or Relative Humidity: 37 % BB Source: Yes Atmospheric Pressure: 1013 mbars

Deviations, Additions, or Exclusions: None

12 Receiver Radiated Spurious Emissions

12.1 Method

Tests are performed in accordance with FCC 47CFR Part 15 Subpart B, ANSI C63.10:2009, ICES-003

TEST SITE: 10m ALSE

The 10m ALSE is 13m (Length) x 21m (Depth) x 10m (Height) with the effective size in terms of space from the tips of the absorber is 12m (Length) x 20m (Depth) x 8.5m (Height). This chamber achieves broadband performance using a unique arrangement of hybrid and ferrite tile absorber. This chamber has a built in 3m diameter turntable (Embedded type). The metal structure of the table makes electrical connection around the entire circumference of the turntable to the ground plane with a metal brush type connection. The turntable is located on one end of the chamber and the antennas are mounted 3 and 10 meters away at the other end of the chamber on the adjustable an Antenna Mast. The antenna mast is a non-conductive bore sighted type with remote control of antenna height and polarization. The Antenna Mast and the turntable can be remotely controlled through the controller located in the adjacent Control room. A wooden table 80 cm high is used for table-top equipment.

Measurement Uncertainty

For radiated emissions, U_{lab} (3.5 dB at 3m and 3.5 dB at 10m below 1 GHz, and 4.2 dB at 3m above 1 GHz) $< U_{CISPR}$ (5.2 dB), which is the reference value in CISPR 16-4-2 Table 1, hence the compliance of the product is only based on the measured value, and no measurement uncertainty correction is required, based on CISPR 22 and CISPR 11 (for 2006 and later revisions) Clause 11.

Page 95 of 110 Client: IntelliSAW, Product Designation: Modular Device (RF Card)

Sample Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

FS = RA + AF + CF - AG

Where $FS = Field Strength in dB\mu V/m$

RA = Receiver Amplitude (including preamplifier) in dBµV

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB AG = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows.

Assume a receiver reading of 52.0 dB_µV is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32 dBμV/m. This value in dB_μV/m was converted to its corresponding level in μV/m.

 $RA = 52.0 dB\mu V$ AF = 7.4 dB/mCF = 1.6 dB $AG = 29.0 \, dB$ $FS = 32 dB\mu V/m$

To convert from $dB\mu V$ to μV or mV the following was used:

UF =
$$10^{(NF/20)}$$
 where UF = Net Reading in μ V NF = Net Reading in dB μ V

Example:

FS = RA + AF + CF - AG =
$$52.0 + 7.4 + 1.6 - 29.0 = 32.0$$
 UF = $10^{(32 \, dB_{\mu}V \, / \, 20)} = 39.8 \, \mu V/m$

Non-Specific EMC Report Shell Rev. May 2014 Page 96 of 110

Report Number: 102085252BOX-001c Issued: 06/05/2015

12.2 Test Equipment Used:

Asset	Description	Manufacturer	Model	Serial	Cal Date	Cal Due
145128'	EMI Receiver (20 Hz - 40 Ghz)	Rohde & Schwarz	ESIB 40	839283/001	03/14/2015	03/14/2016
145-410'	Cables 145-400 145-403 145-405 145-406 145-407	Huber + Suhner	10m Track A Cables	multiple	10/04/2014	10/04/2015
145106'	Bilog Antenna (30MHz - 5GHz)	Sunol Sciences	JB5	A111003	10/24/2014	10/24/2015
Dav004'	Weather Station	Davis Instruments	7400	PE80529A61A	10/06/2014	10/06/2015
REA003'	1GHz High Pass Filter	Reactel, Inc	7HS-1G/10G-S11	06-1	12/30/2013	12/30/2015
145-416'	Cables 145-400 145-402 145-404 145-408	Huber + Suhner	3m Track B cables	multiple	10/04/2014	10/04/2015
145014'	Preamplifier (1 GHz to 26.5 GHz)	Hewlett Packard	8449B	3008A00232	05/05/2014	05/05/2015
ETS002'	1-18GHz DRG Horn Antenna	ETS Lindgren	3117	00143260	04/10/2015	04/10/2016


Software Utilized:


Name	Manufacturer	Version		
EMI Boxborough	Intertek	8/27/2010		
C5	TESEQ	Build 5.26.46.46		


12.3 Results:


The sample tested was found to Comply.

12.4 Setup Photographs:









Test Information

Test Details

User Entry Radiated - FCC15 Class B @ 10m Test:

Project:


Threllisaw_G102014290

5VDC, Antenna (IA-MM-TPD, PIFA Patched Inverted F), Idle/Rx mod 22 deg C

10%, 1007 mB Test Notes: Temperature:

Humidity: Tested by: Test Started: Vathana Ven 26 Feb 2015 23 : 26

Prescan Emission Graph



Measured Peak Value Measured Quasi Peak Value Measured Average Value

Maximum Value of Mast and Turntable

Swept Peak Data

Swept Quasi Peak Data

Additional Information

Swept Average Data

Emissions Test Data


Trace2: Measured Quasi Peak


Frequency (Hz)	Level (dBuV/m)	AF	PA+CL	Limit (dBuV/m)	Margin (dBuV/m)	Hor (), Ver ()	Azimuth (deg)(Deg)	Mast Height(m)	RBW(Hz)	Comment
275.129459198 M	12.54	13.403	-23.356	36.020	-23.48		360	1.06	120 k	
100.051302685 M	22.33	10.310	-24.729	33.520	-11.19		275	4.00	120 k	
80.030260301 M	19.85	7.497	-24.948	30.000	-10.15		31	3.21	120 k	
62.621242301 M	21.01	7.700	-25.056	30.000	-8.99		281	4.00	120 k	
57.327455052 M	21.86	7.200	-25.062	30.000	-8.14		328	2.83	120 k	
150.006212285 M	25.55	12.700	-24.130	33.520	-7.97	İ	328	1.16	120 k	
48.485370874 M	23.33	8.606	-25.230	30.000	-6.67		259	4.00	120 k	
30.684769595 M	23.95	20.789	-25.461	30.000	-6.05		1	2.72	120 k	
42.723246896 M	27.50	12.194	-25.324	30.000	-2.50		230	3.73	120 k	

Non-Specific EMC Report Shell Rev. May 2014 Page 100 of 110


Client: IntelliSAW, Product Designation: Modular Device (RF Card)


Azimuth Plots







Turntable Plots

































All Polarities




Non-Specific EMC Report Shell Rev. May 2014 Client: IntelliSAW, Product Designation: Modular Device (RF Card)


Azimuth (Degrees)
















All Polarities Azimuth (Degrees)





Test Information

Test Details

User Entry Radiated - FCC15 Class B @ 3m Test:

Project:

ThrelliSaw_G102014290


5VDC, Antenna (IA-MM-TPD, PIFA Patched Inverted F), Idle/Rx mod 22 deg C

10%, 1007 mB Test Notes: Temperature:

Humidity: Tested by: Test Started: Vathana Ven 27 Feb 2015 01 : 47

Additional Information

Prescan Emission Graph



Measured Peak Value

Measured Quasi Peak Value Measured Average Value

Maximum Value of Mast and Turntable

Swept Peak Data

Swept Quasi Peak Data

Swept Average Data

Emissions Test Data


Trace1: Measured Peak


Frequency (Hz)	Level (dBuV/m)	AF	PA+CL	Limit (dBuV/m)	Margin (dBuV/m)	Hor (), Ver ()	Azimuth (deg)(Deg)	Mast Height(m)	RBW(Hz)	Comment
1.16251169 G	42.94	27.812	-28.184	74.000	-31.06		0	1.08	1 M	
1.265190381 G	43.44	28.610	-27.839	74.000	-30.56		15	1.32	1 M	
2.178804275 G	48.98	31.290	-25.987	74.000	-25.02		320	1.06	1 M	
2.019124916 G	49.52	31.224	-25.906	74.000	-24.48		360	1.78	1 M	
2.937254509 G	50.45	32.853	-25.170	74.000	-23.55		172	1.91	1 M	
2.419826319 G	50.84	32.094	-25.873	74.000	-23.16	1	193	1.07	1 M	

Trace3: Measured Average


Frequency (Hz) 1.16251169 G	Level (dBuV/m) 29.33	AF 27.812	PA+CL -28.184	Limit (dBuV/m) 54.000	Margin (dBuV/m) -24.67	Hor (), Ver ()	Azimuth (deg)(Deg)	Mast Height(m)	RBW(Hz)	Comment
1.265190381 G	30.01	28.610	-27.839	54.000	-23.99		15	1.32	1 M	
2.178804275 G	35.15	31.290	-25.987	54.000	-18.85		320	1.06	1 M	
2.419826319 G 2.019124916 G	35.30 36.01	32.094 31.224	-25.873 -25.906	54.000 54.000	-18.70 -17.99		193 360	1.07 1.78	1 M 1 M	
2.937254509 G	36.27	32.853	-25.170	54.000	-17.73	<u></u>	172	1.91	1 M	


Azimuth Plots








Turntable Plots































Vathana Ver Test Personnel: Supervising/Reviewing Engineer: (Where Applicable) N/A FCC Part 15 Subpart C, RSS-210 Product Standard: Input Voltage:

Section 15.231(e), RSS-210

Test Date: 02/27/2015

Pretest Verification w/ Ambient Signals or BB Source:

Powered from 24VDC Host

Ambient Temperature: See data tables

Limit Applied:

Ambient Signals Relative Humidity: See data tables

Atmospheric Pressure: See data tables

Report Number: 102085252BOX-001c Issued: 06/05/2015

13 Revision History

Revision	Date	Report Number	Prepared	Reviewed	Notes
Level			Ву	Ву	
0	06/05/2015	102085252BOX-001c	VFV	MFM 💯	Original Issue