GETTING STARTED

When you first start using your Yepzon tracker, plug it into a charger and if possible, charge it for two hours. This ensures that the device wakes up and has optimal performance.

A recommended precaution is to request a reset link from the **Settings**. You will need the reset link if you suddenly don't have access to your phone anymore or you accidentally delete the app. Requesting a reset link sends you an e-mail message with a link that can be used to remove all the users. Your e-mail address is not collected, saved or used by Yepzon for anything else than sending the reset link.

After pairing you should see your tracker in the App either on a list or map view and you are able to toggle between the views from the top right corner icon. List view shows current status of the device, map view shows the last location of the Yepzon tracker on a map.

SETTINGS

In the Settings you are able to control the following functions:

Manage access rights: Adding and allowing more users to locate and manage the Yepzon tracker.

Note: All users will have full access.

Activate buzzer and led: Turns on device's buzzer and led to help you find the device nearby.

Flight mode: Device will be powered off for the set duration. You may also use this to save battery for times when tracking is not required.

Edit notifications: Select what Yepzon activity you want to be notified about.

Edit sensor alerts: Set alerts for selected temperature and acceleration values.

Turn off the Yepzon: Shuts down the tracker. Note: After shutdown the tracker can be activated only by charger or by pressing the SOS button for 3 seconds.

SERVICE

Yepzon tracker has a built-in SIM card and it uses mobile network to transfer information to the mobile app.

Your tracker includes 1 month of free service to start with, after which you can easily purchase more via application **Service** or Yepzon.com/shop. The pre-paid subscription with length of your choice includes unlimited usage.

If you want to use your tracker outside EU, USA, Russia and China [Note: Please check yepzon.com/roaming for any changes in this list], you must buy roaming through Yepzon app **Settings** \rightarrow **Purchase roaming package**. Price depends on country and length of visit. Countries applicable and prices can be found on **yepzon.com/roaming**.

LOCATING

Yepzon Smart Tracker uses cell towers, GPS and Wi-Fi for positioning, and Bluetooth to find the tracker nearby.

In **Quick location** mode the tracker is always online and can be located instantly by tapping **Update location**. In **Constant tracking** mode the interval setting determines how frequently the accurate location is given. You may increase battery life by setting longer intervals. We recommend using frequent constant tracking for Geofencing. In **SOS only** mode location can be initiated only by pressing the SOS button on the device.

Accuracy of the position can be checked by tapping the location pin on the map. If GPS signal is not strong enough [e.g indoors] and WiFi hotspots are not present, a rough position based on cell towers might be shown when the radius, shown as red circle, can be up to kilometers/miles.

SOS ALERT

Pressing the SOS button of the Smart Tracker for 3 seconds initiates a SOS alert to the Yepzon App and provides the accurate location of the tracker.

You need to enable Yepzon App notifications on your smartphone or tablet to receive notification on the alert, and sounds to hear the SOS alarm sound.

SOS alert works same way in all modes.

More information, FAQ, announcements etc. available at **YEPZON.COM/SUPPORT**.

Please read carefully the Safety and Compliance leaflet and content printed inside the packaging sleeve.

Note! Over six months of tracker inactivity may cause SIM card deactivation and/or battery deep discharge.

Smart Tracker by Yepzon™
QUICK START
Android/iPhone







