

• Previous song : Press volume- button for 2 seconds

• Next song : Press volume+ button for 2 seconds

• Incoming call/Music playback : Short press the Multifunction button (the music will pause)

• End call/Music playback : Short press the Multifunction button (the headset will play/pause the music)

• Reject call : Press and hold the Multifunction button for 2 seconds

• Make a call : Double press the Multifunction button to dial/number (the music will pause)

LED indicator status

• Power on : The blue LED will flash twice

• Power off : The red LED will flash once

• Pairing mode : The red and blue LED lights will flash in an alternating pattern

• Standby mode without BT connection : The blue led light will flash once every 5 seconds

• Standby mode with BT connection : The blue led light will flash once every 3 seconds

• Incoming call : The blue led light will flash quickly

• Making a call : The blue led light will flash quickly

• Calling : The blue led light will flash every 3 seconds

• Playing music : The blue led light will flash twice every 4 seconds

• Charging : Red LED light

• Charging completed : Blue LED light

• When the BS0508 has a low battery, the red led light will flash once every 20 seconds,you will hear a prompt : "battery low"

Notes:

• If the headset doesn't connect with any devices, it will turn off automatically after 5 minutes

• Pairing time : Pairing mode will remain active for 3 minutes; if the headset doesn't connect with the mobile phone after 3 minutes, the headset will quit the pairing mode automatically.

Connect with two mobile phones

Steps :

- First disconnect the Bluetooth device from your phone if it is already connected.
- Press and hold red and blue led at the same time until the red and blue LED lights will flash in an alternating pattern, the BS0508 will enter pairing mode again.
- Turn on and search Bluetooth device on your second phone until you find "BS0508" and select to begin pairing.
- These reconnect with the first mobile phone.
- Now you should have two mobile phones connected with the headset. Transfer Calls :

When you are talking on the phone and receive another incoming call, press the MFB for 2 seconds to reject the incoming call if you click vol+ and vol- concurrently (with the remaining button, you will answer the incoming call, if you click vol+ will be placed on hold; if you click vol- and vol- concurrently again, you will transfer back to your first call. You should hear a beep. During the time your second call will not be placed on hold. You can also do the call by clicking the MFB.

Music play operation

Music play : Operate on the phone or on the headset.

(Music will play automatically on some mobile phones when i connect with Bluetooth device)

- Pause music : Press multifunction button to pause music
- Play music : Press multifunction button again to restart music
- Increase volume : Press volume+ button, when the volume reaches the maximum level, the BS0508 will produce a short tone.
- Decrease volume : Press volume- button, when the volume reaches the minimum level, the BS0508 will produce a short tone.

• Answering call : Press the Multifunction button until you hear a tone "call answered"

• Reject incoming call : Press and hold the Multifunction button for 2 seconds until you hear a tone "call rejected"

• Press and hold vol+ and vol- at the same time until you hear a tone "call terminated"

• Adjusting the volume : Press the Volume Up button or Press the Volume down button will produce a short tone

- Redial but call : Double press the MFB button when no call is in progress and headset will say "Last number redial"
- Mute microphone : Press either the - or the + volume button for 2 seconds to mute
- Microphone : Press either the - or the + volume button for 2 seconds to unmute
- Replay music : Repeat and hold the - or the + volume button for 2 seconds to unmute
- Switching between Your Mobile-Phone and Headset : When talking on the phone, double-click the MFB to switch the voice from your headset to your mobile phone, you double-click the MFB again, the voice will switch back to the headset
- Reconnect : When the headset is disconnected from your mobile phone, you will hear the words "Your headset is disconnected". If you press the MFB, it will reconnect. You'll hear "Your headset is connected"

Some mobile phone may have a prompt screen, that will ask you if you would like to pair your device.

• Switch the language : Press vol+ and vol- button when the headset is power on or you hear a prompt "English/language selected"

Bluetooth Parameters

- Bluetooth Version: 4.1-EDR
- Bluetooth Profile Supported : HSP, HFP, A2DP, AVRCP, APTX
- The remote control to speaker : (MP3/MP4/Power/Sport)
- Vol- : Previous song ; Vol+ : Next song ;
- Device Name : BS0508
- Pass : 0000
- RF transmitter : class II (2.4GHz~4.4GHz)
- Receive Sensitivity : -92dBm
- Transmission Range(s) : 200m
- Transmission distance : 10m

Certification

Mechanical reliability

- Button : 10 thousand times
- Charger port (Mini USB) : 10000 times
- Charger port (Micro USB) : 5000 times
- LED : Luminescence light-bearing lifetime must remain the same

Answer/Make a call

- Power on : When the headset is off, press and hold multifunction button for 3 seconds, the blue led light will flash twice until you will hear a prompt "Power On"
- Power off : When the headset is on, press and hold multifunction button for 3 seconds (Red LED blinking), you will hear a prompt "Power Off"
- Pairing mode : When the headset is off, press and hold multifunction button for 6 seconds (red and blue LED blinking alternately), until you will hear the prompt "Pairing". Turn the headset on.
- Vol+ and vol- : You release the button before the LED blink, the headset will decrease volume; Press volume off the headset when on and hold vol+ and vol- the same time to go into pairing mode again.
- Easy connection function : If the headset doesn't connect with any phones when it is on, press and hold vol+ and vol- at the same time to enter into pairing mode.

Basic Specifications

- Size : 560L*197W*26mm(T)
- Weight : 15.5g (Net Weight)
- Charging port : Micro USB
- GPS : MFB button, Volume+ (Previous song button) , Volume- (Next song button)
- Earbuds : S, M, L
- Battery : Rechargeable Lithium Polymer Battery 3.7V ; 160mAh
- Charging input : DC 5V 800mA
- Charging output : 5V 1.5A ; 1.0A
- Charging indicator : Red LED light (Charging) / Blue LED light (Charging completed)
- Standby time : 150H
- Talk time : 9-10H
- Music Playback time : 8-10H
- Charging time : 2H-2.5H
- Volume adjustment : 16 volume level/ 5 steps of 1.5dB
- Indicator for charge in working stage : Battery voltage lower than 3.2V (the stage of battery lower than 3V), the headset will warning tone of low battery
- Indicator for charge in working stage : Battery voltage lower than 3.2V (the stage of battery lower than 3V), the headset will warning tone of low battery
- Operating temperature : Charge : 0-40°C; Charging from -20-60°C
- Storage temperature : -40-40°C

Speaker and MIC parameters

- Speaker Specification(model) : 69.0mm, Dynamic
- Distortion : below 1%
- Maximum input power : 50mW
- Impedance : 16-20Ω
- Frequency(Hz) : 20Hz-200Hz
- MIC sensitivity : 42±3dB

Stereo Bluetooth Headset User manual

STEREO EARPHONES

BLUETOOTH

FEATURING 4.1 TECHNOLOGY

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.