



FCC&ISED Radio Test Report

FCC ID: 2AO2D-YKF429-004

IC: 23681-YKF429004

This report concerns (check one): ⊠Original Grant □Class I Change □Class II Change

Project No. : 1803C261

Equipment: Bluetooth Remote Control

Test Model : YKF429-004

Series Model : N/A

Applicant : Fengmi(Beijing)Technology Co.,Ltd

Address: 301, 3F, Building 3 No. 10, Shunyi District Renhe

Town Barracks South Street, Beijing, China

Date of Receipt : Mar. 26, 2018

Date of Test : Mar. 28, 2018 ~ May 10, 2018

Issued Date : May 29, 2018 Tested by : BTL Inc.

Testing Engineer

(Paul Li)

Technical Manager

(Shawh Xian)

Authorized Signatory

(David Mag)

BTL INC.

No.3, Jinshagang 1st Road, Shixia, Dalang Town, Dongguan, Guangdong, China.

TEL: +86-769-8318-3000 FAX: +86-769-8319-6000



Report No.: BTL-FICP-1-1803C261 Page 1 of 68





Declaration

BTL represents to the client that testing is done in accordance with standard procedures as applicable and that test instruments used has been calibrated with standards traceable to international standard(s) and/or national standard(s).

BTL's reports apply only to the specific samples tested under conditions. It is manufacture's responsibility to ensure that additional production units of this model are manufactured with the identical electrical and mechanical components. **BTL** shall have no liability for any declarations, inferences or generalizations drawn by the client or others from **BTL** issued reports.

BTL's report must not be used by the client to claim product certification, approval, or endorsement by NVLAP, NIST, or any agency of the Federal Government.

This report is the confidential property of the client. As a mutual protection to the clients, the public and **BTL-self**, extracts from the test report shall not be reproduced except in full with **BTL**'s authorized written approval.

BTL's laboratory quality assurance procedures are in compliance with the **ISO Guide 17025** requirements, and accredited by the conformity assessment authorities listed in this test report.

Limitation

For the use of the authority's logo is limited unless the Test Standard(s)/Scope(s)/Item(s) mentioned in this test report is (are) included in the conformity assessment authorities acceptance respective.

Report No.: BTL-FICP-1-1803C261 Page 2 of 68





Table of Contents	Page
1 . CERTIFICATION	6
2 . SUMMARY OF TEST RESULTS	7
2. SUMMART OF TEST RESULTS 2.1 TEST FACILITY	8
2.1 TEST FACILITY 2.2 MEASUREMENT UNCERTAINTY	8
	_
3 . GENERAL INFORMATION	9
3.1 GENERAL DESCRIPTION OF EUT	9
3.2 DESCRIPTION OF TEST MODES	11
3.3 TABLE OF PARAMETERS OF TEXT SOFTWARE SETTING	11
3.4 BLOCK DIAGRAM SHOWING THE CONFIGURATION OF SYSTEM TES	
3.5 DESCRIPTION OF SUPPORT UNITS	12
4 . EMC EMISSION TEST	13
4.1 CONDUCTED EMISSION MEASUREMENT	13
4.1.1 POWER LINE CONDUCTED EMISSION LIMITS 4.1.2 TEST PROCEDURE	13
4.1.2 TEST PROCEDURE 4.1.3 DEVIATION FROM TEST STANDARD	13 13
4.1.4 TEST SETUP	14
4.1.5 EUT OPERATING CONDITIONS	14
4.1.6 EUT TEST CONDITIONS 4.1.7 TEST RESULTS	14 14
4.1.7 TEST RESULTS 4.2 RADIATED EMISSION MEASUREMENT	15
4.2.1 RADIATED EMISSION MEASUREMENT 4.2.1 RADIATED EMISSION LIMITS	15
4.2.2 TEST PROCEDURE	16
4.2.3 DEVIATION FROM TEST STANDARD	16
4.2.4 TEST SETUP 4.2.5 EUT OPERATING CONDITIONS	17 18
4.2.6 EUT TEST CONDITIONS	18
4.2.7 TEST RESULTS (9KHZ TO 30MHZ)	18
4.2.8 TEST RESULTS (30MHZ TO 1000MHZ)	18
4.2.9 TEST RESULTS (ABOVE 1000MHZ)	18
5 . BANDWIDTH TEST	19
5.1 APPLIED PROCEDURES / LIMIT	19
5.1.1 TEST PROCEDURE 5.1.2 DEVIATION FROM STANDARD	19 19
5.1.3 TEST SETUP	19
5.1.4 EUT OPERATION CONDITIONS	19
5.1.5 EUT TEST CONDITIONS	19 10
5.1.6 TEST RESULTS	19
6 . MAXIMUM OUTPUT POWER TEST	20

Report No.: BTL-FICP-1-1803C261





Table of Contents	Page
6.1 APPLIED PROCEDURES / LIMIT 6.1.1 TEST PROCEDURE 6.1.2 DEVIATION FROM STANDARD 6.1.3 TEST SETUP 6.1.4 EUT OPERATION CONDITIONS 6.1.5 EUT TEST CONDITIONS 6.1.6 TEST RESULTS	20 20 20 20 20 20 20 20
7 . ANTENNA CONDUCTED SPURIOUS EMISSION	21
7.1 APPLIED PROCEDURES / LIMIT 7.1.1 TEST PROCEDURE 7.1.2 DEVIATION FROM STANDARD 7.1.3 TEST SETUP 7.1.4 EUT OPERATION CONDITIONS 7.1.5 EUT OPERATION CONDITIONS 7.1.6 TEST RESULTS	21 21 21 21 21 21 21
8 . POWER SPECTRAL DENSITY TEST	22
8.1 APPLIED PROCEDURES / LIMIT 8.1.1 TEST PROCEDURE 8.1.2 DEVIATION FROM STANDARD 8.1.3 TEST SETUP 8.1.4 EUT OPERATION CONDITIONS 8.1.5 EUT TEST CONDITIONS 8.1.6 TEST RESULTS	22 22 22 22 22 22 22
9 . MEASUREMENT INSTRUMENTS LIST	23
10 . EUT TEST PHOTO	25
APPENDIX A - CONDUCTED EMISSION	28
APPENDIX B - RADIATED EMISSION (9KHZ TO 30MHZ)	29
APPENDIX C - RADIATED EMISSION (30MHZ TO 1000MHZ)	34
APPENDIX D - RADIATED EMISSION (ABOVE 1000MHZ)	41
APPENDIX E - BANDWIDTH	54
APPENDIX F - MAXIMUM OUTPUT POWER TEST	57
APPENDIX G - ANTENNA CONDUCTED SPURIOUS EMISSION	59
APPENDIX H - POWER SPECTRAL DENSITY TEST	66

Report No.: BTL-FICP-1-1803C261





REPORT ISSUED HISTORY

Issued No.	Description	Issued Date
BTL-FICP-1-1803C261	Original Issue.	May 22, 2018
MDG1805049	Update the applicant name.	May 29, 2018

Report No.: BTL-FICP-1-1803C261 Page 5 of 68





1. CERTIFICATION

Equipment : Bluetooth Remote Control

Brand Name: N/A

Test Model : YKF429-004

Series Model: N/A

Applicant : Fengmi(Beijing)Technology Co.,Ltd Date of Test : Mar. 28, 2018 ~ May 10, 2018

Test Sample: Engineering Sample

Standard(s) : FCC Part15, Subpart C (15.247) / ANSI C63.10-2013

RSS-247 Issue 2, Feb. 2017 RSS-GEN Issue 4, Nov. 2014

The above equipment has been tested and found compliance with the requirement of the relative standards by BTL Inc.

The test data, data evaluation, and equipment configuration contained in our test report (Ref No. BTL-FICP-1-1803C261) were obtained utilizing the test procedures, test instruments, test sites that has been accredited by the Authority of NVLAP according to the ISO-17025 quality assessment standard and technical standard(s).

Report No.: BTL-FICP-1-1803C261 Page 6 of 68





2. SUMMARY OF TEST RESULTS

Test procedures according to the technical standard(s):

Applied Standard(s): FCC Part15 (15.247) , Subpart C Canada RSS-247 Issue 2, Feb. 2017, RSS-GEN Issue 4, Nov. 2014					
Standard(s) Section	Test Item	Judgment	Remark	
FCC	IC				
15.207	RSS-GEN 8.8	Conducted Emission	N/A		
15.247(d)	RSS-247 5.5	Antenna conducted Spurious Emission	PASS		
15.247(a)(2)	RSS-247 5.2 (a)	6dB Bandwidth	PASS		
15.247(b)(3)	RSS-247 5.4 (d)	Peak Output Power	PASS		
15.247(e)	RSS-247 5.2 (b)	Power Spectral Density	PASS		
15.203	-	Antenna Requirement	PASS		
15.247(d)/ 15.205/ 15.209	RSS-247 5.5	Transmitter Radiated Emissions	PASS		

NOTE:

(1)" N/A" denotes test is not applicable to this device.

Report No.: BTL-FICP-1-1803C261 Page 7 of 68





2.1 TEST FACILITY

The test facilities used to collect the test data in this report is at the location of No.3, Jinshagang 1st Road, Shixia, Dalang Town, Dongguan, Guangdong, China.

BTL's test firm number for FCC: 854385 BTL's designation number for FCC: CN5020 BTL's test firm number for IC: 4428B-1

2.2 MEASUREMENT UNCERTAINTY

The measurement uncertainty figures shall be calculated according the methods described in the ETSI TR 100 028 and shall correspond to an expansion factor (coverage factor) k=1.96 or k=2(which provide confidence levels of respectively 90% and 95.45% in the case where the distributions characterizing the actual measurement uncertainties are normal (Gaussian)). Measurement Uncertainty for a Level of Confidence of 95 %, U=2xUc(y).

The BTL measurement uncertainty as below table:

A. Radiated Measurement:

Test Site	Method	Measurement Frequency Range	Ant. H / V	U, (dB)
		9KHz~30MHz	V	3.79
		9KHz~30MHz	Ι	3.57
		30MHz ~ 200MHz	V	3.82
		30MHz ~ 200MHz	Η	3.78
DG-CB03	CISPR	200MHz ~ 1,000MHz	V	4.10
DG-CB03 (CISER	200MHz ~ 1,000MHz	Η	4.06
		1GHz~18GHz	V	3.12
	1GHz~18GHz	Ι	3.68	
		18GHz~40GHz	V	4.15
		18GHz~40GHz	Н	4.14

Note: Unless specifically mentioned, the uncertainty of measurement has not been taken into account to declare the compliance or non-compliance to the specification.

Report No.: BTL-FICP-1-1803C261





3. GENERAL INFORMATION

3.1 GENERAL DESCRIPTION OF EUT

Equipment	Bluetooth Remote Control			
Brand Name	N/A	N/A		
Test Model	YKF429-004			
Series Model	N/A			
Model Difference	N/A			
Product Description	Operation Frequency	2402~2480 MHz		
	Modulation Technology	GFSK(1Mbps)		
1 Toddot Boodilpilott	Bit Rate of Transmitter	GI SK(TIVIDPS)		
	Output Power (Max.)	-0.88 dBm (1Mbps)		
Power Source	Battery supplied.			
Power Rating	2.4V ~ 3.3V			

Note

1. For a more detailed features description, please refer to the manufacturer's specifications or the user's manual.

Report No.: BTL-FICP-1-1803C261





2. Channel List:

Channel	Frequency (MHz)	Channel	Frequency (MHz)
00	2402	20	2442
01	2404	21	2444
02	2406	22	2446
03	2408	23	2448
04	2410	24	2450
05	2412	25	2452
06	2414	26	2454
07	2416	27	2456
08	2418	28	2458
09	2420	29	2460
10	2422	30	2462
11	2424	31	2464
12	2426	32	2466
13	2428	33	2468
14	2430	34	2470
15	2432	35	2472
16	2434	36	2474
17	2436	37	2476
18	2438	38	2478
19	2440	39	2480

3. Table for Filed Antenna:

Ant.	Brand	Model Name	Antenna Type	Connector	Gain (dBi)
1	N/A	N/A	Internal	N/A	1.5

Report No.: BTL-FICP-1-1803C261 Page 10 of 68





3.2 DESCRIPTION OF TEST MODES

To investigate the maximum EMI emission characteristics generates from EUT, the test system was pre-scanning tested base on the consideration of following EUT operation mode or test configuration mode which possible have effect on EMI emission level. Each of these EUT operation mode(s) or test configuration mode(s) mentioned above was evaluated respectively.

Pretest Mode	Description
Mode 1	TX Mode NOTE (1)

The EUT system operated these modes were found to be the worst case during the pre-scanning test as following:

For Conducted Test			
Final Test Mode Description			
Mode 1	TX Mode		

For Radiated Test		
Final Test Mode	Description	
Mode 1	TX Mode NOTE (1)	

Note:

(1) The measurements are performed at the high, middle, low available channels.

3.3 TABLE OF PARAMETERS OF TEXT SOFTWARE SETTING

During testing channel & power controlling software provided by the customer was used to control the operating channel as well as the output power level. The RF output power selection is for the setting of RF output power expected by the customer and is going to be fixed on the firmware of the final end product power parameters of BT LE


Test Software Version		IPOP	
Frequency (MHz)	2402 2440 2480		
BT LE	N/A	N/A	N/A

Report No.: BTL-FICP-1-1803C261 Page 11 of 68





3.4 BLOCK DIAGRAM SHOWING THE CONFIGURATION OF SYSTEM TESTED



3.5 DESCRIPTION OF SUPPORT UNITS

The EUT has been tested as an independent unit together with other necessary accessories or support units. The following support units or accessories were used to form a representative test configuration during the tests.

Item	Equipment	Mfr/Brand	Model/Type No.	FCC ID	Series No.
Α	Test Fixture	N/A	N/A	N/A	N/A
В	Notebook	Dell	DCSM	DOC	G7K832X

Item	Shielded Type	Ferrite Core	Length	Note
1	NO	NO	5cm	Data Cable
2	NO	NO	1.2m	Data Cable

Report No.: BTL-FICP-1-1803C261 Page 12 of 68





4. EMC EMISSION TEST

4.1 CONDUCTED EMISSION MEASUREMENT

4.1.1 POWER LINE CONDUCTED EMISSION LIMITS (Frequency Range 150KHz-30MHz)

Frequency of Emission (MHz)	Conducted Limit (dBµV)		
	Quasi-peak	Average	
0.15 -0.5	66 to 56*	56 to 46*	
0.50 -5.0	56	46	
5.0 -30.0	60	50	

Note:

(1) The limit of " * " decreases with the logarithm of the frequency

(2) The test result calculated as following: Measurement Value = Reading Level + Correct Factor Correct Factor = Insertion Loss + Cable Loss + Attenuator Factor(if use) Margin Level = Measurement Value - Limit Value

The following table is the setting of the receiver

Receiver Parameters	Setting
Attenuation	10 dB
Start Frequency	0.15 MHz
Stop Frequency	30 MHz
IF Bandwidth	9 kHz

4.1.2 TEST PROCEDURE

- a. The EUT was placed 0.8 meters from the horizontal ground plane with EUT being connected to the power mains through a line impedance stabilization network (LISN). All other support equipment powered from additional LISN(s). The LISN provide 50 Ohm/ 50uH of coupling impedance for the measuring instrument.
- b. Interconnecting cables that hang closer than 40 cm to the ground plane shall be folded back and forth in the center forming a bundle 30 to 40 cm long.
- c. I/O cables that are not connected to a peripheral shall be bundled in the center. The end of the cable may be terminated, if required, using the correct terminating impedance. The overall length shall not exceed 1 m.
- d LISN at least 80 cm from nearest part of EUT chassis.
- e For the actual test configuration, please refer to the related Item -EUT Test Photos.

4.1.3 DEVIATION FROM TEST STANDARD


No deviation

Report No.: BTL-FICP-1-1803C261 Page 13 of 68





4.1.4 TEST SETUP



Note: 1.Support units were connected to second LISN.

2.Both of LISNs (AMN) are 80 cm from EUT and at least 80 from other units and other metal planes

4.1.5 EUT OPERATING CONDITIONS

The EUT was configured for testing in a typical fashion (as a customer would normally use it). The EUT has been programmed to continuously transmit during test. This operating condition was tested and used to collect the included data.

4.1.6 EUT TEST CONDITIONS

Temperature: 24°C Relative Humidity: 60% Test Voltage: N/A

4.1.7 TEST RESULTS

Please refer to the Appendix A.

Remark:

- (1) All readings are QP Mode value unless otherwise stated AVG in column of Note. If the QP Mode Measured value compliance with the QP Limits and lower than AVG Limits, the EUT shall be deemed to meet both QP & AVG Limits and then only QP Mode was measured, but AVG Mode didn't perform. In this case, a " * " marked in AVG Mode column of Interference Voltage Measured.
- (2) Measuring frequency range from 150KHz to 30MHz.
- (3) "N/A" denotes test is not applicable to this device.

Report No.: BTL-FICP-1-1803C261 Page 14 of 68





4.2 RADIATED EMISSION MEASUREMENT

4.2.1 RADIATED EMISSION LIMITS

In case the emission fall within the restricted band specified on 15.205(a) and RSS-247 5.5, then the 15.209(a) and RSS-Gen limit in the table below has to be followed.

LIMITS OF RADIATED EMISSION MEASUREMENT (9KHz-1000MHz)

Frequency	Field Strength	Measurement Distance
(MHz)	(microvolts/meter)	(meters)
0.009~0.490	2400/F(KHz)	300
0.490~1.705	24000/F(KHz)	30
1.705~30.0	30	30
30~88	100	3
88~216	150	3
216~960	200	3
960~1000	500	3

LIMITS OF RADIATED EMISSION MEASUREMENT (Above 1000MHz)

Frequency (MHz)	(dBuV/m) (at 3 meters)		
Frequency (Miriz)	PEAK	AVERAGE	
Above 1000	74	54	

Notes:

- (1) The limit for radiated test was performed according to FCC PART 15C and RSS-247.
- (2) The tighter limit applies at the band edges.
- (3) Emission level (dBuV/m)=20log Emission level (uV/m).
- (4) The test result calculated as following: Measurement Value = Reading Level + Correct Factor Correct Factor = Antenna Factor + Cable Loss - Amplifier Gain(if use) Margin Level = Measurement Value - Limit Value

Report No.: BTL-FICP-1-1803C261 Page 15 of 68





Spectrum Parameter	Setting
Attenuation	Auto
Start Frequency	1000 MHz
Stop Frequency	10th carrier harmonic
RBW / VBW	RBW 1MHz VBW 3MHz peak detector for Pk value
(Emission in restricted band)	RMS detector for AV value

Receiver Parameter	Setting
Attenuation	Auto
Start ~ Stop Frequency	9KHz~90KHz for PK/AVG detector
Start ~ Stop Frequency	90KHz~110KHz for QP detector
Start ~ Stop Frequency	110KHz~490KHz for PK/AVG detector
Start ~ Stop Frequency	490KHz~30MHz for QP detector
Start ~ Stop Frequency	30MHz~1000MHz for QP detector

4.2.2 TEST PROCEDURE

- a. The measuring distance of 3 m shall be used for measurements. The EUT was placed on the top of a rotating table 0.8 meter above the ground at a 3 meter semi-anechoic chamber. The table was rotated 360 degrees to determine the position of the highest radiation.(below 1GHz)
- b. The measuring distance of 3 m shall be used for measurements. The EUT was placed on the top of a rotating table 1.5 meter above the ground at a 3 meter semi-anechoic chamber. The table was rotated 360 degrees to determine the position of the highest radiation. (above 1GHz)
- c. The height of the equipment or of the substitution antenna shall be 0.8m or 1.5m; the height of the test antenna shall vary between 1 m to 4 m. Both horizontal and vertical polarizations of the antenna are set to make the measurement.
- d. For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights find the maximum reading (used Bore sight function).
- e. The receiver system was set to peak and average detect function and specified bandwidth with maximum hold mode when the test frequency is above 1GHz.
- f. The initial step in collecting radiated emission data is a receiver peak detector mode pre-scanning the measurement frequency range. Significant peaks are then marked and then Quasi Peak detector mode re-measured.
- g. All readings are Peak unless otherwise stated QP in column of Note. Peak denotes that the Peak reading compliance with the QP Limits and then QP Mode measurement didn't perform. (below 1GHz)
- h. All readings are Peak Mode value unless otherwise stated AVG in column of Note. If the Peak Mode Measured value compliance with the Peak Limits and lower than AVG Limits, the EUT shall be deemed to meet both Peak & AVG Limits and then only Peak Mode was measured, but AVG Mode didn't perform. (above 1GHz)
- i. For the actual test configuration, please refer to the related Item –EUT Test Photos.

4.2.3 DEVIATION FROM TEST STANDARD

No deviation


Report No.: BTL-FICP-1-1803C261 Page 16 of 68






4.2.4 TEST SETUP

(A) Radiated Emission Test Set-Up Frequency Below 1 GHz



(B) Radiated Emission Test Set-Up Frequency Above 1 GHz




Report No.: BTL-FICP-1-1803C261 Page 17 of 68





(C) For radiated emissions below 30MHz



4.2.5 EUT OPERATING CONDITIONS

The EUT was programmed to be in continuously transmitting mode.

4.2.6 EUT TEST CONDITIONS

Temperature: 22°C Relative Humidity: 56% Test Voltage: AC 120V/60Hz

4.2.7TEST RESULTS (9KHZ TO 30MHZ)

Please refer to the Appendix B

Remark:

- (1) The amplitude of spurious emissions which are attenuated by more than 20 dB below the permissible value has no need to be reported.
- (2) Distance extrapolation factor = 40 log (specific distance / test distance) (dB).
- (3) Limit line = specific limits (dBuV) + distance extrapolation factor.

4.2.8TEST RESULTS (30MHZ TO 1000MHZ)

Please refer to the Appendix C.

4.2.9TEST RESULTS (ABOVE 1000MHZ)

Please refer to the Appendix D.

Remark:

(1) No limit: This is fundamental signal, the judgment is not applicable. For fundamental signal judgment was referred to Peak output test.

Report No.: BTL-FICP-1-1803C261 Page 18 of 68





5. BANDWIDTH TEST

5.1 APPLIED PROCEDURES / LIMIT

	FCC Part15 (15.247) , Subpart C / RSS-247				
Section Test Item Limit Frequency Range (MHz)				Result	
15.247(a)(2) RSS-GEN section 6.6 RSS-247 5.2 (a)	Bandwidth	>= 500KHz (6dB bandwidth)	2400-2483.5	PASS	

5.1.1 TEST PROCEDURE

- a. The EUT was directly connected to the spectrum analyzer and antenna output port as show in the block diagram below,
- b. Spectrum Setting: RBW= 100KHz, VBW=300KHz, Sweep time = 2.5 ms.

5.1.2 DEVIATION FROM STANDARD

No deviation.

5.1.3 TEST SETUP

EUT		SPECTRUM
		ANALYZER

5.1.4 EUT OPERATION CONDITIONS

The EUT tested system was configured as the statements of 4.1.5 unless otherwise a special operating condition is specified in the follows during the testing.

5.1.5 EUT TEST CONDITIONS

Temperature: 24°C Relative Humidity: 60% Test Voltage: AC 120V/60Hz

5.1.6 TEST RESULTS

Please refer to the Appendix E.

Report No.: BTL-FICP-1-1803C261 Page 19 of 68





6. MAXIMUM OUTPUT POWER TEST

6.1 APPLIED PROCEDURES / LIMIT

	FCC Part15 (15.247) , Subpart C / RSS-247				
Section	Test Item	Limit	Frequency Range (MHz)	Result	
15.247(b)(3) RSS-247 5.4 (d)	Maximum Output Power	1 watt or 30dBm	2400-2483.5	PASS	

6.1.1 TEST PROCEDURE

- a. The EUT was directly connected to the power meter and antenna output port as show in the block diagram below,
- b. The maximum peak conducted output power was performed in accordance with method 9.1.2 of FCC KDB 558074 D01 v04 DTS Meas Guidance.

6.1.2 DEVIATION FROM STANDARD

No deviation.

6.1.3 TEST SETUP

EUT	Power Meter

6.1.4 EUT OPERATION CONDITIONS

The EUT tested system was configured as the statements of 4.1.5 unless otherwise a special operating condition is specified in the follows during the testing.

6.1.5 EUT TEST CONDITIONS

Temperature: 24°C Relative Humidity: 60% Test Voltage: AC 120V/60Hz

6.1.6 TEST RESULTS

Please refer to the Appendix F.

Report No.: BTL-FICP-1-1803C261 Page 20 of 68





7. ANTENNA CONDUCTED SPURIOUS EMISSION

7.1 APPLIED PROCEDURES / LIMIT

In any 100 kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated device is operating, the RF power that is produced shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement, provided that the transmitter demonstrates compliance with the peak conducted power limits.


7.1.1 TEST PROCEDURE

- a. The EUT was directly connected to the spectrum analyzer and antenna output port as show in the block diagram below,
- b. Spectrum Setting: RBW= 100KHz, VBW=300KHz, Sweep time = 10 ms.
- c. Offset=antenna gain+cable loss

7.1.2 DEVIATION FROM STANDARD

No deviation.

7.1.3 TEST SETUP



7.1.4 EUT OPERATION CONDITIONS

The EUT tested system was configured as the statements of 4.1.5 unless otherwise a special operating condition is specified in the follows during the testing.

7.1.5 EUT OPERATION CONDITIONS

Temperature: 24°C Relative Humidity: 60% Test Voltage: AC 120V/60Hz

7.1.6 TEST RESULTS

Please refer to the Appendix G.

Report No.: BTL-FICP-1-1803C261 Page 21 of 68





8. POWER SPECTRAL DENSITY TEST

8.1 APPLIED PROCEDURES / LIMIT

FCC Part15 (15.247) , Subpart C / RSS-247								
Section	Test Item	Limit	Frequency Range (MHz)	Result				
15.247(e) RSS-247 5.2 (b)	Power Spectral Density	8 dBm (in any 3KHz)	2400-2483.5	PASS				

8.1.1 TEST PROCEDURE

- a. The EUT was directly connected to the spectrum analyzer and antenna output port as show in the block diagram below,
- b. Spectrum Setting: RBW=3KHz, VBW=10 KHz, Sweep time = auto.

8.1.2 DEVIATION FROM STANDARD

No deviation.

8.1.3 TEST SETUP

EUT	SPECTRUM
	ANALYZER

8.1.4 EUT OPERATION CONDITIONS

The EUT tested system was configured as the statements of 4.1.5 unless otherwise a special operating condition is specified in the follows during the testing.

8.1.5 EUT TEST CONDITIONS

Temperature: 24°C Relative Humidity: 60% Test Voltage: AC 120V/60Hz

8.1.6 TEST RESULTS

Please refer to the Appendix H.

Report No.: BTL-FICP-1-1803C261 Page 22 of 68





9. MEASUREMENT INSTRUMENTS LIST

	Radiated Emission Measurement - Below 1GHz									
Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until					
1	Antenna	Schwarbeck	VULB9160	9160-3232	Mar. 11, 2019					
2	Amplifier	HP	8447D	2944A09673	Oct. 19, 2018					
3	Receiver	Agilent N9038A		MY52130039	Aug. 20, 2018					
4	Cable	emci	LMR-400(30MHz-1 GHz)(8m+5m)	N/A	Jun. 26, 2018					
5	Controller	CT	SC100	N/A	N/A					
6	Controller	MF	MF-7802	MF780208416	N/A					
7	Measurement Software	Farad	EZ-EMC Ver.NB-03A1-01	N/A	N/A					
8	Antenna	EM	EM-6876-1	230	Feb. 07, 2019					

	Radiated Emission Measurement - Above 1GHz									
Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until					
1	Double Ridged Guide Antenna	ETS	3115	75789	Mar. 11, 2019					
2	Broad-Band Horn Antenna	Schwarzbeck	BBHA 9170	9170319	Jun. 08, 2018					
3	Amplifier	Agilent	8449B	3008A02274	Mar. 11, 2019					
4	Microwave Preamplifier With Adaptor	EMC INSTRUMENT	EMC2654045	980039 & HA01	Mar. 11, 2019					
5	Receiver	Agilent	N9038A	MY52130039	Aug. 20, 2018					
6	Controller	СТ	SC100	N/A	N/A					
7	Controller	MF	MF-7802	MF780208416	N/A					
8	Cable	emci	EMC104-SM-SM-1 2000(12m)	N/A	Jun. 26, 2018					
9	Measurement Software	Farad	EZ-EMC Ver.NB-03A1-01	N/A	N/A					

Report No.: BTL-FICP-1-1803C261 Page 23 of 68





6dB Bandwidth Measurement							
Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until		
1	Spectrum Analyzer	R&S	FSP40	100185	Aug. 20, 2018		

Peak Output Power Measurement								
Item	Item Kind of Equipment Manufacturer Type No. Serial No. Calibrated							
1	Power Meter	ANRITSU	ML2495A	1128009	Mar. 11, 2019			
2	Pulse Power Sensor	ANRITSU	MA 2411B	1027500	Mar. 11, 2019			

Antenna Conducted Spurious Emission Measurement							
Item	Kind of Equipment Manufacturer		Type No. Serial No.		Calibrated until		
1	Spectrum Analyzer	R&S	FSP40	100185	Aug. 20, 2018		

Power Spectral Density Measurement								
Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until			
1	Spectrum Analyzer	R&S	FSP40	100185	Aug. 20, 2018			

Remark: "N/A" denotes no model name, serial no. or calibration specified.

All calibration period of equipment list is one year.

Report No.: BTL-FICP-1-1803C261 Page 24 of 68





10. EUT TEST PHOTO

Radiated Measurement Photos

9KHz to 30MHz





Report No.: BTL-FICP-1-1803C261 Page 25 of 68





Radiated Measurement Photos

30MHz to 1000MHz





Report No.: BTL-FICP-1-1803C261 Page 26 of 68





Radiated Measurement Photos

Above 1000MHz





Report No.: BTL-FICP-1-1803C261 Page 27 of 68





APPENDIX A - CONDUCTED EMISSION

Note: "N/A" denotes test is not applicable to this device.

Report No.: BTL-FICP-1-1803C261 Page 28 of 68






 APPENDIX B - RADIATED EMISSION (9KHZ TO 30MHZ)

Report No.: BTL-FICP-1-1803C261 Page 29 of 68





Ant 0°




No. Mk.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1 *	0.0193	31.90	19.71	51.61	121.89	-70.28	AVG	
2	0.0376	26.60	19.09	45.69	116.10	-70.41	AVG	
3	0.0640	21.30	18.45	39.75	111.48	-71.73	AVG	

Report No.: BTL-FICP-1-1803C261 Page 30 of 68





Ant 0°




No. Mk.	Freq.		Correct Factor	Measure- ment	Limit	Margin		
	MHz	dBuV	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1	0.2730	25.30	16.64	41.94	98.88	-56.94	AVG	
2 *	0.7391	21.20	16.19	37.39	70.23	-32.84	QP	
3	2.6221	18.70	15.33	34.03	69.54	-35.51	QP	

Report No.: BTL-FICP-1-1803C261 Page 31 of 68





Ant 90°




No. Mk.	Freq.	Reading Level	Correct Factor	Measure- ment	Limit	Margin		
	MHz	dBuV	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1 *	0.0185	33.20	19.82	53.02	122.26	-69.24	AVG	
2	0.0380	25.40	19.08	44.48	116.01	-71.53	AVG	
3	0.0690	18.90	18.35	37.25	110.83	-73.58	AVG	

Report No.: BTL-FICP-1-1803C261 Page 32 of 68





Ant 90°



No. Mk.	Freq.		Correct Factor	Measure- ment	Limit	Margin		
	MHz	dBuV	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1	0.2818	22.70	16.63	39.33	98.61	-59.28	AVG	
2 *	0.8944	21.20	16.02	37.22	68.57	-31.35	QP	
3	2.1783	18.60	15.46	34.06	69.54	-35.48	QP	

Report No.: BTL-FICP-1-1803C261 Page 33 of 68





AI	PPENDIX C - RADIATED EMISSION (30MHZ TO 1000MHZ)

Report No.: BTL-FICP-1-1803C261 Page 34 of 68





Test Mode: TX 2402MHz _CH00_1Mbps

Vertical



No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1	54. 2500	32. 10	-15. 43	16. 67	40.00	-23.33	Peak	
2	158. 0399	30. 14	-11.47	18. 67	43.50	-24.83	Peak	
3	214. 3000	33. 04	-15.80	17. 24	43.50	-26. 26	Peak	
4	293.8400	29. 20	-11.48	17.72	46.00	-28. 28	Peak	
5	433. 5200	32. 09	-8. 76	23. 33	46.00	-22. 67	Peak	
6 *	564. 4699	29. 80	-6. 40	23. 40	46.00	-22. 60	Peak	


Report No.: BTL-FICP-1-1803C261 Page 35 of 68





Test Mode: TX 2402MHz _CH00_1Mbps

Horizontal



No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1 *	37.7599	33. 55	-15. 08	18. 47	40.00	-21.53	Peak	
2	52. 3100	31. 12	-15. 35	15. 77	40.00	-24.23	Peak	
3	144.4600	31.72	-12. 50	19. 22	43.50	-24. 28	Peak	
4	275. 4100	30. 11	-12.63	17.48	46.00	-28.52	Peak	
5	433. 5200	31.74	-8. 76	22. 98	46.00	-23.02	Peak	
6	568. 3500	30. 92	-6. 46	24.46	46.00	-21.54	Peak	


Report No.: BTL-FICP-1-1803C261 Page 36 of 68





Test Mode: TX 2440MHz _CH19_1Mbps

Vertical



No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1	54. 2500	32. 79	-15. 43	17. 36	40.00	-22.64	Peak	
2	156. 1000	30. 35	-11.64	18.71	43.50	-24.79	Peak	
3	237. 5800	32. 40	-15.48	16. 92	46.00	-29.08	Peak	
4	295. 7800	29.06	-11. 37	17.69	46.00	-28. 31	Peak	
5 *	433. 5200	32. 15	-8. 76	23. 39	46.00	-22.61	Peak	
6	540. 2199	29.83	-6. 75	23. 08	46.00	-22. 92	Peak	


Report No.: BTL-FICP-1-1803C261 Page 37 of 68





Test Mode: TX 2440MHz _CH19_1Mbps

Horizontal



No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1	52. 3100	31. 87	-15. 35	16. 52	40.00	-23.48	Peak	
2	144.4600	31. 39	-12.50	18.89	43.50	-24.61	Peak	
3	298. 6900	28. 48	-11. 20	17. 28	46.00	-28.72	Peak	
4	433. 5200	32. 10	-8. 76	23. 34	46.00	-22.66	Peak	
5	535. 3700	30. 37	-7. 05	23. 32	46.00	-22. 68	Peak	
6 *	669. 2300	30. 68	-4. 91	25. 77	46.00	-20. 23	Peak	


Report No.: BTL-FICP-1-1803C261 Page 38 of 68





Test Mode: TX 2480MHz _CH39_1Mbps

Vertical



No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1	46. 4900	30.74	-15. 20	15. 54	40.00	-24.46	Peak	
2	144. 4600	30.89	-12. 50	18. 39	43.50	-25. 11	Peak	
3	158. 0399	29. 58	-11.47	18. 11	43.50	-25.39	Peak	
4	238. 5500	31.91	-15. 46	16. 45	46.00	-29. 55	Peak	
5	295. 7800	29. 14	-11. 37	17.77	46.00	-28. 23	Peak	
6 *	433. 5200	31.74	-8. 76	22. 98	46.00	-23. 02	Peak	


Report No.: BTL-FICP-1-1803C261 Page 39 of 68





Test Mode: TX 2480MHz _CH39_1Mbps

Horizontal



No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1	37.7599	31.65	−15. 08	16. 57	40.00	-23.43	Peak	
2	158. 0399	30. 07	-11.47	18.60	43.50	-24.90	Peak	
3	260.8599	31.44	-14. 16	17. 28	46.00	-28.72	Peak	
4	433. 5200	32. 67	-8. 76	23. 91	46.00	-22. 09	Peak	
5	558. 6500	29. 57	-6. 30	23. 27	46.00	-22.73	Peak	
6 *	695. 4200	30. 08	-3. 63	26. 45	46.00	-19. 55	Peak	

Report No.: BTL-FICP-1-1803C261 Page 40 of 68





APPENDI	X D - RADIATED EMISSION (ABOVE 1000MHZ)


Report No.: BTL-FICP-1-1803C261 Page 41 of 68





Test Mode: TX 2402MHz _CH00_1Mbps

Vertical




No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1	2390.0000	37.61	9. 00	46. 61	74.00	-27.39	Peak	
2	2390.0000	28. 24	9. 00	37. 24	54.00	-16.76	AVG	
3	2401.7500	69. 62	9. 00	78. 62	74.00	4.62	Peak	No Limit
4 *	2401.9500	68. 07	9. 00	77. 07	54.00	23. 07	AVG	No Limit

Report No.: BTL-FICP-1-1803C261 Page 42 of 68





(MHz)



No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1 *	4803.7100	26. 61	5. 73	32. 34	54.00	-21.66	AVG	
2	4803. 9300	38. 60	5. 73	44. 33	74.00	-29.67	Peak	


Report No.: BTL-FICP-1-1803C261 Page 43 of 68





Test Mode: TX 2402MHz _CH00_1Mbps

Horizontal



No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1	2390.0000	44. 19	9. 00	53. 19	74.00	-20.81	Peak	
2	2390.0000	28. 51	9. 00	37. 51	54.00	-16.49	AVG	
3 *	2402.0000	79. 76	9. 00	88. 76	54.00	34.76	AVG	No Limit
4	2402. 2500	81. 19	9. 00	90. 19	74.00	16. 19	Peak	No Limit

Report No.: BTL-FICP-1-1803C261 Page 44 of 68





Test Mode: TX 2402MHz _CH00_1Mbps

Horizontal



No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1 *	4803.9400	25. 79	5. 73	31. 52	54.00	-22.48	AVG	
2	4806. 4100	37. 24	5. 74	42. 98	74.00	-31. 02	Peak	


Report No.: BTL-FICP-1-1803C261 Page 45 of 68





Test Mode: TX 2440MHz _CH19_1Mbps

Vertical




No.	Freq.	Keading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1 *	2439. 9000	68. 88	8. 98	77.86	54.00	23.86	AVG	No Limit
2	2440. 1000	70. 19	8. 98	79. 17	74.00	5. 17	Peak	No Limit

Report No.: BTL-FICP-1-1803C261 Page 46 of 68







No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1	4880. 1150	38. 08	5. 92	44.00	74.00	-30.00	Peak	
2 *	4880.8450	26. 60	5. 92	32. 52	54.00	-21.48	AVG	


Report No.: BTL-FICP-1-1803C261 Page 47 of 68





Test Mode: TX 2440MHz _CH19_1Mbps

Horizontal



No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1	2439.9500	82.60	8. 98	91.58	74.00	17. 58	Peak	No Limit
2 *	2440. 0000	81. 27	8. 98	90. 25	54.00	36. 25	AVG	No Limit

Report No.: BTL-FICP-1-1803C261 Page 48 of 68





Test Mode: TX 2440MHz _CH19_1Mbps

Horizontal



No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1 *	4878.7550	25. 04	5. 92	30. 96	54.00	-23.04	AVG	
2	4879. 2450	36. 25	5. 92	42. 17	74.00	-31.83	Peak	


Report No.: BTL-FICP-1-1803C261 Page 49 of 68





Test Mode: TX 2480MHz _CH39_1Mbps

Vertical




No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1	2479.9000	70. 98	8. 97	79. 95	74.00	5. 95	Peak	No Limit
2 *	2480.0000	69. 67	8. 97	78. 64	54.00	24.64	AVG	No Limit
3	2483. 5000	46. 20	8. 97	55. 17	74.00	-18.83	Peak	
4	2483. 5000	28. 15	8. 97	37. 12	54.00	-16.88	AVG	

Report No.: BTL-FICP-1-1803C261 Page 50 of 68







No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1 *	4958. 2750	25. 92	6. 12	32. 04	54.00	-21.96	AVG	
2	4959.6700	37.70	6. 12	43.82	74.00	-30. 18	Peak	


Report No.: BTL-FICP-1-1803C261 Page 51 of 68





Test Mode: TX 2480MHz _CH39_1Mbps

Horizontal



No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1 *	2480.0000	78. 89	8. 97	87.86	54.00	33.86	AVG	No Limit
2	2480.0500	80. 28	8. 97	89. 25	74.00	15. 25	Peak	No Limit
3	2483. 5000	53. 34	8. 97	62. 31	74.00	-11.69	Peak	
4	2483. 5000	28. 59	8. 97	37. 56	54.00	-16.44	AVG	

Report No.: BTL-FICP-1-1803C261 Page 52 of 68





Test Mode: TX 2480MHz _CH39_1Mbps

Horizontal



No.	Freq.	Reading Level	Correct Factor	Measure ment	Limit	Margin		
	MHz	dBuV/m	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1 *	4960. 0299	25. 09	6. 12	31. 21	54.00	-22.79	AVG	
2	4960. 3400	36. 90	6. 12	43.02	74.00	-30. 98	Peak	

Report No.: BTL-FICP-1-1803C261 Page 53 of 68





APPENDIX E - BANDWIDTH

Report No.: BTL-FICP-1-1803C261 Page 54 of 68






Test Mode: TX Mode

Frequency (MHz)	6dB Bandwidth (MHz)	99% Occupied BW (MHz)	Min. Limit (kHz)	Test Result
2402	0.704	1.092	500	Pass
2440	0.714	1.096	500	Pass
2480	0.696	1.096	500	Pass


TX CH00




Date: 12.APR.2018 12:08:53







Date: 12.APR.2018 12:12:16



Date: 12.APR.2018 12:14:09





APPENDIX F - MAXIMUM OUTPUT POWER TEST

Report No.: BTL-FICP-1-1803C261 Page 57 of 68





Test Mode: CH00, CH19, CH39 - 1Mbps

Frequency	Conducted	Conducted	Max. Limit	Max. Limit	Toot Dooult
(MHz)	Power (dBm)	Power (W)	(dBm)	(W)	Test Result
2402	-0.88	0.0008	30.00	1.00	Pass
2440	-1.13	0.0008	30.00	1.00	Pass
2480	-1.65	0.0007	30.00	1.00	Pass

Report No.: BTL-FICP-1-1803C261 Page 58 of 68






APPENDIX G - ANTENNA CONDUCTED SPURIOUS EMISSION


Report No.: BTL-FICP-1-1803C261 Page 59 of 68








CH00 (Lower) - 1Mbps



Date: 5.MAY.2018 15:21:47

CH39 (upper) - 1Mbps




Date: 5.MAY.2018 15:25:15










Date: 5.MAY.2018 15:22:02

CH00 (10 Harmonic of the frequency) 2




Date: 5.MAY.2018 15:22:11










Date: 5.MAY.2018 15:22:21

CH19 (10 Harmonic of the frequency) 1




Date: 5.MAY.2018 15:23:47










Date: 5.MAY.2018 15:23:56

CH19 (10 Harmonic of the frequency) 3




Date: 5.MAY.2018 15:24:05










Date: 5.MAY.2018 15:25:29

CH39 (10 Harmonic of the frequency) 2




Date: 5.MAY.2018 15:25:38

Report No.: BTL-FICP-1-1803C261 Page 64 of 68





CH39 (10 Harmonic of the frequency) 3



Date: 5.MAY.2018 15:25:48





APPENDIX H - POWER SPECTRAL	DENSITY TEST

Report No.: BTL-FICP-1-1803C261 Page 66 of 68





Test Mode: CH00, CH19, CH39 - 1Mbps

Frequency (MHz)	Power Density (dBm/3kHz)	Power Density (mW/3kHz)	Max. Limit (dBm/3kHz)	Test Result
2402	-15.740	0.027	8.00	Pass
2440	-16.230	0.024	8.00	Pass
2480	-17.200	0.019	8.00	Pass

TX CH00




Date: 5.MAY.2018 15:22:27


Report No.: BTL-FICP-1-1803C261 Page 67 of 68







Date: 5.MAY.2018 15:24:12



Date: 5.MAY.2018 15:25:55