



Charger (included) or the USB port of a personal computer via the USB Cable (included).
Warning: Recharge your Headset only with the AC or Car Charger included. Using any other types may be dangerous and will void product approvals and warranty of your Headset.

This Bluetooth Headset runs on a high energy built-in rechargeable battery. Follow the instructions below to recharge the Headset when the built-in battery is exhausted.

- To recharge the Headset using the AC Charger, connect the mini USB socket of the provided USB Cable to the Charging Socket of your Headset and then the other end to the USB output socket of the provided AC Charger. Now plug the AC Charger to a household power outlet.
- To recharge from your personal computer instead, connect the other end of the USB Cable to a free USB port on your PC directly.

-7-

-8-

recommended to keep your phone and wear your Headset on the same side of your body.

Please also refer to the diagrams on the right for proper wearing of the Headset with or without Ear Hook. The Headset is designed to sit at a acute angle in your ear. This allows for maximum listening volume and comfort. You may wear the Headset on your right or left ear by adjusting the direction of the Ear Hook.

CALL HANDLING

To make a call

Operate your phone in the normal way when the Headset is connected to your phone.

-15-

To make a call by voice control (voice dialing)

If your mobile phone supports voice dialing function, you can tap the Answer/End Button and wait for a signal tone. Speak out one of the names saved in your mobile phone's contact list clearly after the signal tone. If the recipient's name is correctly identified, his/her phone number will be dialed out accordingly.

To answer a call

Tap the Answer/End Button or use the phone key. If the automatic answer function is set on, your phone automatically answers the incoming call after one ring.

To end a call

Tap the Answer/End Button or use the phone key.

-16-

INTRODUCTION
 Thank you for purchasing this Bluetooth enabled Headset. Together with Bluetooth mobile phones or other Bluetooth embedded Headsets, this device allows you make and receive calls freely while on the move or remaining in a confined area. You can connect your Headset to a compatible mobile phone that supports Bluetooth wireless technology.
 Please read the user manual to make the best use of all its features.

WHAT IS BLUETOOTH WIRELESS TECHNOLOGY?
 Bluetooth wireless technology makes it possible to connect compatible communication Headsets without using cables. A Bluetooth connection does not require the phone and the headset to be in line of sight, but both Headsets should be within 33 feet from each other. Connections can be subjected to interference from obstructions, such as walls or other electronic Headsets.

-1-

The headset is compliant with Bluetooth Specification 2.1 class 2, supporting Headset profile 1.1 and Handfree profile 1.5. Check with the manufacturers of the other devices to determine their compatibility with this Headset. There may be restrictions on using Bluetooth enabled Headsets in some locations. Check with your local authorities or service provider.

SAFETY
 Always observe and follow strictly the regulations governing the use of wireless/Bluetooth devices when you are on an aircraft or in a hospital or you are using this product with other electronic medical devices, such as pacemaker or hearing aids.

COMPLIANCE WITH FCC
 This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

-2-

When the battery becomes exhausted, the Left Indicator starts to flash and a prompt sound will be emitted every 15 seconds.

SWITCHING THE HEADSET ON OR OFF

- To switch on, press and hold the Answer/End Button for 3 seconds. Both indicators will flash 3 times with 2 successive beep tones emitted.
- To switch off, press and hold the Answer/End Button for 3 seconds until the Headset emits 2 beep tones and both indicators flash 3 times.

PAIRING THE HEADSET WITH A COMPATIBLE PHONE

- To pair with a compatible mobile phone, press and hold the Answer/End Button for 6 seconds until both indicators flash rapidly and continuously. You must complete the pairing process within 3 minutes.
- Activate the Bluetooth function of your mobile phone and set it to search for Bluetooth enabled headset. Refer to the user manual of your phone if necessary.

-9-

DISCONNECTING THE HEADSET FROM YOUR PHONE

To disconnect the Headset from your mobile phone, you may do one of the following:

-10-

- From the list of discovered headsets on your mobile phone, select "KT4700" for your Hello Kitty Headset.
- For some phones, you may need to make the connection separately after pairing. Refer to the user manual of your phone if necessary. Note that you only need to pair this Headset with your phone once.
- If pairing is successful, the Right Indicator of the Headset will flash once every 5 seconds. The Headset's name (KT4700) also appears in the paired Bluetooth device list on your phone.

Note:

If the Headset fails to pair or connect to a compatible mobile phone in 10 minutes, it will power itself off.

GETTING STARTED

OVERVIEW

Carefully note that certain parts of the Headset are magnetic. Matters made of magnetic materials may be attracted to the earpiece. Do not place magnetic sensitive objects, e.g. credit cards, near the Headset. Otherwise data stored on them may be erased unintentionally.

CONNECTING YOUR HEADSET WITH 2 MOBILE PHONES AT THE SAME TIME

This Headset is capable of connecting two mobile phones at the same time. This will give you extra convenience of using only one headset to operate two mobile phones.

Activating the Multipoint Function

- Press and hold the Volume Up and Volume Down Buttons simultaneously.
- Switch off the Headset by holding the Answer/End Button for 3 seconds or more.
- Delete the pairing of the Headset from the paired device menu of your phone.
- Move the Headset more than 33 feet away from the paired phone. The Headset will be temporarily disconnected from the phone but without deleting the pairing status.

CHARGING THE BLUETOOTH HEADSET

Before first use, you must charge the Headset for 3 hours until it is completely full.

The Headset can be charged either using the AC Charger (included), Car

-11-

FUNCTIONS AND CONTROLS

The Headset contains the following parts as shown in the figure below:

1	Answer / End Button	2	Left Indicator (red LED)	3	Right Indicator (red LED)
4	Microphone	5	Charge Socket	6	Earpiece
7	Volume Down (-) Button	8	Volume Up (+) Button	9	Ear Hook

-12-

UNDERSTANDING THE INDICATORS

INDICATOR STATUS	WHAT DOES IT MEAN?
Both indicators flash 3 times	Seeking pairing mode. If no different confirmation tone is heard, it is likely the case when successfully paired to a phone.
Both indicators flashing rapidly	Pairing in progress; a confirmation tone is heard when successfully paired to a phone.
Right Indicator flashes every 3 seconds	In standby mode
Right Indicator flashing every 5 seconds	Incoming call; ringer sound is heard in the earpiece or during a call
Both indicators light for 2 seconds	Multipoint function has been activated
Red Indicator flashing rapidly	Low battery; an alert tone is heard every 15 seconds
Left Indicator lights steadily	Battery recharging in process
Right Indicator goes off while recharging	Battery is fully charged

-13-

NOTE

If you cannot connect the Headset to your phone, check the following:

- Ensure that the Bluetooth feature is activated on your phone.
- Ensure that the Headset is charged, switched on, paired with and connected to your phone.
- Check that your Headset is within 33 feet from your connected phone and that there is no big obstacle, such as concrete wall, metal partition or other wireless or Bluetooth headset between them.

BASIC USE

WEARING THE HEADSET

Wear the headset in your ear and secure it in position using the Ear Hook. Best performance can be achieved when there is no obstacle between the Headset and your mobile phone, including your body. Thus it is

-14-

To redial the last dialed number

If your mobile phone supports last number dialing (LND) function, you can press and hold Volume Up button of this Headset to redial the last dialed number. A brief confirmation tone will be heard.

To reject a call

When you need to reject an incoming call, press Answer/End Button for 3 seconds. This function requires support of a compatible mobile phone.

To switch calls between your 2 connected phones

- Suppose you are in the middle of a call using the first Phone A when someone else calls your second Phone B. You will hear a signal tone in the earpiece.
- Simply press the Volume Up button for 1.5 seconds to pick up the new call on Phone B and place the call on Phone A on hold.

-17-

3. Press the Volume Up Button for 1.5 seconds again to switch back to the held call on Phone A and place Phone B on hold. Repeat this as many times as you want.

4. When you have finished talking with the current recipient, tap the Answer/End Button to end the call and resume the call previously on hold.

5. Tap the Answer/End Button again to end the call with the remaining recipient.

ADJUSTING THE EARPIECE VOLUME

Increasing Volume

During a call, tap the Volume Up button once to increase the volume by 1 step. A beep tone will be heard when the maximum volume is reached.

Reducing Volume

During a call, tap the Volume Down button to decrease the volume by 1 step. A beep tone will be heard when the minimum volume is reached.

-18-

ACCESSORIES INCLUDED

- Carrying Pouch
- Transparent Ear Hook
- In-ear Cushion Rings (1 x large, 1 x mid and 1 x small size)
- USB Cable
- AC Charger (Input: 100-240V~ 50/60Hz 0.4A; Output: 5V= 200mA)
- Car Charger (Input: 12-24V~; Output: 5V= 500mA)
- User Manual

-5-

FUNCTIONS AND CONTROLS

The Headset contains the following parts as shown in the figure below:

1	Answer / End Button	2	Left Indicator (red LED)	3	Right Indicator (red LED)
4	Microphone	5	Charge Socket	6	Earpiece
7	Volume Down (-) Button	8	Volume Up (+) Button	9	Ear Hook

CHARGING THE BLUETOOTH HEADSET

Before first use, you must charge the Headset for 3 hours until it is completely full.

The Headset can be charged either using the AC Charger (included), Car

-6-

Lithium Battery Safety Instructions

A Do not bury batteries. Do not puncture or crush. Do not disassemble.

Recycle lithium batteries. Do not dispose of in the trash. If the electrolyte in the cells could get on your skin, thoroughly wash with soap and water. If in the eyes, rinse thoroughly with cool water. Immediately seek medical attention.

Use only chargers rated for lithium cells. Be sure the charger's voltage and current settings are correct for the battery pack being charged.

Charge batteries on a fireproof surface away from flammable items or liquids.

Batteries should NEVER be left unattended while charging. Only adults should charge the batteries.

Follow the manufacturer's instructions for charging the product and do not charge longer than recommended. Unplug the charger when the battery is charged.

-21-

Recycle Rechargeable Batteries

Recycle your old rechargeable batteries at one of the many collection sites in the U.S. and Canada. To find the site nearest you, visit www.call2recycle.org or call toll-free 1-877-2-RECYCLE.

CARE AND MAINTENANCE

Your Headset is a fine product of superior design and craftsmanship. It should always be treated with extra care. The following suggestions will help you protecting your warranty coverage.

- Keep the accessories and enhancements out of the reach of small children.
- Keep the Headset dry. All types of liquids or water moisture can have a negative effect that will damage the internal circuitry. If your Headset does not seem to be dry, allow it to dry completely.
- Do not use corrosive chemicals, cleaning solvents or strong detergents to clean the Headset. Wipe the external surface of the Headset, Ear Hook and In-ear Cushion Ring with a damp lint-free cloth.

-22-

90 DAY LIMITED WARRANTY AND SERVICE VALID IN THE U.S.A ONLY

SPECTRA MERCHANDISING INTERNATIONAL, INC. warrants this to be free from defects in material or factory workmanship for a period of 90 days from the date of original purchase. The unit must be shipped to SPECTRA at the address shown below. IF THE UNIT IS RETURNED WITHIN THE 90 DAY WARRANTY PERIOD, THE UNIT MUST INCLUDE A PROOF OF PURCHASE (DATED RECEIPT) AND A COPY OF THIS WARRANTY. SPECTRA reserves the right to offer alternative options for repair or replacement.

2. Claims are made within the warranty period.

2. This warranty does not cover damage or equipment failure caused by electrical wiring not in compliance with electrical codes or SPECTRA user manual specifications, or failure to provide reasonable care and necessary maintenance as outlined in the user manual.

3. Warranty of all SPECTRA products applies to residential use only and is void when products are used in a nonresidential environment or installed outside the United States.

-23-

THE UNIT IS OUTSIDE THE WARRANTY PERIOD, please include a check for \$25.00 to cover the cost of repair, handling and return postage.

All out of warranty returns must be pre-paid.

IF THE UNIT IS OUTSIDE THE WARRANTY PERIOD, please include a check for \$25.00 to cover the cost of repair, handling and return postage.

All out of warranty returns must be pre-paid.

-24-

This warranty is valid only in accordance with the conditions set forth below:

- The warranty applies to the SPECTRA product only;
- It remains in the possession of the original purchaser and proof of purchase is demanded;
- It has not been subjected to accident, misuse, abuse, improper service, usage or handling that would damage the internal circuitry. If your Headset does not seem to be dry, allow it to dry completely;
- Claims are made within the warranty period;
- This warranty does not cover damage or equipment failure caused by electrical wiring not in compliance with electrical codes or SPECTRA user manual specifications, or failure to provide reasonable care and necessary maintenance as outlined in the user manual.
- Warranty of all SPECTRA products applies to residential use only and is void when products are used in a nonresidential environment or installed outside the United States.

-25-

This warranty gives you specific legal rights, and you may also have other rights which vary from state to state. TO OBTAIN SERVICE please remove all batteries (if any) and pack the unit carefully and send it freight prepaid to SPECTRA at the address shown below. IF THE UNIT IS RETURNED WITHIN THE 90 DAY WARRANTY PERIOD, THE UNIT MUST INCLUDE A PROOF OF PURCHASE (DATED RECEIPT) AND A COPY OF THIS WARRANTY. SPECTRA reserves the right to offer alternative options for repair or replacement.

THE UNIT IS OUTSIDE THE WARRANTY PERIOD, please include a check for \$25.00 to cover the cost of repair, handling and return postage.

All out of warranty returns must be pre-paid.

-26-

It is recommended that you contact SPECTRA first at 1-800-777-5331 or by email at custserv@spectraint.com for updated information on the unit requiring service. In some cases the model you have may be discontinued, and SPECTRA reserves the right to offer alternative options for repair or replacement.

SPECTRA MERCHANDISING INTERNATIONAL, INC.
 4230 North Normandy Avenue,
 Chicago, IL60634, USA
 1-800-777-5331

To register your product, visit the link below to enter your information.
<http://www.spectraint.com/vform.htm>

-27-

Made in China

Bluetooth is a registered trademark of Bluetooth SIG, Inc.

-28-

FCC Information

This device complies with Part 15 of the FCC rules.

Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received; including interference that may cause undesired operation.

Federal Communications Commission (FCC) Statement

This Equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user authority to operate the equipment.

Tested to comply with FCC standard. FOR HOME OR OFFICE USE.

Warning :

This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. & This device and its antenna(s) must not be co-located or conjunction with any other antenna or transmitter.