## WTEB-D155D-120 BOM

No	1/N	M/N	Specification	Location	Qty	Unit	UL file Nub	Remark
1	.,	Fuse	125V/3A	F1	1	pcs	E221465	
Ė			12017 011			Poo	E56092	Replace
2		Capacitor	150nF/25V	C5	1	pcs	200002	Кортаоо
3		Capacitor	220nF/25V	C6	1	pcs		
4		Capacitor	100pF/25V	C7	1	pcs		
5		Capacitor	100nF/50V	C8	1	pcs		
6		Capacitor	47nF/50V	C11	1	pcs		
7		Capacitor	10nF/25V	C14	1	pcs		
8		Capacitor	100nF/25V	C15	1	pcs		
9		Capacitor	4.7nF/25V	C17	1	pcs		
10		Capacitor	10nF/50V	C22	1	pcs		
11		Capacitor	220nf/250V	C1	1	pcs		
12		Capacitor	68uF/200V	C3,C4	2	pcs		
13		Capacitor	10uF/50V	C9,C16	2	pcs		
14		Capacitor	47nf/400V	C10	1	pcs		
15		Capacitor	1000pf/1KV	C12	1	pcs		
16		Capacitor	680pf/1KV	C13	1	pcs		
17		Capacitor	330nf/63V	C18,C19	2	pcs		
18		Capacitor	6.8nf/1250V	C20	1	pcs		
19		Capacitor	330pf/1KV	C21	1	pcs		
20		Resistor	470K	R1,R2	2	pcs		
21		Resistor	33.2K	R3	1	pcs		
22		Resistor	270	R4	1	pcs		
23		Resistor	100K	R5	1	pcs		
24		Resistor	22	R9	1	pcs		
25		Resistor	3.0K	R12	1	pcs		
26		Resistor	100K	R13	1	pcs		
27		Resistor	10K	R14	1	pcs		
28		Resistor	1.5	R15	1	pcs		
29		Resistor	130K	R16	1	pcs		
30		Resistor	51K	R17,R20	2	pcs		
31		Resistor	11K	R18	1	pcs		
32		Resistor	4.32K	R19	1	pcs		
33		Resistor	910K	R21	1	pcs		
34	Щ	Resistor	22K	R22	1	pcs		
35		Resistor	100K	R23	1	pcs		
36	Щ	Resistor	30K	R24	1	pcs		
37		Resistor	0	R26	1	pcs		
38		Resistor	100K	R6,R7,R8	3	pcs		
39		Resistor	22	R10	1	pcs		
40		Resistor	1.0	R11	1	pcs		
41		Resistor	100	R25	1	pcs		
42		Jumper	¢ 0.6mm,4*18*4mm	J1	1	pcs		
43		Jumper	¢0.6mm,4*8*4mm	J2	1	pcs		

44	DIODE	RL207	D1,D2	2	pcs		
45	DIODE	1N4007	D3,D4	2	pcs		
46	DIODE	14V	D5	1	pcs		
47	DIODE	LL4148	D6,D8	2	pcs		
48	IC	UBA2014	U1	1	pcs		
49	Inductance	EF25 1.2mH	T2	1	pcs		
50	Inductance	UU10.5 6.0mH min	T1	1	pcs		
		EE1916 6.0mH min					Replace
51	MOSFET	730 T0220	Q1,Q2	2	pcs		
52	Transistor	BC846B	Q3	1	pcs		
53	Rheostat	10K	VR	1	pcs		
54	PCB	83*83*1.6mm,UL94V-0		1	pcs	E255554	
						E89842	Replace
55	PCB	43*18*1.6mm,UL94V-0		1	pcs	E255554	
						E89842	Replace
56	Bushing	Fiberglas bushing, 7.0, L=150mm,		1	pcs		
57	Bushing	Pyrocondensation bushing, 3.0,L=40mm,Black	L,N,GRN. RED,BLE,	5	pcs	E203950	
58	loincloth	4.8*160mm,		1	pcs	E225882	
59	Insulated sheet	25*28*0.5mm	X1,X2,Y1,Y2	1	pcs		
60	Insulated sheet	55*96mm*0.5,		1	pcs		
61	Wire	0.6*30mm	X1,X2,Y1,Y2	4	pcs		
62	Flexible cord	18AWG UL1007 wire,White,L=320mm,one end strip wire to 5mm, other end strip wire to 12mm	N	1	pcs		
		18AWG UL1015 wire,White,L=320mm,one end strip wire to 5mm, other end strip wire to 12mm					Replace
63	Flexible cord	18AWG UL1007 wire,Black,L=320mm,one end strip wire to 5mm, other end strip wire to 12mm	L	1	pcs		
		18AWG UL1015 wire,Black,L=320mm,one end strip wire to 5mm, other end strip wire to 12mm				E72332-4	Replace
64	Flexible cord	20AWG UL1007 wire,Blue,L=320mm,one end strip wire to 5mm, other end strip wire to 12mm	BLE	1	pcs		
65	Flexible cord	20AWG UL1007 wire,yellow,L=320mm,one end strip wire to 5mm, other end strip wire to 12mm	GRN	1	pcs		
66	Flexible cord	20AWG UL1007 wire,Red,L=320mm,one end strip wire to 5mm, other end strip wire to 12mm	RED	1	pcs		
67	Mini wire	L=200mm		1	pcs		
68	Top crust	PC,White,94.2*94.2*30.8mm, fireproofing,		1	pcs		
69	Bottom crust	PC,White,94.2*94.2*19.6mm, fireproofing,		1	pcs		
70	Terminal	Yellow Coppery,T=0.3mm,L=21.5mm		4	pcs		
71	Terminal Cover	PC,White,13.85*12.1*12.1mm, fireproofing,		1	pcs		
72	DIODE	Not use	D7	0	pcs		