

## www.kokkia.com

FCC ID:XWAKOKKIA

# MarathonS - Tiny Bluetooth Stereo Headset with apt-X®

(A) Charging Point
(D) Vol+ (short press)
Next (long press)

(B) MFB (Multi-Function Button)

(C) Vol- (short press)
Previous (long press)

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications to device will void the user's authority to operate the device.

#### **English**

## Specifications

- V4.0. A2DP, AVRCP, HS/HF Profiles.
- PIN code of '0000'.
- Operating distance up to 10 meters (33feet).

#### Charging the MarathonS

- Red light flashing indicates low battery.
- Plug the USB charging cable into the MarathonS Charger port (A).
- Plug the other side of the USB charging cable into a powered USB port. When charging, the LED (E) will be lit.
- LED (E) will turn off when unit is finished charging.
   (~2 hours)

Note: Do not try to charge MarathonS if it is wet.

### Pairing MarathonS to phone/transmitter

- Turn off all previously paired Bluetooth devices to MarathonS.
- Press MFB button (B) for about 6secs until Red LED (E) flashes.
- Set your phone/transmitter in pairing mode, refer to your device user guide.
- Select "KOKKIA MarathonS" on phone.
- Enter pin code '0000' to pair and connect MarathonS to your phone.
- Blue LED (E) flashes when paired and connected successfully.

#### Powering ON/OFF

- ON: Press MFB Button (B), until Blue LED lights up. To re-connect to previously paired device, just power ON MarathonS
- OFF: Press MFB Button (B), until Red LED lights up.

## MarathonS Functions

- Receive Call: Quick press, release MFB (B)
- Hang-up call: Quick press, release MFB (B)
- <u>Re-dial Last Number</u>: Double quick press, release MFB (B)
- <u>Reject In-coming Call</u>: Press MFB (B) for 1 sec, and release press
- <u>Mute/Un</u>-Mute Microphone during Voice call: Double quick press MFB (B)
- <u>Enter/Exit Voice Control</u>: Quick Press Vol+, Voltogether.
- <u>Multi-point</u>: MarathonS can be paired to 2 cell-phones to receive voice calls from either phone. Turn off Bluetooth of 1<sup>st</sup> cell-phone when pairing MarathonS to 2<sup>nd</sup> cell-phone.
- <u>Play/Pause Music</u>: Quick Press Release MFB (B)
- <u>Volume</u> +: Quick Press (D). <u>Volume</u> -: Quick Press (C)
- Next: Long Press (D). Previous: Long Press (C)