

QUICK STARTER GUIDE

Seoul



KEEP MOVING **KEEP TALKING**
burgsmartwatch.com

INDEX


Burg 14

■ ENGLISH	----- 1 - 17
-----------	--------------

Your watchphone

Keys and parts

- A** SIM card slot
- B** Microphone
- C** Green key *
- D** Red key **
- E** Signal indicator
- F** Watch knob (adjust/set time)
- G** USB headset connector/
USB charger connector
- H** Loudspeaker
- I** Keypad ***
- J** Movement



*Green key - OK / Dial / Speed dial setting


**Red key - On / Off / End / lock&unlock keypad

*** Press and hold 8 key for "*", and 9 key for "#"


1. Insert sim card



Always make sure the watch phone is switched off while putting in and taking out the SIM card. Taking out and inserting the SIM card while the watch phone is switched on can cause damage to the watch phone and SIM.





1



Chip up

2

2. Charge the battery




Red: Battery charging


Blue: Battery fully charged

The initial state of the battery is charged about 25%. Please empty the battery fully and charge to full battery for the first 3 times to achieve the best use of the battery.


First time use


3. Switch on/off

 Forced shutdown only



4. SIM password security (when required)

- 1 PIN is activated if the indicator light is solid red when start up.
- 2 Enter your PIN code using the keypad on the Watch phone.
- 3 Press the green key  to confirm.
- 4 The phone will sound the welcome chime.

 As there is no screen to display the numbers you input, it is suggested to de-activate the pin function.

Signal indicator

LED indicator	Explanation
Red flashing (10 seconds interval) at standby mode	SIM card is not inserted or SIM card is not valid.
Yellow flashing (10 seconds interval) at standby mode	Weak signal or no signal
Blue flashing (10 seconds interval) at standby mode	Good signal
Solid red when start up	PIN is activated. Ready to enter PIN or PUK code
Three colors alternately flashing	On/Off or incoming call
Red flashing (8 seconds interval, three flashes each time)	Low battery
Solid red (watch mode)	Battery charging
Solid blue (watch mode)	Battery is fully charged
Solid yellow	Speed dial setting mode
Blue flash in speed dial	Speed dial setting saved
Red flash in speed dial mode	Speed dial setting failed

Standby mode

Continuously press the Red key until you hear the water sound.

To lock/ unlock the keypad

In standby mode press the Red key, you will hear the lock/unlock sound.

To call/ to receive a call

To make a call enter the phone number and press the green key .

To answer a call press the green key .

To reject a call, press the red key .

To set up a speed dial number

- 1 Long press green key; the signal indicator becomes yellow.
- 2 Press the speed dial number you want to set (1 to 9). Press green key to confirm.
- 3 Blue light will light up.
- 4 Press the contact number you want to set as speed dial.

- 5 Press green key to confirm, if accepted the yellow light will light up; if not accepted the red light will flash.
- 6 After setting the speed dial press the red button to return to the standby function.
- 7 long press choosen speed dial number to make a phone call

To turn on/off voice count function

In standby mode press '00080' followed by the green key to turn on/off the voice count function. When this function is activated, the phone will speak the phone number of the incoming/outgoing call.

FM radio

- 1 Activate FM
Plug in the headset (will be used as FM antenna), unlock the keypad, press *2 + green key* to activate the FM.
- 2 Function key
*0*key: On /Off voice
*1*key: Auto search next channel

"2"key: Activate loudspeaker

"3"key: Volume up

"4"key: Volume down

3 Deactivate FM

Press the Red key to deactivate FM

Bluetooth

1 Bluetooth settings

1.1 First turn on the bluetooth device so it can be searched

1.2 Unlock the keypad, press "1 + green key" to switch on the Bluetooth, and at the same time Bluetooth settings mode will be activated, Yellow light will light up.

Search Bluetooth audio device

- While in Bluetooth settings mode, it will search audio devices automatically.
- When a new device is found, Red light will light up;
- When no device is found, indicator light will be off and it will quit the Bluetooth settings mode, press "1 + green key" key to search again.

Basic functions

1.3 Pair device

- After device found (red light on), press the green key to activate pair mode
- Light will turn off when pair success;
- Keypad light will be off when pair failed, press green key to pair again.

1.4 Connect device


- After pair success, press the green key to connect. if the device need input password (you can find the password in bluetooth device menu), blue light on, input the password.
- Yellow light will light up shortly when connect success, it will automatically quit the Bluetooth settings mode (yellow light will off), it's now connected.
- Keypad light will off when pair failed, input the password, then press the green key to connect again.

1.5 Quit the Bluetooth settings mode

- Continuously press the Red key till the yellow light off. The Bluetooth of the device will still be on.

2 Switch off Bluetooth

Unlock the keypad, press "0 + green key" to switch off the Bluetooth

-  To reconnect bluetooth device after connection has been broken it might take slightly more time to connect, FM function can not use in bluetooth mode.

Track my Burg



For more information about your Watch Phone download the complete manual from our website.

Check with your local Burg shop or contact your distributor to make sure the tracking service is available in your country.


- 1 Purchase the 'Track my Burg' activation card at your local Burg shop.
- 2 Visit your local BURG website to register and activate your BURG account.
- 3 Click on the link Create account to start registration or fill in your username and password if you have already a BURG tracking account.
- 4 Insert the required information.
- 5 A confirmation email will be send, click the link to activate the account.
- 6 After you pressed the confirmation link you can log in with your Username and Password.

Basic functions

- 7 After first time log in you need to set up your Track My BURG account and add your device.
- 8 Please accept the disclaimer to go to the next step.
- 9 Configure your device.
- 10 Your device is added and configured now.
- 11 Activate your account with the information on your purchased 'Track my Burg' activation card by clicking on the 'Enter voucher code' on the website.



Product and safety information

 For more information about your Watch Phone download the complete manual from our website

WARNING AND DISCLAIMER

Do not use or place the Watch Phone under water. Avoid dropping it or stepping on it. Switch your watch phone off in aircraft, near medical equipment, fuel, blasting areas, or chemicals. Your watch phone and its accessories are not toys. Keep it out of the reach of small children and pets! Please stop the car before making or answering phone calls. Do not attempt to repair the watch phone yourself in case of damage or malfunction, as this will void the warranty. The device complies with RF specifications when the device used at 1.5cm from your body. Use careful with the earphone maybe possible excessive sound pressure from earphones and headphones can cause hearing loss.

CAUTION

RISK OF EXPLOSION IF BATTERY IS REPLACED BY AN INCORRECT TYPE.
DISPOSE OF USED BATTERIES ACCORDING TO THE INSTRUCTIONS.

DECLARATION OF CONFORMITY

"Hereby, Burg China Connection declares that this product is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC.

FCC Declaration

FCC Declaration

1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference.

(2) This device must accept any interference received, including interference that may cause undesired operation.

2. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

FCC Declaration

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

SAR Information Statement

Your wireless phone is a radio transmitter and receiver. It is designed and manufactured not to exceed the emission limits for exposure to radiofrequency (RF) energy set by the Federal Communications Commission of the U.S.

Government. These limits are part of comprehensive guidelines and establish permitted levels of RF energy for the general population. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. The standards include a substantial safety margin designed to assure the safety of all persons, regardless of age and health. The exposure standard for wireless Smart Watch employs a unit of measurement known as the Specific Absorption Rate, or SAR. The SAR limit set by the FCC is 1.6 W/kg. * Tests for SAR are conducted with the phone transmitting at its highest certified power level in all tested frequency bands.

Although the SAR is determined at the highest certified power level, the actual SAR

FCC Declaration

level of the phone while operating can be well below the maximum value. This is because the phone is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a wireless base station antenna, the lower the power output. Before a phone model is available for sale to the public, it must be tested and certified to the FCC that it does not exceed the limit established by the government adopted requirement for safe exposure. The tests are performed in positions and locations (e.g., at the Mouth and worn on the Wrist) as required by the FCC for each model. The highest SAR value for this Watch phone when tested for use at the Mouth is 0.362 W/Kg and when worn on the Wrist, as described in this user guide, is 0.517 W/Kg (Wrist-worn measurements differ among phone models, depending upon available accessories and FCC requirements). While there may be differences between the SAR levels of various phones and at various positions, they all meet the government requirement for safe exposure. The FCC has granted an Equipment Authorization for this model phone with all reported SAR levels evaluated as in compliance with the FCC RF exposure guidelines. SAR information on this model phone is on file with the FCC and can be found under the Display Grant section of <http://www.fcc.gov/oet/fccid> after searching on

FCC ID: YLABURG14 Additional information on Specific Absorption Rates (SAR) can be found on the Cellular Telecommunications Industry Association (CTIA) web-site

FCC Declaration

at <http://www.wow-com.com>. * In the United States and Canada, the SAR limit for Smart Watch used by the public is 1.6 watts/kg (W/kg) averaged over one gram of tissue. The standard incorporates a sub-stantial margin of safety to give additional protection for the public and to account for any variations in measurements.

Device is restricted to worn on the wrist operations.

You can also find the after sale details on our burg website:
www.burgsmartwatch.com





Designed by BURG in Holland , Assembled in China