

Operational Description of the equipment

PRODUCT	ANT + Heart Rate Transmitter
MODEL NO.	ZT22A
POWER SUPPLY	DC power source from battery : 3Vdc/65uA
CABLE	NA
FREQUENCY BAND	2.400GHz ~ 2.483.5GHz
CARRIER FREQUENCY	2.457GHz
CHANNEL SPACING	NA
NUMBER OF CHANNEL	1
RATED RF OUTPUT POWER	82.8dBuV/m
MODULATION TYPE	GFSK
BIT RATE OF TRANSMISSION	250Kbit/sec
MODE OF OPERATION	Simplix
ANTENNA TYPE	Chip Antenna
ANTENNA GAIN	2 dBi
OPERATING TEMPERATURE RANGE	-10 ~ 60°C

PUTTING ON THE TRANSMITTER

- Attach one end of the adjustable elastic strap to the transmitter
- Moisten the rubber electrodes of the belt with either water or saliva as shown
- Position the transmitter on the chest just below the breastbone, with the Cardiosport logo the right way up.
- Pass the elastic strap around your chest and attach to the other end of the transmitter.
- Adjust the strap to give a close but comfortable fit.

