

GENERAL INFO

- The system should be powered down completely and the solar panels stowed inside the trailer when the site is unoccupied.
- All controls are below and to the right as you face the battery bank.
- Battery electrolyte levels should be topped up once per season.
- **CAUTION:** Never turn on PV unless **MASTER** and **BATTERY TO CHARGE CONTROLLER** switches are **ON**, it will damage the charge controller.

USING THE INVERTER

- 1 Ensure the system **MASTER SWITCH** is in the **ON** position.
- 2 Press and hold the black **POWER** button on the top panel of the inverter until the green status LED lights. *You should be able to hear the fan at this point.*
- 3 Attach your **120 VAC** load to the plug exiting the bottom of the inverter.
- 4 When done using the inverter, press and hold the black **POWER** button until the green status LED goes off. *Verify that the inverter fan is no longer running.*

CHARGING THE BATTERIES

- 1 Ensure that the DC breaker labelled **PV TO CHARGE CONTROLLER** is in the **OFF** position.
- 2 Remove the two solar panels from the trailer and lean them against the south wall next to the doorway.
- 3 Connect the solar panels in series (positive lead to negative lead) then attach the extension cables running to the charge controller.
- 4 Ensure the system **MASTER SWITCH** is in the **ON** position.
- 5 Move the lever switch labelled **BATTERY TO CHARGE CONTROLLER** to the **ON** position. *A blue status light on the charge controller should be flashing.*
- 6 Move the DC breaker labelled **PV TO CHARGE CONTROLLER** to the **ON** position. *The blue status light on the charge controller should now be solid.*
- 7 Close and lock the trailer door.

SHUTTING DOWN THE SYSTEM

- 1 Ensure the DC breaker labelled **PV TO CHARGE CONTROLLER** is in the **OFF** position.
- 2 Ensure the lever switch labelled **BATTERY TO CHARGE CONTROLLER** is in the **OFF** position. *Verify that no status light on the charge controller is lit.*
- 3 Ensure the system **MASTER SWITCH** is in the **OFF** position.
- 4 Disconnect all the connectors on the solar panels and bring them and the extension cables inside the trailer.
- 5 Close and lock the trailer door.