

Touch Client Setup Guide for Windows

Prerequisites

1. Windows 10/11

- 64-bit processor with Second Level Address Translation (SLAT)
- 4GB system RAM minimum
- BIOS-level hardware virtualization support must be enabled

2. Docker Desktop for Windows

- Download from: <https://docs.docker.com/desktop/install/windows-install/>
- This includes WSL 2 (Windows Subsystem for Linux)

Installation Steps

1. Install Docker Desktop

- Run the Docker Desktop Installer
- Follow the installation wizard
- When prompted, ensure WSL 2 installation is selected
- Restart your computer when installation completes

2. Verify Installation

- Open PowerShell or Command Prompt
- Run `docker --version` to verify Docker installation
- Run `docker-compose --version` to verify Docker Compose installation

Running Touch Client from USB Drive

1. Prepare USB Drive

- Insert the USB drive containing the Touch Client files
- Note the drive letter assigned (e.g., E:, F:, etc.)
- Ensure you have at least 1GB of free space for the database and Docker images

2. Start the Application

- Open PowerShell or Command Prompt
- Navigate to the USB drive:

```
cd /d X: # Replace X with your USB drive letter
cd touch-monorepo
```

- Start the containers:

```
docker-compose up
```

3. Access the Application

- Open your web browser
- Navigate to: `http://localhost:3000`
- The application should now be running
- Your data will be stored in a SQLite database and persisted between sessions

Data Management

1. Database Location

- The SQLite database is stored in the `data` directory
- Data persists between application restarts
- Back up the `data` directory regularly if needed

2. Moving to Another Computer

- The database file moves with the USB drive
- No additional setup needed - just plug and play

Troubleshooting

1. Docker Desktop Issues

- Ensure Hyper-V and WSL 2 are properly enabled
- Check Task Manager to verify Docker Desktop is running
- Restart Docker Desktop if needed

2. Port Conflicts

- If port 3000 is in use, modify the `docker-compose.yml` file
- Change the port mapping to an available port (e.g., 3001:3000)

3. Performance Issues

- Ensure your USB drive is USB 3.0 or higher for better performance

- Consider copying the files to your local drive for optimal performance

Shutting Down

1. Press `ctrl+c` in the terminal where docker-compose is running
2. Wait for containers to stop gracefully
3. Run `docker-compose down` to remove containers
4. Safely eject the USB drive