

Customer : ETD

Type: A380

Rev. Date: Jan 01, 2016

Manual : TSM Selected applicability : ALL

36-22-11-991-02600-00-A / SHEET 2/2 - Engine 3 Pylon, Loop 'B' - Fault Location Zone and Access Table (Short Circuit/Overheat)

	FAULT LOCATION ZONE									
Loc	START OF ZONE m ft ITEM			MID POSITION m ft ITEM			END OF ZONE m ft ITEM			ACCESS PANEL(S)
053	0.34		111HF3	0.35		111HF3	0.36		111HF3	473AR
054	0.38		111HF3	0.39	1.28	111HF3	0.40		111HF3	
055	0.42		111HF3	0.43	1 41	111HF3	0.44		111HF3	473AR
056	0.12	1.00	11111110	0.71	2.33	119HF3	0.11		1111110	473AR
057				3.00	9.84	119HF3				473AR
058				5.30		119HF3				473AR
059				0.84	2.76	66				
060				2.05	6.73	66				
061				3.26	10.70	66				
062				4.46	14.63	66				
063				1.11	3.64	4143				
064				2.32	7.61	4143				
065				3.53	11.58	4143				
066				4.74	15.55	4143				
067				5.95	19.52	4143				
068 069				7.16	23.49 27.43	4143 4143				
070				8.36 9.57	31.40	4143				
070				10.78	35.37	4143				
072				11.99	39.34	4143				
072				13.20	43.31	4143				
074				14.41	47.28	4143				
075				15.62	51.25	4143				
076				0.39	1.28	7588				
077				1.60	5.25	7588				
078				2.81	9.22	7588				
079				4.02	13.19	7588				
080				5.23	17.16	7588				
081				6.44	21.13	7588				
082				7.65	25.10	7588				
083				8.85	29.04	7588				
084				10.06	33.01	7588				
085				11.27	36.98	7588				
086				12.48	40.94	7588				
087 088	+			13.69	44.91	7588 7588				
089	+			14.90 0.92	48.88 3.02	7588				
090	+			2.12	6.96	26				
090	+			3.33	10.93	26				
092	+			4.54	14.90	26				
093				5.75	18.86	26				
094				6.96	22.83	26				
095				8.17	26.80	26				
096				9.38	30.77	26				
097				10.58	34.71	26				
098				0.97	3.18	18				
099				2.18	7.15	18				
100				3.39	11.12	18				

NOTE: THE DIMENSIONS OF THE START, MID POSITION AND THE END OF THE FAULT LOCATION ZONE ARE MEASURED FROM THE START OF EACH APPLICABLE ITEM (WIRE OR FIN).

ALL THE WIRE IDENTS ARE PREFIXED WITH 3622. THE OVERHEAT DETECTION SYSTEM CANNOT CALCULATE A FAULT LOCATION ZONE FOR THE CONNECTING CABLES OR WIRING. THUS, ONLY THE MID POSITION OF A FAULT IS GIVEN TO HELP YOU DO THE TROUBLESHOOTING PROCEDURE FOR THESE ITEMS.

L_TS_362211_2_AFAA_02_00

Figure 36-22-11-991-02600-A- / SHEET 2/2 - Engine 3 Pylon, Loop 'B' - Fault Location Zone and Access Table (Short Circuit/Overheat)

** ON A/C ALL

Print Date: January 19, 2016 Page 1 of 1