

**COMMANDS (I/O ADDRESS HEX 64)**

<b>COMMAND</b>	<b>FUNCTION</b>
20	Read Command Byte of Keyboard Controller
60	Write Command Byte of Keyboard Controller <b>BIT      BIT DEFINITIONS</b> 7      Reserved 6      IBM PC Compatible Mode 5      IBM PC Mode 4      Disable Keyboard 3      Inhibit Override 2      System Flag 1      Reserved 0      Enable Output Buffer Full Interrupt
AA	Self-test <b>BIT      BIT DEFINITIONS</b> 00      No Error Detected 01      K/B Clock Line is Stuck Low 02      K/B Clock Line is Stuck High 03      K/B Data Line is Stuck Low 04      K/B Data Line is Stuck High
AB	Interface Test
AD	Disable Keyboard Feature
AE	Enable Keyboard Interface
C0	Read Input Port
D0	Read Output Port
D1	Write Output Port
E0	Read Test Inputs
F0-FF	Pulse Output Port