
Panasonic



Capable of 2A to 3A high-frequency load switching

PhotoMOS® HE 1 Form A High Capacity



FEATURES


1. Greatly increased load current in a compact DIP package

Continuous load current: 3.5A (AQV251G)

2. Greatly improved specifications allow you to use this in place of mercury and mechanical relays. 3. Low on-resistance (typ. $35m\Omega$, AQV251G)

TYPICAL APPLICATIONS

- Measuring instrument market (Testers etc.)
- Industrial machinery and equipment
- Power supply controls
- Security/Disaster prevention market I/O sections of warning devices, security systems, etc.



RoHS compliant

TYPES

	Output rating*				Par				
					Through hole terminal Surface-mount terminal			Packing quantity	
			Package	Tube packing style		Tape and reel packing style			
	Load voltage	Load current				Picked from the 1/2/3-pin side	Picked from the 4/5/6-pin side	Tube	Tape and reel
AC/DC	30 V	3.5 A	DIP6-pin	AQV251G	AQV251GA	AQV251GAX	AQV251GAZ	1 tube contains: 50 pcs.	1,000 pcs.
dual use	60 V	2.5 A	DIP6-pin	AQV252G	AQV252GA	AQV252GAX	AQV252GAZ	1 batch contains: 500 pcs.	1,000 pcs.

^{*}Indicate the peak AC and DC values.

Note: The surface mount terminal indicator "A" and the packing style indicator "X" or "Z" are not marked on the device.

RATING


1. Absolute maximum ratings (Ambient temperature: 25°C 77°F)

	Item	Symbol	Type of connection	AQV251G(A)	AQV252G(A)	Remarks	
	LED forward current	lF		50 mA 5 V 1 A			
Input	LED reverse voltage	VR	1 \				
	Peak forward current	IFP	1 \ [f = 100 Hz, Duty factor = 0.1%	
	Power dissipation		1 \	75 mW			
	Load voltage (peak AC)	VL] \	30 V	60 V		
			Α	3.5 A	2.5 A		
Output	Continuous load current	l _L	В	4.0 A	4.0 A 3.5 A A connection B, C conne		
Output			С	6.0 A	5.0 A	B, O connection. Do	
	Peak load current	Ipeak		6.0 A		100ms (1 shot), V _L = DC	
	Power dissipation	Pout	1 \	600 mW			
Total power dissipation	P⊤	1 \	650 mW 1,500 V AC				
I/O isolation voltage	Viso	1 \					
Tampavatura limita	Operating	Topr	1 \	-40°C to +85°C	–40°F to +185°F	Non-condensing at low temperatures	
Temperature limits	Storage	T _{stg}	1 \	-40°C to +100°C -40°F to +212°F			

2. Electrical characteristics (Ambient temperature: 25°C 77°F)

	Symbol	Type of connection	AQV251G(A)	AQV252G(A)	Condition		
Input	LED energies augment	Typical	IFon	_	0.55 mA	0.5 mA	I∟ = 100mA
	LED operate current	Maximum			3 mA	3 mA	
	LED turn off current	Minimum	Foff	_	0.2 mA	0.2 mA	I∟ = 100mA
		Typical			0.45 mA	0.45 mA	
	LED dropout voltage	Typical	VF	_	1.14 V (1.32 V at I _F = 50 mA)		I _F = 5 mA
	LED dropout voitage	Maximum			1.5 V		
	On resistance	Typical	Ron	А	0.035 Ω	0.08 Ω	I _F = 5 mA I _L = Max. Within 1 s on time
		Maximum			0.08 Ω	0.12 Ω	
		Typical	Ron	В	0.018 Ω	0.04 Ω	
Output		Maximum			0.04 Ω	0.06 Ω	
		Typical	Ron	С	0.01 Ω	0.02 Ω	
		Maximum			0.02 Ω	0.03 Ω	
	Off state leakage current	Maximum	Leak	_	1 μΑ		$I_F = 0 \text{ mA}, V_L = \text{Max}.$
	Turn on time*	Typical	— Ton	_	1.1 ms		IF = 5 mA, IL = 100 mA VL = 10 V
	Turri ori time	Maximum	Ion		5.0 ms		
	Turn off time*	Typical	Toff	_	0.1 ms	0.25 ms	I _F = 5 mA, I _L = 100 mA
Transfer characteristics	Turri on time	Maximum	loff		0.5 ms		V _L = 10 V
	I/O canacitanas	Typical	Ciso	_	0.8 pF		f = 1 MHz V _B = 0 V
	I/O capacitance	Maximum	Ciso		1.5 pF		
	Initial I/O isolation resistance	Minimum	Riso	_	1,000 ΜΩ		500 V DC
	Max. switching frequency	Maximum	_	_	10 times/s	_	$I_F = 5 \text{ mA, duty} = 50\%$ $V_L \times I_L = 100 \text{ V} \cdot \text{A}$

^{*}Turn on/Turn off time



RECOMMENDED OPERATING CONDITIONS

Please obey the following conditions to ensure proper device operation and resetting.

Item	Symbol	Recommended value	Unit	
Input LED current	lF	5 to 10	mA	

■ These products are not designed for automotive use.

If you are considering to use these products for automotive applications, please contact your local Panasonic Corporation technical representative.

-2-

REFERENCE DATA

1.-(1) Load current vs. ambient temperature characteristics

Tested sample: AQV251G;

0 -40 -20 0 20

Allowable ambient temperature: -40°C to +85°C -40°F to +185°F

V C connection

B connection


A connection

8085

1.-(2) Load current vs. ambient temperature characteristics


Tested sample: AQV252G;

Allowable ambient temperature: -40°C to +85°C -40°F to +185°F



2. On resistance vs. ambient temperature characteristics


Measured portion: between terminals 4 and 6; LED current: 5 mA; Load voltage: Max. (DC) Continuous load current: Max.(DC)



3. Turn on time vs. ambient temperature characteristics


Tested sample: All; LED current: 5 mA; Load voltage: 10 V (DC); Continuous load current: 100 mA (DC)

Ambient temperature, °C




4. Turn off time vs. ambient temperature characteristics

LED current: 5 mA; Load voltage: 10 V (DC); Continuous load current: 100 mA (DC)




5. LED operate current vs. ambient temperature characteristics

Tested sample: All; Load voltage: 10 V (DC); Continuous load current: 100mA (DC)




6. LED turn off current vs. ambient temperature characteristics

Tested sample: All; Load voltage: 10 V (DC); Continuous load current: 100mA (DC)




7. LED dropout voltage vs. ambient temperature characteristics

Tested sample: All; LED current: 5 to 50 mA




8. Current vs. voltage characteristics of output at MOS portion

Measured portion: between terminals 4 and 6; Ambient temperature: 25°C 77°F




9. Off state leakage current vs. load voltage characteristics

Measured portion: between terminals 4 and 6; Ambient temperature: $25^{\circ}C$ $77^{\circ}F$



10. Turn on time vs. LED forward current characteristics


Measured portion: between terminals 4 and 6; Tested sample: All; Load voltage: 10 V (DC); Continuous load current: 100 mA (DC); Ambient temperature: 25°C 77°F



11. Turn off time vs. LED forward current characteristics


Measured portion: between terminals 4 and 6; Load voltage: 10 V (DC);

Continuous load current: 100 mA (DC); Ambient temperature: 25°C 77°F




12. Output capacitance vs. applied voltage characteristics

Measured portion: between terminals 4 and 6; Frequency: 1 MHz; Ambient temperature: 25°C 77°F



13. Max. switching frequency Tested sample: AQV251G; LED current: 5 mA; Ambient temperature: 25°C 77°F



-4-