## PRELIMINARY INFORMATION-SEARCH-FURTHER-YOURSELF:

(A)OffGridSolarBatteryInvertorDOMESTIC(4 no. Batteries i.e. 4x12volt In Series Connection = 48volts, 150AH-200AH, each battery 12 volt SolarTallTubular):

MonoPERC Panel: JinkoSolar/Waaree/UTLsolar:32cell/36cell/60cell/72cell VOC.

Two-Variations:

- Luminous MPPT Charge Controller 48Volt/50Ampere-VOCrange--Alongwith--3Kilowatt/(3750VA(80%efficiency)-4000VA(75%efficiency) y) AlreadyExistingAtHome Normal Inverter)--OR--
- 2. 3Kilowatt Luminous Solar Inverter NXT+ MPPT3750VA-PCU-VOCrange, PCU has built-in MPPT. [PanelStandAloneVOC/PanelsInSeriesVOC < ChargeControllerVOCrange/PCUSolarInverterVOCrange] MC4connectorIP68/PanelJunctionBox

GI/MS PanelStructure

DCDB-MCB/BatteryChargeMeter/dcSPD/DCearthing

ACDB-GridMCBoff/InverterOutputMCB/InverterOutputUnitMeterDigitalDisplay/acSPDwhenGridOn/ACeart hing-AlsoSameForInverterBody

DCwire-10mmsquarePanelChargeController/10mmsquareChargeControllerBattery/16mmmetersquareBatteryInverter

ACwire-6mmsquareInverterACDB

LighteningArrester(LA)(ProtectionRadius)

Seperate 3 meter Deep Earthing AC&DC&LA-Copper Electrodes-Chemical Compound-3 mm Thick-Strips-With-Saddle -Saddle

ChemicalCompoundTypes:1.BackfillCompound(Rocksalt+Charcoal+Anticorrosion mixture) BLACKcolor for Normal areas 2. BackfillCompound(Clay+Bentonite+Charcoal+Rocksalt) BROWNcolor for Desert Areas.

Seperate/ExistingFor-ACEarthing

(B)Gridtie/Bidirectional/NetMetering SolarInvertorDOMESTIC+INCOMEfromGrid(Batteries not required): LuminousCompanyGridtieInverter7500VA/6.0KW & SecureCompanyMeterForReading.

NoteX: 3 Kilowatt Gridtie SolarInverter --or-- 3 kilowatt MPPT SolarInvertor PCU will get you

40%Govt.subsidy on 3KW-solar-panels or less than 3KW-solar-panels.(Check)

NoteY: 6 Kilowatt Solar Panels will get you 20%Govt.subsidy on 6KW-solar-panels.(Check)

NoteZ: MPPT is better than PWM efficiency wise.

## MINIMAL-SETUP-STANDALONE-TOP-SELLER:

Luminous [MODEL:Solar Home UPS NXG+ 1400VA(PWMbased)],

150-200AH:12VoltSingleSolarTallTubularBattery

The Inverter Supports up to 1000 Watts of solar Panels. It is suitable for running up to 720 watts of AC load during power cuts.

- -Savings of 25-30% on electricity bills by reducing charging time with the help of Intelligent Logic Control
- -Power savings of 1.5 3 units per day\* with the help of Intelligent Solar Optimization Technique (iSOT).
- -In this, NXG+ Solar UPS uses Intelligent Solar Optimization Technique (ISOT). Once the batteries get charged, it cuts off grid power and supplies electricity through solar panels thus maximizing solar energy usage.
- -VOCrange:19volt-25volt, Charge Controller Rating 40 Amp/12V, with 98% efficiency for fast charging, Sine wave Solar hybrid UPS with 80%(0.8) efficiency, Rated AC power: 900VA, 12V (So,  $900\times0.8$  = 720Watts)
- -Eq. UTL Solar MonoPERC 165Watts,12volt Design:upto6Panels:VOC=21.82volts