batmonitor 0.76-py: decision tables (bm_tables.h, 15 tables, 67 rows) - first matching row wins, - = any; green 1, red 0; share = input combinations the row decides (DEAD = never reached)

D7 house on AC-out1

D7								
mode_off	mode_on	over_on	under_off	under_long	on	**on**	**under**	share
1	-	-	-	-	-	**0**	**0**	32/64
-	1	-	-	-	-	**1**	**0**	16/64
-	-	1	-	-	-	**1**	**0**	8/64
-	-	-	1	1	-	**0**	**1**	2/64
-	-	-	1	-	1	**1**	**1**	1/64
-	-	-	1	-	-	**0**	**1**	1/64
-	-	-	-	-	-	**KEEP**	**0**	4/64

D7: house on AC-out1. HOUSE_ACOUT 0 = off, 1 = on, auto: on above 99 W, off after 60 s below 30 W.

D5 DO4 pulse

D5						
lockout_over	acout_over	pcc_over	grace_over	pcc_hard	**do4**	share
0	-	-	-	-	**0**	16/32
-	1	-	-	-	**1**	8/32
-	-	1	1	-	**1**	2/32
-	-	1	-	1	**1**	1/32
-	-	-	-	-	**0**	5/32

D5: DO4 pulse (FoxESS shedding): PCC > 20 kW for the grace time or > DO4_HARD_W, or grid offline and PV overfeeds one AC-out; never twice within the lockout.

D3 discharge PROP / IDLE

D3						
any_dis	house_import	prop_prev	prop_hold	deficit_gt_hold	**prop**	share
0	-	-	-	-	**0**	16/32
-	1	-	-	-	**1**	8/32
-	-	1	-	1	**1**	2/32
-	-	-	1	1	**1**	1/32
-	-	-	-	-	**0**	5/32

D3: PROPORTIONAL (1) while importing, or (already proportional / night floor) while the deficit > 20 W.

SoC balancing

DLEAD					
both_ok	has_lead	diff_gt_on	diff_lt_off	**lead**	share
0	-	-	-	**NONE**	8/16
-	0	1	-	**NEW**	2/16
-	1	-	1	**END**	2/16
-	-	-	-	**KEEP**	4/16

SoC balancing: the stack more than SOC_BALANCE_ON ahead leads, cleared below SOC_BALANCE_OFF.

D1 Sofar first, source, winter heat pump rule

D1_WP_CAP				
winter	wp_on	b1_dis	**wp_cap**	share
1	1	1	**ZERO**	1/8
1	1	0	**MAX**	1/8
-	-	-	**NONE**	6/8

D1: winter heat pump rule. Stacks give 0 W while the Sofar Bat1 discharges, else at most WP_WINTER_W.

D1_LATCH				
b1_above_min	bat1_first	b1_ge_release	**bat1_first**	share
0	-	-	**0**	4/8
1	0	1	**1**	1/8
-	-	-	**KEEP**	3/8

D1: Sofar first latch. Off at or below BAT1_SOC_MIN, on again from BAT1_SOC_MIN + 2 %.

bat1_first

D1_B1_FIRST			
bat1_first	wp_on	**b1_first**	share
1	1	**1**	1/4
-	-	**0**	3/4

D1: Sofar first acts only while the heat pump runs.

b1_first

D1_SRC					
night	b1_first	winter	wp_on	**src**	share
0	-	-	-	**DAY**	8/16
1	1	-	-	**B1**	4/16
1	-	1	1	**WPG**	1/16
-	-	-	-	**STK**	3/16

D1: S3 source of the discharge. DAY by day, B1 = Sofar first at night, WPG = winter night with the heat pump running (no night floor), STK = night floor.

src

effect tables (bm_logic.py / bm_logic.c)

src_rule BM_SRC_RULE: the discharge per source				
src	b1_signed	trickle	idle_w	prop_hold
DAY	0	0	20	0
B1	0	0	20	0
STK	1	1	0	1
WPG	0	0	20	0

mode_rule BM_MODE_RULE: what a mode does			
mode	**action**	**capped**	**rule text**
BMS_MISSING	0 W	0	NAME
FORCE	FORCE_CHARGE_W	1	NAME(soc %)
STALE	0 W	0	NAME
LADESPERRE	0 W	0	NAME(peak h)
CHARGE	charge amount	1	NAME SRC:..
FULL	0 W	0	NAME
PROT	0 W	0	NAME(soc %)
CHARGING	0 W	0	NAME(BMS W)
DIS	discharge amount	1	(discharge path)
HOLD	0 W	0	NAME(soc %)

D2 per stack: latches and mode

D2_LOW					
bms_ok	low_on	low_off	soc_ge_release	**low**	share
1	1	-	-	**1**	4/16
1	-	1	1	**0**	1/16
-	-	-	-	**KEEP**	11/16

D2: LOW force charge per stack: DCL 0 or lowest cell < CELL_FORCE_V; ends once DCL is back, the cell >= CELL_FORCE_RELEASE_V and the SoC >= SOC_MIN_RELEASE.

low

D2_FORCE				
bms_ok	soc_lt_force	soc_ge_force_release	**force**	share
1	1	-	**1**	2/8
1	-	1	**0**	1/8
-	-	-	**KEEP**	5/8

D2: grid force charge per stack, SOC_FORCE .. SOC_FORCE_RELEASE.

force

D2_PROT				
bms_ok	soc_lt_min	soc_ge_release	**prot**	share
1	1	-	**1**	2/8
1	-	1	**0**	1/8
-	-	-	**KEEP**	5/8

D2: SoC protection per stack, SOC_MIN .. SOC_MIN_RELEASE (only while the BMS reports).

prot

D2_CHARGE_MODE				
surplus_gt_on	chg_prev	surplus_gt_hold	**charge_mode**	share
1	-	-	**1**	4/8
-	1	1	**1**	1/8
-	-	-	**0**	3/8

D2: charge mode on the surplus (> 200 W), held down to 20 W once charging.

charge_mode

D2_MODE													
bms_ok	force	low	stale	charge_mode	block	soc_lt_100	ff	top	prot	charging	**mode**	share
0	-	-	-	-	-	-	-	-	-	-	**BMS_MISSING**	1024/2048
-	1	-	-	-	-	-	-	-	-	-	**FORCE**	512/2048
-	-	1	-	-	-	-	-	-	-	-	**FORCE**	256/2048
-	-	-	1	-	-	-	-	-	-	-	**STALE**	128/2048
-	-	-	-	1	1	-	-	-	-	-	**LADESPERRE**	32/2048
-	-	-	-	1	-	1	-	-	-	-	**CHARGE**	16/2048
-	-	-	-	1	-	-	1	-	-	-	**CHARGE**	8/2048
-	-	-	-	1	-	-	-	1	-	-	**CHARGE**	4/2048
-	-	-	-	1	-	-	-	-	-	-	**FULL**	4/2048
-	-	-	-	-	-	-	1	-	-	-	**HOLD**	32/2048
-	-	-	-	-	-	-	-	-	1	-	**PROT**	16/2048
-	-	-	-	-	-	-	-	-	-	1	**CHARGING**	8/2048
-	-	-	-	-	-	-	-	-	-	-	**DIS**	8/2048

D2: mode per stack, priority from top to bottom (force / low / prot = the latches above, ff = force_full_from_pv names this stack, top = top hold window of this stack).

mode

block

D4 summer peak window

D4								
enabled	season	fc_cap_ahead	surplus_cap_on	chg_prev	surplus_cap_hold	**block**	**cap**	share
0	-	-	-	-	-	**0**	**0**	32/64
-	0	-	-	-	-	**0**	**0**	16/64
-	-	0	-	-	-	**0**	**0**	8/64
-	-	-	1	-	-	**0**	**1**	4/64
-	-	-	-	1	1	**0**	**1**	1/64
-	-	-	-	-	-	**1**	**1**	3/64

D4: summer peak window, outputs block (wait below EXPORT_CAP) and cap (charge only above it).

D4_PEAK			
pcc_peak	new_day	**peak_today**	share
1	-	**1**	2/4
-	1	**0**	1/4
-	-	**KEEP**	1/4

D4: PCC above 20 kW seen today (display).

batmonitor: observed states, last 30 days (wagodb.pv_victron, one row per minute = the state of the last 5 s cycle; generated 2026-11-05 13:30)

coverage 07.10. 00:00 .. 05.11. 13:30: 16020 of 42571 minutes with a state (37.63 %)			
day	**minutes**	**D1 cells**	**rule states**
Sun 25.10.	875	6	25
Mon 26.10.	1440	8	39
Tue 27.10.	1433	8	27
Wed 28.10.	1440	10	6
Thu 29.10.	1418	17	21
Fri 30.10.	1403	9	33
Sat 31.10.	1440	8	27
Sun 01.11.	1440	8	24
Mon 02.11.	1440	12	30
Tue 03.11.	1440	6	26
Wed 04.11.	1440	8	26
Thu 05.11.	811	5	16
gaps (minutes without a row)			
07.10. 00:00 .. 02:33 154 min 07.10. 11:42 .. 11:43 2 min 07.10. 16:20 .. 16:27 8 min 07.10. 20:12 .. 20:12 1 min 07.10. 22:18 .. 22:18 1 min 07.10. 22:21 .. 22:22 2 min 27.10. 15:38 .. 15:43 6 min 27.10. 17:18 .. 17:18 1 min 29.10. 20:28 .. 20:49 22 min 30.10. 06:44 .. 06:46 3 min 30.10. 06:59 .. 07:23 25 min 30.10. 07:36 .. 07:36 1 min			

D1 cells (pv_victron.bm_d1_id) through the D1 tables of bm_tables.h					
cell	**bits**	**minutes**	**set bits**	**src**	**wp_cap**
93	1+4+8+16+64	4044	night, b1_above_min, b1_ge_release, winter, bat1_first	STK	none
95	1+2+4+8+16+64	3641	night, wp_on, b1_above_min, b1_ge_release, winter, bat1_first	B1	WP_WINTER_W
92	4+8+16+64	3190	b1_above_min, b1_ge_release, winter, bat1_first	DAY	none
94	2+4+8+16+64	2590	wp_on, b1_above_min, b1_ge_release, winter, bat1_first	DAY	WP_WINTER_W
127	1+2+4+8+16+32+64	575	night, wp_on, b1_above_min, b1_ge_release, winter, b1_dis, bat1_first	B1	0 W
87	1+2+4+16+64	389	night, wp_on, b1_above_min, winter, bat1_first	B1	WP_WINTER_W
85	1+4+16+64	374	night, b1_above_min, winter, bat1_first	STK	none
125	1+4+8+16+32+64	320	night, b1_above_min, b1_ge_release, winter, b1_dis, bat1_first	STK	none
126	2+4+8+16+32+64	263	wp_on, b1_above_min, b1_ge_release, winter, b1_dis, bat1_first	DAY	0 W
124	4+8+16+32+64	186	b1_above_min, b1_ge_release, winter, b1_dis, bat1_first	DAY	none
17	1+16	111	night, winter	STK	none
16	16	107	winter	DAY	none
19	1+2+16	92	night, wp_on, winter	WPG	WP_WINTER_W
18	2+16	69	wp_on, winter	DAY	WP_WINTER_W
84	4+16+64	51	b1_above_min, winter, bat1_first	DAY	none
22	2+4+16	11	wp_on, b1_above_min, winter	DAY	WP_WINTER_W
86	2+4+16+64	4	wp_on, b1_above_min, winter, bat1_first	DAY	WP_WINTER_W
28	4+8+16	1	b1_above_min, b1_ge_release, winter	DAY	none
61	1+4+8+16+32	1	night, b1_above_min, b1_ge_release, winter, b1_dis	STK	none
29	1+4+8+16	1	night, b1_above_min, b1_ge_release, winter	STK	none

rule states L1 | L2 | L3 (measured values in brackets removed), 127 different		
minutes	**%**	**L1 | L2 | L3**
2387	14.9	PROP SRC:STK EQ | PROP SRC:STK EQ | PROP SRC:STK EQ
2358	14.7	PROP SRC:B1 EQ WPMAX(100) | PROP SRC:B1 EQ WPMAX(100) | PROP SRC:B1 EQ WPMAX(100)
1740	10.9	HOUSE SRC:Z2 EQ | HOUSE SRC:Z2 EQ | HOUSE SRC:Z2 EQ
1014	6.3	CHARGE SRC:DAY EQ | CHARGE SRC:DAY EQ | CHARGE SRC:DAY EQ
955	6.0	CHARGE SRC:DAY BAL | CHARGE SRC:DAY BAL | CHARGE SRC:DAY BAL
534	3.3	CHARGE SRC:DAY EQ TOP CELL | FULL | FULL
505	3.2	FORCE LOW | PROT | PROT
484	3.0	PROP SRC:DAY EQ WPMAX(100) | PROP SRC:DAY EQ WPMAX(100) | PROP SRC:DAY EQ WPMAX(100)
365	2.3	PROP SRC:DAY EQ | PROP SRC:DAY EQ | PROP SRC:DAY EQ
352	2.2	PROP SRC:B1 EQ WPMAX(0) | PROP SRC:B1 EQ WPMAX(0) | PROP SRC:B1 EQ WPMAX(0)
301	1.9	HOUSE SRC:Z2 BAL | HOUSE SRC:Z2 WAIT | HOUSE SRC:Z2 WAIT
275	1.7	PROP SRC:B1 BAL WPMAX(100) | PROP SRC:B1 WAIT WPMAX(100) | PROP SRC:B1 WAIT WPMAX(100)
263	1.6	PROP SRC:DAY BAL WPMAX(100) | PROP SRC:DAY WAIT WPMAX(100) | PROP SRC:DAY WAIT WPMAX(100)
246	1.5	PROP SRC:B1 WAIT WPMAX(100) | PROP SRC:B1 BAL WPMAX(100) | PROP SRC:B1 BAL WPMAX(100)
237	1.5	CHARGE SRC:Z2 BAL | CHARGE SRC:Z2 BAL | CHARGE SRC:Z2 BAL
236	1.5	CHARGE SRC:DAY EQ TOP | FULL | FULL
232	1.4	FORCE LOW | FORCE LOW | FORCE LOW
202	1.3	PROP SRC:B1 1PH WPMAX(1000) | PROP SRC:B1 STBY WPMAX(1000) | PROP SRC:B1 STBY WPMAX(1000)
197	1.2	PROP SRC:STK 1PH | PROP SRC:STK STBY | PROP SRC:STK STBY
183	1.1	PROP SRC:STK BAL | PROP SRC:STK WAIT | PROP SRC:STK WAIT
178	1.1	PROP SRC:STK STBY | PROP SRC:STK 1PH | PROP SRC:STK STBY
173	1.1	PROP SRC:B1 STBY WPMAX(1000) | PROP SRC:B1 1PH WPMAX(1000) | PROP SRC:B1 STBY WPMAX(1000)
169	1.1	PROP SRC:STK WAIT | PROP SRC:STK BAL | PROP SRC:STK BAL
112	0.7	IDLE SRC:DAY EQ | IDLE SRC:DAY EQ | IDLE SRC:DAY EQ
95	0.6	HOUSE SRC:Z2 BAL | PROT | PROT
94	0.6	FORCE LOW | CHARGE SRC:DAY BAL | CHARGE SRC:DAY BAL
93	0.6	FORCE LOW | PROP SRC:STK EQ | PROP SRC:STK EQ
93	0.6	CHARGE SRC:Z2 EQ | CHARGE SRC:Z2 EQ | CHARGE SRC:Z2 EQ
91	0.6	IDLE SRC:DAY EQ WPMAX(0) | IDLE SRC:DAY EQ WPMAX(0) | IDLE SRC:DAY EQ WPMAX(0)
91	0.6	FORCE LOW | HOUSE SRC:Z2 EQ | HOUSE SRC:Z2 EQ
90	0.6	FULL | FULL | FULL
89	0.6	HOUSE SRC:Z2 STBY | HOUSE SRC:Z2 1PH | HOUSE SRC:Z2 STBY
83	0.5	PROP SRC:DAY BAL | PROP SRC:DAY WAIT | PROP SRC:DAY WAIT
79	0.5	PROP SRC:DAY EQ WPMAX(1000) | PROP SRC:DAY EQ WPMAX(1000) | PROP SRC:DAY EQ WPMAX(1000)
75	0.5	PROP SRC:DAY BAL WPMAX(1000) | PROP SRC:DAY WAIT WPMAX(1000) | PROP SRC:DAY WAIT WPMAX(1000)
71	0.4	CHARGE SRC:DAY BAL TOP CELL | FULL | FULL
66	0.4	PROP SRC:B1 BAL WPMAX(1000) | PROP SRC:B1 WAIT WPMAX(1000) | PROP SRC:B1 WAIT WPMAX(1000)
66	0.4	HOUSE SRC:Z2 WAIT | HOUSE SRC:Z2 BAL | HOUSE SRC:Z2 BAL
65	0.4	BMS_MISSING | FULL | FULL
61	0.4	PROP SRC:DAY EQ WPMAX(0) | PROP SRC:DAY EQ WPMAX(0) | PROP SRC:DAY EQ WPMAX(0)
55	0.3	PROP SRC:DAY 1PH | PROP SRC:DAY STBY | PROP SRC:DAY STBY
54	0.3	PROP SRC:B1 WAIT WPMAX(0) | PROP SRC:B1 BAL WPMAX(0) | PROP SRC:B1 BAL WPMAX(0)
52	0.3	FULL | CHARGE SRC:DAY BAL | CHARGE SRC:DAY BAL
47	0.3	CHARGE SRC:DAY BAL CCL | FULL | FULL
46	0.3	PROP SRC:B1 EQ WPMAX(1000) | PROP SRC:B1 EQ WPMAX(1000) | PROP SRC:B1 EQ WPMAX(1000)
46	0.3	CHARGE SRC:DAY BAL | FULL | FULL
42	0.3	CHARGE SRC:Z2 BAL CCL | FULL | FULL
41	0.3	CHARGE SRC:Z2 BAL | FULL | FULL
36	0.2	FORCE LOW | PROP SRC:B1 EQ WPMAX(1000) | PROP SRC:B1 EQ WPMAX(1000)
34	0.2	PROP SRC:DAY STBY | PROP SRC:DAY 1PH | PROP SRC:DAY STBY
31	0.2	PROP SRC:DAY STBY WPMAX(1000) | PROP SRC:DAY 1PH WPMAX(1000) | PROP SRC:DAY STBY WPMAX(1000)
26	0.2	EXPCAP SRC:Z2 EQ | EXPCAP SRC:Z2 EQ | EXPCAP SRC:Z2 EQ
24	0.1	PROP SRC:DAY 1PH WPMAX(1000) | PROP SRC:DAY STBY WPMAX(1000) | PROP SRC:DAY STBY WPMAX(1000)
23	0.1	BMS_MISSING | CHARGE SRC:DAY EQ | CHARGE SRC:DAY EQ
23	0.1	CHARGE SRC:Z2 BAL | FORCE LOW | FORCE LOW
21	0.1	PROP SRC:STK BAL | FORCE LOW | FORCE LOW
21	0.1	CHARGE SRC:DAY EQ CELL | FULL | FULL
20	0.1	IDLE SRC:DAY BAL | IDLE SRC:DAY WAIT | IDLE SRC:DAY WAIT
20	0.1	CHARGE SRC:DAY FF CCL | FULL | FULL
20	0.1	HOUSE SRC:Z2 BAL | FORCE LOW | FORCE LOW
19	0.1	CHARGING | PROP SRC:DAY EQ WPMAX(100) | PROP SRC:DAY EQ WPMAX(100)
19	0.1	IDLE SRC:DAY EQ WPMAX(100) | IDLE SRC:DAY EQ WPMAX(100) | IDLE SRC:DAY EQ WPMAX(100)
18	0.1	CHARGE SRC:Z2 BAL | CHARGE SRC:Z2 BAL CCL | CHARGE SRC:Z2 BAL CCL
18	0.1	CHARGE SRC:DAY EQ CCL | CHARGE SRC:DAY EQ | CHARGE SRC:DAY EQ
17	0.1	IDLE SRC:DAY BAL WPMAX(0) | IDLE SRC:DAY WAIT WPMAX(0) | IDLE SRC:DAY WAIT WPMAX(0)
14	0.1	IDLE SRC:DAY BAL WPMAX(100) | IDLE SRC:DAY WAIT WPMAX(100) | IDLE SRC:DAY WAIT WPMAX(100)
13	0.1	PROP SRC:B1 1PH WPMAX(0) | PROP SRC:B1 STBY WPMAX(0) | PROP SRC:B1 STBY WPMAX(0)
12	0.1	CHARGING | PROP SRC:B1 EQ WPMAX(100) | PROP SRC:B1 EQ WPMAX(100)
12	0.1	CHARGE SRC:DAY EQ | FULL | FULL
11	0.1	FORCE LOW | CHARGE SRC:DAY EQ | CHARGE SRC:DAY EQ
11	0.1	BMS_MISSING | BMS_MISSING | BMS_MISSING
10	0.1	PROP SRC:DAY BAL | CHARGING | CHARGING
10	0.1	PROP SRC:B1 BAL WPMAX(1000) | FORCE LOW | FORCE LOW
9	0.1	BMS_MISSING | CHARGING | CHARGING
9	0.1	IDLE SRC:DAY WAIT WPMAX(100) | IDLE SRC:DAY BAL WPMAX(100) | IDLE SRC:DAY BAL WPMAX(100)
8	0.0	IDLE SRC:DAY BAL | CHARGING | CHARGING
7	0.0	CHARGE SRC:STK EQ | CHARGE SRC:STK EQ | CHARGE SRC:STK EQ
7	0.0	CHARGE SRC:DAY EQ TOP CCL | FULL | FULL
7	0.0	CHARGING | IDLE SRC:DAY EQ | IDLE SRC:DAY EQ
6	0.0	CHARGE SRC:DAY FF | FULL | FULL
6	0.0	CHARGE SRC:DAY EQ TOP CCL | CHARGE SRC:DAY EQ CCL | CHARGE SRC:DAY EQ CCL
5	0.0	FORCE LOW | PROP SRC:DAY EQ | PROP SRC:DAY EQ
5	0.0	CHARGE SRC:DAY BAL TOP CCL | FULL | FULL
5	0.0	IDLE SRC:B1 EQ WPMAX(0) | IDLE SRC:B1 EQ WPMAX(0) | IDLE SRC:B1 EQ WPMAX(0)
5	0.0	PROP SRC:B1 EQ WPMAX(100) | CHARGING | CHARGING
4	0.0	PROP SRC:DAY BAL WPMAX(1000) | FORCE LOW | FORCE LOW
4	0.0	IDLE SRC:STK EQ | IDLE SRC:STK EQ | IDLE SRC:STK EQ
4	0.0	IDLE SRC:DAY 1PH | IDLE SRC:DAY STBY | IDLE SRC:DAY STBY
4	0.0	PROP SRC:DAY WAIT WPMAX(100) | PROP SRC:DAY BAL WPMAX(100) | PROP SRC:DAY BAL WPMAX(100)
4	0.0	CHARGE SRC:DAY EQ CCL | CHARGE SRC:DAY EQ CCL | CHARGE SRC:DAY EQ CCL
3	0.0	PROP SRC:DAY BAL WPMAX(0) | PROP SRC:DAY WAIT WPMAX(0) | PROP SRC:DAY WAIT WPMAX(0)
3	0.0	IDLE SRC:DAY BAL WPMAX(1000) | IDLE SRC:DAY WAIT WPMAX(1000) | IDLE SRC:DAY WAIT WPMAX(1000)
3	0.0	IDLE SRC:DAY WAIT WPMAX(1000) | IDLE SRC:DAY BAL WPMAX(1000) | IDLE SRC:DAY BAL WPMAX(1000)
3	0.0	IDLE SRC:DAY STBY | IDLE SRC:DAY 1PH | IDLE SRC:DAY STBY
3	0.0	PROP SRC:DAY 1PH WPMAX(0) | PROP SRC:DAY STBY WPMAX(0) | PROP SRC:DAY STBY WPMAX(0)
2	0.0	FORCE LOW | CHARGING | CHARGING
2	0.0	IDLE SRC:DAY WAIT WPMAX(0) | IDLE SRC:DAY BAL WPMAX(0) | IDLE SRC:DAY BAL WPMAX(0)
2	0.0	BMS_MISSING | HOUSE SRC:Z2 EQ | HOUSE SRC:Z2 EQ
2	0.0	PROP SRC:DAY BAL WPMAX(100) | CHARGING | CHARGING
2	0.0	CHARGING | PROP SRC:DAY EQ | PROP SRC:DAY EQ
2	0.0	PROP SRC:DAY EQ WPMAX(100) | CHARGING | CHARGING
2	0.0	CHARGE SRC:DAY BAL CCL | CHARGE SRC:DAY BAL | CHARGE SRC:DAY BAL
2	0.0	IDLE SRC:STK WAIT | IDLE SRC:STK BAL | IDLE SRC:STK BAL
1	0.0	CHARGING | PROP SRC:DAY EQ WPMAX(1000) | PROP SRC:DAY EQ WPMAX(1000)
1	0.0	IDLE SRC:STK BAL | IDLE SRC:STK WAIT | IDLE SRC:STK WAIT
1	0.0	FORCE LOW | IDLE SRC:DAY EQ | IDLE SRC:DAY EQ
1	0.0	IDLE SRC:DAY BAL WPMAX(0) | CHARGING | CHARGING
1	0.0	IDLE SRC:STK 1PH | IDLE SRC:STK STBY | IDLE SRC:STK STBY
1	0.0	FULL | BMS_MISSING | BMS_MISSING
1	0.0	HOUSE SRC:Z2 BAL | CHARGING | CHARGING
1	0.0	CHARGING | HOUSE SRC:Z2 EQ | HOUSE SRC:Z2 EQ
1	0.0	CHARGE SRC:Z2 EQ | FULL | FULL
1	0.0	PROP SRC:STK EQ | BMS_MISSING | BMS_MISSING
1	0.0	CHARGE SRC:DAY BAL | CHARGE SRC:DAY BAL CCL | CHARGE SRC:DAY BAL CCL
1	0.0	PROP SRC:STK BAL | PROP SRC:STK SPILL | PROP SRC:STK SPILL
1	0.0	IDLE SRC:B1 BAL WPMAX(0) | IDLE SRC:B1 WAIT WPMAX(0) | IDLE SRC:B1 WAIT WPMAX(0)
1	0.0	PROP SRC:STK BAL | CHARGING | CHARGING
1	0.0	PROP SRC:B1 EQ WPMAX(0) | CHARGING | CHARGING
1	0.0	CHARGING | IDLE SRC:DAY EQ WPMAX(100) | IDLE SRC:DAY EQ WPMAX(100)
1	0.0	IDLE SRC:B1 WAIT WPMAX(0) | IDLE SRC:B1 BAL WPMAX(0) | IDLE SRC:B1 BAL WPMAX(0)
1	0.0	IDLE SRC:DAY EQ WPMAX(0) | CHARGING | CHARGING
1	0.0	CHARGING | PROP SRC:DAY EQ WPMAX(0) | PROP SRC:DAY EQ WPMAX(0)
1	0.0	CHARGING | CHARGING | CHARGING
1	0.0	IDLE SRC:DAY EQ | CHARGING | CHARGING
1	0.0	PROP SRC:DAY EQ | CHARGING | CHARGING
1	0.0	CHARGE SRC:DAY EQ TOP CELL | CHARGE SRC:DAY EQ CCL | CHARGE SRC:DAY EQ CCL
1	0.0	CHARGE SRC:DAY EQ CCL | FULL | FULL